

JP1 Version 11

JP1/Operations Analytics Messages

3021-3-B93-20(E)

Notices

■ Relevant program products

P-2A2C-DCBL JP1/Operations Analytics 11-50(for Windows Server 2008 R2, Windows Server 2012, Windows Server 2012 R2, Windows Server 2016)

■ Trademarks

HITACHI, JP1 are either trademarks or registered trademarks of Hitachi, Ltd. in Japan and other countries.

IBM, AIX are trademarks of International Business Machines Corporation, registered in many jurisdictions worldwide.

Internet Explorer is either a registered trademark or trademark of Microsoft Corporation in the United States and/or other countries.

Linux(R) is the registered trademark of Linus Torvalds in the U.S. and other countries.

Microsoft is either a registered trademark or a trademark of Microsoft Corporation in the United States and/or other countries.

Oracle and Java are registered trademarks of Oracle and/or its affiliates.

RSA and BSAFE are either trademarks or registered trademarks of EMC Corporation in the United States and/or other countries.

Windows is either a registered trademark or a trademark of Microsoft Corporation in the United States and/or other countries.

Windows Server is either a registered trademark or a trademark of Microsoft Corporation in the United States and/or other countries.

Other company and product names mentioned in this document may be the trademarks of their respective owners.

JP1/Operations Analytics includes RSA BSAFE(R) Cryptographic software of EMC Corporation.

This product includes software developed by the Apache Software Foundation (<http://www.apache.org/>).

This product includes software developed by Ben Laurie for use in the Apache-SSL HTTP server project.

This product includes software developed by IAIK of Graz University of Technology.

Portions of this software were developed at the National Center for Supercomputing Applications (NCSA) at the University of Illinois at Urbana-Champaign.

This product includes software developed by the University of California, Berkeley and its contributors.

This software contains code derived from the RSA Data Security Inc. MD5 Message-Digest Algorithm, including various modifications by Spyglass Inc., Carnegie Mellon University, and Bell Communications Research, Inc (Bellcore).

Regular expression support is provided by the PCRE library package, which is open source software, written by Philip Hazel, and copyright by the University of Cambridge, England. The original software is available from <ftp://ftp.csx.cam.ac.uk/pub/software/programming/pcre/>

This product includes software developed by Ralf S. Engelschall <rse@engelschall.com> for use in the mod_ssl project (<http://www.modssl.org/>).

This product includes software developed by the Java Apache Project for use in the Apache JServ servlet engine project (<http://java.apache.org/>).

This product includes software developed by Daisuke Okajima and Kohsuke Kawaguchi (<http://relaxngcc.sf.net/>).

This product includes software developed by Andy Clark.

Java is a registered trademark of Oracle and/or its affiliates.



■ Microsoft product name abbreviations

This manual uses the following abbreviations for Microsoft product names.

Abbreviation		Full name or meaning
Windows Server 2008 R2		Microsoft(R) Windows Server(R) 2008 R2 Datacenter Microsoft(R) Windows Server(R) 2008 R2 Enterprise Microsoft(R) Windows Server(R) 2008 R2 Standard
Windows Server 2012	Windows Server 2012	Microsoft(R) Windows Server(R) 2012 Datacenter Microsoft(R) Windows Server(R) 2012 Standard
	Windows Server 2012 R2	Microsoft(R) Windows Server(R) 2012 R2 Datacenter Microsoft(R) Windows Server(R) 2012 R2 Standard
Windows Server 2016		Microsoft(R) Windows Server(R) 2016 Datacenter Microsoft(R) Windows Server(R) 2016 Standard

Windows is sometimes used generically, referring to Windows Server 2008 R2, Windows Server 2012, and Windows Server 2016.

■ Restrictions

Information in this document is subject to change without notice and does not represent a commitment on the part of Hitachi. The software described in this manual is furnished according to a license agreement with Hitachi. The license agreement contains all of the terms and conditions governing your use of the software and documentation, including all warranty rights, limitations of liability, and disclaimers of warranty.

Material contained in this document may describe Hitachi products not available or features not available in your country. No part of this material may be reproduced in any form or by any means without permission in writing from the publisher.

■ Edition history

Nov. 2017: 3021-3-B93-20(E)

■ Copy right

All Rights Reserved. Copyright (C) 2016, 2017, Hitachi, Ltd.

Summary of amendments

The following table lists changes in this manual (3021-3-B93-20(E)) and product changes related to this manual.

Changes	Location
<p>The following messages were added: KNAQ03623-I - KNAQ03625-I, KNAQ70001-E - KNAQ70009-E, KNAQ70011-E - KNAQ70013-E, KNAQ73001-I - KNAQ73005-E</p>	<p>1.2.1(2), 1.3.2</p>
<p>The following messages were added: KNAV21000-E - KNAV21003-W, KNAV30164-E - KNAV30184-E, KNAV50418-E - KNAV50429-E, KNAV50803-E - KNAV50842-E, KNAV50980-E - KNAV50988-E</p>	<p>1.3.1</p>
<p>The following messages were added: KAPM00146-E, KAPM01193-E, KAPM02497-E, KAPM03972-E, KAPM03973-E, KAPM04667-W, KAPM04686-W, KAPM04689-W, KAPM04696-W, KAPM04698-W, KAPM04846-E, KAPM05058-W, KAPM05059-I, KAPM05350-E, KAPM05351-E, KAPM05664-W, KAPM06820-E - KAPM06827-E, KAPM08330-E, KAPM08923-E, KAPM15279-I - KAPM15283-W, KAPM16056-E, KAPM16450-I - KAPM16469-E, KAPM16479-E - KAPM16490-E, KAPM16492-E - KAPM16499-E</p>	<p>1.4.1</p>
<p>The following messages were deleted: KAPM01170-I, KAPM01171-I, KAPM01174-I, KAPM01175-I, KAPM01178-E, KAPM01179-E, KAPM01189-W, KAPM02455-E, KAPM02514-I, KAPM02516-I, KAPM02518-I, KAPM02522-W, KAPM02526-I - KAPM02529-I, KAPM02709-I, KAPM04065-I, KAPM04066-I, KAPM04082-I, KAPM04083-I, KAPM05051-W, KAPM05054-I, KAPM05641-I, KAPM06692-W, KAPM06703-I, KAPM06704-I, KAPM06710-I - KAPM06718-I, KAPM06723-I, KAPM06760-I, KAPM06761-I, KAPM06812-W, KAPM14150-I, KAPM14151-I, KAPM15303-I, KAPM15304-I, KAPM15463-I, KAPM15464-I, KAPM15620-I, KAPM15621-I, KAPM15920-I, KAPM15921-I, KAPM15950-I, KAPM15951-I, KAPM16050-I, KAPM16051-I, KAPM16420-I, KAPM16421-I</p>	<p>1.4.1</p>

In addition to the above changes, minor editorial corrections were made.

Preface

This manual describes the messages output by JP1/Operations Analytics that are prefixed with message IDs (such as messages output to logs) and the messages displayed in the **Event** tab of JP1/Operations Analytics.

■ Intended readers

This manual is intended for:

- System administrators who are responsible for introducing and operating JP1/Operations Analytics.

■ Organization of this manual

PART 1: Messages prefixed with message IDs

This part describes the messages that have message IDs.

PART 2: Messages displayed in the **Event** tab

This part describes the messages that are output in the **Event** tab.

APPENDIX A: Version Changes

This part describes the changes in each version.

■ Conventions: Fonts and symbols

The following table explains the text formatting conventions used in this manual:

Text formatting	Convention
Bold	Bold characters indicate text in a window, other than the window title. Such text includes menus, menu options, buttons, radio box options, or explanatory labels. For example: <ul style="list-style-type: none">• From the File menu, choose Open.• Click the Cancel button.• In the Enter name entry box, type your name.
<i>Italic</i>	Italic characters indicate a placeholder for some actual text to be provided by the user or system. For example: <ul style="list-style-type: none">• Write the command as follows: <code>copy source-file target-file</code>• The following message appears: <code>A file was not found. (file = file-name)</code> Italic characters are also used for emphasis. For example: <ul style="list-style-type: none">• Do <i>not</i> delete the configuration file.
Monospace	Monospace characters indicate text that the user enters without change, or text (such as messages) output by the system. For example: <ul style="list-style-type: none">• At the prompt, enter <code>dir</code>.• Use the <code>send</code> command to send mail.• The following message is displayed: <code>The password is incorrect.</code>

The following table lists the conventions used in syntax explanations:

Symbol	Convention
	In syntax explanations, a vertical bar separates multiple items, and has the meaning of OR. For example: <code>A B C</code> means A, or B, or C.

Symbol	Convention
{ }	In syntax explanations, curly brackets indicate that only one of the enclosed items is to be selected. For example: {A B C} means only one of A, or B, or C.
[]	In syntax explanations, square brackets indicate that the enclosed item or items are optional. For example: [A] means that you can specify A or nothing. [B C] means that you can specify B, or C, or nothing.
...	In coding, an ellipsis (...) indicates that one or more lines of coding have been omitted. In syntax explanations, an ellipsis indicates that the immediately preceding item can be repeated as many times as necessary. For example: A, B, B, ... means that, after you specify A, B, you can specify B as many times as necessary.

■ Terms used in this manual

This manual uses the following terms:

Term	Description
Installation destination folder of JP1/OA	The folder into which JP1/OA is installed. The default installation destination is C:\Program Files\HITACHI\JP1OA.
Common component	The component shared by several products and used by JP1/OA. The common component is shared between JP1/OA and JP1/Automatic Operation, or between JP1/OA and Hitachi Command Suite products.
Common component of installation destination folder	The folder into which the common component is installed. When JP1/OA is installed, this folder is created automatically. The default installation destination is C:\Program Files\HITACHI\HiCommand\Base64. If one or more products that use the common component have already been installed, the folder in which those products are installed is used.

■ Conventions: Abbreviations for product names

This manual uses the following abbreviations for product names.

Abbreviation	Full name or meaning
JP1/IM	JP1/Integrated Management
JP1/NP	JP1/Navigation Platform
JP1/OA	JP1/Operations Analytics
JP1/SS	JP1/Service Support
Linux	A generic term used to refer to the following OSs monitored by JP1/OA: CentOS, Oracle Linux(R), Red Hat Enterprise Linux(R), and SUSE Linux(R)
vCenter Server or vCenter	VMware vCenter Server(R)
VMware	VMware(R)
VMware ESXi or ESX	VMware vSphere(R) ESXi(TM)

■ Conventions: Acronyms

This manual uses the following acronyms.

Acronym	Full name or meaning
CPU	Central Processing Unit
CSR	Certificate Signing Request
CSV	Character Separated Values
DBMS	Database Management System
DN	Domain Name
DNS	Domain Name System

Acronym	Full name or meaning
FC	Fibre Channel
GUI	Graphical User Interface
HBA	Host Bus Adapter
HTTP	Hypertext Transfer Protocol
IP	Internet Protocol
LAN	Local Area Network
LUN	Logical Unit Number
MIB	Management Information Base
NIC	Network Interface Card
OS	Operating System
SMI-S	Storage Management Initiative - Specification
SMTP	Simple Mail Transfer Protocol
SNMP	Simple Network Management Protocol
SSH	Secure Shell
SSL	Secure Sockets Layer
UDP	User Datagram Protocol
UNC	Universal Naming Convention
URL	Uniform Resource Locator
UUID	Universally Unique Identifier
VM	Virtual Machine
WBEM	Web-Based Enterprise Management
WMI	Windows Management Instrumentation
WWN	World Wide Name

■ Conventions: "Administrator permissions" as used in this manual

In this manual, *Administrator permissions* refers to Administrator permissions for the local PC. The local user, domain user, or user of the Active Directory environment can perform tasks requiring Administrator permissions if granted Administrator permissions for the local PC.

■ Conventions: Version numbers

The version numbers of Hitachi program products are usually written as two sets of two digits each, separated by a hyphen. For example:

- Version 1.00 (or 1.0) is written as 01-00.
- Version 2.05 is written as 02-05.
- Version 2.50 (or 2.5) is written as 02-50.
- Version 12.25 is written as 12-25.

The version number might be shown on the spine of a manual as *Ver. 2.00*, but the same version number would be written in the program as *02-00*.

Contents

1. Messages prefixed with message IDs	9
1.1 Message overview	9
1.1.1 Message output format	9
1.1.2 Message specification format	9
1.2 Message output destinations	10
1.2.1 Output destinations of messages output by JP1/OA	10
1.2.2 Output destinations of messages output by common components	12
1.3 List of messages (for JP1/OA).....	13
1.3.1 Messages starting with KNAV	13
1.3.2 Messages starting with KNAQ.....	213
1.4 List of messages (for common component).....	247
1.4.1 Messages starting with KAPM	247
2. Messages displayed in the Event tab	732
2.1 Information displayed in the Level column.....	732
2.2 Information displayed in the Message column	733
2.2.1 Message specification format	733
2.2.2 Messages indicating changes in the system status.....	733
2.2.3 Messages indicating changes in a metric status.....	775
Appendix A. Version Changes.....	779

1. Messages prefixed with message IDs

1.1 Message overview

1.1.1 Message output format

The following shows the format of messages output by JP1/OA that are prefixed with message IDs.

```
KNAV<nnnnn>-<Y> <message-text>  
KNAQ<nnnnn>-<Y> <message-text>  
KAPM<nnnnn>-<Y> <message-text>
```

The components of message IDs are shown below.

KNAV, KNAQ, and KAPM

KNAV and KNAQ: Indicate messages output by JP1/OA.

KAPM: Indicates messages output by common components.

<nnnnn>

Indicates the message serial number.

<Y>

Indicates the message type.

E: Indicates an error-level message. When this type of message is output, processing stops.

W: Indicates a warning-level message. After this type of message is output, processing continues.

I: Indicates an information-level message. This type of message gives information to the user.

Q: Indicates an information-level message. These messages ask the user to choose an action.

1.1.2 Message specification format

In this manual, the messages output to logs by JP1/OA and common components are specified in the format shown below. However, some items might be omitted in actual messages.

<message-ID>

<English-message-text>

Cause: Indicates the cause of the output message.

Action: Indicates the action to be taken when the message is output.

Description: Indicates the description of the message.

The description provides information about the variables in the message text, which are represented by *{n}* or *a...a*.

1.2 Message output destinations

1.2.1 Output destinations of messages output by JP1/OA

(1) Output destinations of messages starting with KNAV

The table below shows the message output destinations.

In the table, output destinations are expressed as follows:

(Legend)

Event log: Windows event logs

Public log: Process-specific logs that are output to one of the files below

- <JP1/OA-installation-folder>/logs/ServiceMessage<n>.log
- <JP1/OA-installation-folder>/logs/AdapterMessage_<n>_<m>.log
- <JP1/OA-installation-folder>/logs/RegistryMessage<n>.log
- <JP1/OA-installation-folder>/logs/Server<n>.log
- <JP1/OA-installation-folder>/logs/Command_<command-name><n>.log

In the above, <n> and <m> represent numbers.

Y: Output

--: Not output

Table 1-1 Message output destinations (for messages starting with KNAV)

Message ID	Output destination	
	Event log	Public log
KNAV00001 to KNAV00999	--	Y
KNAV01092, KNAV01093	Y	--
KNAV20001 to KNAV70999	--	Y

(2) Output destinations of messages starting with KNAQ

The table below shows the message output destinations.

In the table, output destinations are expressed as follows:

(Legend)

Event log: Windows event logs

Public log: Process-specific logs that are output to one of the following files

- <JP1/OA-installation-folder>/logs/ServiceMessage<n>.log
- <JP1/OA-installation-folder>/logs/AdapterMessage_<n>_<m>.log
- <JP1/OA-installation-folder>/logs/RegistryMessage<n>.log
- <JP1/OA-installation-folder>/logs/Server<n>.log
- <JP1/OA-installation-folder>/logs/Command_<command-name><n>.log

In the above, <n> and <m> represent numbers.

Standard output: Standard output

Standard error output: Standard error output

Screen: On-screen dialog box

Y: Output

--: Not output

Table 1-2 Message output destinations (for messages starting with KNAQ)

Message ID	Output destination				
	Event log	Public log	Standard output	Standard error output	Screen
KNAQ00022	--	--	--	--	Y
KNAQ00911 to KNAQ00931	--	--	--	--	Y
KNAQ00986 to KNAQ00999	--	--	--	--	Y
KNAQ01901	--	Y	--	--	--
KNAQ03000 to KNAQ03001	--	Y	Y	--	--
KNAQ03002 to KNAQ03013	--	Y	--	Y	--
KNAQ03014 to KNAQ03015	--	Y	--	Y	--
KNAQ03016 to KNAQ03034	--	Y	--	Y	--
KNAQ03036	--	Y	Y	--	--
KNAQ03042	--	Y	--	Y	--
KNAQ03044 to KNAQ03045	--	Y	--	Y	--
KNAQ03050 to KNAQ03051	--	Y	Y	--	--
KNAQ03052	--	Y	--	Y	--
KNAQ03053 to KNAQ03054	--	Y	Y	--	--
KNAQ03143 to KNAQ03182	--	Y	--	Y	--
KNAQ03183	--	Y	Y	--	--
KNAQ03184 to KNAQ03201	--	Y	--	Y	--
KNAQ03202 to KNAQ03204	--	Y	Y	--	--
KNAQ03205	--	Y	--	Y	--
KNAQ03208	--	Y	Y	--	--
KNAQ03209 to KNAQ03213	--	Y	--	Y	--
KNAQ03226	--	--	--	Y	--
KNAQ03229	--	Y	--	Y	--
KNAQ03525 to KNAQ03526	--	Y	Y	Y	--
KNAQ03530 to KNAQ03531	--	Y	Y	--	--
KNAQ03532 to KNAQ03533	--	Y	--	Y	--
KNAQ03534	--	Y	--	--	--
KNAQ03535	--	Y	--	Y	--
KNAQ03540 to KNAQ03541	--	Y	Y	--	--
KNAQ03542 to KNAQ03544	--	Y	--	Y	--
KNAQ03565 to KNAQ03566	--	Y	--	Y	--

Message ID	Output destination				
	Event log	Public log	Standard output	Standard error output	Screen
KNAQ03567	--	Y	Y	--	--
KNAQ03568 to KNAQ03570	--	Y	--	Y	--
KNAQ03571	--	Y	Y	--	--
KNAQ03572 to KNAQ03573	--	Y	--	Y	--
KNAQ03574	--	Y	Y	--	--
KNAQ03575	--	Y	--	--	--
KNAQ03576 to KNAQ03582	--	Y	--	Y	--
KNAQ03583 to KNAQ03584	--	Y	Y	--	--
KNAQ03585	--	Y	--	Y	--
KNAQ03586	--	Y	Y	--	--
KNAQ03587 to KNAQ03590	--	Y	--	Y	--
KNAQ03591	--	Y	Y	--	--
KNAQ03592 to KNAQ03596	--	Y	--	Y	--
KNAQ03598 to KNAQ03601	--	Y	Y	Y	--
KNAQ03602	--	Y	--	Y	--
KNAQ03610 to KNAQ03611	--	Y	--	--	--
KNAQ03616	--	Y	Y	--	--
KNAQ03617 to KNAQ03620	--	Y	Y	Y	--
KNAQ03621	--	Y	--	Y	--
KNAQ03622	--	--	--	Y	--
KNAQ03623 to KNAQ03625	--	Y	--	Y	--
KNAQ70001 to KNAQ70009	--	Y	--	--	Y
KNAQ70011 to KNAQ70013	--	Y	--	--	Y
KNAQ73001 to KNAQ73004	--	Y	Y	--	--
KNAQ73005	--	Y	--	Y	--
KNAQ10084 to KNAQ10089	Y	Y	--	--	--
KNAQ10195	--	Y	--	--	Y
KNAQ10199	--	Y	--	--	Y
KNAQ13000	--	Y	--	--	Y

1.2.2 Output destinations of messages output by common components

(1) Output destinations of messages starting with KAPM

Messages starting with KAPM that are listed in this manual are output to the Windows event logs, audit logs, standard output, standard error output, and other destinations.

1.3 List of messages (for JP1/OA)

1.3.1 Messages starting with KNAV

(1) Information-level messages

KNAV00140-W

The message is unregistered. (catalog ID: {0}, message key: {1}, args[]: {2})

{0}: Catalog ID

{1}: Message key

{2}: Padding characters

KNAV00200-I

The registry server was started.

KNAV00402-I

The control file was deleted.

KNAV01092-I

HAnalytics Engine is starting.

KNAV01093-I

HAnalytics Engine was stopped.

KNAV20006-W

The trial version has expired (expiration date: {0}).

{0}: Date (in YYYY-MM-DD format)

KNAV20028-I

The processing to update the configuration information of the monitored resources has started.

KNAV20029-I

The processing to update the configuration information of the monitored resources finished. (successful: {0}, failed: {1})

{0}: Number of devices for which the processing was successful

{1}: Number of devices for which the processing failed

KNAV20088-I

Service has started.

KNAV20089-I

Service has stopped.

KNAV20109-I

The scheduler function is changed to the stand-by state.({0} second)

{0}: Number of seconds for which the scheduler function will wait

KNAV20110-I

The scheduler function returned from the stand-by state.

KNAV20116-I

{0} credential was added.

{0}: User ID

KNAV20117-I

{0} credential was modified.

{0}: User ID

KNAV20118-I

{0} credential was deleted.

{0}: User ID

KNAV20119-I

IP Range({0}) was added.

{0}: Search range name

KNAV20120-I

IP Range({0}) was modified.

{0}: Search range name

KNAV20121-I

IP Range({0}) was deleted.

{0}: Search range name

KNAV20124-I

The update was skipped because this time and date is within a configuration-effective period. (last update:{0}, effective interval:{1}[s])

{0}: Date and time of last update

{1}: Effective interval (in seconds)

KNAV20138-I

The discovery has started.

KNAV20139-I

The discovery has finished.

KNAV20178-I

The performance history will now be collected.

KNAV20179-I

The performance history was collected. (successful:{0}, skipped:{1})

{0}: Number of devices for which the processing was successful

{1}: Number of devices for which the processing was skipped

KNAV20180-W

The performance history was collected. (successful:{0}, skipped:{1}, failed:{2})

{0}: Number of devices for which the processing was successful

{1}: Number of devices for which the processing was skipped

{2}: Number of devices for which the processing failed

The number of devices is the number specified in ArgusNode.

KNAV20191-I

The performance history will now be collected.

KNAV20192-I

The performance history was collected. (successful:{0}, skipped:{1})

{0}: Number of devices for which the processing was successful

{1}: Number of devices for which the processing was skipped

KNAV20193-W

The performance history was collected. (successful:{0}, skipped:{1}, failed:{2})

{0}: Number of devices for which the processing was successful

{1}: Number of devices for which the processing was skipped

{2}: Number of devices for which the processing failed

KNAV20196-I

The aggregation of the performance history will now start.

KNAV20197-I

The aggregation of the performance history has finished.

KNAV20201-W

The performance management initialization has been skipped.

KNAV20246-I

The performance threshold profile will now be created. (profile:{0})

{0}: Threshold profile name

KNAV20247-I

The performance threshold profile was successfully created. (profile:{0})

{0}: Threshold profile name

KNAV20248-I

An attempt to create the performance threshold profile failed. (profile:{0})

{0}: Threshold profile name

KNAV20249-I

The performance threshold profile will now be updated. (profile:{0})

{0}: Threshold profile name

KNAV20250-I

The performance threshold profile was successfully updated. (profile:{0})

{0}: Threshold profile name

KNAV20251-I

An attempt to update the performance threshold profile failed. (profile:{0})

{0}: Threshold profile name

KNAV20252-I

The resources will now be associated with the performance threshold profile.

KNAV20253-I

The resources were successfully associated with the performance threshold profile.

KNAV20254-I

An attempt to associate the resources with the performance threshold profile failed.

KNAV20255-I

The performance threshold profile will now be deleted. (internal information:{0})

{0}: Internal information

KNAV20256-I

The performance threshold profile was successfully deleted. (internal information:{0})

{0}: Internal information

KNAV20257-I

The performance threshold profile was successfully deleted. (internal information:{0})

{0}: Internal information

KNAV20258-I

An attempt to delete the performance threshold profile failed. (internal information:{0})

{0}: Internal information

KNAV20310-I

There is {0} Resource specified as the argument.

{0}: Number of devices that are specified as arguments

KNAV20312-I

The monitoring mode of the device will now be changed. (device name:{0}, specified mode:{1})

{0}: Name of the device for which the monitoring mode is to be changed

{1}: Specified mode

KNAV20343-I

The device ({1}) was discovered by using the authentication information of the credential ({0}).

{0}: Credential name

{1}: Device name

KNAV20344-I

{0} has no response to "ping".

{0}: IP address

KNAV20345-E

{0} was an invalid Internet Protocol address.

{0}: IP address

KNAV20373-I

The processing to update the status information of the monitored devices finished. (successful:{0}, failed:{1}, skipped:{2})

{0}: Number of devices for which the processing was successful

{1}: Number of devices for which the processing failed

{2}: Number of devices for which the processing was skipped

KNAV20376-I

The status update was skipped because this time is within an interval of the status update. (last update:{0}, effective interval:{1}[s])

{0}: Date and time of last update

{1}: Effective interval (in seconds)

KNAV20378-I

Remove the specified device. (device ID:{0}, device name:{1})

{0}: Device ID

{1}: Device name

KNAV20415-I

The device for the trap reception will now be configured. ({0})

{0}: Target device name

KNAV20419-I

A new device was discovered and registered. (device name:{0}, device type:{1})

{0}: Device name

{1}: Device type

KNAV20431-I

The status of the monitored device is currently being updated.

KNAV20557-I

A notification problem occurred after the configuration information was updated. (device name:{0})

{0}: Device name

KNAV20574-E

The monitoring mode of the virtual machine on the hypervisor was changed. (hypervisor name:{0}, virtual machine name:{1})

{0}: Hypervisor name

{1}: Virtual machine name

KNAV20578-I

The processing to change the monitoring modes of the components will now start. (number of components:{0})

{0}: Number of components

KNAV20579-I

The processing to change the monitoring modes of the components finished. (successful:{0}, failed:{1})

{0}: Number of devices for which the processing was successful

{1}: Number of devices for which the processing failed

KNAV20609-I

The database status is normal.

KNAV20610-I

The email notification regarding the database status was canceled.

KNAV20632-I

The status of the component ({1}) of the device ({0}) changed. (old status:{2}, new status:{3}, details:{4})

{0}: Device name

{1}: Component name

{2}: Old status

{3}: New status

{4}: Detailed information

KNAV20657-I

The database stopped abnormally or was blocked. Remove the cause of the I/O error and then restart the service. If the server cannot be restarted, restore the database.

KNAV20711-W

The database is approaching the maximum disk space capacity. Either reorganize the database, or expand the scale of the database. Please refer to the Help for details.

KNAV20712-W

There is not enough free disk space to automatically increment the database. Either create free disk space of at least {0} MB, or move the database to a disk drive that has sufficient capacity. Please refer to the Help for details.

{0}: Amount of free disk space

KNAV20713-E

The current capacity of the database is insufficient. Please expand the scale of the database. Please refer to the Help for details.

KNAV20714-E

There is not enough free disk space to automatically increment the database. Either create free disk space of at least {0} MB, or move the database to a disk drive that has sufficient capacity. Please refer to the Help for details.

{0}: Amount of free disk space

KNAV20715-E

Not enough free disk space exists for either automatically increment the database or for expanding the scale of the database. The free disk space needs to be at least {0} MB. Move the database to a disk drive that has sufficient capacity, then expand the scale of the database. Please refer to the Help for details.

{0}: Amount of free disk space

KNAV20716-E

The database is full. Please increase the free disk space at the database storage destination, or if the database scale is 'Large', move the database to another disk. Either reorganize the database or expand the scale of the database, except if the database scale is 'Large'. Please refer to the Help for details.

KNAV20717-I

The command setting of Event Action was applied. (file path:"{0}", max count:{1}, timeout:{2})

{0}: Path to the executable file

{1}: Maximum number of concurrent command executions

{2}: Maximum wait time before timeout

KNAV20726-I

The processing time will be reset. (type:{0})

{0}: Processing type

KNAV20727-I

The processing time has been reset.

KNAV20728-I

The processing time could not be reset.

KNAV20758-I

The update processing will be skipped because a temporary connection error occurred. (device name:{0})

{0}: Device name

KNAV20759-I

The status history aggregation was skipped because there is no status history to aggregate.

KNAV20947-I

Data collection by the Collector function is already in progress. (device name:{0})

{0}: Collector name

KNAV20948-I

The processing to change the management statuses of the virtual machines will now start. (number of virtual machines:{0}, operation:{1})

{0}: Number of virtual machines

{1}: Operation

KNAV20949-I

The processing to change the management statuses of the virtual machines finished. (number of virtual machines:{0}, operation:{1})

{0}: Number of virtual machines

{1}: Operation

KNAV20956-I

The processing to collect event information from the monitored devices has started.

KNAV20957-I

The processing to collect event information from the monitored devices finished. (successful:{0}, failed:{1})

{0}: Number of devices for which the processing was successful

{1}: Number of devices for which the processing failed

KNAV20971-I

The collection processing will be skipped because the information collection processing of the Collector function is already being executed. (Collector name:{0})

{0}: Collector name

KNAV20972-I

The processing of the Collector discovery has started.

KNAV20973-I

The processing of the Collector discovery finished.

KNAV20978-W

Event registration might have failed in the processing of the Event Action command. (ANALYTICS_EVENTID:{0}, EXITVALUE:{1})

{0}: Event ID

{1}: Return code

KNAV20983-W

The value of the property key "{1}" set in the template definition file "{0}" is outside the valid input range, so the default value will be used.

{0}: File name

{1}: Key name

KNAV20984-W

The value of the property key "{1}" set in the template definition file "{0}" includes a control character, so the default value will be used.

{0}: File name

{1}: Key name

KNAV20985-W

The value of the property key "{1}" set in the template definition file "{0}" could not be obtained, so the default value will be used.

{0}: File name

{1}: Key name

KNAV20992-W

Processing was interrupted because the number of template definition files that were read in exceeded the upper limit

{0}). Delete unnecessary mail template definition files, and then run the reloadproperty command.

{0}: Number of files

KNAV20993-I

Processing to read the template definition files will now start.

KNAV20994-I

Processing to read the template definition files has ended. (target files:{0}, successfully read files:{0})

{0}: Number of files for which the processing was to be performed

{1}: Number of files for which the processing was successful

KNAV30153-I

Execution of the command (action name:{0}) will now start. Messages output by the command are output immediately after this message.

{0}: Action name

KNAV30154-I

Execution of the command ended. (action name:{0}, command's return code:{1})

{0}: Action name

{1}: Command's return code

KNAV30156-W

The value of the property key "{1}" set in the template definition file "{0}" is not a numerical value, so the default value will be used.

{0}: File name

{1}: Key name

KNAV30165-I

Processing to read the user defined files will now start. (filename:{0})

{0}: File name

KNAV30166-I

Processing to read the user defined files has ended. (filename:{0})

{0}: File name

KNAV30167-W

Ignored the invalid definition in the user defined file. (filename:{0}, row:{1}, detail: {2})

{0}: Filename

{1}: Row

{2}: Detail

KNAV30168-I

Results of applying the custom collector: collector name = {0}, processing = {1}, result = {2}

{0}: Collector name

{1}: Processing

{2}: Result

KNAV30173-I

The update of the custom-collector definition was successful. (collector name:{0})

{0}: Collector name

KNAV30178-I

The folder for custom-collector definitions does not exist. (folder path:{0})

{0}: Folder path

KNAV40028-I

The processing was successful. (operation:{0})

{0}: Operation details

KNAV40031-I

Specified information(operation:{0}, set content:{1})

{0}: Operation details

{1}: Specified settings (arguments)

KNAV40069-W

{0} was skipped.

{0}: Process name

KNAV40070-I

{0} is already in process. It cannot be run simultaneously.

{0}: Process name

KNAV40103-I

No action is required.

KNAV40110-I

Monitoring of the resource ({0}) was disabled.

{0}: Device name

KNAV40111-I

Check whether there are any problems with the resource ({0}) or its management server. After troubleshooting,

enable monitoring of the resource.

{0}: Device name

KNAV40112-I

Collector({0}) was added.

{0}: Collector name

KNAV40113-I

Collector({0}) was modified.

{0}: Collector name

KNAV40114-I

Collector({0}) was deleted.

{0}: Collector name

KNAV50001-I

The adapter started.

KNAV50002-I

The adapter stopped.

KNAV50040-I

Processing finished normally.

KNAV50043-W

A warning is associated with the results of the process.

KNAV50052-I

{0} has no response to the ping.

{0}:IP address

KNAV50468-I

VMware Tools are not installed on the guest OS. Please install VMware Tools on the guest OS, then recollect the host(ESX) again.

KNAV50550-I

Physical port is not found in the SMI-S agent.

KNAV50551-I

The volume cannot be monitored because the number of volumes exceeds {0}.

{0}: Maximum number of SMI-S storage volumes that can be managed

KNAV50650-I

{0}#{1}:{2}

{0}#{1}:{2}

{0}: Class name

{1}: Method name

{2}: Message

KNAV50655-I

Please wait a few minutes, then try again.

KNAV50657-I

Please contact customer support.

KNAV50716-E

Based on the job type, a DSM call sequence was not found.

(job type:{0})

{0}: Job type

KNAV50723-I

The protocol cassette manager started.

KNAV50724-I

The protocol cassette manager stopped.

KNAV50739-I

The adapter process shutdown has started.

KNAV50800-W

Same business key components were detected.(class name : {0}, property : {1}, element class name : {2})

{0}: Class name

{1}: Property name

{2}: Element class name

KNAV50900-I

Hotfix for Microsoft Windows({0})

{0}: Hotfix ID

KNAV60080-I

The request was not found. (request ID :{0}, transferred adapter process ID : {1})

{0}: Request ID

{1}: Adapter ID

KNAV60081-I

The request has reassigned the serial version. (request ID : {0}, old serial version : {1}, new serial version : {2})

{0}: Request ID

{1}: Old serial version

{2}: New serial version

KNAV60082-I

The request had repopulated already. (request ID : {0}, old serial version : {1}, new serial version : {2})

{0}: Request ID

{1}: Old serial version

{2}: New serial version

KNAV60083-I

The salvaged FW_Response of the request from adapter process is null. (request ID : {0}, serial version : {1}, transferred adapter process ID : {2})

{0}: Request ID

{1}: Serial version

{2}: Adapter ID

KNAV60085-I

The output property, ({0}), has a value of {1}.

{0}: Property key name

{1}: Property value

KNAV70089-I

The SEGMENT REUSE value was changed. Table:{0}, Value:{1}

{0}: Table name

{1}: Changed value

(2) Error-level messages

KNAV00100-E

An attempt to initialize the logger failed. ({0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Name of the method that failed to initialize the logger or other comment

KNAV00120-E

An attempt to read the system properties failed.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV00121-E

An attempt to read the file of the system property failed.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV00122-I

The property file cannot be located.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV00123-E

An attempt to obtain the property failed.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV00124-E

An attempt to acquire the value of the key ("{0}") in the properties file failed. Check the value and, if it has been changed, restart the service.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Key name

KNAV00125-E

The property could not be checked.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV00126-W

The default value of the key ("{0}") was used, because the value specified for the key in the properties file could not be acquired. Check the value and, if it has been changed, restart the service.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Key name

KNAV00141-E

An error occurred when converting the message.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV00201-E

An attempt to start the registry server failed.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV00202-E

An attempt to register the RMI registry failed.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV00203-E

An attempt to release the registration of the RMI registry failed.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV00204-E

An attempt to invoke the RMI failed.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV00205-E

The following message was output from Commons-Logging. : {0}

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Message output by Commons-Logging

KNAV00206-E

The following message was output from Commons-Logging. : {0}

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Message output by Commons-Logging

KNAV00400-E

An attempt to initialize the logger instance failed. (output format: {0}, error code: {1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Output format

{1}: Error code

KNAV00401-E

An attempt to delete the control file failed.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV00403-E

An attempt to delete the process status file failed.

(error message: {0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Exception message

KNAV20001-E

An attempt to initialize ({0}) has failed.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Component name

KNAV20002-E

Update processes of the data ({0}) collided with each other. Nothing could be updated.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: String identifying the information that failed to be updated

KNAV20003-E

An error occurred when submitting tasks to the thread pool.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20005-E

A running thread has been interrupted.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20007-E

There is a mistake in the schedule data. (internal information: {0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Internal information

KNAV20008-E

An attempt to terminate ({0}) has failed.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Component name

KNAV20009-E

Invalid Thread ID ({2}) are specified ({0}#{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Class name

{1}: Method name

{2}: Invalid thread ID

KNAV20010-E

There is no thread pool corresponding to the specified Thread ID ({2}) at ({0}#{1}).

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Class name

{1}: Method name

{2}: Invalid thread ID (value given as a character string)

KNAV20018-E

There is a mistake in the configured condition or item.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20023-E

The email server could not be configured.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20027-E

The specified resource does not exist.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20039-E

An attempt to execute the Collector or Discovery function failed.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20040-E

An exception occurred with the scheduler function.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20042-E

A timeout occurred with the demanded process ({0}).

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Process or function name

KNAV20053-E

An attempt to configure mail delivery settings has failed.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20056-E

An attempt to delete the IP range failed.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20057-E

An attempt to acquire the latest discovery log failed.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20058-E

An attempt to cancel the Discovery function failed.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20062-E

During the processing of the event, an exception was generated.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20063-E

An attempt to register an event failed.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20064-W

The event registration has stopped.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20065-E

An attempt to delete events failed.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20067-E

An attempt to update events failed.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20068-E

The events update has stopped.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20069-E

An attempt to notify users failed.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20071-E

An attempt to acquire a Enum{0} matching EventType{1} failed.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Enumerator to be acquired

{1}: Property value of the event

KNAV20084-E

The schedule change was unsuccessful.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20086-E

The status of resource {0} could not be updated.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Resource name

KNAV20087-E

The update to the configuration was unsuccessful.

The resource name in which the failure occurred: {0}

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Resource name

KNAV20090-E

An attempt to update the status has failed.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20096-E

The status of device ({0}) could not be updated.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Device name

If there are multiple devices, the device names are concatenated. The fourth and subsequent devices are not displayed, and the total number of these devices is displayed instead.

KNAV20100-E

The status update notification event has failed.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20125-E

IP Range could not be added.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20126-E

IP Range could not be deleted.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20127-E

IP Range could not be modified.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20128-E

Credential({0}) could not be added.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Credential name

KNAV20129-E

The Collector or Credential could not be deleted.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20130-E

Credential({0}) could not be modified.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Credential name

KNAV20134-E

The default profile could not be applied to the resource. (resource name:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Resource name

KNAV20148-E

E2E information could not be configured.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20151-E

The log in attempt was unsuccessful.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20166-E

The expiration date of the specified session could not be extended.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20171-W

The discovery completion mail could not be sent.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20181-E

The collection of the performance history was unsuccessful.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20194-W

The collection of the performance history has been skipped.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20195-E

The collection of the performance history was unsuccessful.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20200-E

The aggregation of the performance history was unsuccessful.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20202-E

The performance management initialization was unsuccessful.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20204-E

An attempt to stop the performance management was unsuccessful.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20205-E

PerformanceIntegratedData having PerformanceCollectionType:{0} was not found.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Enumerator name of the performance value collection type

KNAV20206-E

PerformanceNonIntegratedData having PerformanceCollectionType:{0} was not found.(PerformanceMetricType:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Enumerator name of the performance value collection type

{1}: Enumerator name of the metric type

KNAV20207-E

There is non-integrated PerformanceCollectionType in the PerformanceIntegratedData class. (Performance Collection Type:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Enumerator name of the performance value collection type

KNAV20208-E

There is integrated PerformanceCollectionType in the PerformanceNonIntegratedData class. (Performance Collection Type:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Enumerator name of the performance value collection type

KNAV20209-E

An attempt to create the performance threshold profile failed. (profile:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Threshold definition name

KNAV20210-E

An invalid threshold value exists. (profile:{0}, metric:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Threshold definition name

{1}: Metric

KNAV20231-E

An attempt to delete the performance threshold profile failed. (internal information:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Internal information

KNAV20235-E

An attempt to update the performance threshold profile failed. (profile:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Threshold profile name

KNAV20241-E

An attempt to add the resource to the performance threshold profile failed.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20259-E

An attempt to register the data in the database failed. (profile:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Threshold profile name

KNAV20260-E

An attempt to update the data in the database failed. (internal information:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Internal information

KNAV20264-E

An attempt to acquire the default performance threshold profile failed. (resource type:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Resource type

KNAV20267-E

An invalid argument is specified.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20275-E

The error occurred in configuration necessary for monitoring. (device name:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Device name

KNAV20277-E

Detailed information about the discovered resource could not be acquired.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20284-E

One or more devices could not be correctly registered. The resources might not be correctly displayed in the resource list in the resource management window. (device names:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Device name

KNAV20287-E

Device information could not be updated because a processing conflict occurred. (device name:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Device name

KNAV20289-E

An attempt to save the detailed information about the device failed. (device name:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Device name

KNAV20332-I

Device information could not be acquired. (internal information:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Internal information

KNAV20334-E

An invalid change in the connection status occurred. (device name:{0}, old connection status:{1}, new connection status:{2}, old monitoring status:{3}, new monitoring status:{4})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Device name

{1}: Previous connection status

{2}: Current connection status

{3}: Previous monitoring status

{4}: Current monitoring status

KNAV20336-E

The processing to consolidate the status history was skipped.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20338-E

An attempt to consolidate the status history failed.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20339-E

An attempt to initialize the resource status determination function failed.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20341-E

The status history could not be registered in the database. (device name:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Device name

KNAV20347-E

The device-status update processing triggered by the SNMP trap failed.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20349-E

The configuration could not be updated.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20350-E

An attempt to update the configuration information for one or more devices failed.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20351-E

An attempt to compare of the old configuration with the new one failed. (device name:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Device name

KNAV20363-I

System has skipped the status update that was triggered by SNMP Trap. (device name:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Device name

KNAV20364-E

An attempt to delete the performance threshold profile failed. An error occurred in the processing to apply the default profile instead of the profile to be deleted. (failed resource:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Resource for which the processing failed

KNAV20365-E

The specified authentication information could not be associated with the search range condition.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20366-E

The association between the authentication information and the search range condition could not be deleted.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20367-E

The association between all of the authentication information and the search range condition could not be deleted.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20368-E

An internal error occurred.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20374-E

An error occurred in the processing to collect the performance history of each device. (device list:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: List of devices for which the processing failed

KNAV20375-E

An error occurred in the processing to collect the performance history of each device. (device list:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: List of devices for which the processing failed

KNAV20391-I

The network type could not be set.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20397-E

The event manager could not be notified of the internal event. (message ID:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Message ID to be sent

KNAV20398-E

An attempt to collect the performance history of each device failed. (internal information:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Internal information

KNAV20403-E

An attempt to acquire performance information from the device failed. (device name:{0}, IP address:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Device name

{1}: IP address

KNAV20404-E

An attempt to collect the performance history for each metric failed. (device name:{0}, component name:{1}, metric:{2})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Device name

{1}: Component name

{2}: Metric name

KNAV20407-E

An attempt to determine the status of the node failed. (internal information:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Internal information

KNAV20408-E

An attempt to monitor the capacity of each file system failed. (device name:{0}, component name:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Device name

{1}: Component name

KNAV20409-E

An attempt to monitor the capacity of each storage system failed. (device name:{0}, component name:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Device name

{1}: Component name

KNAV20410-E

An attempt to delete the performance history failed. (delete start time:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Standard time at which to delete the performance history

KNAV20411-E

An attempt to aggregate the performance history by the component failed. (component id:{0}, compression type:{1}, start time:{2}, end time:{3})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Component ID

{1}: Consolidation unit

{2}: Consolidation start time

{3}: Consolidation end time

KNAV20412-E

An attempt to initialize the performance history failed. (component name:{0}, device type:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Component name

{1}: Device type

KNAV20413-E

An attempt to initialize the performance history of the Hitachi storage system failed. (component name:{0}, number of controllers:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Component name

{1}: Number of controllers

KNAV20414-E

An attempt to refresh the performance management failed.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20416-E

An attempt to determine the performance status failed. (metric:{0}, previous status:{1}, performance value:{2}, warning threshold value:{3}-{4}, error threshold value:{5}-{6})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Performance metric name

{1}: Previous performance status

{2}: Performance value

{3}: Warning threshold value

{4}: Lower limit of the warning threshold range

{5}: Error threshold value

{6}: Lower limit of the error threshold range

KNAV20434-E

An attempt to initialize the scheduler failed.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20436-E

An attempt to configure the schedule ({0}) failed.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Schedule type

KNAV20439-E

An attempt to start the schedule. (schedule type:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Schedule type

The enum.schedulertype string is set as is.

KNAV20441-E

An unexpected error occurred in the schedule management function. (schedule type:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Schedule type

The enum.schedulertype string is set as is.

KNAV20459-E

An attempt to remove the device failed. (device name:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Device name

KNAV20460-E

An attempt to remove one or more devices failed. (device names:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: List of device names

Multiple device names might be set. In such cases, device names are delimited by commas (,).

KNAV20524-E

An attempt to monitor the capacity for each storage filesystem failed. (device name:{0}, component name:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Device name

{1}: Component name

KNAV20530-W

The processing to update the status was skipped. (device ID:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Device ID

KNAV20554-E

An attempt to send the test email failed.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20558-I

Because configuration information first time has not been updated, the performance update processing is skipped.
(device name:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Device name

KNAV20561-I

The status could not be changed, because the configuration information was updated. (device name:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Device name

KNAV20566-E

An error occurred in the configuration necessary for monitoring. (device ID: {0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Device ID

KNAV20568-I

The processing to update the status will be skipped, because the initial update of the configuration information has not been performed. (device name:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Device name

KNAV20572-E

An attempt to delete the device from the E2E information when changing the device type failed. (device name:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Device name

KNAV20573-E

An attempt to update the configuration information when changing the device type failed. (device name:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Device name

KNAV20575-E

An attempt to change the monitoring mode of the virtual machine on the hypervisor failed. (hypervisor name:{0}, virtual machine name:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Hypervisor name

{1}: Virtual machine name

KNAV20580-E

An attempt to change the monitoring modes of the components failed.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20581-E

An attempt to remove related components failed.(target:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Name of the component to be removed

KNAV20582-E

An attempt to remove the component failed.(target:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Name of the component to be removed

KNAV20584-E

An attempt to save the updates to the configuration information failed. (status:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Status in which an attempt was made to update the configuration information

Note: Stopped or Running is set.

KNAV20585-E

An attempt to generate the E2E information failed.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20589-E

The monitoring mode of the device is incorrect. (device name:{0}, monitoring mode:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Device name

{1}: Device monitoring mode

KNAV20597-W

Because the usage rate of the database exceeded the threshold, it resulted in a condition that is similar to a full database.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20598-E

There is insufficient free disk space to expand the database.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20599-E

The database is full.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20608-E

The process for checking the database status has failed.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20614-W

The free disk space that is required to automatically increment the database is becoming limited.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20618-E

The database has been blocked, or it has stopped abnormally.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20620-E

The database cannot be incremented automatically.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20622-E

An automatic increment of the database cannot be completed. Please expand the current database scale so that there is sufficient free disk space.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20630-E

The performance history could not be collected.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20635-E

The expected status was not returned.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20636-E

An attempt to determine the status of the device failed. (device name:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Device name

KNAV20654-E

The IP address of the specified device could not be found.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20658-E

The monitoring modes of the resources could not be changed to {0}. (resources:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Monitoring status

{1}: Resource list

KNAV20662-E

The SNMP Trap receiver failed to start. (UDP Port:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Port number

KNAV20701-E

It failed in the acquisition of "Authentication information with the possibility of the account lock" list.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20702-E

It failed in acquisition of the list of Internet Protocol address guessed that it was SMI-S agent.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20703-E

The discovery process could not be initiated.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20718-E

The EventAction command could not be executed.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20721-E

A time-out occurred when processing the Event Action command.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20729-E

The processing time could not be updated. (schedule type:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Schedule type

KNAV20854-E

An attempt to register the notification profile ({0}) failed.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Profile name

KNAV20855-E

An attempt to update the notification profile ({0}) failed.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Profile name

KNAV20856-E

An attempt to delete the notification profile ({0}) failed.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Profile name

KNAV20938-E

Component statuses could not be aggregated.(device name:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Node name

KNAV20950-E

An attempt to change the management statuses of the virtual machines failed.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20953-E

An attempt to collect the event information failed.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20954-E

An attempt to collect the event information of one or more devices failed.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20958-E

An attempt to collect event information from one or more devices failed. (devices for which collection failed:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Device name

KNAV20959-E

An attempt to collect event information from the device failed. (device name:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Device name

KNAV20961-E

An error occurred in the processing to collect the event information that is necessary for monitoring. (device name:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Device name

KNAV20962-E

An attempt to save the event information of the device failed. (device name:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Device name

KNAV20967-E

The specified Collector does not exist.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20970-E

The information collection processing of the Collector function failed.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV20974-E

The IP address could not be obtained from the host name specified in the collector. (Collector name:{0}, host name:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Collector name

{1}: Host name

KNAV20986-E

An attempt to read the template definition file "{0}" failed.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: File name

KNAV20989-E

The folder "{0}", which stores the template definition file, could not be accessed. Make sure that the folder exists and can be accessed.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Folder path

KNAV20995-E

A specified template does not exist.

KNAV21001-W

Registration processing is skipped, because the application is already registered. (collector name:{0}, application name:{1}, host name:{2}, registered application type:{3}, defined application type:{4})

{0}: Collector name

{1}: Application name

{2}: Host name

{3}: Registered application type

{4}: Defined application type

KNAV21002-E

The processing to collect an application failed. Check the adapter message log.

KNAV21003-W

Registration of at least one application was skipped, because the application definition file was invalid. Check the adapter message log.

KNAV30135-E

An attempt to read the specified template definition file ({0}) failed. Make sure that the file exists and can be accessed.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: File name

KNAV30144-E

An attempt to read the template definition file "{0}" interrupted.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: File name

KNAV30151-E

The Collector could not be added.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV30152-E

The Collector could not be modified.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV30155-E

Execution of the command failed. (action name:{0}, template definition file:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Action name

{1}: Template definition file

KNAV30157-E

The value of the required property key "{0}" is not a numerical value.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Key name

KNAV30159-E

An unexpected error occurred during execution of the command.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV30160-E

Verify that the specified command "{0}" is executable.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: File name

KNAV30161-E

The command timed out and was forcibly stopped. (action name:{0}, template definition file:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Action name

{1}: Template definition file

KNAV30162-E

Revise the timeout period, or revise the specification of the command "{0}".

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: File name

KNAV30163-E

Verify that the specified command "{0}" is executable. If the problem persists, contact your system administrator.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: File name

KNAV30164-E

The user defined file format is invalid. (filename:{0}, row:{1}, detail: {2})

{0}: File name

{1}: Row

{2}: Detail

KNAV30169-E

Results of applying the custom collector: collector name = {0}, processing = {1}, invalid key = {2}

{0}: Collector name

{1}: Processing

{2}: Key

KNAV30170-E

The file of custom-collector definitions does not exist. (collector name:{0})

{0}: Collector name

KNAV30171-E

A custom-collector definition failed to load.

KNAV30172-E

The version of the format of the custom-collector definition is invalid. (collector name:{0}, invalid format version that was specified:{1})

{0}: Collector name

{1}: Format version

KNAV30174-E

The list of custom-collector folders could not be obtained.

KNAV30175-E

This is not a folder. (path:{0})

{0}: Folder path

KNAV30176-E

The length of the name of the custom-collector folder is invalid. (collector name:{0})

{0}: Collector name

KNAV30177-E

The name of the custom-collector folder contains invalid characters. (collector name:{0})

{0}: Collector name

KNAV30179-E

Another collector is already using the specified collector name. (collector name:{0})

{0}: Collector name

KNAV30180-E

The custom-collector definition contains invalid characters. (collector name:{0}, key:{1})

{0}: Collector name

{1}: Key

KNAV30181-E

An unexpected exception occurred. (collector name:{0})

{0}: Collector name

KNAV30182-E

The length of the custom-collector definition is invalid. (collector name:{0}, key:{1})

{0}: Collector name

{1}: Key

KNAV30183-E

A custom-collector definition failed to load. (collector name:{0}, file path:{1})

{0}: Collector name

{1}: File path

KNAV30184-E

A required key is not defined. (file:{0}, definition key:{1})

{0}: File path

{1}: Key

KNAV40001-E

Invalid argument ({0}) is specified in ({1}#{2})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Name and value of the invalid argument

{1}: Class name

{2}: Method name

KNAV40003-E

Object ({0}) not found.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Class name of the object

KNAV40005-E

There are unexpected enumerator ({1}) in enumerated type ({0}).

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Enumerated type

{1}: Enumerator

KNAV40006-E

An unexpected error ({2}) occurred at {0}#{1}.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Name of the class to be called

{1}: Name of the method to be called

{2}: Description of the exception (in English)

KNAV40010-E

An attempt to insert or update the data has failed.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV40011-E

An attempt to insert or update the data {0} has failed, because of the database re-execution error.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: String identifying the information that failed to be registered

KNAV40012-E

An attempt to delete the data from the database has failed.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV40023-W

{0} is not acquired.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: String identifying the information to be obtained

KNAV40025-E

{0} was skipped.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Processing name

KNAV40029-E

The processing was unsuccessful. (operation:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Operation details

KNAV40035-E

The device information could not be found. (device name:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Device name

KNAV40038-E

An attempt to update the device information failed. (device name:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Device name

KNAV40062-E

An attempt to obtain the data failed.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV40067-E

The message was not able to be generated.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV40068-E

The event was not able to be issued.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV40071-E

An attempt to apply the profile to the device failed. (device name:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Device name

KNAV40097-E

The processing for task registration failed.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV40098-W

The processing for task registration has stopped.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV40104-E

{0} could not be created.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Target name

KNAV40105-E

{0} could not be modified.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Target name

KNAV40109-E

The processing to acquire information from the resource took too long. (device name:{0}, resource type:{1})

{0}: Device name

{1}:Resource type

KNAV50010-W

Although the adapter started, the service has not yet started.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV50011-E

A time-out occurred when acquiring the IP address and processing the information, using the specified protocol. (Protocol:{0}, IP address:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Protocol

{1}: IP address

KNAV50012-E

An error occurred in the device discovery processing of the Collector or Discovery function. (IP address:{0}, credential name:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

{1}: Credential name

KNAV50013-E

An error occurred while acquiring the configuration information. (IP address:{0}, device name:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

{1}: Device name

KNAV50014-E

An error occurred while acquiring the status information. (IP address:{0}, device name:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

{1}: Device name

KNAV50015-E

An error occurred while acquiring the performance. (IP address:{0}, device name:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

{1}: Device name

KNAV50016-E

An error occurred while registering the trap.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV50024-E

Because frequent time-outs occur when acquiring information using the specified protocol, no more information can be acquired by using the protocol. (Protocol:{0}, IP address:{1}, list of time-out IP addresses:{2})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Protocol

{1}: IP address

{2}: List of IP addresses for which timeout occurred

KNAV50027-E

An error occurred during the ping. (start IP address:{0}, end IP address:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Starting IP address

{1}: Ending IP address

KNAV50028-E

Execution permissions for the device could not be acquired. (IP address:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

KNAV50031-E

The protocol rights could not be obtained.(Protocol:{0}, IP address:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Type of information acquisition

{1}: IP address

KNAV50036-E

Because frequent time-outs occur when acquiring information using the specified protocol, no more information can be acquired by using the protocol. (Protocol:{0}, IP address:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Protocol

{1}: IP address

KNAV50039-E

No credentials for the protocol were set. (IP address : {0}, Protocol : {1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

{1}: Protocol

KNAV50041-E

Processing ended abnormally.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV50044-E

The system file could not be read.(File : {0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: File path

KNAV50048-E

An error occurred during the shutdown procedure. (IP address:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

KNAV50049-E

An error occurred during the reboot procedure. (IP address:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

KNAV50050-E

An internal error occurred. (start IP address:{0}, end IP address:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Starting IP address

{1}: Ending IP address

KNAV50053-E

An error occurred while controlling the power. (IP address:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

KNAV50054-E

An error occurred while controlling the LED. (IP address:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

KNAV50055-E

An error occurred during the ipmiutil command operation. (IP address:{0} ,operation:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

{1}: Operation

KNAV50056-E

An error occurred while acquiring the event log information. (IP address:{0}, device name:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

{1}: Device name

KNAV50057-E

An error occurred while acquiring the sensor information. (IP address:{0}, device name:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

{1}: Device name

KNAV50058-E

An error occurred while controlling the BMC user. (IP address:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

KNAV50061-E

The specified choice is invalid. (value:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Specified choice

KNAV50062-E

The value is unexpected.(name:{0}, value:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Parameter name

{1}: Parameter value

KNAV50100-E

An attempt to establish a connection by using the communication protocol for managing Hitachi storage systems failed. (IP address:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

KNAV50101-E

This is an unsupported Hitachi storage. (IP address:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

KNAV50102-E

An authentication error occurred. This prevented information from being acquired by the Hitachi storage management protocol. (IP address:{0}, credential name:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

{1}: Credential name

KNAV50103-E

An attempt to acquire information by using the communication protocol for managing Hitachi storage systems failed, because another user is already logged in by using that protocol. (IP address:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

KNAV50104-E

An attempt to acquire information by using the communication protocol for managing Hitachi storage systems failed,

because you do not have the necessary permissions. (IP address:{0}, credential name:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

{1}: Credential name

KNAV50105-E

The information was acquired using the communication protocol for the Hitachi storage management; however, the equipment is different from what was previously acquired. (IP address:{0}, old serial number:{1}, new serial number:{2})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

{1}: Previous serial number

{2}: Current serial number

KNAV50106-E

An attempt to acquire information by using the communication protocol for managing Hitachi storage systems failed, because sufficient memory could not be secured. (IP address:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

KNAV50107-E

An attempt to acquire information by using the communication protocol for managing Hitachi storage systems failed, because an unknown error occurred. (IP address:{0}, credential name:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

{1}: Credential name

KNAV50108-E

The environment variable STONAVM_HOME could not be set.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV50151-E

An attempt to acquire detailed information about the device failed. (device name:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

KNAV50152-E

An attempt to acquire the status of the device failed. (device name:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

KNAV50153-E

An attempt to acquire performance information about the device failed. (device name:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

KNAV50162-E

DCOM on the Management Server is not enabled.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV50163-E

The HBA storage device driver installed on the server might cause problems. Update the device driver. (IP address:{0}, vendor:{1}, version:{2})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

{1}: Vendor

{2}: Version

KNAV50164-E

The IP address is not responding. (IP address:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

KNAV50168-E

The system has failed in the WMI connection. (IP address:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

KNAV50169-E

The WMI authentication was unsuccessful. (IP address:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

KNAV50170-E

You do not have privileges for the WMI connection. (IP address:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

KNAV50171-E

The Connecting IP address is a virtual server address. (IP address:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

KNAV50172-E

The format of the device ID is invalid. (IP address:{0}, device ID:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

{1}: Device ID

KNAV50173-E

The device access parameter is invalid. (device access parameter:{0}, credential name:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Device access parameter name

{1}: Credential name

KNAV50174-E

When the same virtual machine name existed, the same performance object identifier was made by Windows, so it wasn't possible to specify the virtual machine as which Performance value is set. (IP address:{0}, virtual machine name:{1}, number of virtual machine:{2})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

{1}: Duplicate virtual machine name

{2}: Number of virtual machines with the same name

KNAV50175-E

The same performance object identifier was made by Windows, so it wasn't possible to the virtual disk as which Performance value is set. (IP address:{0}, performance object ID:{1}, pass of virtual disk:{2})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

{1}: Duplicate ID

{2}: List of virtual disk file paths

KNAV50200-E

The trap reception could not be started.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV50201-E

A notification about the trap reception could not be sent.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV50202-E

The SNMP could not be initialized.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV50203-E

SNMP could not be stopped.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV50204-E

The SNMP request was sent, but no response was returned during the defined time. (IP address:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

KNAV50205-E

SNMP packets could not be sent. (IP address:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

KNAV50206-E

The MIB of SNMP, which is necessary for monitoring, is unsupported. (IP address:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

KNAV50207-E

The information was obtained using SNMP; however, the equipment differs from what was previously acquired because it was changed or the port was added/removed. (IP address:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

KNAV50208-E

Although the system acquired the information via SNMP, this is an unsupported model. (IP address:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

KNAV50250-E

The email could not be sent.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV50300-E

A timeout error occurred in the processing to connect to the device by using the SMI-S WBEM credential. (URL:{0}, credential name:{1}, namespace:{2})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: URL of the device

{1}: Credential name

{2}: Namespace

KNAV50301-E

An attempt to connect to the device by using the SMI-S WBEM credential failed. (URL:{0}, credential name:{1}, namespace:{2})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: URL of the device

{1}: Credential name

{2}: Namespace

KNAV50302-E

The request to connect to the device by using the SMI-S WBEM credential was denied. (URL:{0}, credential name:{1}, namespace:{2})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: URL of the device

{1}: Credential name

{2}: Namespace

KNAV50303-E

The namespace specified in the SMI-S WBEM credential does not exist. (URL:{0}, credential name:{1}, namespace:{2})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: URL of the node

{1}: Credential name

{2}: Namespace

KNAV50304-E

An unknown error occurred in the processing to connect the device by using the SMI-S WBEM credential. (URL:{0}, credential name:{1}, namespace:{2})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: URL of the device

{1}: Credential name

{2}: Namespace

KNAV50305-I

The SMI-S device could not be found. (URL:{0}, credential name:{1}, namespace:{2})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: URL of the device

{1}: Credential name

{2}: Namespace

KNAV50306-W

The SMI-S discovery processing was skipped, because a connection timeout error occurred. (port:{0}, credential

name:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Port number

{1}: Credential name

KNAV50310-E

A timeout error occurred while connecting to the SMI-S storage. (URL:{0}, device name:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: URL of the SMI-S provider

{1}: Device name

KNAV50311-E

Connection to the SMI-S storage was unsuccessful.(URL:{0}, device name:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: URL of the SMI-S provider

{1}: Device name

KNAV50312-E

The connection to the SMI-S storage was denied. (URL:{0}, user ID:{1}, device name:{2})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: URL of the SMI-S provider

{1}: User ID

{2}: Device name

KNAV50313-E

The SMI-S storage does not exist in the specified namespace. (URL:{0}, device name:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: URL of the SMI-S provider

{1}: Device name

KNAV50314-E

An unexpected error occurred while connecting to the SMI-S storage. (URL:{0}, device name:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: URL of the SMI-S provider

{1}: Device name

KNAV50315-E

The SMI-S storage could not be found. (URL:{0}, device name:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: URL of the SMI-S provider

{1}: Device name

KNAV50320-E

A timeout error occurred while connecting to the FC switch. (URL:{0}, device name:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: URL of the SMI-S provider

{1}: Device name

KNAV50321-E

An attempt to connect to the FC Switch has failed. (URL:{0}, device name:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: URL of the SMI-S provider

{1}: Device name

KNAV50322-E

The connection to the FC switch was denied. (URL:{0}, user ID:{1}, device name:{2})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: URL of the SMI-S provider

{1}: User ID

{2}: Device name

KNAV50323-E

The FC switch does not exist in the specified namespace. (URL:{0}, device name:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: URL of the SMI-S provider

{1}: Device name

KNAV50324-E

An unexpected error occurred while connecting to the FC switch. (URL:{0}, device name:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: URL of the SMI-S provider

{1}: Device name

KNAV50325-E

The FC switch could not be found. (URL:{0}, device name:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: URL of the SMI-S provider

{1}: Device name

KNAV50326-E

The FC switch port could not be found. (URL:{0}, device name:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: URL of the SMI-S provider

{1}: Device name

KNAV50327-W

The FC switch port could not be acquired, so the system will try to acquire it again. (URL:{0}, device name:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: URL of the SMI-S provider

{1}: Device name

KNAV50330-W

Although an error occurred when acquiring the component, the process continued. ({0}, {1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Component name

{1}: Error details

KNAV50331-E

The specified method is not supported by the WBEM server.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV50332-E

The specified parameters are not supported by the WBEM server.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV50333-E

Because the WBEM server is in the process of shutting down, the requested operation can not be processed.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV50334-E

The specified context is already closed, it does not exist, or it is incorrect.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV50335-E

The SMIS session has been closed.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV50336-E

The resource limits of the WBEM server have been exceeded. The operation stopped.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV50350-E

The device is not associated with an IP address. (device name:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Resource ID

KNAV50351-E

The value of the connection information of the applicable device is null.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV50352-E

The connection information of the applicable device is not supported. (connection information:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Class name of the connection information

KNAV50361-E

The device is not a target device of the shutdown and reboot functions. (IP address:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

KNAV50401-E

The SSH connection was unsuccessful. (IP address:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

KNAV50407-E

The device IDs are different. (IP address:{0}, old device ID:{1}, new device ID:{2})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

{1}: Old device ID

{2}: New device ID

KNAV50408-E

An unexpected error occurred during SSH connection. (IP address:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

KNAV50409-E

Although the SSH connection succeeded, this is an unsupported model. (IP address:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

KNAV50410-E

There is no response when using the SSH protocol from the server. (IP address:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

KNAV50411-E

A communication error occurred during the SSH connection. (IP address:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

KNAV50412-E

There was no server response during the SSH connection. (IP address:{0}, command ID:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

{1}: Command ID

KNAV50413-E

The SSH authentication was unsuccessful. (IP address:{0}, credential name:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

{1}: Credential name

KNAV50416-I

The command could not be executed. (IP address:{0}, command:{1}, response:{2})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address of the connection destination

{1}: Command that failed to be executed

{2}: Response of the command

KNAV50418-E

An error occurred while information was being acquired. (The command response data may have been reached. command : {0}, size : {1}). Check the configuration of the collector and the status of the target host. If no problem is found, restart the product and try the operation again.

{0}: Command

{1}: Response data size

KNAV50419-E

An error occurred while information was being acquired. (The SSH public key authentication was failed. IP address : {0}, credential : {1}). Check the configuration of the collector and the status of the target host. If no problem is found, restart the product and try the operation again.

{0}: IP address

{1}: Credential Name

KNAV50420-E

An error occurred while information was being acquired. (The SSH authentication invalid. IP address : {0}, credential : {1}). Check the configuration of the collector and the status of the target host. If no problem is found, restart the product and try the operation again.

{0}: IP address

{1}: Credential Name

KNAV50421-E

An error occurred while information was being acquired. (The SSH public key authentication was unsuccessful. IP address : {0}, credential : {1}). Check the configuration of the collector and the status of the target host. If no problem is found, restart the product and try the operation again.

{0}: IP address

{1}: Credential Name

KNAV50422-E

An error occurred while information was being acquired. (The SSH keyboard-interactive authentication was failed. IP address : {0}, credential : {1}). Check the configuration of the collector and the status of the target host. If no problem is found, restart the product and try the operation again.

{0}: IP address

{1}: Credential Name

KNAV50423-E

An error occurred while information was being acquired. (The SSH keyboard-interactive authentication was unsuccessful. IP address : {0}, credential : {1}). Check the configuration of the collector and the status of the target host. If no problem is found, restart the product and try the operation again.

{0}: IP address

{1}: Credential Name

KNAV50424-E

An error occurred while information was being acquired. (The callback factory class was not specified. IP address : {0}, credential : {1}). Check the configuration of the collector and the status of the target host. If no problem is found, restart the product and try the operation again.

{0}: IP address

{1}: Credential Name

KNAV50425-E

An error occurred while information was being acquired. (The callback factory class was not found. IP address : {0}, credential : {1}). Check the configuration of the collector and the status of the target host. If no problem is found, restart the product and try the operation again.

{0}: IP address

{1}: Credential Name

KNAV50426-E

An error occurred while information was being acquired. (The callback factory class was incorrected. IP address : {0}, credential : {1}). Check the configuration of the collector and the status of the target host. If no problem is found, restart the product and try the operation again.

{0}: IP address

{1}: Credential Name

KNAV50427-E

An error occurred while information was being acquired. (An error has occurred when callback constructor. IP address : {0}, credential : {1}). Check the configuration of the collector and the status of the target host. If no problem is found, restart the product and try the operation again.

{0}: IP address

{1}: Credential Name

KNAV50428-E

An error occurred while information was being acquired. (An attempt to acquire instance failed. IP address : {0}, credential : {1}). Check the configuration of the collector and the status of the target host. If no problem is found, restart the product and try the operation again.

{0}: IP address

{1}: Credential Name

KNAV50429-E

An error occurred while information was being acquired. (The instance is not exist. IP address : {0}, credential : {1}). Check the configuration of the collector and the status of the target host. If no problem is found, restart the product and try the operation again.

{0}: IP address

{1}: Credential Name

KNAV50450-E

The URL of the vCenter server could not be accessed. (URL:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: URL of the vCenter server

KNAV50451-E

The authentication of the vCenter server was unsuccessful. (URL:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: URL of the vCenter server

KNAV50452-E

The connection to the vCenter Server was denied. (URL:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: URL of the vCenter server

KNAV50453-E

An unexpected error occurred when obtaining information from the vCenter server. (URL:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: URL of the vCenter server

KNAV50456-E

A communication failure occurred when obtaining information from the vCenter server. (URL:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: URL of the vCenter server

KNAV50459-E

Information was acquired from the vCenter server, but the acquired device ID is different from the previously acquired device ID. (URL:{0}, old device ID:{1}, new device ID:{2})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: URL of the vCenter server

{1}: Old device ID

{2}: New device ID

KNAV50469-W

Configuration information for the virtual machine could not be obtained. (virtual machine name:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Virtual machine name

KNAV50472-E

The information for updating a vCenterServer resource could not be obtained because the specified IP address is not the vCenter Server. (specified IP address:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Specified IP address

KNAV50474-E

Creation of an SSL socket factory failed because the SunJSSE provider was not registered in the security provider list. (URL:{0}, credentials:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: URL of the connection-destination server

{1}: Credential name

KNAV50475-E

Creation of an SSL socket factory failed because the SSL socket factory is not implemented correctly. (URL:{0}, collector name:{1}, SSL socket factory:{2})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: URL of the connection-destination server

{1}: Collector name

{2}: SSL socket factory name

KNAV50476-E

Creation of an SSL socket factory failed because the SSL socket factory was not found. (URL:{0}, collector name:{1}, SSL socket factory:{2})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: URL of the connection-destination server

{1}: Collector name

{2}: SSL socket factory name

KNAV50477-E

Creation of an SSL socket factory failed because the SSL socket factory threw an exception. (URL:{0}, collector name:{1}, SSL socket factory:{2})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: URL of the connection-destination server

{1}: Collector name

{2}: SSL socket factory name

KNAV50478-E

Failed to connect to vCenter Server. (URL:{0}, Collector name:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: URL of the connection-destination server

{1}: Collector name

KNAV50500-E

An unsupported generic component was detected.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV50552-W

The physical (iSCSI) could not be monitored. (device name:{0}, port:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Device name

{1}: Port number

KNAV50554-W

Unused physical port (iSCSI) was detected. (device name:{0}, port:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Device name

{1}: Port number

KNAV50600-E

An unexpected error occurred in IPMI. (IP address : {0}, user ID : {1}, port : {2})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

{1}: User ID

{2}: Port number

KNAV50601-E

The IPMI request was sent, but no response was returned during the defined time. (IP address : {0}, user ID : {1}, port : {2})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

{1}: User ID

{2}: Port number

KNAV50602-E

The user ID does not have Administrator authority for IPMI. (IP address : {0}, user ID : {1}, port : {2})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

{1}: User ID

{2}: Port number

KNAV50603-E

The device does not support the use of IPMI. (IP address:{0}, port:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

{1}: Port number

KNAV50604-E

A user ID or a password of the IPMI is wrong. (IP address : {0}, user ID : {1}, port : {2})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

{1}: User ID

{2}: Port number

KNAV50605-E

The IPMI request was sent, but it was not received at the port. (IP address : {0}, port : {1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

{1}: Port number

KNAV50606-E

The device does not support the authentication type of the IPMI that can be used with this product. (IP address:{0}, port:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

{1}: Port number

KNAV50611-E

The RMCP+ protocol is not supported for the IPMI target.(IP address:{0}, credential:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

{1}: Credential

KNAV50612-E

The user ID is invalid and cannot be used for the IPMI connection. (IP address:{0}, credential:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

{1}: Credential

KNAV50613-E

The password is invalid and cannot be used for the IPMI connection. (IP address:{0}, credential:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

{1}: Credential

KNAV50614-E

Because the BMC Key is not specified, the IPMI connection cannot be established. (IP address:{0}, credential:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

{1}: Credential

KNAV50615-E

The BMC Key is invalid and cannot be used for the IPMI connection. (IP address:{0}, credential:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

{1}: Credential

KNAV50616-E

The Cipher Suite ID is not supported for the target. (IP address:{0}, credential:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

{1}: Credential

KNAV50700-E

Information could not be acquired from the common-library. (type:{0}, IP address:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Execution type

{1}: IP address

KNAV50701-E

An error occurred when acquiring information about the session. (type:{0}, IP address:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Execution type

{1}: IP address

KNAV50702-E

An error occurred in the processing to discover devices. (DSM ID:{0}, function ID:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: DSM ID

{1}: Function ID

KNAV50703-E

A unknown error occurred.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV50704-E

The credential that was used for the Collector or Discovery function could not be found. (DSM ID:{0}, IP address:{1}, discovered DSM IDs:{2})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: ID of the DSM that was running

{1}: IP address of the DSM that was running

{2}: List of DMS IDs included in AccessPath

KNAV50705-E

A null value is not a valid entry for the DSMCredential object.(DSMID: {0}, IP address: {1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: DSM ID of the invalid DSM Credential object

{1}: IP address of the invalid AccessPoint object

KNAV50706-E

An invalid argument was identified for the job. (job type: {0}, DSMID: {1}, argument Name: {2}, value: {3})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Job that was called

{1}: ID of the DSM that was running

{2}: Name of the invalid argument

{3}: Value of the argument

KNAV50707-E

Could not find the specified class.

(class:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Class that could not be found

KNAV50708-E

The class cannot be used to implement IDeviceSupportModule.

(class:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Class that cannot implement IDeviceSupportModule

KNAV50709-E

The instance was not found.

(module ID:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Module ID

KNAV50710-E

The class could not be instantiated.

(class:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Class that failed to be instantiated

KNAV50711-E

The class could not be accessed.

(class:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Class that failed to be accessed

KNAV50712-E

The thread function could not be initiated.

(thread ID:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Thread ID

KNAV50713-E

The thread counter reached its limit.

(Key:{0}, IPAddress:{1}, PerIpStatus:{2})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Key

{1}: IP address

{2}: Status of each IP address

KNAV50714-E

The thread counter reached the max for each IP address.

(Key:{0}, IPAddress:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Key

{1}: IP address

KNAV50715-E

Invalid Arguments.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV50717-E

Could not create a session manager.

(IP Address:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

KNAV50718-E

An invalid argument is specified.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV50720-E

The specified object is incorrect.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV50721-E

The IP address specified for the object is invalid. (IP address:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

KNAV50725-E

An initialization error occurred.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV50735-E

The session builder could not be initialized.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV50737-E

An invalid value was specified for the license key.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV50738-E

The SSH connection is invalid.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV50740-E

An initialization error occurred.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV50745-E

The WMI authentication was unsuccessful. (IP address:{0}, credential name:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

{1}: Credential name

KNAV50746-E

You do not have authority to change the WMI connection. (IP address:{0}, credential name:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

{1}: Credential name

KNAV50747-E

The device access parameter is invalid. (credential name:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Credential name

KNAV50748-E

A timeout error occurred in the processing to connect to the device by using the SMI-S WBEM credential. (URL:{0}, credential name:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: URL of the device

{1}: Credential name

KNAV50749-E

An attempt to connect to the device by using the SMI-S WBEM credential failed. (URL:{0}, credential name:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: URL of the device

{1}: Credential name

KNAV50750-E

The request to connect to the device by using the SMI-S WBEM credential was denied. (URL:{0}, credential name:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: URL of the device

{1}: Credential name

KNAV50751-E

The namespace specified in the SMI-S WBEM credential does not exist. (URL:{0}, credential name:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: URL of the node

{1}: Credential name

KNAV50752-E

An unexpected error occurred in the processing to connect to the device by using the SMI-S WBEM credential. (URL:{0}, credential name:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: URL of the device

{1}: Credential name

KNAV50753-E

An unexpected error occurred in IPMI.(IP address : {0}, credential name : {1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

{1}: Credential name

KNAV50754-E

The IPMI request was sent, but no response was returned during the defined time. (IP address : {0}, Credential name : {1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

{1}: Credential name

KNAV50755-E

The user ID does not have Administrator authority for IPMI.(IP address : {0}, Credential name : {1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

{1}: Credential name

KNAV50756-E

The device does not support the use of IPMI. (IP address:{0}, credential name:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

{1}: Credential name

KNAV50757-E

Either the user ID or the password of the IPMI is wrong.(IP address : {0}, credential name : {1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

{1}: Credential name

KNAV50758-E

The IPMI request was sent, but it was not received at the port. (IP address : {0}, credential name : {1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

{1}: Credential name

KNAV50759-E

The device does not support the authentication type of the IPMI that can be used with this product. (IP address:{0}, credential name:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

{1}: Credential name

KNAV50760-E

The IPMI request was sent, but the device is in a busy state.(IP address : {0}, credential name : {1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

{1}: Credential name

KNAV50761-E

The WMI authentication was unsuccessful. (IP address:{0}, credential name:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

{1}: Credential name

KNAV50762-E

You do not have authority to change the WMI connection. (IP address:{0}, credential name:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

{1}: Credential name

KNAV50763-E

The device access parameter is invalid. (credential name:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Credential name

KNAV50764-E

The authentication of the vCenter server was unsuccessful. (URL:{0}, collector name:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: URL of the vCenter server

{1}: Collector name

KNAV50765-E

The connection to the vCenter Server was denied. (URL:{0}, collector name:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: URL of the vCenter server

{1}: Collector name

KNAV50766-E

An unexpected error occurred when obtaining information from the vCenter server. (URL:{0}, collector name:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: URL of the vCenter server

{1}: Collector name

KNAV50767-E

A communication failure occurred when obtaining information from the vCenter server. (URL:{0}, collector name:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: URL of the vCenter server

{1}: Collector name

KNAV50768-E

The connection to the SMI-S storage was denied. (URL:{0}, credential name:{1}, device name:{2})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: URL of the SMI-S provider

{1}: Credential name

{2}: Device name

KNAV50769-E

The connection to the FC switch was denied. (URL:{0}, credential name:{1}, device name:{2})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: URL of the SMI-S provider

{1}: Credential name

{2}: Device name

KNAV50770-E

The library could not load.{0}

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Absolute path of the library that was assembled after the library failed to load

KNAV50773-E

The property value is invalid.(key:{0}, value:{1}, limit:{2})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Specified key

{1}: Specified value
{2}: Allowable values

KNAV50774-E

No authority exists for VLAN information using the SNMP protocol.(IP address:{0}, credential name:{1}, VLAN ID:{2})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address
{1}: Credential name
{2}: VLAN ID

KNAV50775-E

The MIB that is defined in SNMP and that is necessary for management is not supported. (IP address:{0}, credential name:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address
{1}: Credential name

KNAV50776-E

The device is not supported. (IP address:{0}, credential name:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address
{1}: Credential name

KNAV50778-E

An error occurred while acquiring the matching key patterns.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV50782-E

Currently, the connected target is the vCenter Server. However, VMware DSM does not support the vCenter Server. (IP Address: {0}, collector name: {1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

{1}: Credential name

KNAV50783-E

An error occurred during the collection of performance information of the virtual host, because several virtual hosts have same UUID. (UUID: {0}, virtual host name: {1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Duplicate UUID

{1}: Virtual host name

KNAV50785-E

The specified credential is invalid. (parameter:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Parameter

KNAV50786-E

No authority exists using the SNMP protocol. (Type:AuthorizationError, IP address:{0}, credential name:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

{1}: Credential name

KNAV50787-E

A problem occurred during the SNMP certification. (Type:usmStatsUnsupportedSecLevels, IP address:{0}, credential name:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

{1}: Credential name

KNAV50788-E

An error occurred in SNMP. (Type:usmStatsNotInTimeWindows, IP address:{0}, credential name:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

{1}: Credential name

KNAV50789-E

A problem occurred during the SNMP certification. (Type:usmStatsUnknownUserNames, IP address:{0}, credential name:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

{1}: Credential name

KNAV50790-E

An error occurred in SNMP. (Type:usmStatsUnknownEngineIDs, IP address:{0}, credential name:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

{1}: Credential name

KNAV50791-E

A problem occurred during the SNMP certification. (Type:usmStatsWrongDigests, IP address:{0}, credential name:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

{1}: Credential name

KNAV50792-E

A problem occurred during the SNMP certification. (Type:usmStatsDecryptionErrors, IP address:{0}, credential name:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

{1}: Credential name

KNAV50793-E

An unexpected error occurred in SNMP. (IP address:{0}, credential name:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

{1}: Credential name

KNAV50794-E

The MIB of SNMP, which is necessary for monitoring, is unsupported. (IP address:{0}, credential name:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

{1}: Credential name

KNAV50795-E

SNMP packets could not be sent. (IP address:{0}, credential name:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

{1}: Credential name

KNAV50796-E

The SNMP request was sent, but no response was returned during the defined time. (IP address:{0}, credential name:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

{1}: Credential name

KNAV50798-E

COM could not be initialized.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV50801-E

The error occurred in login processing of the destination server. (URL:{0}, collector name:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: URL of the connection-destination server

{1}: Collector name

KNAV50802-E

Method should not be run after the session has been closed.(IP address : {0}, credential name: {1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

{1}: Credential name

KNAV50803-E

The connection attempt failed. Check the status of the target host, and then try the operation again. (target host : {0}, credential name : {1})

{0}: Target host

{1}: Credential name

KNAV50804-E

The login attempt failed. Check the configuration of the collector, and then try the operation again. (target host : {0}, credential name : {1})

{0}: Target host

{1}: Credential name

KNAV50805-E

An error occurred while information was being acquired. (Another server is already created session. IP address : {0}, credential name : {1}). Check the configuration of the collector and the status of the target host. If no problem is found, restart the product and try the operation again.

{0}: IP address

{1}: Credential name

KNAV50806-E

An error occurred while information was being acquired. (Another server is already running service. IP address : {0}, service name : {1}). Check the configuration of the collector and the status of the target host. If no problem is found, restart the product and try the operation again.

{0}: IP address

{1}: Service name

KNAV50807-E

An error occurred while information was being acquired. (Launcher does not exist. IP address : {0}, launcher path :

{1}). Check the configuration of the collector and the status of the target host. If no problem is found, restart the product and try the operation again.

{0}: IP address

{1}: Launcher path

KNAV50808-E

An error occurred while information was being acquired. (An attempt to create the launcher folder failed. IP address : {0}). Check the configuration of the collector and the status of the target host. If no problem is found, restart the product and try the operation again.

{0}: IP address

KNAV50809-E

An error occurred while information was being acquired. (An attempt to transfer the launcher failed. IP address : {0}, launcher path : {1}). Check the configuration of the collector and the status of the target host. If no problem is found, restart the product and try the operation again.

{0}: IP address

{1}: Launcher path

KNAV50810-E

An error occurred while information was being acquired. (An attempt to register the setting service failed. IP address : {0}, service name : {1}). Check the configuration of the collector and the status of the target host. If no problem is found, restart the product and try the operation again.

{0}: IP address

{1}: Service name

KNAV50811-E

An error occurred while information was being acquired. (The session could not be opened. IP address : {0}, credential name : {1}). Check the configuration of the collector and the status of the target host. If no problem is found, restart the product and try the operation again.

{0}: IP address

{1}: Credential name

KNAV50812-E

Authentication on the target host failed. Check the relevant user privileges. (target host : {0}, credential name : {1})

{0}: Target host

{1}: Credential name

KNAV50813-E

The connection attempt failed. Check the status of the target host, and then try the operation again. (target host : {0}, credential name : {1})

{0}: IP address

{1}: Credential name

KNAV50814-E

An error occurred while information was being acquired. (The property was invalid. key : {0}, value : {1}). Check the configuration of the collector and the status of the target host. If no problem is found, restart the product and try the operation again.

{0}: Key name

{1}: Value

KNAV50815-E

An error occurred while information was being acquired. (An attempt to transfer the file failed. IP address : {0}, credential name : {1}, file path : {2}). Check the configuration of the collector and the status of the target host. If no problem is found, restart the product and try the operation again.

{0}: IP address

{1}: Credential name

{2}: File path

KNAV50816-E

An error occurred while information was being acquired. (The path was not absolute path. path : {0}). Check the

configuration of the collector and the status of the target host. If no problem is found, restart the product and try the operation again.

{0}: Path

KNAV50817-E

An error occurred while information was being acquired. (The path was not relative path. path : {0}). Check the configuration of the collector and the status of the target host. If no problem is found, restart the product and try the operation again.

{0}: Path

KNAV50818-E

An error occurred while information was being acquired. (An attempt to execute command failed. IP address : {0}, credential name : {1}, command : {2}). Check the configuration of the collector and the status of the target host. If no problem is found, restart the product and try the operation again.

{0}: IP address

{1}: Credential name

{2}: Command

KNAV50819-E

An error occurred while information was being acquired. (An attempt to acquire command result status failed. IP address : {0}, credential name : {1}, command ID : {2}). Check the configuration of the collector and the status of the target host. If no problem is found, restart the product and try the operation again.

{0}: IP address

{1}: Credential name

{2}: Command ID

KNAV50820-E

An error occurred while information was being acquired. (An attempt to stop command failed. IP address : {0}, credential name : {1}, command ID : {2}). Check the configuration of the collector and the status of the target host. If no problem is found, restart the product and try the operation again.

{0}: IP address
{1}: Credential name
{2}: Command ID

KNAV50821-E

An error occurred while information was being acquired. (Internal error has occurred). Check the configuration of the collector and the status of the target host. If no problem is found, restart the product and try the operation again.

KNAV50822-E

An error occurred while information was being acquired. (The parameter was invalid. parameter name : {0}, value : {1}). Check the configuration of the collector and the status of the target host. If no problem is found, restart the product and try the operation again.

{0}: Parameter name
{1}: Value

KNAV50823-E

An error occurred while information was being acquired. (The total number of active process may have been reached. IP address : {0}, process number : {1}). Check the configuration of the collector and the status of the target host. If no problem is found, restart the product and try the operation again.

{0}: IP address
{1}: Process number

KNAV50824-E

An error occurred while information was being acquired. (The execute history does not exist. IP address : {0}, credential name : {1}, command ID : {2}). Check the configuration of the collector and the status of the target host. If no problem is found, restart the product and try the operation again.

{0}: IP address
{1}: Credential name
{2}: Command ID

KNAV50825-E

An error occurred while information was being acquired. (An attempt to delete the file failed. IP address : {0}, credential name : {1}, path : {2}). Check the configuration of the collector and the status of the target host. If no problem is found, restart the product and try the operation again.

{0}: IP address
{1}: Credential name
{2}: Path

KNAV50826-E

An error occurred while information was being acquired. (An attempt to release the service failed. IP address : {0}, credential name : {1}, service name : {2}). Check the configuration of the collector and the status of the target host. If no problem is found, restart the product and try the operation again.

{0}: IP address
{1}: Credential name
{2}: Service name

KNAV50827-E

Authentication on the target host failed. Check the relevant user privileges. (target host : {0}, destination folder path : {1})

{0}: Target host
{1}: Folder path

KNAV50828-E

Authentication on the target host failed. Check the relevant user privileges. (target host : {0}, credential name : {1})

{0}: Target host
{1}: Credential name

KNAV50829-E

An error occurred while information was being acquired. (A time-out occurred while connecting to the launcher. IP address : {0}, credential name : {1}). Check the configuration of the collector and the status of the target host. If no problem is found, restart the product and try the operation again.

{0}: IP address

{1}: Credential name

KNAV50830-E

An error occurred while information was being acquired. (An attempt to run the service failed. IP address : {0}, service name : {1}). Check the configuration of the collector and the status of the target host. If no problem is found, restart the product and try the operation again.

{0}: IP address

{1}: Service name

KNAV50831-E

An error occurred while information was being acquired. (An attempt to connect the ADMIN\$ or share folder failed. IP address : {0}). Check the configuration of the collector and the status of the target host. If no problem is found, restart the product and try the operation again.

{0}: IP address

KNAV50832-E

Authentication on the target host failed. Check the relevant user privileges. (target host : {0}, credential name : {1})

{0}: Target host

{1}: Credential name

KNAV50833-E

An error occurred while information was being acquired. (The processing could not be execute, because launcher was not running. IP address : {0}, process name : {1}). Check the configuration of the collector and the status of the target host. If no problem is found, restart the product and try the operation again.

{0}: IP address

{1}: Process name

KNAV50834-E

An error occurred while information was being acquired. (The folder name was too long. folder name : {0}). Check the configuration of the collector and the status of the target host. If no problem is found, restart the product and try the operation again.

{0}: Folder name

KNAV50835-E

An error occurred while information was being acquired. (The same name exist. IP address : {0}, folder name : {1}). Check the configuration of the collector and the status of the target host. If no problem is found, restart the product and try the operation again.

{0}: IP address

{1}: Folder name

KNAV50836-E

An error occurred while information was being acquired. (An attempt confirm the launcher service failed. IP address : {0}). Check the configuration of the collector and the status of the target host. If no problem is found, restart the product and try the operation again.

{0}: IP address

KNAV50837-E

An error occurred while information was being acquired. (out of memory). Check the configuration of the collector and the status of the target host. If no problem is found, restart the product and try the operation again.

KNAV50838-E

An error occurred while information was being acquired. (An attempt to acquire request the launcher failed. IP address : {0}). Check the configuration of the collector and the status of the target host. If no problem is found, restart the product and try the operation again.

{0}: IP address

KNAV50839-E

An error occurred while information was being acquired. (An attempt to acquire response the launcher failed. IP address : {0}). Check the configuration of the collector and the status of the target host. If no problem is found, restart the product and try the operation again.

{0}: IP address

KNAV50840-E

An error occurred while information was being acquired. (An attempt to delete setting service failed. IP address : {0}). Check the configuration of the collector and the status of the target host. If no problem is found, restart the product and try the operation again.

{0}: IP address

KNAV50841-E

IPv6 is not supported. Specify IPv4.

KNAV50842-E

The host name could not be resolved. Check whether the host name can be resolved.

KNAV50855-I

The credential that was used for the Collector or Discovery function could not be found. (IP address:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

KNAV50856-E

An error occurred when acquiring information about the session.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV50857-W

The host is not connected or it is powered off. (vCenter server:{0}, host:{1}, connection status:{2})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address of the vCenter server

{1}: Host that is not connected

{2}: Connection status of the host

KNAV50858-W

The component could not be created, because the necessary data could not be found. (component type:{0}, component name:{1}, necessary data:{2})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Component type

{1}: Component name

{2}: Necessary data

KNAV50859-W

The attribute of the component could not be set or added, because the necessary data could not be found. (component type:{0}, component name:{1}, attribute name:{2}, necessary data:{3})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Component type

{1}: Component name

{2}: Attribute name

{3}: Necessary data

KNAV50860-E

The processing will be terminated, because the necessary data could not be acquired from the device. (necessary data:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Necessary data

KNAV50861-W

The configuration information for the ESX server could not be found. (vCenter server:{0}, ESX server:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: vCenter server name

{1}: ESX server name

KNAV50901-E

An internal error occurred. (target IP address:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

KNAV50903-E

An error occurred during the collection of vCenter events. (target IP address:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

KNAV50904-E

An error occurred during the collection of vCenter events. (URL:{0}, collector name:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: URL of the vCenter server

{1}: Collector name

KNAV50950-E

An internal error occurred. (message:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Message

KNAV50951-E

An XML-API error occurred. (URI:{0}, message:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: URI of the resource

{1}: Message

KNAV50952-E

The attempt to log in to Device Manager was unsuccessful. (user:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: User name

KNAV50953-E

An error occurred in the authentication processing of Device Manager. (IP address:{0}, device name:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

{1}: Device name

KNAV50954-E

An error occurred in the processing to connect to Device Manager. (IP address:{0}, port:{1}, message:{2})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

{1}: Port

{2}: Message

KNAV50955-E

An error occurred in the request that was sent to Device Manager. (IP address:{0}, device name:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

{1}: Device name

KNAV50956-E

An error occurred in the processing of the response data. (IP address:{0}, device name:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

{1}: Device name

KNAV50957-E

An internal error occurred.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV50958-E

An error occurred in REST-API.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV50959-E

An error occurred in the processing to acquire performance information. (IP address:{0}, device name:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

{1}: Device name

KNAV50960-E

The log in to HTnM server was unsuccessful. (IP address:{0}, port:{1}, user:{2}, message:{3})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

{1}: Port

{2}: User

{3}: Message

KNAV50961-E

An error occurred in the authentication processing of the HTnM server. (IP address:{0}, port:{1}, message:{2})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

{1}: Port

{2}: Message

KNAV50962-E

An error occurred by the connection to HTnM server. (IP address:{0}, port:{1}, host:{2}, instance:{3}, message:{4})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

{1}: Port

{2}: Host

{3}: Instance

{4}: Message

KNAV50963-E

An error occurred by request. (IP address:{0}, port:{1}, host:{2}, instance:{3}, HTTP code:{4}, message:{5})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

{1}: Port

{2}: Host

{3}: Instance

{4}: HTTP code

{5}: Message

KNAV50964-E

An error occurred during the handling of response data.(IP address:{0}, port:{1}, host:{2}, instance:{3}, message:{4})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: IP address

{1}: Port

{2}: Host

{3}: Instance

{4}: Message

KNAV50965-E

An error occurred by request. (URL:{0}, HTTP code:{1}, message:{2})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: URL

{1}: HTTP code

{2}: Message

KNAV50966-E

The URL is unjust format. (URL:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: URL

KNAV50967-E

An error occurred by connection. (URL:{0}, message:{1})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: URL

{1}: Message

KNAV50968-E

A request method is unjust. (URL:{0}, method:{1}, message:{2})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: URL

{1}: Method

{2}: Message

KNAV50969-E

Storage system information could not be collected.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV50980-E

Collection of an application failed. (collector name:{0})

{0}: Collector name

KNAV50983-E

Collection of an application failed. (collector name:{0})

{0}: Collector name

KNAV50986-E

A required item is not defined. (collector name:{0}, line number:{1}, definition item:{2})

{0}: Collector name

{1}: Line number

{2}: Definition item

KNAV50987-E

The definition is invalid. (collector name:{0}, line number:{1}, definition item:{2}, defined information:{3})

{0}: Collector name

{1}: Line number

{2}: Definition item

{3}: Defined information

KNAV50988-E

The definition is duplicated. (collector name:{0}, line number:{1}, application name:{2}, host name:{3})

{0}: Collector name

{1}: Line number

{2}: Application name

{3}: Host name

KNAV60002-E

The process has been interrupted.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV60003-E

A job was canceled.(ID:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Identifier

KNAV60004-E

The request could not be completed.(ID:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Identifier

KNAV60005-E

The job ended abnormally.

(ID:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Identifier

KNAV60008-E

An error occurred with the Adapter.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV60050-E

The request ended abnormally.

(ID:{0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Identifier

KNAV60052-E

The requester could not be initialized.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV60053-E

The accepter could not be initialized.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV60056-E

The object of the key "{0}" in the property file could not be obtained.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Name of the property key

KNAV60059-E

The request could not be invoked.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV60062-E

The request priority processing has failed.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV60068-E

The request distribution has failed.(request ID : {0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Request ID

KNAV60070-E

The RMI object from the adapter process could not obtained.(request id : {0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Request ID

KNAV60073-E

The request could not be executed. (request ID : {0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Request ID

KNAV60074-E

The request could not be deleted. (request ID : {0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Request ID

KNAV60075-E

The FW Result could not be built. (request ID : {0})

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Request ID

KNAV60076-E

The request delete process has failed.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV60084-W

Although the adapter started, the service has not yet started.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV70001-E

{0} command ended because of a time-out.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Command name

KNAV70002-E

{0} command has ended abnormally.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Command name

KNAV70003-E

The {0} command could not be started.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: Command name

KNAV70004-E

The DB access function could not be initialized.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV70005-E

A database access function could not be completed successfully.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV70019-E

The database operation failed.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV70023-E

An error occurred during the database operation. The system performed more retries than the specified times; however, the operation still failed.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV70037-E

An internal error occurred in the database operation function.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV70044-E

A database access error occurred.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV70055-E

Performance history information could not be deleted.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV70057-E

The RD area, {0}, is blocked.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: RD area name

KNAV70059-E

The status of the database's storage could not be acquired.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV70060-W

The status of the database's storage (RD area name:{0}) could not be acquired.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

{0}: RD area name

KNAV70066-E

Database maintenance is required.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV70070-E

While converting the data, an unexpected error occurred.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV70071-E

A database blockage has been detected.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV70072-E

The password length is invalid.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV70080-E

The password could not be changed.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

KNAV70086-E

The database cannot be expanded.

Cause: For details on the cause, see the message that is output after this message.

Action: For details on the action to be taken, see the message that is output after this message.

(3) Cause-related messages

KNAV00004-I

An unexpected error occurred. (error message: {0})

{0}: Exception message

KNAV00010-I

The system environment is invalid.

KNAV00227-I

One of the following problems occurred:

- A timeout occurred.
 - A communication error occurred in the processing to call the RMI.
 - The RMI that was called does not exist.
 - You do not have the necessary access permissions for the RMI that was called.
 - An error occurred in the RMI that was called.
 - An unknown exception occurred.
-

KNAV20011-E

The entered value contains an error.

KNAV20030-I

There is no progress information of the discovery.

KNAV20031-I

The Collector or Discovery function is already being executed.

KNAV20032-I

The search range condition is missing.

KNAV20054-E

An attempt to obtain the {0} device information has failed.

{0}: Device name

KNAV20072-I

The number of the obtained schedules is invalid. (number: {0})

{0}: Number of records obtained from the Schedule table of the database

KNAV20073-I

The initialization is not finished.

KNAV20074-I

The termination has already finished.

KNAV20075-I

The events to be updated do not exist.

KNAV20078-I

A running thread is interrupted.

KNAV20079-I

The retry count of event registration exceeded a system limit. (limit: {0})

{0}: Maximum number of retries (preset value)

KNAV20081-I

An attempt to acquire the user notification settings has failed.

KNAV20082-I

The specified event type is out of the valid range

KNAV20083-I

All of the attempts to update events have failed.

KNAV20092-E

The specified resource has been deleted.

KNAV20094-I

An internal error has occurred.(component name:{0})

{0}: Component name

KNAV20108-E

Have duplicate keys.(class: {0})

{0}: Class name

KNAV20115-I

The type of storage and network equipment cannot be changed.

KNAV20122-E

IP Range does not exist.

KNAV20131-E

IP Range({0}) has already been registered.

{0}: IP range

KNAV20132-E

Credential({0}) has already been registered.

{0}: Credential name

KNAV20135-I

Credential has already been deleted.

KNAV20137-I

An error exists in the CredentialValue({0})

{0}: Incorrect value

KNAV20149-I

The specified resource ({0}) has already been deleted.

{0}: Resource name

KNAV20150-I

Multiple servers existed in the connection destination ({0}).

{0}: Device name

KNAV20152-I

The specified token is invalid.

KNAV20154-I

The User ID or Password is invalid.

KNAV20156-I

The Password is invalid.

KNAV20168-I

The user who specified it is a user who has the last update authority.

KNAV20169-I

The specified user has already been registered.

KNAV20170-I

You do not have permissions to complete this task.

KNAV20172-I

The email could not be sent using the specified mail server.

KNAV20177-I

The destination address for the email notification has not been specified.

KNAV20182-I

An unexpected error occurred.

KNAV20183-I

The initialization has not started.

KNAV20184-I

The process has already finished.

KNAV20212-I

The value specified for an error threshold is less than the minimum specifiable value. (metric:{0}, error threshold value:{1}, minimum value:{2})

{0}: Metric

{1}: Error threshold value

{2}: Minimum value

KNAV20213-I

An error threshold that is greater than or equal to the warning threshold was specified. (metric:{0}, error threshold value:{1}, warning threshold value:{2})

{0}: Metric

{1}: Error threshold value

{2}: Warning threshold value

KNAV20214-I

A warning threshold that is greater than the maximum allowed value was specified. (metric:{0}, warning threshold value:{1}, maximum value:{2})

{0}: Metric

{1}: Warning threshold value

{2}: Maximum value

KNAV20215-I

A warning threshold that is less than the minimum allowed value was specified. (metric:{0}, warning threshold value:{1}, minimum value:{2})

{0}: Metric

{1}: Warning threshold value

{2}: Minimum value

KNAV20216-I

An error threshold that is less than or equal to the warning threshold was specified. (metric:{0}, error threshold value:{1}, warning threshold value:{2})

{0}: Metric

{1}: Error threshold value

{2}: Warning threshold value

KNAV20217-I

An error threshold that is greater than the maximum allowed value was specified. (metric:{0}, error threshold value:{1}, maximum value:{2})

{0}: Metric

{1}: Warning threshold value

{2}: Maximum value

KNAV20218-I

An error threshold that is less than the minimum allowed value was specified. (metric:{0}, error threshold bottom:{1}, minimum value:{2})

{0}: Metric

{1}: Specified value that is less than the minimum error threshold value

{2}: Minimum value

KNAV20219-I

A warning threshold that is less than the minimum allowed value was specified. (metric:{0}, warning threshold bottom:{1}, minimum value:{2})

{0}: Metric

{1}: Specified value that is less than the minimum error threshold value

{2}: Minimum value

KNAV20220-I

The specified profile cannot be modified. (profile type:{0})

{0}: Threshold profile type

KNAV20223-I

Null was specified in the argument profile.

KNAV20224-I

No performance threshold profile was specified.

KNAV20225-I

A performance threshold profile for which no content is set was specified.

KNAV20226-I

The performance threshold profile in which the threshold value was null was specified.

KNAV20227-I

There is no threshold value having a necessary metric type. (metric type:{0})

{0}: Metric type

KNAV20228-I

There is the threshold value having an unnecessary metric type.(metric type:{0})

{0}: Metric type

KNAV20229-I

Multiple threshold values exist for the same metric type. (metric type:{0})

{0}: Metric type

KNAV20230-I

A user definition profile corresponding to the profile name already exists. (profile:{0})

{0}: Performance threshold definition name

KNAV20232-I

Null was specified for the argument "key".

KNAV20234-I

Null was specified in the argument. (argument:{0})

{0}: Argument name

KNAV20236-I

The performance threshold profile does not exist.

KNAV20237-I

A preset profile was specified as the target profile.

KNAV20238-I

The non-editable property is modified. (property name:{0})

{0}: Property name

KNAV20240-I

Different resource types were specified for the performance threshold profile and the target resource. (profile:{0}, resource name:{1})

{0}: Threshold profile name

{1}: Resource type

KNAV20268-I

The performance threshold profile was specified, in which the creatorType was null.

KNAV20269-I

The performance threshold profile was specified, in which the nodeType was null.

KNAV20270-I

The performance threshold profile was specified, in which the threshold value was null.

KNAV20271-I

The performance threshold profile was specified, in which the metricType was null.

KNAV20281-I

The saved information about discovered resources could not be found. The information might have been deleted.

KNAV20288-I

Multiple processes are currently being executed to update the same device information.

KNAV20296-I

An unexpected status transition. ({0} -> {1})

{0}: Old status

{1}: New status

KNAV20302-I

The item whose name is the same as the target has already been registered.

KNAV20304-I

The target does not exist.

KNAV20333-I

The device might have been removed from the system.

KNAV20335-I

The same data has already been registered in the database.

KNAV20337-I

The processing to consolidate the status history is already being executed.

KNAV20342-E

The error occurred during the database access.

KNAV20346-I

Users cannot specify a password that matches the user name.

KNAV20348-I

An invalid SNMP Trap was received.

KNAV20399-I

The profile contains an invalid threshold. (device name:{0}, profile:{1})

{0}: Device name

{1}: Threshold profile name

KNAV20417-I

The metric in the performance history does not match the metric in the threshold profile. (performance history:{0}, threshold profile:{1})

{0}: Metric performance history

{1}: Performance metric in threshold data

KNAV20418-I

No performance status corresponds to the performance value.

KNAV20435-I

The schedule could not be initialized because of "{0}".

{0}: Error position

KNAV20437-I

The schedule could not be configured because of "{0}".

{0}: Exception that caused the failure

KNAV20438-I

An attempt to start the scheduler resident thread failed.

KNAV20440-I

The schedule could not be started because of "{0}".

{0}: Exception that caused the failure

KNAV20442-I

The number of processes executed by the scheduler exceeded the acceptable number of simultaneous executions, or an unexpected notification of process completion was sent. (current value:{0})

{0}: Number of simultaneous executions that were attempted

KNAV20443-I

The function ({0}) could not start because of an unexpected cause.

{0}: Name of the function to be executed

KNAV20465-E

There was a conflict with some update processes, so nothing was updated.

KNAV20472-E

A timeout occurred with the ({0}) process.

{0}: Process or function name

KNAV20473-I

An error occurred during the thread execution.

KNAV20501-I

The monitoring mode of the device is incorrect. (device name:{0}, monitoring mode:{1})

{0}: Device name

{1}: Device monitoring status

KNAV20502-I

There is no component. (component ID:{0})

{0}: Component ID

KNAV20506-I

The component could not be returned to its previous status. The status might have already been changed.
(component name:{0})

{0}: Component name

KNAV20555-I

The destination address is not specified.

KNAV20559-I

Device information cannot be obtained until the configuration update has finished.

KNAV20562-I

An argument (code) associated with the device is incorrect.

KNAV20563-I

An attempt to stop the communication with the server failed.

KNAV20569-I

The network has already been removed.

KNAV20576-E

The monitoring mode of the virtual machine on the hypervisor could not be changed.

KNAV20583-E

No associations were found between the status and component. ({0})

{0}: Component name

KNAV20590-I

The monitoring mode of the device might have been changed.

KNAV20591-I

Monitor setting of the threshold is incorrect. (metric:{0}, watching:{1}, collecting:{2})

{0}: Performance name

{1}: History collection settings

{2}: Judgment settings

KNAV20600-I

Because the usage rate of the database exceeded the threshold, immediate database maintenance is required.

KNAV20601-I

There is insufficient free disk free space. Expand the size of the database (the DB scale), now.

KNAV20602-I

Perform database maintenance immediately.

KNAV20611-I

The monitoring mode of the specified device could not be changed to {0}.

{0}: Specified managed status

KNAV20615-I

Free disk space is very limited. Expand the database, now.

KNAV20619-I

An I/O error occurred during database access.

KNAV20621-I

There is not enough free disk space.

KNAV20623-I

There is insufficient free disk free space. Perform database and disk maintenance immediately.

KNAV20655-I

The device might no longer be connected via the specified IP address. (IP address:{0}, device name:{1})

{0}: IP address

{1}: Device name

KNAV20659-I

The possible causes of the problem are as follows:

- The status of the specified resource has already been changed to a different status.
 - The specified resource does not exist.
 - The specified resource was registered by using the Collector function.
-

KNAV20663-I

The port is already in use.

KNAV20719-E

The specified file could not be executed. (File:"{0}")

{0}: File path

KNAV20731-I

The composition of the threshold profile object is invalid. (internal infomation: {0})

{0}: Internal information

KNAV20732-I

The start time is invalid. (time: {0}:{1})

{0}: *hh*

{1}: *mm*

KNAV20733-I

The duration is invalid. (repeat type:{0}, duration:{1})

{0}: Repetition type

{1}: Duration

KNAV20734-I

A day of the week is not specified.

KNAV20735-I

The application day is invalid. (date:{0})

{0}: Date

KNAV20736-I

The frequency on a day of the week is invalid. (value:{0})

{0}: Value that indicates the *n*th occurrence (between the first and fifth) of a particular day of week in each month

KNAV20737-I

The specified day of the week is invalid.(value:{0})

{0}: Value that indicates the day of the week

KNAV20738-I

The type of the repetition is not specified.

KNAV20755-I

Processing to edit, delete, or apply the threshold profile is already being executed.

KNAV20883-E

An internal error has occurred.

KNAV20951-E

The specified values include an error.

KNAV20963-I

The value of "componentType" in the specified performance threshold profile is "null".

KNAV20964-I

The value of "resourceType" in the specified performance threshold profile is "null".

KNAV20965-I

The specified device was registered by using the Collector function.

KNAV20968-I

The specified Collector has already been deleted or does not exist.

KNAV20975-I

The specified host name could not be resolved.

KNAV20977-I

The credentials are missing. (IP Range:{0})

{0}: IP Range

KNAV20979-I

A duplicated IP Range was specified.

KNAV20981-I

A duplicated IP address or host name was specified.

KNAV20987-E

Make sure that the template definition file exists, and can be accessed as an executable file.

KNAV20990-E

An attempt to read the folder storing the template definition file failed. Make sure that the folder exists and can be accessed.

KNAV21000-E

An error occurred in the processing to collect an application. (collector name:{0})

{0}: Collector name

KNAV30136-E

The reloadproperty command might have been executed and might have modified the information in a template definition file.

KNAV30138-E

The destination does not exist.

KNAV30140-E

The resource type of resource assignment rule is invalid.

KNAV30142-E

The number of rules to change the priority does not match.

KNAV30145-E

The value of the required property key "{0}" is outside the valid input range.

{0}: Key name

KNAV30146-E

The value of the required property key "{0}" includes a control character.

{0}: Key name

KNAV30147-E

The value of the required property key "{0}" could not be obtained.

{0}: Key name

KNAV30148-E

The value of the required property key "{0}" is not input.

{0}: Key name

KNAV40002-I

Invalid argument. (Argument name = {0})

{0}: Argument name

KNAV40007-I

An unexpected error occurred. (Errormessage = {0})

{0}: Exception message (in English)

KNAV40008-E

Access to the database is crowded now.

KNAV40019-I

The credential settings are invalid.

KNAV40020-I

The device is in an unresponsive state.

KNAV40026-I

{0} is already in process. It cannot be run simultaneously.

{0}: Process name

KNAV40033-I

(See the message log of the service for messages pertaining to each device.)

KNAV40034-I

The execution exception occurred in the update task.

KNAV40036-I

The device information might have been deleted.

KNAV40040-I

Data in operation on the database might be updated by another process.

KNAV40041-I

No device is specified as a device to be monitored.

KNAV40047-I

The {0} data does not exist.

{0}: Name of the non-existent object

KNAV40048-I

The {0} data already exists and cannot be registered.

{0}: Name of the non-existent object

KNAV40049-I

There is an unexpected value in the enumerated data type. (enum class:{0}, enum value:{1})

{0}: Enumerated type class name

{1}: Enumerator

KNAV40050-I

The argument is invalid.

KNAV40051-I

The previous task is being processed.

KNAV40053-I

No credential exists for any of the IP addresses associated with the device.

KNAV40074-I

(For the execution results of each device, see the monitoring status information. For details, see the service message log.)

KNAV40080-I

An unexpected error occurred.

KNAV40081-I

A large number of IP addresses were identified. (number of IP addresses: {0})

{0}: Number of target IP addresses

KNAV40083-I

A memory shortage occurred. (InternalInformation:{0})

{0}: Process name

KNAV40086-I

An error occurred. (ErrorMessage = {0})

{0}: Exception message

KNAV40092-I

An exception occurred in the execution of the event collection task.

KNAV40093-I

There is a possibility that a connection to the monitored device temporarily could not be established.

KNAV40094-I

The discovery function, using a specified IP Range or credentials, is in progress. (IP Range for discovery function:{0})

{0}: Target name that is being used by the discovery function

KNAV40095-I

The specified credentials are assigned to resources. (credentials:{0}, number of assigned resources:{1})

{0}: Credentials

{1}: Number of target resources

KNAV40099-I

The retry count for task registration exceeded a system limit. (limit:{0})

{0}: Maximum number of retries (preset value)

KNAV50025-I

Information could not be acquired by using this protocol, because the protocol is already in use by other devices, resulting in many timeout errors.

KNAV50029-I

Permissions for the device could not be acquired, because a processing conflict occurred.

KNAV50032-I

This protocol is being used in processing for other devices.

KNAV50034-I

This product cannot communicate with the target device.

KNAV50037-I

Information from the device could not be acquired by using this protocol, because the protocol is already in use by other devices, resulting in many timeout errors.

KNAV50045-I

The system environment is invalid.

KNAV50157-I

An attempt to execute the API on the device failed. (IP address:{0}, cause:{1})

{0}: IP address

{1}: Reason

KNAV50158-I

The device IDs are different. (old device ID:{0}, new device ID:{1})

{0}: Old device ID

{1}: New device ID

KNAV50159-I

The Connection IP address is a virtual server address. (IP address:{0})

{0}: IP address

KNAV50160-I

COM could not be initialized.

KNAV50251-I

The email could not be encoded.

KNAV50252-I

The Transport instance could not be obtained.

KNAV50253-I

The SocketFactory instance could not be obtained.

KNAV50254-I

The email address is not in the correct RFC 822 format.

KNAV50255-I

Failed to disconnect.

KNAV50256-I

A problem occurred during the SMTP certification.

KNAV50257-I

An email could not be sent to some recipients. (sent email address list:[{0}], unsent valid email address list:[{1}], unsent invalid email address list:[{2}])

{0}: List of addresses to which the email was sent

{1}: List of valid addresses to which the email could not be sent

{2}: List of invalid addresses to which the email could not be sent

KNAV50258-I

There is a problem with the IP address and the corresponding server name.

KNAV50259-I

The connection was denied.

KNAV50260-I

A time-out occurred.

KNAV50261-I

A problem occurred during SSL connection.

KNAV50262-I

The cause is unknown.

KNAV50337-I

The WBEM server's memory, connections, or other resources have been exceeded.

KNAV50340-I

The specified credential for the SMI-S WBEM is invalid. Confirm that the Port, SSL checkbox, UserID, and Password or the combination of these is valid.

KNAV50343-I

The process runs when the WBEM server is shut down.

KNAV50345-I

Information could not be obtained because the session that was used to acquire the information, closed.

KNAV50354-I

The login was unsuccessful. (IP address:{0})

{0}: IP address

KNAV50357-I

A connection failure occurred. (IP address:{0})

{0}: IP address

KNAV50359-I

The command could not be run. (IP address:{0}, command:{1}, response:{2})

{0}: IP address

{1}: Command

{2}: Return code

KNAV50414-I

The host name of the device has changed from the host name at the time of discovery. Possible causes are as follows:

- (1) The host name of the Linux server was changed.
 - (2) A different server is now connected to the applicable IP address.
 - (3) A different Linux OS was started in a dual-boot environment.
-

KNAV50417-I

The {0} could not be obtained. The privilege might not be given to the user who has been specified for Credential.

{0}: Acquisition target

KNAV50454-I

vSphere API error occurred because of an invalid property.

KNAV50455-I

vSphere API error occurred because of an execution error.

KNAV50457-I

vSphere API error occurred because of communication failure.

KNAV50460-I

The hardware configuration of the ESX server was changed.

KNAV50462-I

One of the following items has caused the issue:

- (1) The URL does not correspond to the vCenter server.
- (2) The IP address or Port number is invalid.
- (3) SSL is specified incorrectly.
- (4) The server is down.

(5) A problem exists with the network.

KNAV50464-I

The User ID or Password is invalid.

KNAV50466-I

The User ID that is associated with the collector setting does not have the necessary permissions.

KNAV50470-I

The file could not be accessed: Either the virtual machine was in the process of creating the file, or it was completing a reconfiguration task.

KNAV50473-E

A vSphere API error occurred. (cause exception:{0}, error message:{1})

{0}: Cause exception

{1}: Exception message

KNAV50553-I

MAC address overlaps with other physical ports (iSCSI). (device name:{0}, port:{1}, MAC address:{2})

{0}: Device name

{1}: Port number

{2}: MAC address

KNAV50555-I

The MAC address of the physical port (iSCSI) is invalid. (device name:{0}, port:{1}, MAC address:{2})

{0}: Device name

{1}: Port number
{2}: MAC address

KNAV50608-I

The total number of active sessions may have been reached.

KNAV50719-I

Null was specified in the argument. (argument:{0})

{0}: Argument name

KNAV50726-I

A unexpected error occurred.

KNAV50727-I

{0} not found in property.

{0}: Property key name

KNAV50728-I

An invalid key name was specified in getting {0} property.

{0}: Property key name

KNAV50729-I

The {0} value is invalid.

{0}: Property key name

KNAV50731-I

An error occurred in Protocol Cassette load.(message:{0})

{0}: Cause exception message

KNAV50732-I

The specified cassette ID was invalid.(cassette ID:{0})

{0}: Cassette ID

KNAV50733-I

The cassette ID was not specified.

KNAV50734-I

Could not load cassette.

KNAV50741-E

The {0} value is invalid.

{0}: Property key name

KNAV50743-I

An unexpected error occurred in the common-library.

KNAV50744-I

No response was returned from the common-library.

KNAV50771-I

An Exception occurred.{0}

{0}: Exception information

KNAV50799-I

The system has failed in the WMI connection. (IP address:{0})

{0}: IP address

KNAV50850-I

The WMI authentication was unsuccessful. (IP address:{0}, credential name:{1})

{0}: IP address

{1}: Credential name

KNAV50851-I

DCOM on the Management Server is not enabled.

KNAV50852-I

You do not have privileges for the WMI connection. (IP address:{0}, Credential name:{1})

{0}: IP address

{1}: Credential name

KNAV50853-I

The credential is invalid. (credential name:{0})

{0}: Credential name

KNAV50854-I

An unexpected value was returned from the common-library.

KNAV50981-E

A definition file failed to load. (file:{0})

{0}: File path

KNAV50984-E

The defined information is invalid. (file:{0})

{0}: File path

KNAV60006-I

The status of the job is abnormal. (status:{0})

{0}: Status

KNAV60051-I

The status of the request is abnormal. (status:{0})

{0}: Status

KNAV60054-I

The value of the key "{0}" in the property file is illegal.

{0}: Property key name

KNAV60058-I

The callback object {0} could not be obtained.

{0}: Name of the callback object

KNAV60060-I

The FW_Argument is not set.

KNAV60063-I

The priority of the request is illegal. (priority:{0})

{0}: Priority of the request

KNAV60065-I

The output of callback object {0} is null.

{0}: Name of the callback object

KNAV60067-I

The FW_Argument in FW_Request is not set.

KNAV60077-E

The status of the deleting request is invalid. (request ID :{0}, transferred adapter process ID : {1}, request status : {2})

{0}: Request ID

{1}: Adapter ID

{2}: Request status

KNAV60078-E

The deleting request is null.

KNAV60079-E

The thread to execute the request delete process is invalid.

KNAV70007-I

The number of schema-version is invalid. (the number = {0})

{0}: Number of schema versions obtained from the database

KNAV70008-I

The schema-version value is invalid. (the value = {0})

{0}: Number of schema versions obtained from the database

KNAV70010-I

An unexpected error occurred.

KNAV70020-I

A unique constraint error occurred. You tried to insert the duplicate value into the database, or you tried to update the database by using the duplicate value.

KNAV70021-I

An optimistic lock error occurred. The data is updated or deleted by other administrators.

KNAV70024-I

A transaction time out occurred. Access to the database might be crowded.

KNAV70025-I

Either the database server has stopped, or the database server operation took longer than the timer monitoring time. Access to the database might be crowded.

KNAV70026-I

There are insufficient database resources.

KNAV70027-I

Deadlock has occurred. Access to the database might be crowded.

KNAV70028-I

There is an insufficient working space for the mutually-exclusive control. Access to the database might be crowded.

KNAV70029-I

The global buffer is insufficient.

KNAV70030-I

There is insufficient memory for the database operation.

KNAV70031-I

The number of connections to the database exceeds the maximum number of simultaneous connections.

KNAV70032-I

The networking buffer is insufficient.

KNAV70034-I

A reference constraint error occurred during the data operation. Other users might delete the data.

KNAV70038-I

The format of the specified argument for creating the primary key is invalid.

KNAV70039-I

The system cannot establish the session with the database. An error occurred during the communication with the database server, or the database server is down.

KNAV70040-I

A failure occurred during the internal retry for the failed database operation.

KNAV70041-I

An unknown database error occurred.

KNAV70042-I

The parameter is null.

KNAV70043-I

The length of one parameter List is not equivalent to that of the other List.

KNAV70045-I

Necessary resources are occupied by other transactions.

KNAV70046-I

There is insufficient space in the database.

KNAV70048-I

An error occurred in the database.

KNAV70051-I

Because several sources were accessing the database simultaneously, additional access to the database was temporarily locked.

KNAV70056-I

Either the database cannot be deleted, or an unexpected exception occurred.

KNAV70058-I

The blockage of the RD area could not be released.

KNAV70061-I

The status of the RD area could not be acquired.

KNAV70067-I

The database has insufficient space.

KNAV70073-I

The specified password is not within the acceptable length parameters.

KNAV70081-I

Either a necessary resource is occupied by another transaction, or access to the database is currently limited.

KNAV70082-I

An unexpected failure occurred. The database might be the cause of the failure. Please contact customer support.

KNAV70083-I

An unexpected exception occurred. The system environment might be invalid.

KNAV70087-I

There is not enough free disk space.

(4) Action messages

KNAV00001-I

Re-install the product. If the problem persists, contact customer support.

KNAV00002-I

Contact customer support.

KNAV00003-I

Uninstall and then re-install the product.

KNAV00005-I

Restart the system. If the problem persists, re-install the product.

KNAV00228-I

Restart the service.

KNAV20012-I

Check and, if necessary, revise the input value.

KNAV20019-I

Check and, if necessary, revise the settings or the items.

KNAV20024-I

Check the outgoing SMTP server settings.

KNAV20059-E

Environment is not configured correctly. Check it again.

KNAV20085-I

Select the events to be updated.

KNAV20093-E

Please Refresh.

KNAV20153-I

Check and, if necessary, revise the specified token.

KNAV20155-I

Check and, if necessary, revise the User ID or Password.

KNAV20157-I

Check and, if necessary, revise the password.

KNAV20211-I

Check and, if necessary, revise the performance threshold value.

KNAV20221-I

Check and, if necessary, revise the profile type of the performance threshold profile.

KNAV20222-I

Check and, if necessary, revise the content of the performance threshold profile.

KNAV20233-I

Check and, if necessary, revise the arguments.

KNAV20272-I

Refresh the display and confirm the existence of the performance threshold profile.

KNAV20276-I

Update the configuration manually. If the same error occurs, contact customer support.

KNAV20282-I

If you cannot find necessary resources after confirming the results of the collector or discovery, start the collector or discovery again.

KNAV20283-I

Specify the applicable resource as a resource to be monitored, and then configure the profile manually.

KNAV20285-I

Remove the applicable resource, and then re-execute the Collector or Discovery function.

KNAV20291-I

Specify the applicable device as a device to be monitored. Then, after the device changes to a state in which it can be connected, update the configuration information.

KNAV20303-I

Run it again by using the other name.

KNAV20305-I

Confirm the existence of the target, then repeat the process.

KNAV20306-I

Enter the Name correctly, then repeat the process.

KNAV20309-I

Select the target, then repeat the process.

KNAV20340-E

Restart the service. If the exception reoccurs, re-install the product.

KNAV20377-I

Acquire it after the discovery starts.

KNAV20400-I

Re-create the threshold profile.

KNAV20556-I

Check and, if necessary, revise an email address (a destination), then retry.

KNAV20560-I

Wait for the configuration information to be updated, and then try again.

KNAV20564-I

Wait for a while, then update the configuration information again.

KNAV20567-I

Remove the device. Then, from [Resource Registration], re-execute the Collector or Discovery function.

KNAV20570-I

Remove all devices related to the network. Then, from [Resource Registration], re-execute the Collector or Discovery function. (network:{0})

{0}: Relevant network

KNAV20577-E

The monitoring mode of the virtual machine on the hypervisor could not be changed. Try again later.

KNAV20603-I

Reorganize the database or expand the scale of the database.

KNAV20604-I

Expand the scale of the database.

KNAV20605-I

Reorganize the database or expand the scale of the database.

KNAV20616-I

A minimum of {0} MB of free disk space is necessary. Perform either of the following:

1. On the management server, increase the free disk space of the database storage destination.
 2. Expand the scale of the database.
-

{0}: Amount of free disk space that is required

KNAV20617-I

A minimum of {0} MB of free disk space is necessary. Perform either of the following:

1. Increase the free disk space of the database storage destination.
2. Make sure the disk to which the database is to be moved has sufficient free disk space, and then move the database.

{0}: Amount of free disk space that is required

KNAV20624-I

A minimum of {0} MB of free disk space is necessary. Perform either of the following:

1. On the management server, increase the free disk space of the database storage destination, and then expand the scale of the database.
2. Make sure the disk to which the database is to be moved has sufficient free disk space, and then move the database.

{0}: Amount of free disk space that is required

KNAV20660-I

Make sure the checkboxes corresponding resources that were registered by using the Collector function are not selected. Refresh the display, and then try the operation again.

KNAV20720-E

Check that the file specified with EventAction.properties can be accessed as an executable file.

KNAV20722-E

Check the contents of the execution file.

KNAV20730-I

After a while, the performance statuses of the devices will be updated by the performance monitoring function.

KNAV20756-I

Remove the cause of the I/O error. Then, restart the service or execute the restore.exe command to recover the database.

KNAV20852-I

Reorganize the database or expand the scale of the database.

KNAV20864-I

Refresh the display and confirm the existence of the email address.

KNAV20865-I

Refresh the display and then make sure the notification profiles exist.

KNAV20912-I

When using the trap function, consider the number of devices that are supported by the function. Then, reduce the number of the following devices to be notified of the trap.(IP switch:{0})

{0}: Maximum number of IP switches

KNAV20939-I

The monitoring interval may be too short. Please increase the monitoring interval and retry.

KNAV20952-I

Check and, if necessary, revise the specified values.

KNAV20966-I

Do not specify devices that were registered by using the Collector function.

KNAV20969-I

Refresh the monitoring window and then try again.

KNAV20976-I

Make sure that the specified host name can be resolved, and try again.

KNAV20980-I

Specify another IP Range, and try again.

KNAV20982-I

Specify another IP address or host name, and try again.

KNAV20988-E

Make sure that the template definition file exists, and can be accessed as an executable file. Then run the reloadproperty command.

KNAV20991-E

An attempt to read the folder storing the template definition file failed. Make sure that the folder exists and can be accessed. Then run the reloadproperty command.

KNAV20996-E

Set a specifiable resource, and try again.

KNAV20997-E

Information collection failed because the collector access point is duplicated. (Collector name:{0}, host name:{1})

{0}: Collector name

{1}: Host name

KNAV20998-I

A different collector is already collecting information about the same device.

KNAV20999-I

Delete the unnecessary collector.

KNAV30137-E

Make sure that the specified template definition file exists, and then execute the reloadproperty command.

KNAV30139-E

Confirm the existence of the destination, then repeat the process.

KNAV30141-E

Check and, if necessary, revise the resource type of resource assignment rule.

KNAV30143-E

After having confirmed that all rule exist, please execute the change of priorities again.

KNAV30149-E

After having modified the specified key, run the reloadproperty command.

KNAV30150-E

Please execute reloadproperty command after putting time for a while. When the same error occurs again, please contact a manager.

KNAV40009-I

Please wait for a while, and retry.

KNAV40014-I

Please contact customer support.

KNAV40015-I

Restart the service. If the problem persists, contact customer support.

KNAV40016-I

Re-install the product. If the problem persists, contact customer support.

KNAV40017-I

Refer to the Adapter log.

KNAV40018-I

Confirm the credential.

KNAV40021-I

Check the network connection status of this device, and set the appropriate connection information.

KNAV40022-I

Contact customer support if this problem recurs.

KNAV40027-I

Check and, if necessary, revise the interval of {0}.

{0}: Process name

KNAV40030-I

Select a device.

KNAV40032-I

(See the message log of the service for messages pertaining to each device.)

KNAV40037-I

Check the event log to see whether the device has been excluded from the monitoring targets.

KNAV40039-I

Refresh the display, and then check whether the specified {0} exists. If it exists but processing does not start, contact customer support.

{0}: Keywords

Discovery conditions or credentials are set as the keywords.

KNAV40042-I

Specify a device to be monitored.

KNAV40044-I

Select an appropriate device.

KNAV40045-I

The process will start again the next time that the schedule is processed.

KNAV40046-I

Please update the display, and confirm whether {0} exists.

{0}: Name of the non-existent object

KNAV40052-I

Review the execution schedule.

KNAV40054-I

Make sure the credential is correct, and then re-execute the Collector or Discovery function.

KNAV40065-I

Select the component.

KNAV40073-I

(For the execution results of each device, see the monitoring status information. For details, see the service message log.)

KNAV40082-I

Select a range with fewer IP addresses ({0} or less).

{0}: Maximum number of IP addresses

KNAV40096-I

Make sure the credentials used by the resource are correct, and then try to delete the resource again.

KNAV40100-I

Specify a value that is bigger than 0.

KNAV40101-I

Specify a file name.

KNAV40102-I

Please re-execution after the change of the monitoring setting and the Collector or Discovery function will not be carried out.

KNAV50026-I

Make sure there are no problems with the communication routes between the devices to be monitored and this product or with the protocol used by those devices. Next, restart this product and then try the operation again.

KNAV50030-I

Make sure there are no problems with the communication route between the applicable device and this product. Next, restart this product and then try the operation again.

KNAV50033-I

Make sure there are no problems with any of the devices using this protocol or with the communication route between each device and this product. Next, restart this product and then try the operation again.

KNAV50035-I

Make sure there are no problems with the communication route between the applicable device and this product. Next, restart this product and then try the operation again.

KNAV50038-I

Make sure there are no problems with the communication routes between the nodes to be monitored and this product, or with the protocol used by these nodes. Next, restart the product and then try the operation again.

KNAV50046-I

Please confirm the status of the collection target. If no problem have found, please restart the product. If that does not resolve the issue, please contact technical support.

KNAV50051-I

Please refer to the Adapter Trace log.

KNAV50263-I

Please confirm that the email address is correct, then retry.

KNAV50264-I

Please confirm that the SMTP server settings (user name, password) are correct, then retry.

KNAV50265-I

Please confirm that the SMTP server name is correct, then retry.

KNAV50266-I

Please confirm that the SMTP server settings (server name, port number, secure connection) are correct, then retry.

KNAV50267-I

Please confirm that the SMTP server settings (server name, port number, secure connection) are correct, and check the communication route to the SMTP server. Then, retry.

KNAV50268-I

Please confirm that the encoding type is correct, then retry.

KNAV50269-I

Make sure the SMTP server settings and email address are correct, and then try again. If the problem persists, restart this product and then try the operation again.

KNAV50338-I

Please wait for a few minutes, then try again.

KNAV50347-I

After the WBEM server has been powered on, please try your operation again.

KNAV50355-I

Please confirm that the Server setting and the credential are correct, then retry.

KNAV50358-I

Please confirm that the Server setting and the network environment are correct, then retry.

KNAV50360-I

Please confirm that the Server setting is correct, then retry.

KNAV50415-I

To keep the original device information, return the environment to its original state.
To apply the new settings, re-execute the Discovery function.

KNAV50458-I

Please address the communication failure, then retry.

KNAV50461-I

Remove the currently monitored resources from the monitoring targets, and then re-execute the discovery processing of the Collector function.

KNAV50463-I

Make sure the settings of the Collector and Discovery functions are correct, check the vCenter server status and network status, and then try to reconnect.

KNAV50465-I

Please check the collector setting that are being used, then try reconnecting.

KNAV50467-I

After reviewing the account or credential information of the vCenter server, try reconnecting.

KNAV50471-I

Please wait until after the virtual machine has completed the processing or reconfiguration task, then try accessing the file.

KNAV50556-I

Assign IP address to the physical port (iSCSI).

KNAV50609-I

Please wait for a few minutes, then try again.

KNAV50722-I

Please review the arguments.

KNAV50730-I

Check the property setting.

KNAV50736-I

Contact customer support.

KNAV50742-I

Reset the property value then reboot the system.

KNAV50772-I

Confirm libraries and their paths.

KNAV50902-I

Please refer to the Adapter Trace log.

KNAV50982-E

Make sure that the definition file exists and can be read.

KNAV50985-E

Check whether the defined information is correct.

KNAV60007-I

Please contact customer support.

KNAV60009-E

Please refer to the Adapter Trace log.

KNAV60055-I

Please check the value then restart the system.

KNAV60057-I

Please check the object then restart the system.

KNAV60061-I

Please check the FW_Argument then restart the system.

KNAV60064-I

Please check the priority of the request then restart the system.

KNAV60066-I

Please check the behavior of the callback object.

KNAV60069-I

The adapter ID for acceptor initialization is null.

KNAV60071-I

The adapter ID is illegal.

KNAV60072-I

Please check the adapter ID for the acceptor initialization then restart the system.

KNAV70022-I

If other administrators are using the data simultaneously, there may be a conflict. Please wait before acquiring the latest data.

KNAV70033-I

Please wait for a while, then retry. If other administrators are accessing the same information simultaneously, then wait until their task is finished, and retry. If the problem occurs repeatedly, restart the product. In case the problem occurs regardless of low database load, contact customer support.

KNAV70047-I

Please contact customer support.

KNAV70068-I

Database reorganization is required, using `dbreorg` command. Afterward, expand the database using `expanddb` command.

KNAV70074-I

Please specify a password within the range of 8 to 30 characters.

KNAV70084-I

No particular action is required. If the exception occurs repeatedly, please contact customer support.

1.3.2 Messages starting with KNAQ

KNAQ00022-W

Temporary files stored by your browser are out of date; therefore, if you continue, an incorrect window might be displayed.

Cause: Your web browser is storing temporary files from an older version.

Action: Delete your web browser's temporary files, and then display the login window again.

KNAQ00911-E

The operation failed because an element requires a value to be entered. (element name: {0})

Cause: A value was not entered.

Action: Revise the entered value.

{0}: Element name

KNAQ00912-E

The operation failed because an entered value is outside the range for the allowed number of characters in a string. (element name: {0})

Cause: A string of {1} to {2} characters can be entered.

Action: Revise the entered value.

{0}: Element name

{1}: Minimum length

{2}: Maximum length

KNAQ00913-E

The operation failed because an entered value is outside the range for the allowed number of characters in a string. (element name: {0})

Cause: A string of {1} or more characters can be entered.

Action: Revise the entered value.

{0}: Element name

{1}: Minimum length

KNAQ00914-E

The operation failed because an entered value is outside the range for the allowed number of characters in a string. (element name: {0})

Cause: A string of {1} or fewer characters can be entered.

Action: Revise the entered value.

{0}: Element name

{1}: Maximum length

KNAQ00915-E

The operation failed because an entered value contains one or more unusable characters. (element name: {0})

Cause: An entered value contains one or more unusable characters. (unusable characters: [{1}])

Action: Revise the entered value.

{0}: Element name

{1}: Restricted string

KNAQ00916-E

The operation failed because an entered value is not an integer. (element name: {0})

Cause: An entered value is not an integer.

Action: Revise the entered value.

{0}: Element name

KNAQ00917-E

The operation failed because an entered integer value is outside the valid range. (element name: {0})

Cause: The entered value must be an integer in the range from {1} to {2}.

Action: Revise the entered value.

{0}: Element name

{1}: Minimum integer

{2}: Maximum integer

KNAQ00918-E

The operation failed because an entered integer value is outside the valid range. (element name: {0})

Cause: The entered value must be an integer greater than {1}.

Action: Revise the entered value.

{0}: Element name

{1}: Minimum integer

KNAQ00919-E

The operation failed because an entered integer value is outside the valid range. (element name = {0})

Cause: The entered value must be an integer less than {1}.

Action: Revise the entered value.

{0}: Element name

{1}: Maximum integer

KNAQ00920-E

The operation failed because an entered value contains non-ASCII characters. (element name: {0})

Cause: An entered value contains non-ASCII characters.

Action: Revise the entered value.

{0}: Element name

KNAQ00921-E

The operation failed because an entered value contains control characters. (element name: {0})

Cause: An entered value contains control characters

Action: Revise the entered value.

{0}: Element name

KNAQ00922-E

The operation failed because an entered value contains surrogate pair characters. (element name: {0})

Cause: An entered value contains surrogate pair characters.

Action: Revise the entered value.

{0}: Element name

KNAQ00923-E

The operation failed because the entered value could not be converted to the original password. (element name = {0})

Cause: The entered value could not be converted to the original password.

Action: Revise the entered value.

{0}: Element name

KNAQ00924-E

The operation failed because non-ASCII characters were entered for the original password. (element name: {0})

Cause: Non-ASCII characters were entered for the original password.

Action: Revise the entered value.

{0}: Element name

KNAQ00925-E

The operation failed because the value entered for the original password is outside the range for the allowed number of characters in a string. (element name: {0})

Cause: The entered original password must be from {1} to {2} characters.

Action: Revise the entered value.

{0}: Element name

{1}: Minimum length

{2}: Maximum length

KNAQ00926-E

The operation failed because an entered value is an invalid string. (element name: {0})

Cause: An entered value is an invalid string. (correct string: [{1}])

Action: Revise the entered value.

{0}: Element name

{1}: correctString

KNAQ00927-E

The operation failed because a member that cannot be specified in the query parameter is specified. (element name: {0})

Cause: A member that cannot be specified in the query parameter is specified.

Action: Revise the members specified in the query parameters.

{0}: Element name

KNAQ00928-E

The operation failed because an invalid value is specified for the profile threshold value. (threshold value name: {0}, member name: {1})

Cause: An invalid value is specified for the profile threshold value.

Action: Revise the profile threshold value.

{0}: Threshold value name

{1}: Member name

KNAQ00929-E

Non-existent data was referenced. (element name: {0}, non-existent data: {1})

Cause: The specified data does not exist.

Action: Revise the entered value.

{0}: Element name

{1}: Non-existent data

KNAQ00930-E

The operation failed because an invalid value is specified in the query parameter. (element name: {0})

Cause: The invalid value is specified in the Query Parameter.

Action: Revise the values specified in the query parameters.

{0}: Element name

KNAQ00931-E

The operation failed because a format of entered value is invalid. (element name: {0})

Cause: A format of entered value is invalid.

Action: Revise the entered value.

{0}: Element name

KNAQ00986-E

E2E view can not be shown because there is too many resources that cannot be handled by E2E view.

Cause: There is too many resources that cannot be handled by E2E view.

Action: Please reduce the number of the base point, or, change the base point.

KNAQ00987-I

E2E view can not be shown because there is no resources.

KNAQ00988-E

E2E view can not be shown because the resource does not support E2E view.

Cause: The resource does not support E2E view.

Action: Please select other resource.

KNAQ00989-E

E2E view can not be shown because the resources(component) is not managed.

Cause: The resource(component) is not managed.

Action: Please make the resources(component) as managed.

KNAQ00990-E

E2E view can not be shown because the resources(device) is not managed.

Cause: The resources(device) is not managed.

Action: Please make the resources(device) as managed.

KNAQ00991-E

I was received incorrect content.

Cause: Input contents missing.

Or, contains can not be processed in the input content data.

Action: Please contact the administrator.

KNAQ00992-E

Authentication error has occurred.

Cause: User information at the time of login is not valid.

Action: Review the user information, please log in again.

If you fail to log in, please contact the administrator.

KNAQ00993-E

Operation that is not allowed have been made.

Cause: You do not have permission to operate to the user at login.

Action: Please contact the administrator.

KNAQ00994-E

Non-existent data was referenced.

Cause: The specified data does not exist.

Action: Please refresh your screen.

KNAQ00995-W

Registration of duplicate data have been made.

Cause: The specified data already exists.

Action: Please review your entries.

KNAQ00996-E

A failure occurred when communicating with the service.

Cause: Service is not running.

Or, an error has occurred in the service.

Action: Please contact the administrator.

KNAQ00997-E

An internal error has occurred.

Cause: The product services have not started properly or the environment might be invalid.

Action: Stop the product services, and then restart them. After that, try the operation again. If the problem persists, use the data collection tool to collect data, and contact a system administrator.

KNAQ01901-W

The configuration file contains an error (file name: {0}, line number: {1}).

Action: Edit the specified value in the configuration file.

{0}: File name

{1}: Line Number

KNAQ03000-I

The {0} command will now start.

{0}: Command name

KNAQ03001-I

The {0} command ended normally.

{0}: Command name

KNAQ03002-E

The {0} command ended abnormally ({1}).

{0}: Command name

{1}: Return code

KNAQ03003-E

The specified argument is incorrect.

Action: Review the specified argument, and then try again.

KNAQ03004-W

The execution of the {0} command stopped.

{0}: Command name

KNAQ03005-E

You do not have access permission to execute the {0} command.

Action: Check the permissions, and then retry the operation.

{0}: Command name

KNAQ03006-W

The command ended because it cannot be executed concurrently with another command.

Action: Wait for the previous command to end, and then re-execute the command.

KNAQ03007-E

The specified folder was not found (folder name: {0}).

Action: Specify an existing folder, and then try again.

{0}: Folder name

KNAQ03008-E

Cannot connect to the server (host: {0}, port: {1}, protocol: {2}).

Action: Check the server name. Make sure that the specified service is running. Check the communication path to the server, and then retry the operation.

{0}: IP address or host name

{1}: Port

{2}: Protocol

KNAQ03009-E

The password file could not be loaded (path: {0}).

Action: Re-create the password file, and then try again. Alternatively, use the existing password specified as an option and re-execute the command.

{0}: Path name

KNAQ03010-E

User authentication failed.

Cause: The specified user name, password or password file is incorrect. Or the proper user permissions are not set.

Action: Specify the correct user name, password and password file, or confirm the assigned permissions, and then retry the operation.

KNAQ03011-E

The specified character encoding is not supported.

Cause: The specified character encoding is not supported.

Action: Specify a supported character encoding, and then retry the operation.

KNAQ03012-E

The {0} service is inactive or has not completely started.

Action: Check the status of the service. If the service is inactive, start the service. If the service has not completely started, restart the service.

{0}: Service name

KNAQ03013-E

The {0} service has not stopped.

Action: Stop the service.

{0}: Service name

KNAQ03014-E

Cannot start the service {0}.

Action: If you have already performed some operation that uses the service, wait a while, and then retry the operation.

{0}: Service name

KNAQ03015-E

Cannot stop the service {0}.

Action: If you have already performed some operation that uses the service, wait a while, and then retry the operation.

{0}: Service name

KNAQ03016-E

The specified folder is not empty (folder name: {0}).

Cause: The specified folder contains files or folders.

Action: Specify an empty folder, and then retry the operation.

{0}: Folder name

KNAQ03017-E

The specified path does not exist (path: {0}).

Action: Specify an existing path, and then retry the operation.

{0}: Path name

KNAQ03018-E

There is not enough memory or disk space.

Action: Wait a few minutes, and then retry when the computer is running limited processes. Alternatively, delete any unnecessary files, and then try again.

KNAQ03019-E

The specified character string is too long for the option value (option: {0}).

Action: Modify the specified option value, and then re-execute the command.

{0}: option

KNAQ03032-E

Analytics could not be backed up.

KNAQ03034-E

A database access error occurred.

Cause: Database files might be corrupted.

Action: After collecting information, reorganize the database. If the problem persists, you will need to re-create the database.

KNAQ03036-W

Unable to delete the backup data file (file name: {0}).

Action: Manually delete the backup data file.

{0}: File name

KNAQ03042-E

Restoration of Analytics failed.

KNAQ03044-E

The specified backup file is invalid.

Cause: The file required for restoration does not exist or it is corrupted.

Action: Re-execute the command with a valid backup file.

KNAQ03045-E

A database access error occurred.

Cause: The database has been blocked. Alternatively, database files might be corrupted.

Action: After collecting the required information, reorganize the database. If the problem persists, you will need to re-create the database.

KNAQ03050-I

Collection of RAS log data for Automation system will now start (maintenance information: {0}).

{0}: Maintenance information

KNAQ03051-I

Collection of RAS log data for Automation system was successful (maintenance information: {0}).

{0}: Maintenance information

KNAQ03052-E

Collection of RAS log data for Automation system failed (maintenance information: {0}, {1}).

{0}: Maintenance information

{1}: Return code of RAS_SCRIPT

KNAQ03053-W

Cannot delete the temporary folder (folder name: {0}).

Action: Manually delete the folder.

{0}: Folder path

KNAQ03054-W

Cannot archive the folder (folder name: {0}).

Action: Compress the folder.

{0}: Folder path

KNAQ03143-E

The character string specified as an option value contains one or more invalid characters (option: {0}).

Action: Specify valid characters as the option string value, and then then retry the operation.

{0}: Option

KNAQ03144-E

The path specified in the option cannot be accessed.

Cause: Possible causes are as follows:

- You do not have the permissions required to access the file or folder.
- There is not enough disk space.

Action: Confirm the following, and then try again:

- The file or folder permissions
- The unused disk space

KNAQ03147-E

The file specified in the option already exists (file name: {0}).

Action: Specify a path that does not already exist, and then retry the operation.

{0}: File name

KNAQ03148-E

An error occurred during processing.

Cause: The service might not have started.

If the service of the stop is a prerequisite, the service might not stopped.

Action: Restart the service. If the service of the stop is a prerequisite, check the service status. Please retry then.

If the error persists, collect the relevant information, and then contact the system administrator.

KNAQ03171-E

The password file format is incorrect.

Action: Re-create the password file.

KNAQ03174-E

Copying of a file failed (file name: {0}).

Cause: Possible causes are as follows:

- You do not have the permissions required to access the file or folder.
- There is not enough disk space.

Action: Confirm the following, and then try again:

- The file or folder permissions
- The unused disk space

{0}: File name

KNAQ03176-E

The server connection timed out.

Action: Wait a while, and then retry the operation.

KNAQ03179-E

{0} is not a file.

Action: Revise the specified option, and then retry the operation.

{0}: Specified file name

KNAQ03180-E

{0} is not a folder.

Action: Revise the specified option, and then retry the operation.

{0}: Specified folder name

KNAQ03182-E

Cannot create the specified file (file name: {0}).

Cause: Possible causes are as follows:

- You do not have the required permissions to access the file or folder.
- There is not enough disk space.

Action: Confirm the following, and then try again:

- The file or folder permissions
- The unused disk space

{0}: Path name

KNAQ03183-I

The file was created successfully.

KNAQ03184-E

Cannot read the file (file name: {0}).

Cause: Possible causes are as follows:

- The specified file does not exist.
- You do not have the required permissions to access the file or folder.

Action: Confirm the following, and then try again:

- Whether the specified file exists
- The file or folder permissions

{0}: Path name

KNAQ03185-E

Path acquisition failed.

Cause: A path might not be specified.

Action: Re-execute the command with a valid option specified. If the problem persists, collect the relevant information, and then contact a system administrator.

KNAQ03201-E

A folder with the same name as the specified path already exists (path: {0}).

Cause: If you specify a path without an extension, a folder with the same name as the specified path might already

exist.

Action: Revise the specified path, and then retry the operation.

{0}: File path

KNAQ03202-I

The service was started.

KNAQ03203-I

The service was stopped.

KNAQ03204-I

Processing to back up ({0}) was successful.

{0}: Backup information

KNAQ03205-E

Cannot back up ({0}).

Cause: Either the specified path is not on the local disk, or the environment is invalid.

Action: Revise the specified path or environment, and then try again. If the problem persists, collect the relevant information, and then contact your system administrator.

{0}: Backup information

KNAQ03208-I

Processing to restore ({0}) was successful.

{0}: Restore information

KNAQ03209-E

Cannot restore ({0}).

Cause: Either the specified path is not on the local disk, or the environment is invalid.

Action: Revise the specified path or environment, and then retry the operation. If the problem persists, collect the relevant information, and then contact your system administrator.

{0}: Restore information

KNAQ03210-W

Restore processing ({0}) finished with warnings.

Cause: Either the specified path is not on the local disk, or the environment is invalid.

Action: Revise the specified path or environment, and then retry the operation. If the problem persists, collect the relevant information, and then contact your system administrator.

{0}: Restore information

KNAQ03212-E

The specified path is invalid (path: {0}).

Cause: The specified path contains an invalid file or folder name.

Action: Confirm that the specified path does not contain any OS reserved word, and then retry the operation.

{0}: File path

KNAQ03213-E

Cannot start the service (service name: {0}).

Action: Collect the relevant information, and then contact your system administrator.

{0}: Service name

KNAQ03226-E

The user does not have the required permission to execute the command.

KNAQ03229-E

The specified option is invalid (option name: {0}).

Action: Revise the specified option, and then retry the operation.

{0}: Option name

KNAQ03525-E

The environment for the restore may become mismatched with the environment backed up.(mismatch information: {0}, backup information: {1}, restore information: {2})

{0}: mismatch information

{1}: backup information

{2}: restore information

KNAQ03526-E

The backup file is invalid. Backup command may fail.

KNAQ03530-I

Monitoring status changed to enable(ID: {0}).

{0}: Resource ID

KNAQ03531-I

Monitoring status changed to disable(ID: {0}).

{0}: Resource ID

KNAQ03532-E

Failed to change monitoring status (ID: {0}).

Action: Revise the environment, and then try again. If the problem persists, collect the necessary information, and then contact your system administrator.

{0}: Resource ID

KNAQ03533-W

The specified ID was not found (ID: {0}).

Action: Review the specified argument, and then try again.

{0}: Resource ID

KNAQ03534-E

The JSON format differs from the schema.

Action: Revise the JSON, and then retry the operation.

KNAQ03535-E

Cannot acquire the resource list (type: {0}).

Action: Revise the environment, and then try again. If the problem persists, collect the necessary information, and then contact your system administrator.

{0}: Resource type

KNAQ03540-I

The number of reload target files: {0}

{0}: the number of reload target files

KNAQ03541-I

The number of files successfully reload: {0}

{0}: the number of files successfully reload

KNAQ03542-W

{0} files cannot reload.

Cause: You may not have the permissions required to access the file or folder.

Action: Confirm the permissions required to access the file or folder, and then try again.

{0}: The number of files reload failed

KNAQ03543-E

Reload property failed.

Action: Revise the environment, and then try again. If the problem persists, collect the necessary information, and then contact your system administrator. For details, please check the log files.

KNAQ03544-E

The specified path is not directory({0}).

Cause: Either the specified path is not on the local disk.

Action: Revise the specified path, and then try again. If the problem persists, collect the relevant information, and then contact your system administrator.

{0}: path

KNAQ03565-E

The input file format is invalid. (line: {0},column: {1})

Action: Check input file format, and try again.

{0}: Line number

{1}: Column number

KNAQ03566-E

Failed to change credential.

Action: Revise the environment, and then try again. If the problem persists, collect the necessary information, and then contact your system administrator.

KNAQ03567-I

The credential (line: {0},name: {1}) was changed.

{0}: Line number

{1}: Credential name

KNAQ03568-E

The credential ({0}) cannot be changed. A credential with the same as the target has already been registered.

Action: Run it again by using the other name.

{0}: Credential name

KNAQ03569-E

The credential (line: {0},name: {1}) cannot be changed. The system cannot find the credential specified.

Action: Run it again by using the other name.

{0}: Line number

{1}: Credential name

KNAQ03570-E

Failed to create consumer.

Action: Revise the environment, and then try again. If the problem persists, collect the necessary information, and then contact your system administrator.

KNAQ03571-I

The consumer (line: {0},name: {1}) was created.

{0}: Line number

{1}: Consumer name

KNAQ03572-E

The consumer ({0}) cannot be changed. A consumer with the same name has already been registered.

Action: Run it again by using the other name.

{0}: Consumer name

KNAQ03573-E

Failed to obtain the list of consumers.

Action: Revise the environment, and then try again. If the problem persists, collect the necessary information, and

then contact your system administrator.

KNAQ03574-I

The list of consumers was obtained successfully. (output file path: {0})

{0}: Output file path

KNAQ03575-E

The path specified already exists. ({0})

Action: Specify a path that is not exists.

{0}: Output file path

KNAQ03576-E

The {0} (name: {1}) cannot be created, because it has the same name as another {0} that has already been registered.

Action: Run it again by using the other name.

{0}: Setting type

{1}: Setting information name

KNAQ03577-E

The {0} (name: {1}) cannot be added, because it has the same name as another {0} that has already been registered.

Action: Run it again by using the other name.

{0}: Setting type

{1}: Setting information name

KNAQ03578-E

The IP address range (name: {0}) cannot be added. A duplicate IP address range was specified.

Action: Run it again by using the other range.

{0}: IP Range name

KNAQ03579-E

Plural JP1/IM - Manager and cooperation setting are not possible.

Action: Please change setting information of JP1/IM - Manager.

KNAQ03580-E

The IP address range (line: {0},name: {1}) cannot be added. The system cannot find the credential specified.

Action: Run it again by using the other name.

{0}: Line number

{1}: IP add range name

KNAQ03581-E

Failed to create the {0} (name: {1}).

Action: Revise the environment, and then try again. If the problem persists, collect the necessary information, and then contact your system administrator.

{0}: Setting type

{1}: Setting information name

KNAQ03582-E

Failed to add the {0} (name: {1}).

Action: Revise the environment, and then try again. If the problem persists, collect the necessary information, and then contact your system administrator.

{0}: Setting type

{1}: Setting information name

KNAQ03583-I

The {0} (name: {1}) was created successfully.

{0}: Setting type

{1}: Setting information name

KNAQ03584-I

The {0} (name: {1}) was added successfully.

{0}: Setting type

{1}: Setting information name

KNAQ03585-E

Failed to change the {0} (ID: {1}, name: {2}).

Action: Revise the environment, and then try again. If the problem persists, collect the necessary information, and then contact your system administrator.

{0}: Setting type

{1}: Line number

{2}: Setting information name

KNAQ03586-I

The {0} (ID: {1}, name: {2}) was changed successfully.

{0}: Setting type

{1}: Setting information name

KNAQ03587-E

The {0} (ID: {1},name: {2}) cannot be changed. The system cannot find the {0}(ID:{1},name:{2}) specified.

{0}: Setting type

{1}: ID

{2}: Setting information name

KNAQ03588-E

The specified credential could not be associated with the search range condition.

Action: Please wait a few minutes, then try again.If the error occurs repeatedly, use the data collection tool to collect data and contact a system administrator.

KNAQ03589-E

The {0} (name: {1}) cannot be changed, because it has the same name as another {0} that has already been registered.

Action: Run it again by using the other name.

{0}: Setting type

{1}: Setting information name

KNAQ03590-E

Failed to delete the {0} (ID: {1}, name: {2}).

Action: Revise the environment, and then try again. If the problem persists, collect the necessary information, and then contact your system administrator.

{0}: Setting type

{1}: Line number

{2}: Setting information name

KNAQ03591-E

The {0} ({1}) was deleted successfully.

{0}: Setting type

{1}: Setting information name

KNAQ03592-E

The {0} (name: {1}) cannot be deleted. The system cannot find the {0} (name: {1}) specified.

{0}: Setting type

{1}: Setting information name

KNAQ03593-E

You cannot delete this credential. This credential is being used by one or more resources.

Action: Delete or modify the resources that use the credential as necessary. Then try again.

KNAQ03594-E

Default threshold profile cannot be deleted.

Action: Run it again by using the other name.

KNAQ03595-E

Failed to obtain the {0}.

Action: Revise the environment, and then try again. If the problem persists, collect the necessary information, and then contact your system administrator.

{0}: Setting type

KNAQ03596-E

The input file format is invalid. (Detail: {0})

Action: Check input file format, and try again.

{0}: detail

KNAQ03598-E

A retention period shorter than the set value was entered.

Set value: {0} [{1}]

Entered value: {2} [{3}]

The period cannot be shortened.

{0}: settingRetention

{1}: settingUnit

{2}: inputRetention

{3}: inputUnit

KNAQ03599-E

A retention period that is the same as the set value was entered.

Set value: {0} [{1}]

Entered value: {2} [{3}]

{0}: settingRetention

{1}: settingUnit

{2}: inputRetention

{3}: inputUnit

KNAQ03600-I

The retention period will change.

Period before the change: {0} [{1}]

Period after the change: {2} [{3}]

{0}: settingRetention

{1}: settingUnit

{2}: inputRetention

{3}: inputUnit

KNAQ03601-I

The current retention period is {0} [{1}].

{0}: settingRetention

{1}: settingUnit

KNAQ03602-E

The format of the input file is invalid. (line {0})

Action: Check the format of the input file, and try again.

{0}: Line Number

KNAQ03610-E

Failed to add the {0} (name: {1}).

{0}: Setting type

{1}: Detail

KNAQ03611-E

Failed to update the {0} (name: {1}).

{0}: Setting type

{1}: Detail

KNAQ03616-I

The file was created successfully. (output destination: {0})

{0}: Output file path

KNAQ03617-E

Failed to create the file.

Action: Revise the environment, and then try again. If the problem persists, collect the necessary information, and then contact your system administrator.

KNAQ03618-W

The /withrelation option cannot be specified for the specified resource. (ID: {0})

Action: Try again without the /withrelation option.

{0}: Resource ID

KNAQ03619-W

The specified ID was not found. (ID: {0})

Action: Try again with an existing ID.

{0}: Specified ID

KNAQ03620-W

The number of specified IDs exceeds the upper limit. (upper limit: {0})

Action: Make sure the number of IDs does not exceed the upper limit, and then try again.

{0}: upper limit

KNAQ03621-E

The character string specified for the option is outside the specifiable range. (option: {0})

Action: Modify the specified option value, and then try again.

{0}: option

KNAQ03622-Q

Continue processing? (y/n):

KNAQ03623-I

The application relation definitions were changed successfully.

KNAQ03624-W

Failed to change the application relation definitions.

Cause: You may have the wrong format in csv file.

Action: Confirm the csv file format, and then try again. For details, please check the log files.

KNAQ03625-I

The templates were changed successfully.

KNAQ10084-E

Cannot start the application.

Action: Start the server. If this problem persists, contact the Support Center.

KNAQ10086-I

Application is running.

KNAQ10089-I

Application is stopped.

KNAQ10195-E

No content is available for the specified resource type and metric type.

KNAQ10199-E

An unexpected error occurred.(detail = {0})

{0}: Detail

KNAQ13000-E

An error occurred while getting JP1 Events.

Cause: Either JP1/Integrated Management - Manager did not start properly, or the service is busy.

Action: Confirm the service is running and accessible. If the service is running and accessible, wait a few minutes and try again.If the problem persists, use the data collection tool to collect data, and contact a system administrator.

KNAQ70001-E

The number of columns is incorrect. (rows: {0})

Action: Revise the contents of the file.

{0}: Row numbers

KNAQ70002-E

The field name is duplicated. (duplicated field name:{0})

Action: Revise the contents of the file.

{0}: Duplicated field name

KNAQ70003-E

The date field was not found.

Action: Specify the date field {0}.

{0}: Date field

KNAQ70004-E

The date format is invalid. (rows:{0})

Action: Change the format of the date and time to one of the following formats:

{1}

{0}: Row numbers

{1}: Date format

KNAQ70005-E

The date value is duplicated. (rows:{0})

Action: Revise the contents of the file.

{0}: Row numbers

KNAQ70006-E

Non-numeric values are specified for items that require numeric values. (rows: {0})

Action: Revise the contents of the file.

{0}: Row numbers

KNAQ70007-E

The number of concurrent executions reached the upper limit.

Action: Wait a while, and then re-execute the operation.

KNAQ70008-E

Only one of the following items is defined in the imported file:

- {0}

- {1}

Action: Define both items.

{0}: Resource name

{1}: Component name

KNAQ70009-E

An attempt to read the file failed. The possible causes are as follows:

- (1) There is no line feed at the end of the file.
 - (2) The imported file is not a text file.
 - (3) The size of the file exceeds the maximum file size. (max. file size: {0})
-

{0}: Maximum file size

KNAQ70011-E

The data portion is not defined in the imported file.

Action: Revise the contents of the file.

KNAQ70012-E

Items required to make the file readable are not defined.

Action: Revise the contents of the file.

KNAQ70013-E

A definition file failed to load(file:{0}).

Action: Make sure that the definition file can be read.

{0}: File path

KNAQ73001-I

The custom-collector definitions were applied. (successful:{0}, failed:{1})

Action: If there is a collector for which application of the definition failed, check the log files.

{0}: Successful

{1}: Failed

KNAQ73002-I

Results of applying the custom collector: collector name = {0}, processing = {1}, result = {2}

{0}: Collector name

{1}: Processing

{2}: Result

KNAQ73003-W

A custom-collector definition failed to load.

KNAQ73004-W

Application of a custom-collector definition failed. An unexpected exception occurred.

KNAQ73005-E

The specified collector cannot be deleted.

Action: Specify a collector that can be deleted.

1.4 List of messages (for common component)

1.4.1 Messages starting with KAPM

KAPM00001-E

ID=aa...aa,LogTraceLibrary error.Trace START failed. bb...bb

aa...aa: Program ID using the log

bb...bb: Error messages that the log trace library give

KAPM00002-E

ID=aa...aa,LogtraceLibrary error.Trace STOP failed. bb...bb

aa...aa: Program ID using the log

bb...bb: Error messages that the log trace library give

KAPM00003-W

ID=aa...aa,Trace output error.

aa...aa: Program ID using the log

KAPM00004-W

ID=aa...aa,Integrated trace output error.

aa...aa: Program ID using the log

KAPM00005-E

File I/O failed.(filename=aa...aa).

aa...aa: filename

KAPM00006-E

ID=aa...aa,Invalid eventlog source.Eventlog's config not found in the registry(source name="HiCommand Log")

aa...aa: Program ID using the log

KAPM00011-E

ID=aa...aa,Versionfile name is null.

aa...aa: Program ID using the log

KAPM00012-E

ID=aa...aa,PP version is null.

aa...aa: Program ID using the log

KAPM00013-E

ID=aa...aa,Trace log file name is null.

aa...aa: Program ID using the log

KAPM00014-E

ID=aa...aa,Class name is null.

aa...aa: Program ID using the log

KAPM00015-E

ID=aa...aa,Kind of Event is null.

aa...aa: Program ID using the log

KAPM00016-E

ID=aa...aa,Message-ID is null.

aa...aa: Program ID using the log

KAPM00017-E

aa...aa

aa...aa: The message of NullPointerException

KAPM00018-E

aa...aa

aa...aa: The message of Exception

KAPM00019-E

ID=aa...aa,SyslogID size error:idEnt=bb...bb

aa...aa: Program ID using the log

bb...bb: Eventlog ID

KAPM00020-E

ID=aa...aa,Invalid version length:version=bb...bb

aa...aa: Program ID using the log

bb...bb: version

KAPM00021-E

ID=aa...aa,Invalid log file number:logNum=bb...bb

aa...aa: Program ID using the log

bb...bb: Log file number

KAPM00022-E

ID=aa...aa,Invalid log file size:logSize=bb...bb

aa...aa: Program ID using the log

bb...bb: Log file size

KAPM00023-E

ID=aa...aa,Invalid message type:kind=bb...bb

aa...aa: Program ID using the log

bb...bb: Message type

KAPM00024-E

ID=aa...aa,Invalid output level:level=bb...bb

aa...aa: Program ID using the log

bb...bb: Output level

KAPM00025-E

The value of the encoding setting bb...bb of the unique log output of aa...aa is invalid.

aa...aa: Program name that requested the log output

bb...bb: Encoding

KAPM00090-I

The SSO server started successfully.

KAPM00091-E

An attempt to start the SSO server has failed.

KAPM00092-I

The SSO server was stopped successfully.

KAPM00101-E

An authentication error occurred.

KAPM00102-E

An error occurred during DBMS access processing.

KAPM00103-E

The DBMS is not running.

KAPM00104-E

The product name is not specified.

KAPM00105-E

An unexpected value was returned from the integrated authentication server. (aa...aa)

aa...aa: An unexpected returned value

KAPM00106-E

An attempt to update the authentication data has failed.

KAPM00107-E

An attempt to delete the authentication data has failed.

KAPM00108-E

An attempt to print the authentication data has failed.

KAPM00110-E

The HSSOContext value is invalid.

KAPM00111-I

The authentication data was successfully updated.

KAPM00112-I

The authentication data was successfully deleted. (aa...aa)

aa...aa: Product name

KAPM00113-I

The authentication data is already deleted. (aa...aa)

aa...aa: Product name

KAPM00114-I

The authentication data was successfully displayed.

KAPM00115-E

An attempt to communicate with the SSO server has failed.

KAPM00116-E

An attempt to update authentication data has failed.

KAPM00117-E

The RD area of HBase is blocked.

KAPM00119-E

Deletion of the license event data has failed.

KAPM00130-E

There is no value in the request.

KAPM00131-E

A required token is not specified.

KAPM00132-E

The event name is invalid.

KAPM00133-E

The DBMS is not running.

KAPM00134-E

An error occurred during a DBMS access.

KAPM00137-E

An authentication error occurred.

KAPM00138-E

Authentication data for delete processing is invalid.

KAPM00139-I

Deletion of authentication data for all products will now start.

KAPM00140-I

Deletion of authentication data will now start.

Application name: aa...aa

Service name: bb...bb

aa...aa: Application name

bb...bb: Service name

KAPM00141-E

An attempt to lock the table has failed.

KAPM00145-E

The RD area of HBase is blocked.

KAPM00146-E

Requests containing QueryString are not accepted.

KAPM00162-E

There is an error in the protocol. (element = aa...aa)

aa...aa: element

KAPM00163-E

There is an error in the protocol. (element = aa...aa, attribute = bb...bb, value = cc...cc)

aa...aa: element
bb...bb: attribute
cc...cc: value

KAPM00192-E

An exception was detected.

KAPM00199-E

aa...aa

aa...aa: Cause that has occurred and the exception object name or back trace of the exception object

KAPM00203-E

The DBMS is not running.

KAPM00204-E

The RD area of HBase is blocked.

KAPM00205-E

An error occurred during access to the DBMS.

KAPM00206-E

The specified event data has already been registered. (application type = aa...aa, event type = bb...bb, event code = cc...cc)

aa...aa: application type

bb...bb: event type

cc...cc: event code

KAPM00207-E

Event data cannot be updated because no event data exists. (application type = aa...aa, event type = bb...bb, event code = cc...cc)

aa...aa: application type

bb...bb: event type

cc...cc: event code

KAPM00208-E

Communication with the SSO server has failed.

KAPM00209-E

Authentication has failed.

KAPM00210-E

A program type specified for TNB_SoftwareFeature is not registered. (application type = aa...aa)

aa...aa: application type

KAPM00211-E

Associated data does not exist. (application type = aa...aa)

aa...aa: application type

KAPM00212-E

An event management object cannot be deleted because the specified parameter is invalid. (application type = aa...aa, event type = bb...bb, event code = cc...cc)

aa...aa: application type
bb...bb: event type
cc...cc: event code

KAPM00213-E

The value registered in the database is invalid. (application type = aa...aa, event type = bb...bb, event code = cc...cc)

aa...aa: application type
bb...bb: event type
cc...cc: event code

KAPM00214-E

The same information is already registered in the database. (application type = aa...aa, event type = bb...bb, event code = cc...cc)

aa...aa: application type
bb...bb: event type
cc...cc: event code

KAPM00215-E

An attribute value is invalid. (attribute = aa...aa)

aa...aa: attribute

KAPM00216-W

The attribute length exceeds the maximum limit. (attribute = aa...aa, value = bb...bb, maximum limit = cc...cc)

aa...aa: attribute
bb...bb: value
cc...cc: maximum limit

KAPM00217-E

An invalid parameter is specified.

KAPM00218-W

The relation between the license warning window and the version window is not registered. (application type = aa...aa)

aa...aa: application type

KAPM00252-E

The license information file does not exist. (license information file = aa...aa)

aa...aa: license information file

KAPM00253-E

The license information file might be corrupted. (license information file = aa...aa)

aa...aa: license information file

KAPM00254-E

An attempt to read the license information file has failed. (license information file = aa...aa)

aa...aa: license information file

KAPM00255-E

The license information file cannot be accessed. (license information file = aa...aa)

aa...aa: license information file

KAPM00256-E

The license information file contains invalid information. (line number = aa...aa, value = bb...bb)

aa...aa: line number

bb...bb: value

KAPM00257-E

The format ID of the license information in the license information file is invalid. (format ID = aa...aa)

aa...aa: format ID

KAPM00258-E

The length of the license information in the license information file is invalid. (format ID = aa...aa, number of characters = bb...bb)

aa...aa: format ID

bb...bb: number of characters

KAPM00259-E

Valid license information does not exist.

KAPM00260-E

The PPID in the license information file contains non-hexadecimal characters. (PPID = aa...aa)

aa...aa: PPID

KAPM00261-E

The device number in the license information file contains non-alphanumeric characters. (device number = aa...aa)

aa...aa: device number

KAPM00262-E

The license type in the license information file is invalid. (license type = aa...aa)

aa...aa: license type

KAPM00263-E

The license capacity in the license information file contains non-alphanumeric characters. (license capacity = aa...aa)

aa...aa: license capacity

KAPM00264-E

The expiration date in the license information file contains non-numerical characters. (expiration date = aa...aa)

aa...aa: expiration date

KAPM00265-E

The serial number in the license information file contains non-alphanumeric characters. (serial number = aa...aa)

aa...aa: serial number

KAPM00266-E

The subscription license capacity in the license information file contains non-alphanumeric characters. (capacity of subscription license = aa...aa)

aa...aa: capacity of subscription license

KAPM00267-E

The device type in the license information file contains non-alphanumeric characters. (device type = aa...aa)

aa...aa: device type

KAPM00269-E

The specified argument is invalid.

KAPM00270-E

The used capacity of the specified storage system is invalid. (used capacity = aa...aa)

aa...aa: used capacity

KAPM00271-E

The license is in emergency status.

KAPM00272-E

The meter-based term license capacity cannot be reduced because a meter-based term license cannot be applied to the target storage system.

KAPM00273-E

The capacity after reduction falls below the minimum of -99,999,999 TB.

KAPM00274-E

The specified license information is invalid. (attribute = aa...aa)

aa...aa: attribute

KAPM00275-W

The current storage system's used capacity is within the range of the usable capacity under a permanent license. (usable capacity under permanent license = aa...aa, usable capacity under meter-based term license = bb...bb)

aa...aa: usable capacity under permanent license

bb...bb: usable capacity under meter-based term license

KAPM00276-E

The usable capacity under the meter-based term license is less than 0. (usable capacity under meter-based term license = aa...aa)

aa...aa: usable capacity under meter-based term license

KAPM00277-W

An attempt to write to the license history has failed.

KAPM00278-W

An attempt to modify the file attribute failed. (file name = aa...aa)

aa...aa: file name

KAPM00279-E

Exclusive control has failed.

KAPM00280-E

A time out occurred during exclusive control.

KAPM00281-E

The meter-based term licensed capacity cannot be reduced because aa...aa day(s) passed since the usable license capacity became negative.

aa...aa: The number of days from the date on which the capacity of the license becomes minus

KAPM00282-W

The license information file does not exist. (application type = aa...aa)

aa...aa: application type

KAPM00283-E

The license information file might be corrupted. (application type = aa...aa)

aa...aa: application type

KAPM00284-E

An attempt to read the license information file failed. (application type = aa...aa)

aa...aa: application type

KAPM00285-E

The license information file cannot be accessed. (application type = aa...aa)

aa...aa: application type

KAPM00286-E

The number of servers after the subtraction operation fell below the minimum value -99,999,999.

KAPM00287-E

Information related to the exclusion control failure will be output. (function name = aa...aa, detailed error code = bb...bb, processing time = cc...cc)

aa...aa: function name

bb...bb: detailed error code

cc...cc: processing time

KAPM00288-E

An attempt to release the lock failed.

KAPM00900-I

The SSO server started successfully.

KAPM00901-E

An attempt to start the SSO server has failed.

KAPM00902-I

The SSO server was stopped successfully.

KAPM01001-I

Initializing HssoServer configuration.

KAPM01002-E

The system property indicated by hcnds.home could not be found.

KAPM01003-E

HssoServerRes1_0.dtd was not found. path= aa...aa

aa...aa: The folder path in which HssoServerRes1_0.dtd is put

KAPM01004-E

Can't read DTD files.

KAPM01005-W

Failed to close FileStream.

KAPM01008-I

HTTP:POST from aa...aa

aa...aa: IP address

KAPM01010-E

Can't get InputStream from Request.

KAPM01013-E

Unsupported command was requested.

KAPM01017-E

Unsupported method was requested.

KAPM01019-E

Unsupported method was requested.

KAPM01024-I

Request Information: Version = aa...aa, Command = bb...bb, ID = cc...cc

aa...aa: HSSO protocol version

bb...bb: Command name of HSSO

cc...cc: User ID or session ID

KAPM01025-E

A fatal error occurred.

KAPM01026-E

An attempt to initialize the HSSO Server configuration has failed.

KAPM01028-E

The file "aa...aa" could not be read. Path = bb...bb

aa...aa: file name

bb...bb: The absolute path of the file

KAPM01034-E

Can't get the required information from request. Request is invalid.

KAPM01036-E

Request XML can't parse to DOM. - aa...aa

aa...aa: The message of Exception

KAPM01040-E

XML version aa...aa for HssoClient is not supported.

aa...aa: Version of the request

KAPM01042-E

An attempt to parse the request has failed.

KAPM01046-E

The format of the request was invalid. Cause = aa...aa

aa...aa: Cause

KAPM01051-E

The creation of HSSOContext for authentication has failed. aa...aa

aa...aa: The message of Exception

KAPM01052-I

aa...aa accessed.

aa...aa: user ID

KAPM01053-E

Authentication Failed.

KAPM01055-E

The system property specified in hcnds.home cannot be found.

KAPM01056-E

HDVM.user not found at hcnds.home.

KAPM01057-E

HDVM.password not found at hcnds.home.

KAPM01059-E

The specified HSSO session is invalid, or does not exist. Session ID = aa...aa

aa...aa: Session ID that is specified in the request

KAPM01061-E

An invalid value is set in the configuration file. Parameter = aa...aa

aa...aa: Parameter name

KAPM01062-E

A parameter is not set in the configuration file. Parameter = aa...aa

aa...aa: Parameter name

KAPM01063-I

HSSO configuration: Virtual Host Name = aa...aa

aa...aa: Virtual Host Name

KAPM01065-E

Can't create DOM tree. - aa...aa

aa...aa: The message of Exception

KAPM01066-E

A CIM Repository exception occurred.

KAPM01067-E

The status of the response from Device Manager was FAILED.

KAPM01068-E

aa...aa

aa...aa: Error information that is included in the HiCommand Device Manager of response

KAPM01069-E

The protocol version aa...aa for HSSO Client is not supported.

aa...aa: Protocol version

KAPM01073-E

The format of the response from Device Manager was invalid.

KAPM01081-E

Authentication has failed. User ID = aa...aa

aa...aa: User ID

KAPM01084-I

The HSSO session has started. Session ID = aa...aa

aa...aa: Session ID

KAPM01087-W

The specified HSSO session is invalid, or does not exist. Session ID = aa...aa

aa...aa: Session ID

KAPM01088-E

An attempt to load the class failed. Class = aa...aa

aa...aa: Class name

KAPM01089-E

An attempt to create the instance of the class for authentication failed. Class = aa...aa

aa...aa: Class name

KAPM01090-E

An attempt to create the instance of the class for authorization failed. Class = aa...aa

aa...aa: Class name

KAPM01091-E

An attempt to initialize the authentication class failed. Class = aa...aa

aa...aa: Certification class

KAPM01092-E

An attempt to initialize the authorization class failed. Class = aa...aa

aa...aa: Approval class

KAPM01093-I

HSSO configuration: Authentication class = aa...aa

aa...aa: Certification class

KAPM01094-I

HSSO configuration: Authorization class = aa...aa

aa...aa: Approval class

KAPM01095-E

The authenticated user does not have permission. User ID = aa...aa, Application = bb...bb

aa...aa: User ID

bb...bb: Application name

KAPM01096-E

An attempt to authenticate the internal user has failed.

KAPM01097-E

An exception occurred during internal authentication module processing.

KAPM01098-E

An exception occurred during authentication module processing.

KAPM01099-E

An exception occurred during authorization module processing.

KAPM01103-I

HSSO configuration: Device Manager Server URL = aa...aa

aa...aa: HiCommand Device Manager Server URL

KAPM01104-I

HSSO configuration: Device Manager Server Connection Timeout = aa...aa

aa...aa: Timeout period

KAPM01105-E

The JP1 token is invalid.

KAPM01106-E

An attempt to communicate with JP1/Base has failed.

KAPM01107-E

An error occurred due to a virtual host name. Function Code = aa...aa, Result Code = bb...bb

aa...aa: Function Code

bb...bb: Result Code

KAPM01108-E

An attempt to load the library associated with JP1/Base has failed.

KAPM01109-E

An exception occurred during JP1 token authentication processing. Function Code = aa...aa, Result Code = bb...bb

aa...aa: Function Code

bb...bb: Result Code

KAPM01114-E

An attempt to acquire the link and launch information failed.

KAPM01115-E

Exception in DeviceManager. DeviceManager returns FAILED. - aa...aa

aa...aa: Error message obtained from HiCommand Device Manager

KAPM01116-E

No user was returned from DeviceManager.

KAPM01119-E

No user information is set in the HSSO session.

KAPM01123-I

HSSO configuration: HSSO Session Timeout = aa...aa

aa...aa: Session Timeout (second)

KAPM01124-I

The login was successful. (session ID = aa...aa)

aa...aa: session ID

KAPM01125-E

The login process has failed.

KAPM01126-W

The logout processing failed because the user was already logged out. (session ID = aa...aa)

aa...aa: session ID

KAPM01152-E

Can't get the application name from request. Request is invalid.

KAPM01154-W

aa...aa is not registered.

aa...aa: Application name

KAPM01156-E

Exception in Repository. - aa...aa

aa...aa: Failure contents of the repository access

KAPM01167-E

The database has stopped.

KAPM01168-E

The RD area of HBase is blocked.

KAPM01169-E

Authentication of the JP1 token failed.

KAPM01172-E

An error occurred while linking to the external authentication server.

KAPM01176-E

An attempt to acquire the trusted server ID failed.

KAPM01177-E

An attempt to acquire the trusted server information has failed. (trusted server ID = aa...aa)

aa...aa: trusted server ID

KAPM01180-E

Granting of a permission failed because the client of the trusted server and the trusted server have different authentication methods. (user ID = aa...aa)

aa...aa: user ID

KAPM01181-E

Authentication has failed.

KAPM01182-E

Authentication has failed. User ID = aa...aa

aa...aa: User ID D

KAPM01183-E

An error occurred in communication with the HSSO server.

KAPM01184-E

An error occurred on the HSSO server.

KAPM01185-E

No groups that the user belongs to are registered.

KAPM01186-E

The authenticated user cannot be used in mutual authentication. (user ID = aa...aa)

aa...aa: user ID

KAPM01187-W

An attempt to record a login date failed. (user ID = aa...aa)

aa...aa: user ID

KAPM01188-I

The login date was recorded. (user ID = aa...aa, product name = bb...bb)

aa...aa: User ID

bb...bb: Product name

KAPM01190-E

An attempt to authenticate the user failed because a secret file is registered. (user id = aa...aa)

aa...aa: User ID

KAPM01191-E

An attempt to decrypt authentication data failed. (user id = aa...aa)

aa...aa: User ID

KAPM01192-E

The decrypted authentication data is invalid. (user id = aa...aa)

aa...aa: User ID

KAPM01193-E

Requests containing QueryString are not accepted.

KAPM01205-E

No instance of Service associated with ServiceAccessPoint.

KAPM01206-E

No instance of SoftwareFeature associated with Service.

KAPM01208-E

Exception in Repository. - aa...aa

aa...aa: Failure contents of the repository access

KAPM01209-W

ServiceAccessPoint is not registered.

KAPM01220-E

Communication with the external authentication server has failed.

KAPM01255-E

Exception in DeviceManager. DeviceManager returns FAILED. - aa...aa

aa...aa: Error message obtained from HiCommand Device Manager

KAPM01302-E

Can't get the host name or port number of DeviceManager from configuration.

KAPM01308-E

An attempt to communicate with Device Manager failed. URL = aa...aa

aa...aa: HiCommand Device Manager Server URL

KAPM01309-E

The Device Manager Server XML API version aa...aa is not supported.

aa...aa: version

KAPM01312-E

DeviceManager Server version aa...aa is not supported.

aa...aa: HiCommand Device Manager Server version

KAPM01314-E

The connection to Device Manager timed out.

KAPM01331-I

Connecting to DeviceManager Server specified by aa...aa

aa...aa: HiCommand Device Manager URL

KAPM01336-E

URL aa...aa is invalid to DeviceManager Server.

aa...aa: HiCommand Device Manager URL

KAPM01337-E

Authentication Failed in DeviceManager.

KAPM01338-E

I/O Error regarding connection to DeviceManager.

KAPM01353-E

Can not map aa...aa.

aa...aa: User rights

KAPM01401-I

Creating CIMClient.

KAPM01402-E

Can't create CIMClient. - aa...aa

aa...aa: The message of Exception

KAPM01503-W

The default value will be set because the value set for HTTP KeepAlive is invalid. (parameter name = aa...aa, parameter value = bb...bb, parameter default value = cc...cc)

aa...aa: parameter name

bb...bb: parameter value

cc...cc: parameter default value

KAPM02001-E

Can not be found database.

KAPM02001-W

Some of connection updated the same instance together. So didn't update the instance.

KAPM02002-E

Your user name and password are not defined.

KAPM02003-E

An unknown host exception occurred while trying to open a socket connection to server.

KAPM02004-E

No suitable driver.

KAPM02005-E

A socket exception occurred while trying to establish a socket connection to server.

KAPM02006-E

InterServer is unable to locate the InterBase application or service.

KAPM02007-E

aa...aa

aa...aa: The message of Exception

KAPM02008-E

aa...aa

aa...aa: The message of Exception

KAPM02009-E

Failed to unlock a table when inserting a record or records.

KAPM02010-E

Update data doesn't exist.

KAPM02011-E

Delete data doesn't exist.

KAPM02012-E

Search data doesn't exist.

KAPM02013-E

Exception happened when some CIM class was used.

KAPM02014-E

An attempt to load the definition for a class has failed. Class name = aa...aa

aa...aa: Class name

KAPM02015-E

A class definition could not be found. Class name = aa...aa

aa...aa: Class name

KAPM02016-E

A RepositoryException occurred.

KAPM02017-E

The parameter is null.

KAPM02018-E

The parameter is invalid.

KAPM02019-E

The CIMElement already exists.

KAPM02020-E

Duplicate data exists.

KAPM02021-E

The CIMElement could not be found.

KAPM02023-E

The CIMObjectPath is incorrect. A key is required.

KAPM02025-E

The CIMObjectPath contains an invalid property.

KAPM02027-E

The key property could not be changed.

KAPM02029-E

The initialize parameter is invalid.

KAPM02030-E

An unsupported data type was used.

KAPM02031-E

The CIMClass is invalid. A KEY property is required.

KAPM02032-E

The CIMClass could not be deleted, because it contains instances.

KAPM02033-E

The CIMClass could not be deleted, because it contains subclasses.

KAPM02034-E

A ClassNotFoundException occurred.

KAPM02035-E

A CIMInConnectionPoolException occurred.

KAPM02036-E

A connection to the database could not be established.

KAPM02038-W

A DeadLockException occurred. Description = aa...aa

aa...aa: Class name

KAPM02039-W

A CIMInDeadLockException occurred.

KAPM02040-E

The CIMInstance is invalid.

KAPM02041-E

The CIMObjectPath is invalid.

KAPM02042-E

The name of property is invalid.

KAPM02044-E

A DBNotFoundExpection occurred.

KAPM02045-E

The CIMClass is invalid.

KAPM02046-E

The CIMProperty is invalid. The KEY property must be set.

KAPM02047-E

The type of class is invalid.

KAPM02048-E

Failed to get membership groups.

KAPM02049-E

Not authorized object. ObjectName = aa...aa

aa...aa: ObjectName

KAPM02050-E

Host name is invalid.

KAPM02051-E

Cannot connect to InterClient.

KAPM02052-E

Cannot connect to InterBase.

KAPM02053-E

SQLException occurred. Description = aa...aa

aa...aa: Description

KAPM02054-E

Exception occurred. Description = aa...aa

aa...aa: Description

KAPM02055-E

CIMException occurred. Description = aa...aa

aa...aa: Description

KAPM02056-E

A CIMClassNotFoundException occurred.

KAPM02057-E

IOException occurred. Description = aa...aa

aa...aa: Description

KAPM02058-E

InterruptedException occurred. Description = aa...aa

aa...aa: Description

KAPM02059-E

The time limit for establishing a connection is over.

KAPM02060-E

An attempt to establish a connection has failed.

KAPM02061-E

aa...aa

aa...aa: Cause that has occurred and the exception object name or back trace of the exception object

KAPM02062-I

The get method changed the state to the standby state.

KAPM02063-I

The createConnection method changed the state to the standby state.

KAPM02069-E

A time-over error occurred when connecting to the repository.

KAPM02070-E

A CIMUnavailableDatabaseException occurred. Detailed message of exception = aa...aa

aa...aa: Detailed message of exception

KAPM02071-E

HiRDB is not running.

KAPM02072-E

The password of a user connected to HiRDB is invalid. (user name = aa...aa)

aa...aa: user name

KAPM02073-E

The user name of a user connected to HiRDB is invalid. (user name = aa...aa)

aa...aa: user name

KAPM02074-W

The table name registered into DBMS is changed. Before= aa...aa After = bb...bb

aa...aa: Before

bb...bb: After

KAPM02075-E

An attempt to set a connection to the factory has failed.

KAPM02076-I

Processing to initialize the connection pool was executed.

aa...aa: Initial value, bb...bb: Increment value, cc...cc: Maximum value, dd...dd: Keep-alive period, ee...ee: Timeout period, ff...ff: Number of retries, gg...gg: Retry interval

aa...aa: Initial value

bb...bb: Increment value

cc...cc: Maximum value

dd...dd: Keep-alive period

ee...ee: Timeout period

ff...ff: Number of retries

gg...gg: Retry interval

KAPM02077-E

An attempt to release the connection of the connection pool has failed.

KAPM02078-E

A RepositoryException occurred. (details = aa...aa)

aa...aa: details

KAPM02079-E

An attempt to release the JDBC connection has failed.

KAPM02080-E

A CIMHeldRepositoryException has occurred. Exception message = aa...aa

aa...aa: Exception message

KAPM02081-E

A hcmdsDBUserManagementException has occurred. (exception message = aa...aa)

aa...aa: Exception message

KAPM02201-I

The method was invoked.

KAPM02202-I

The following arguments were specified: aa...aa

aa...aa: Parameter

KAPM02203-I

External module processing has started. (module = aa...aa)

aa...aa: module name

KAPM02204-I

External module processing has terminated. (module = aa...aa)

aa...aa: module name

KAPM02210-E

The specified argument is null.

KAPM02211-E

The password is not set.

KAPM02212-E

Authentication has failed.

KAPM02213-E

An attempt to read the password file has failed.

KAPM02214-E

An attempt to write to the password file has failed.

KAPM02215-E

The authenticated user does not have permission to execute the method.

KAPM02216-E

The specified user was not found.

KAPM02217-E

The specified group was not found.

KAPM02218-E

The specified user already exists.

KAPM02219-E

The specified group already exists.

KAPM02220-E

The specified user is already registered in the group.

KAPM02221-E

admin cannot be registered in the group.

KAPM02222-E

An error occurred during user database access.

KAPM02223-E

The specified mode is unsupported.

KAPM02224-E

A fatal error occurred.

KAPM02225-E

The specified user cannot be deleted.

KAPM02226-E

The specified group cannot be deleted.

KAPM02227-E

The common repository is stopping.

KAPM02228-E

The user ID is not set.

KAPM02229-E

The specified user ID is invalid.

KAPM02230-E

The specified password is invalid.

KAPM02231-E

The application type is not set.

KAPM02232-E

The resource group ID is not set.

KAPM02233-E

The specified application is not registered.

KAPM02234-I

The permissions for aa...aa will now be changed. (User ID = aa...aa)

aa...aa: User ID

KAPM02235-I

The permissions for aa...aa were changed. (User ID = aa...aa)

aa...aa: User ID

KAPM02236-I

A user account will now be created. (User ID = aa...aa)

aa...aa: User ID

KAPM02237-I

The user account was created successfully. (User ID = aa...aa)

aa...aa: User ID

KAPM02238-I

The user-account properties will now be changed. (aa...aa)

aa...aa: The property list before the change

KAPM02239-I

The user-account properties were changed. (aa...aa)

aa...aa: The property list after the change

KAPM02240-I

The resource-group properties will now be changed. (aa...aa)

aa...aa: The property list before the change

KAPM02241-I

The resource-group properties were changed. (aa...aa)

aa...aa: The property list after the change

KAPM02242-I

The allocation status of the resource group will now be changed. (aa...aa)

aa...aa: Assignment state before the change

KAPM02243-I

The allocation status of the resource group was changed. (aa...aa)

aa...aa: Assignment state after the change

KAPM02244-I

The password will now be changed. (User ID = aa...aa)

aa...aa: User ID

KAPM02245-I

The password was changed. (User ID = aa...aa)

aa...aa: User ID

KAPM02246-I

The user account will now be deleted. (User ID = aa...aa)

aa...aa: User ID

KAPM02247-I

The user account was deleted. (User ID = aa...aa)

aa...aa: User ID

KAPM02248-I

The resource group will now be deleted. (resource group ID = aa...aa, resource group name = bb...bb)

aa...aa: resource group ID

bb...bb: resource group name

KAPM02249-I

The resource group was deleted. (resource group ID = aa...aa, resource group name = bb...bb)

aa...aa: resource group ID

bb...bb: resource group name

KAPM02250-E

A resource group with the same name has already been registered. (resource group name = aa...aa)

aa...aa: resource group name

KAPM02251-E

A user account with the same user ID has already been registered. (User ID = aa...aa)

aa...aa: User ID

KAPM02252-E

A resource group with the same ID has already been registered. (group ID = aa...aa)

aa...aa: group ID

KAPM02254-I

Request information: (API version = aa...aa, Command name = bb...bb, User ID or session ID = cc...cc)

aa...aa: API version

bb...bb: Command name

cc...cc: User ID or session ID

KAPM02255-E

The specified version is not supported. (version = aa...aa)

aa...aa: version

KAPM02256-E

The specified command is not supported. (command = aa...aa)

aa...aa: command name

KAPM02257-E

Authentication has failed. (user ID = aa...aa)

aa...aa: user ID

KAPM02258-I

Response information: (API version = aa...aa, Command name = bb...bb, Response status = cc...cc)

aa...aa: API version

bb...bb: Command name

cc...cc: Response status

KAPM02259-I

Response information when an error occurs: (Error code = aa...aa, Description = bb...bb)

aa...aa: Error code

bb...bb: Description

KAPM02260-E

An attempt to communicate with a server has failed. (URL = aa...aa)

aa...aa: Server URL

KAPM02261-E

An attempt to parse the response has failed.

KAPM02262-E

The request parameter is invalid.

KAPM02263-E

This user does not have execution permissions. (ID = aa...aa)

aa...aa: Session ID

KAPM02269-E

The specified user was not found.

KAPM02270-E

The same user ID already exists.

KAPM02271-E

An attempt to communicate with a database has failed.

KAPM02272-E

An error occurred within the server.

KAPM02273-I

The user will now be added. (ID = aa...aa, user ID = bb...bb)

aa...aa: Session ID

bb...bb: user ID

KAPM02274-I

The user was added successfully. (ID = aa...aa, user ID = bb...bb)

aa...aa: Session ID

bb...bb: user ID

KAPM02275-I

The password will now be changed. (ID = aa...aa, user ID = bb...bb)

aa...aa: Session ID

bb...bb: user ID

KAPM02276-I

The password was changed successfully. (ID = aa...aa, user ID = bb...bb)

aa...aa: Session ID

bb...bb: user ID

KAPM02277-I

The user profile will now be changed. (ID = aa...aa, user ID = bb...bb)

aa...aa: Session ID

bb...bb: user ID

KAPM02278-I

The user profile was changed successfully. (ID = aa...aa, user ID = bb...bb)

aa...aa: Session ID

bb...bb: user ID

KAPM02279-I

The permissions will now be changed. (ID = aa...aa, user ID = bb...bb, permissions = cc...cc)

aa...aa: Session ID

bb...bb: user ID

cc...cc: permissions

KAPM02280-I

The permissions were changed successfully. (ID = aa...aa, user ID = bb...bb, permissions = cc...cc)

aa...aa: Session ID

bb...bb: user ID

cc...cc: permissions

KAPM02281-I

The user will now be deleted. (ID = aa...aa, user ID = bb...bb)

aa...aa: Session ID

bb...bb: user ID

KAPM02282-I

The user was deleted successfully. (ID = aa...aa, user ID = bb...bb)

aa...aa: Session ID

bb...bb: user ID

KAPM02283-E

The old password is incorrect. (ID = aa...aa, user ID = bb...bb)

aa...aa: Session ID

bb...bb: user ID

KAPM02284-I

The user will now be locked. (ID = aa...aa, user ID = bb...bb)

aa...aa: Session ID

bb...bb: user ID

KAPM02285-I

The user was locked successfully. (ID = aa...aa, user ID = bb...bb)

aa...aa: Session ID

bb...bb: user ID

KAPM02286-E

An attempt to lock the user has failed. aa...aa

aa...aa: Detailed information

KAPM02287-I

The user will now be unlocked. (ID = aa...aa, user ID = bb...bb)

aa...aa: Session ID

bb...bb: user ID

KAPM02288-I

The user was unlocked successfully. (ID = aa...aa, user ID = bb...bb)

aa...aa: Session ID

bb...bb: user ID

KAPM02289-E

An attempt to unlock the user has failed. aa...aa

aa...aa: Detailed information

KAPM02290-I

Authentication was successful. (user ID =aa...aa)

aa...aa: user ID

KAPM02291-W

Authentication has failed. aa...aa

aa...aa: Detailed information

KAPM02292-W

Authentication has failed for aa...aa times in a row, so the user (bb...bb) was locked.

aa...aa: The number of times you failed

bb...bb: user ID

KAPM02294-E

The RD area of HBase is blocked.

KAPM02295-E

A distinguished name has not been set.

KAPM02296-E

A domain name has not been set.

KAPM02297-E

The specified distinguished name already exists. (distinguished name = aa...aa)

aa...aa: distinguished name

KAPM02298-E

The specified distinguished name could not be found. (distinguished name = aa...aa)

aa...aa: distinguished name

KAPM02301-E

hcnds.home is not set in the Java system properties.

KAPM02302-E

An error occurred during loading of a library.

KAPM02303-E

An attempt to acquire user information about a HiRDB-connected user has failed. error code = aa...aa

aa...aa: error code

KAPM02304-E

An attempt to set a system environment variable has failed. error code = aa...aa

aa...aa: error code

KAPM02305-E

Attempts to set the system environment variables PDDIR and PATH have failed. error code = aa...aa

aa...aa: error code

KAPM02306-E

An attempt to clear an HiRDB system environment variable has failed. error code = aa...aa

aa...aa: error code

KAPM02307-E

The application type is required, but is not set.

KAPM02401-E

An attempt to read the file failed. (path = aa...aa)

aa...aa: path

KAPM02409-E

A communication error occurred in an external authentication server. (error code = aa...aa)

aa...aa: error code

KAPM02410-W

Authentication with an external authentication server has failed. (user ID = aa...aa, host = bb...bb, port = cc...cc, protocol = dd...dd)

aa...aa: user ID

bb...bb: host name

cc...cc: port number

dd...dd: protocol

KAPM02411-W

Authentication with an external authentication server has failed. The specified user was not found in the external authentication server. (user ID = aa...aa, host = bb...bb)

aa...aa: user ID
bb...bb: host name

KAPM02412-E

A naming exception occurred. (host = aa...aa, port = bb...bb, protocol = cc...cc)

aa...aa: host name
bb...bb: port number
cc...cc: protocol

KAPM02413-E

The negotiation for a TLS session has failed. (host = aa...aa, port = bb...bb, protocol = cc...cc)

aa...aa: host name
bb...bb: port number
cc...cc: protocol

KAPM02414-I

Authentication with an external authentication server was successful. (user ID = aa...aa, host = bb...bb, port = cc...cc, protocol = dd...dd)

aa...aa: user ID
bb...bb: host name
cc...cc: port number
dd...dd: protocol

KAPM02416-E

A communication error occurred in an external authentication server.

KAPM02417-E

Communication with an external authentication server has failed. (host = aa...aa, port = bb...bb, protocol = cc...cc)

aa...aa: host name
bb...bb: port number
cc...cc: protocol

KAPM02418-E

The LDAP service cannot be used. (host = aa...aa, port = bb...bb, protocol = cc...cc)

aa...aa: host name
bb...bb: port number
cc...cc: protocol

KAPM02419-W

Only local operation is available because the attempt to read the configuration file for the external authentication server has failed.

KAPM02422-W

A parameter in the exauth.properties file contains an invalid value (aa...aa = bb...bb). The default value (cc...cc) will be used.

aa...aa: Parameter name
bb...bb: Parameter value
cc...cc: Default value

KAPM02423-E

Authentication of the search user has failed. (host = aa...aa)

aa...aa: host name

KAPM02424-E

An error occurred in the external authentication server.

KAPM02425-E

A parameter was not specified. (parameter = aa...aa)

aa...aa: parameter name

KAPM02426-E

Authentication stopped because a setting in the configuration file for the external authentication server was invalid.

KAPM02427-E

An invalid character was specified in the URL for a host name or a port number. (host = aa...aa, port = bb...bb)

aa...aa: host name

bb...bb: port number

KAPM02429-I

A RADIUS packet has been received. (packet information = aa...aa)

aa...aa: packet information

KAPM02430-E

Verification of a RADIUS packet has failed. (host = aa...aa, port = bb...bb, protocol = cc...cc, cause = dd...dd)

aa...aa: host name

bb...bb: port number

cc...cc: protocol

dd...dd: cause

KAPM02431-E

The connection to an external authentication server has timed out. (host = aa...aa, port = bb...bb, protocol = cc...cc)

aa...aa: host name

bb...bb: port number

cc...cc: protocol

KAPM02432-E

SSL-encrypted communication with the external authentication server has failed. (host = aa...aa, port = bb...bb, protocol = cc...cc)

aa...aa: host name
bb...bb: port number
cc...cc: protocol

KAPM02434-W

The lock processing was interrupted.

KAPM02435-W

If the selected user accounts are locked, no more users will have the User Management permission.

KAPM02436-E

Determination of whether lock processing was performed has failed.

KAPM02450-I

Authentication by an external authentication server was successful. (server type = aa...aa, host = bb...bb)

aa...aa: server type
bb...bb: host name

KAPM02451-W

Authentication by an external authentication server has failed. (server type = aa...aa, host = bb...bb)

aa...aa: server type
bb...bb: host name

KAPM02452-I

A user's authentication method has been successfully changed. (authentication method = aa...aa, user ID = bb...bb)

aa...aa:authentication method

bb...bb: user ID

KAPM02453-E

An attempt to change a user's authentication method has failed. (authentication method = aa...aa, user ID = bb...bb)

aa...aa:authentication method

bb...bb: user ID

KAPM02454-E

Acquisition of SRV records failed. (domain name = aa...aa, protocol = bb...bb)

aa...aa: domain name

bb...bb: protocol

KAPM02456-E

A function cannot be used because group mapping is disabled. (function name = aa...aa)

aa...aa: function name

KAPM02457-E

Acquisition of the password file failed.

KAPM02458-E

A setting in the configuration file for the external authentication server (exauth.properties) is invalid.

KAPM02459-E

The domain cannot be linked to. (domain name = aa...aa)

aa...aa: domain name

KAPM02460-E

The specified instance is invalid.

KAPM02461-E

No device type has been specified.

KAPM02462-E

The specified device type is too long. (device type = aa...aa)

aa...aa: device type

KAPM02463-E

The specified device type includes non-alphanumeric characters. (device type = aa...aa)

aa...aa: device type

KAPM02464-E

No device number has been specified.

KAPM02465-E

The specified device number is too long. (device number = aa...aa)

aa...aa: device number

KAPM02466-E

The specified device number includes non-alphanumeric characters. (device number = aa...aa)

aa...aa: device number

KAPM02467-E

The specified description is too long. (description = aa...aa)

aa...aa: description

KAPM02468-E

The specified ID is too long. (ID = aa...aa)

aa...aa: ID

KAPM02469-E

The specified display name is too long. (display name = aa...aa)

aa...aa: display name

KAPM02470-E

No application has been specified.

KAPM02471-E

No authorization information is specified for the user group.

KAPM02472-E

A resource group has been specified for the authorization information.

KAPM02473-E

A role has been specified for the authorization information.

KAPM02474-E

No display name has been specified.

KAPM02475-E

The specified resource group was not found. (resource group ID = aa...aa, device type = bb...bb, device number = cc...cc)

aa...aa: resource group ID

bb...bb: device type

cc...cc: device number

KAPM02476-E

The specified user group was not found. (user group ID = aa...aa, device type = bb...bb, device number = cc...cc)

aa...aa: user group ID

bb...bb: device type

cc...cc: device number

KAPM02477-E

A user group with the same ID is already registered. (user group ID = aa...aa, device type = bb...bb, device number = cc...cc)

aa...aa: user group ID

bb...bb: device type

cc...cc: device number

KAPM02478-E

No ID has been specified.

KAPM02479-E

An empty string has been specified for the ID.

KAPM02480-W

The specified application is not registered. (application type = aa...aa)

aa...aa: application type

KAPM02481-E

An application not compatible with the function was specified. (application type = aa...aa, function name = bb...bb)

aa...aa: application type

bb...bb: function name

KAPM02482-E

The method cannot be used. (class name = aa...aa, method name = bb...bb)

aa...aa: class name

bb...bb: method name

KAPM02483-W

Invalid authentication information has been registered. (application type = aa...aa)

aa...aa: application type

KAPM02484-E

The specified user account is not registered. (user ID = aa...aa)

aa...aa: user ID

KAPM02485-E

The specified role was not found. (role ID = aa...aa, device type = bb...bb, device number = cc...cc)

aa...aa: role ID

bb...bb: device type

cc...cc: device number

KAPM02486-E

A role with the same ID has already been registered. (role ID = aa...aa, device type = bb...bb, device number = cc...cc)

aa...aa: role ID

bb...bb: device type

cc...cc: device number

KAPM02487-E

The same role name has already been registered. (role name = aa...aa, device type = bb...bb, device number = cc...cc)

aa...aa: role ID

bb...bb: device type

cc...cc: device number

KAPM02488-E

The specified permission was not found. (permission = aa...aa, application type = bb...bb)

aa...aa: permission name

bb...bb: application type

KAPM02489-E

Encoding failed. (character string = aa...aa)

aa...aa: character string

KAPM02490-E

An attempt to read the BuiltInUserGroup.properties file failed.

KAPM02491-E

A user group with the same name is already registered. (user group name = aa...aa)

aa...aa: user group name

KAPM02492-E

The specified user group was not found. (user group name = aa...aa, device type = bb...bb, device number = cc...cc)

aa...aa: user group name

bb...bb: device type

cc...cc: device number

KAPM02493-E

Multiple resource groups contain the same data. (class = aa...aa, data = bb...bb)

aa...aa: class

bb...bb: data

KAPM02494-E

The specified resource group was not found. (resource group name = aa...aa, device type = bb...bb, device number = cc...cc)

aa...aa: resource group name

bb...bb: device type

cc...cc: device number

KAPM02495-W

Authentication by an external authentication server failed.

KAPM02496-E

There is no configuration corresponding to the specified domain name. (domain name = aa...aa)

aa...aa: Domain name

KAPM02497-E

Requests containing QueryString are not accepted.

KAPM02502-E

Please enter a password that satisfies the following conditions:

A minimum of aa...aa upper-case characters.

A minimum of bb...bb lower-case characters.

A minimum of cc...cc numerals.

A minimum of dd...dd symbols.

Different from the user ID.

aa...aa: The minimum number of characters

bb...bb: The minimum number of characters

cc...cc: The minimum number of characters

dd...dd: The minimum number of characters

KAPM02503-E

A minimum of aa...aa upper-case characters.

aa...aa: The minimum number of characters

KAPM02504-E

A minimum of aa...aa lower-case characters.

aa...aa: The minimum number of characters

KAPM02505-E

A minimum of aa...aa numerals.

aa...aa: The minimum number of characters

KAPM02506-E

A minimum of aa...aa symbols.

aa...aa: The minimum number of characters

KAPM02507-E

Different from the user ID.

KAPM02508-E

Enter a value that is exactly aa...aa characters long.

aa...aa: The maximum number of characters

KAPM02509-E

The following characters can be used for the value:

A-Z a-z 0-9 # + - . @ _

KAPM02510-I

Authentication by using a KDC was successful. (Kerberos principal = aa...aa, KDC = bb...bb)

aa...aa: Kerberos principal

bb...bb: List of KDC

KAPM02511-E

Communication with KDC failed. (KDC = aa...aa)

aa...aa: List of KDC

KAPM02512-E

Resolution of the KDC host name failed. (KDC = aa...aa)

aa...aa: List of KDC

KAPM02513-W

Authentication by using a KDC failed. (Kerberos principal = aa...aa, KDC = bb...bb)

aa...aa: Kerberos principal

bb...bb: List of KDC

KAPM02515-W

Deletion of the krb5.conf file, used for internal processing, failed. (file name = aa...aa)

aa...aa: file name

KAPM02517-E

Creation of the krb5.conf file, used for internal processing, failed. (file name = aa...aa)

aa...aa: file name

KAPM02519-E

Communication with the DNS server failed.

KAPM02520-E

The Kerberos authentication settings are invalid.

KAPM02521-E

The Kerberos realm or KDC definition is invalid. (realm name = aa...aa)

aa...aa: realm name

KAPM02523-I

Acquisition of the SRV records was successful. (SRV record = aa...aa)

aa...aa: SRV record

KAPM02524-E

Acquisition of the SRV records failed. (record key = aa...aa)

aa...aa: SRV record key

KAPM02525-E

An error occurred on the DNS server.

KAPM02551-E

The following characters can be used for the value: aa...aa

aa...aa: value

KAPM02552-W

An invalid permission is registered. (application type = aa...aa)

aa...aa: application type

KAPM02553-E

An attempt to authenticate the user failed because a secret file is registered. (user id = aa...aa)

aa...aa: User ID

KAPM02555-E

An attempt to decrypt the password failed. (user id = aa...aa)

aa...aa: User ID

KAPM02557-E

The decrypted password is invalid. (user id = aa...aa)

aa...aa: User ID

KAPM02603-E

The resource group already exists. (resource group name = aa...aa)

aa...aa:resource group name

KAPM02604-E

An HcmdsInvalidOperationException occurred.

KAPM02605-E

An HcmdsAuthorizationException occurred.

KAPM02606-E

An HcmdsUserManagementException occurred.

KAPM02607-E

Make sure that the users can be added.

KAPM02615-E

An HSSOException occurred.

KAPM02616-E

An IOException occurred.

KAPM02617-E

A CIMException occurred.

KAPM02618-E

A CIMUnavailableDatabaseException occurred.

KAPM02620-E

The resource group was not found.

KAPM02625-E

The specified software definition aa...aa was not found.

aa...aa:Application name

KAPM02630-I

A resource group has been created. (login ID = aa...aa, resource group name = bb...bb, module name = cc...cc)

aa...aa:login ID

bb...bb:resource group name

cc...cc:module name

KAPM02631-I

A resource group has been deleted. (login ID = aa...aa, resource group ID = bb...bb, module name = cc...cc)

aa...aa:login ID
bb...bb:resource group ID
cc...cc:module name

KAPM02632-I

A resource has been added. (login ID = aa...aa, resource group ID = bb...bb, module name = cc...cc)

aa...aa:login ID
bb...bb:resource group ID
cc...cc:module name

KAPM02633-I

A resource has been removed. (login ID = aa...aa, resource group ID = bb...bb, module name = cc...cc)

aa...aa: login ID
bb...bb: resource group ID
cc...cc: module name

KAPM02634-I

A resource group property has been edited. (login ID = aa...aa, resource group ID = bb...bb, module name = cc...cc)

aa...aa: login ID
bb...bb: resource group ID
cc...cc: module name

KAPM02635-E

Creation of a resource group has failed. (login ID = aa...aa, resource group name = bb...bb, module name = cc...cc)

aa...aa:login ID
bb...bb:resource group name
cc...cc:module name

KAPM02636-E

Deletion of a resource group has failed. (login ID = aa...aa, resource group ID = bb...bb, module name = cc...cc)

aa...aa: login ID
bb...bb: resource group ID
cc...cc: module name

KAPM02637-E

Addition of a resource has failed. (login ID = aa...aa, resource group ID = bb...bb, module name = cc...cc)

aa...aa: login ID
bb...bb: resource group ID
cc...cc: module name

KAPM02638-E

Removal of a resource has failed. (login ID = aa...aa, resource group ID = bb...bb, module name = cc...cc)

aa...aa: login ID
bb...bb: resource group ID
cc...cc: module name

KAPM02639-E

An attempt to edit a resource group property has failed. (login ID = aa...aa, resource group ID = bb...bb, module name = cc...cc)

aa...aa: login ID
bb...bb: resource group ID
cc...cc: module name

KAPM02650-I

A parameter has been sent. (HSSO token = aa...aa, application name = bb...bb)

aa...aa:HSSO token
bb...bb:application name

KAPM02651-I

The software definition aa...aa does not exist.

aa...aa:Application name

KAPM02652-I

aa...aa is not associated with a resource bundle.

aa...aa:Application name

KAPM02654-E

A ResourceTabHandleException occurred.

KAPM02656-I

A parameter has been sent. (HSSO token = aa...aa, application name = bb...bb, resource group ID = cc...cc, resource group name = dd...dd)

aa...aa:HSSO token

bb...bb:Application name

cc...cc:resource group ID

dd...dd:resource group name

KAPM02659-I

No users that can be added exist.

KAPM02660-I

A user has been added successfully. (resource group name = aa...aa, user name = bb...bb)

aa...aa:resource group name

bb...bb:user name

KAPM02661-I

A user has been removed successfully. (resource group name = aa...aa, user name = bb...bb)

aa...aa:resource group name

bb...bb:user name

KAPM02670-I

A resource group has been created.

KAPM02671-I

A resource group has been deleted.

KAPM02672-I

A resource has been added.

KAPM02674-I

A resource group property has been edited.

KAPM02675-E

Creation of a resource group has failed.

KAPM02676-E

Deletion of a resource group has failed.

KAPM02677-E

Addition of a resource has failed.

KAPM02679-E

An attempt to edit a resource group property has failed.

KAPM02704-W

An invalid RUAccessPoint object was created. Addition to the launch list is not performed. Name=aa...aa, URL=bb...bb, TokenVersion=cc...cc, IconUrl=dd...dd, IconMsg=ee...ee

aa...aa: Name

bb...bb: Launch URL

cc...cc: TokenVersion

dd...dd: Icon URL

ee...ee: Icon message

KAPM02705-E

CIMException occurred. The processing that acquires RUAccessPoint will now be interrupted.

KAPM02706-E

The URL format is failed. URL=aa...aa

aa...aa: URL

KAPM02801-I

[SQL]: aa...aa

aa...aa: Execution SQL statement

KAPM02802-E

A HcmdsExecException occurred. Message=aa...aa, Reason=bb...bb

aa...aa: Message

bb...bb: Reason

KAPM02803-E

Option is invalid.

KAPM02804-E

A Exception occurred. Message=aa...aa

aa...aa: Message

KAPM02805-E

[Stack Trace]:aa...aa

aa...aa: Stack trace of the exception

KAPM02806-E

A FileNotFoundException occurred.

KAPM02807-E

A IOException occurred.

KAPM02809-E

A SQLException occurred. Message=aa...aa

aa...aa: Message

KAPM02810-E

An EXECUPDATE statement failed. Execution SQL statement = aa...aa

aa...aa: Execution SQL statement

KAPM02811-E

A ClassNotFoundException occurred.

KAPM02812-E

A SQL statement failed. Message=aa...aa, Reason=bb...bb

aa...aa: Message

bb...bb: Reason

KAPM02813-E

An EXECQUERY statement failed. Execution SQL statement = aa...aa

aa...aa: Execution SQL statement

KAPM02814-E

A SQLException occurred.

KAPM02815-E

File is not found. file-name = aa...aa

aa...aa: file name

KAPM02816-I

Record No.: aa...aa

aa...aa: Record number

KAPM02817-I

Column count: aa...aa

aa...aa: Column count

KAPM02818-I

aa...aa: bb...bb

aa...aa: Column name

bb...bb: Value

KAPM02891-E

DB is not found.

KAPM02892-E

User name or password is invalid.

KAPM02893-E

The host name is invalid.

KAPM02894-E

No suitable driver exists.

KAPM02895-E

A connection to InterClient could not be established.

KAPM02896-E

A connection to InterBase could not be established.

KAPM02899-E

Fatal error.

KAPM02901-I

[Trace]: aa...aa

The following message is output.

- Read legacy record.
- Order of hcndsID change from x to 0.
- Change legacy record.
- Update CIMClient From 01-00 to 01-01
- Already update.
- Update DB Version.
- Create TNB_Classes.
- Create TNB_ClassAttribute.
- Drop TNB_SERVICEACCESSBYSAP.
- Drop TNB_SOFTWAREFEATURESERVICEIMPL.
- Drop CIMClasses.
- Succeed in update DataBase.

aa...aa: Trace message

KAPM02902-E

A ClassNotFoundException occurred.

KAPM02903-E

A HcndsUpdateException occurred. Message = aa...aa, Reason = bb...bb

aa...aa: Message

bb...bb: Reason

KAPM02904-E

An option is invalid.

KAPM02905-E

An exception occurred. Message = aa...aa

aa...aa: Message

KAPM02906-E

[Stack Trace]: aa...aa

aa...aa: Stack trace of the exception

KAPM02907-E

A SQLException occurred. Message = aa...aa

aa...aa: Message

KAPM02910-E

A SELECT statement failed. Table name = aa...aa

aa...aa: Table name

KAPM02911-E

An ALTER statement failed. Table name = aa...aa

aa...aa: Table name

KAPM02912-E

A DROP statement failed. Table name = aa...aa

aa...aa: Table name

KAPM02913-E

An UPDATE statement failed. Table name = aa...aa

aa...aa: Table name

KAPM02914-E

An EXECUPDATE statement failed. Execution SQL statement = aa...aa

aa...aa: Execution SQL statement

KAPM02980-I

Update CIMClient from 01-00 to 01-01.

KAPM02981-I

The database has already been updated.

KAPM02982-I

The database was successfully updated.

KAPM02991-E

DB is not found.

KAPM02992-E

User name or password is invalid.

KAPM02993-E

The host name is invalid.

KAPM02994-E

No suitable driver exists.

KAPM02995-E

A connection to InterClient could not be established.

KAPM02996-E

A connection to InterBase could not be established.

KAPM02999-E

Fatal error.

KAPM03001-E

Illegal parameters have been specified to create HSSO Context.

KAPM03004-E

An error occurred on the HSSO Server.

KAPM03005-E

An error occurred when CIM Client was created.

KAPM03006-E

An unexpected error occurred.

KAPM03007-E

A frame-enabled browser is required.

KAPM03026-E

A CIMException was generated during Console screen display processing.

KAPM03050-E

The parameter sent from the JP1/IM-View is invalid.

KAPM03051-E

The Launchurl is invalid.

KAPM03052-E

The JP1user ID is invalid.

KAPM03053-E

The JP1token is invalid.

KAPM03054-E

An acquisition failure occurred in RequestDispatcher.

KAPM03055-E

A JavaScript-enabled browser is required.

KAPM03080-E

HSSOIllegalArgumentException:Illegal parameters have been specified to create HSSO Context.

KAPM03081-E

HSSONotRegisteredException: The application is not registered.

KAPM03082-E

HSSOAuthenticationException: Authentication failed.

KAPM03083-E

HSSOServerErrorException: An error occurred in HSSO Server.

KAPM03084-E

IOException: HSSO SERVER Connection Error.

KAPM03085-E

HSSOIllegalArgumentException: "createToken()" was used before authentication.

KAPM03086-E

HSSOIllegalStateException: An unsupported version is specified.

KAPM03087-E

An error occurred while accessing the DBMS.

KAPM03105-E

A CIMException was generated during menu bar display processing.

KAPM03106-E

A CIMException was generated during subwindow display processing.

KAPM03107-E

A CIMRepositoryException was generated during menu bar display processing.

KAPM03108-E

A CIMRepositoryException was generated during subwindow display processing.

KAPM03109-E

A CIMProviderException was generated during menu bar display processing.

KAPM03110-E

A CIMProviderException was generated during subwindow display processing.

KAPM03111-E

An exception was generated during menu bar display processing.

KAPM03112-E

An exception was generated during subwindow display processing.

KAPM03113-E

A NoSuchElementException was generated during menu bar display processing.

KAPM03114-E

A NoSuchElementException was generated during subwindow display processing.

KAPM03119-I

Are you sure that you want to log out?

KAPM03120-I

Do you want to end the application?

KAPM03122-E

The request parameter for a launch is invalid.

KAPM03123-E

Could not acquire the required parameter. ParmName=aa...aa

aa...aa: parameter name

KAPM03124-E

Failed to changing of token version. Token=aa...aa

aa...aa: Token name

KAPM03125-E

Failed to getting of service information. Description=aa...aa

aa...aa: Description

KAPM03304-E

An attempt to get the path string failed.

KAPM03354-W

A value is not set because an argument is invalid.

KAPM03355-W

A value is not acquired because an argument is invalid.

KAPM03356-W

A default is set because an argument is invalid. default = aa...aa

aa...aa: default

KAPM03357-E

A parameter of request is invalid. paramName = aa...aa, value = bb...bb

aa...aa: parameter name

bb...bb: value

KAPM03358-E

The tree element is invalid. treeElement = aa...aa

aa...aa: tree element

KAPM03361-E

An attempt to get the root element data has failed.

KAPM03362-E

An attempt to get the common repository has failed.

KAPM03363-E

An attempt to get the common resource has failed.

KAPM03364-E

The registered data in the common repository is invalid.

KAPM03366-E

An attempt to get the name of default view is invalid. application name = aa...aa

aa...aa: application name

KAPM03368-W

An invalid association definition exists in the repository. instance = aa...aa

aa...aa: instance

KAPM03370-W

A tree element relation (TNB_AssocNavigationDef) is invalid. name=aa...aa, associationClass=bb...bb, fromName=cc...cc, toClassName=dd...dd, fromRole=ee...ee, toRole=ff...ff

aa...aa: association name

bb...bb: association class

cc...cc: associated original class name

dd...dd: associated destination class name

ee...ee: associated original role

ff...ff: associated destination role

KAPM03371-W

A tree element relation (TNB_AllInstanceNavigationDef) is invalid. name=aa...aa, fromName=bb...bb, toClassName=cc...cc

aa...aa: association name

bb...bb: associated original class name

cc...cc: associated destination class name

KAPM03375-W

An attempt to get the tree element data has failed. element = aa...aa

aa...aa: element

KAPM03377-W

A tree has not been created in the state where the specification object was opened. objectName = aa...aa

aa...aa: object name

KAPM03378-W

The specified object does not exist or is not shown in the tree. pathName = aa...aa, objectName = bb...bb

aa...aa: path name

bb...bb: object name

KAPM03379-E

An attempt to create a tree from a request has failed.

KAPM03380-W

An active object was not found. By default, the root object will be set.

KAPM03381-E

An internal error occurred. If you click the Refresh button, the initial object tree will be displayed. If you cannot display the tree, log in again and then retry.

KAPM03382-E

An internal error occurred. If you click the Refresh button, the initial object tree will be displayed. If you cannot display the tree, collect maintenance information, and then contact customer support.

KAPM03383-E

An internal error has occurred. Retry the operation. If the problem still cannot be solved, log in again and then retry.

KAPM03384-E

An internal error has occurred. Retry the operation. If the problem still cannot be solved, collect maintenance information, and then contact customer support.

KAPM03501-E

A CIM object name is not available for the selected object.

KAPM03502-W

There is no default method.

KAPM03503-W

The repository data is invalid, so the localization object acquisition failed.

KAPM03504-W

A resource is not found, so the localization object acquisition failed.

KAPM03505-W

The selected object is already deleted.

KAPM03702-E

A HSSOIllegalStateException occurred during launch.

KAPM03703-E

An attempt to get to the URL encoding of a token failed.

token = aa...aa

aa...aa: token

KAPM03708-E

A HSSOAuthenticationException was generated during user profile display processing.

KAPM03709-E

A HSSOIllegalArgumentException was generated during user profile display processing.

KAPM03710-E

A HSSOServerErrorException was generated during user profile display processing.

KAPM03712-E

An attempt to get membership groups failed.

KAPM03716-E

The format of the URL bb...bb for the object aa...aa is invalid.

aa...aa: object name

bb...bb: URL

KAPM03717-W

The resource bb...bb for object aa...aa cannot be accessed.

aa...aa: object name

bb...bb: resource name

KAPM03718-E

The data format of the resource bb...bb for the object aa...aa is invalid..

aa...aa: object name

bb...bb: resource name

KAPM03721-E

The attribute bb...bb for object aa...aa is missing.

aa...aa: object name

bb...bb: associated destination value

KAPM03722-E

The resource information of bb...bb for object aa...aa is missing.

aa...aa: object name

bb...bb: association name

KAPM03723-E

Property cc...cc of bb...bb for object aa...aa is missing.

aa...aa: object name

bb...bb: association name

cc...cc: associated destination value

KAPM03931-W

Your session is invalid. Logout, and then login again.

KAPM03951-E

An internal server error has occurred.

KAPM03952-E

An attempt to get the Session has failed.

KAPM03954-E

An attempt to get the HSSOSubject has failed.

KAPM03956-E

The login process has not completed properly.

KAPM03957-E

An error occurred when the Common Repository was accessed.

KAPM03958-E

The request type is not correct.

KAPM03960-E

An attempt to get the string from the ResourceBundle failed.

KAPM03961-E

An attempt to get the RequestDispatcher for "aa...aa" failed.

aa...aa: The unexpected operation name

KAPM03962-E

An attempt to get the application name has failed.

KAPM03963-E

Authentication has failed.

KAPM03964-E

An error occurred on the Single Sign On server.

KAPM03965-E

An error occurred on the Single Sign On server.

KAPM03966-E

Communications of the Single Sign On server have failed.

KAPM03967-E

Communications of the Single Sign On server have failed.

KAPM03968-E

The token is invalid. token=aa...aa.

aa...aa: token

KAPM03969-E

The request is invalid.token=aa...aa. The name of application=bb...bb.

aa...aa: token

bb...bb: application name

KAPM03970-E

The request is invalid.token=aa...aa. The name of application=bb...bb.

aa...aa: token

bb...bb: application name

KAPM03971-E

The application is not registered. The name of application=aa...aa.

aa...aa: application name

KAPM03972-E

Internal authentication failed.

KAPM03973-E

Requests containing QueryString are not accepted.

KAPM04001-I

usage start.

KAPM04002-I

usage is finished.

KAPM04003-I

hcmdssup start.

KAPM04004-I

hcmdssup is finished.

KAPM04006-W

Log initialization has failed.

KAPM04007-E

File is not found. file-name=aa...aa

aa...aa: file name

KAPM04008-E

The error has occurred in file access. file-name=aa...aa

aa...aa: file name

KAPM04009-E

aa...aa

aa...aa: The message of NumberFormatException

KAPM04010-E

aa...aa

aa...aa: The message of IllegalArgumentException

KAPM04011-E

aa...aa

aa...aa: The message of NullPointerException

KAPM04012-E

aa...aa

aa...aa: The message of IndexOutOfBoundsException

KAPM04013-E

aa...aa

aa...aa: The message of SecurityException

KAPM04014-E

aa...aa

aa...aa: The message of Exception

KAPM04022-E

Hostname is too long.

KAPM04023-E

Portnumber is invalid.

KAPM04024-E

Portnumber is invalid.

KAPM04025-I

hcmdssup has succeeded.

KAPM04026-E

hcmdssup has failed.

KAPM04027-E

The SSL port number is invalid.

KAPM04028-E

The SSL port number is invalid.

KAPM04034-E

An attempt to read the configuration file failed.

KAPM04035-E

An attempt to write to the configuration file failed.

KAPM04036-E

The specified command line input is invalid. (input data = aa...aa)

aa...aa: input data

KAPM04038-E

The specified host name is invalid.

KAPM04040-E

The specified port number is invalid.

KAPM04042-E

The specified SSL port number is invalid.

KAPM04050-I

The command hcmds64prmset ended successfully.

KAPM04051-E

The command hcnds64prmset has failed.

KAPM04052-E

An option is invalid.

KAPM04059-E

The specified host name is too long.

KAPM04061-E

The value specified for an option is invalid.

KAPM04062-I

This server is set as a primary server.

KAPM04063-I

This server is set as a secondary server.

KAPM04064-W

The configuration file was re-created because it was missing.

KAPM04067-I

This server is set as a primary server.

KAPM04068-I

This server is set as a secondary server.

KAPM04069-W

An attempt to set the port number failed because the host name is not set. Change the port number together with the host name.

KAPM04070-I

The connection test was successful.

KAPM04071-E

The connection test failed.

KAPM04072-E

A problem occurred on the primary server.

KAPM04073-E

An unexpected error occurred on the primary server.

KAPM04074-E

SSL communication failed.

KAPM04075-E

An attempt to connect to the primary server failed.

KAPM04076-E

An unexpected error occurred during the connection test.

KAPM04077-I

hcnds64prmset [aa...aa]{, [bb...bb],.....[.....]}

aa...aa: Command line argument

bb...bb: Command line argument

KAPM04078-I

A trusted server ID was successfully acquired. (trusted server ID = aa...aa)

aa...aa: trusted server ID

KAPM04079-E

The specified cipher type is invalid, or the specified cipher suites are invalid. (invalid ciphers = aa...aa)

aa...aa: Invalid ciphers

KAPM04080-E

The specified SSL protocols are invalid. (invalid SSL protocols = aa...aa)

aa...aa: Invalid SSL protocols

KAPM04081-E

An attempt to configure SSL communication failed.

KAPM04084-W

The SSL protocols defined by the cipher type will be used. (cipher type = aa...aa, SSL protocols = bb...bb)

aa...aa: cipher type

bb...bb: SSL protocols

KAPM04085-W

The SSL protocol "aa...aa" will be used. To change the SSL protocol, execute this command again with the "sslprotocol" option specified.

aa...aa: SSL protocol

KAPM04101-E

Container server name is invalid. Server= aa...aa

aa...aa: Container server name

KAPM04102-E

Archive file is not found. file=aa...aa

aa...aa: Archive file name

KAPM04103-E

Program type is invalid. type=aa...aa

aa...aa: Program type

KAPM04104-I

Starting web application registration...

KAPM04105-E

Privilege is invalid.

KAPM04106-E

Cannot get tmpjavavm.properties file name.

KAPM04107-E

Failed to get service registration status. service=aa...aa

aa...aa: service name

KAPM04108-E

Cannot get javavm.properties file name.

KAPM04109-E

Cannot set JavaVM option.

KAPM04110-E

Cannot set Java options.

KAPM04111-E

An attempt to check whether a program type exists in the hcndswebpp.ini file has failed.

KAPM04112-E

Cannot write hcndswebpp.ini file.

KAPM04113-E

Service registration has failed. service=aa...aa

aa...aa: service name

KAPM04114-E

Failed to get service registration status. service=aa...aa

aa...aa: service name

KAPM04115-E

Service registration has failed. service=aa...aa

aa...aa: service name

KAPM04116-I

hcndsweb registration has succeeded.

KAPM04117-I

Starting web application deletion...

KAPM04118-E

Program type is not registered. type=aa...aa

aa...aa: Program type

KAPM04119-E

Cannot delete service and folder.

KAPM04120-E

Cannot delete hcndswebpp.ini file.

KAPM04121-I

hcndsweb deletion has succeeded.

KAPM04122-E

Cannot get only a war file name.

KAPM04123-E

Cannot get hcndswebpp.ini file name.

KAPM04124-E

Cannot get tmphcndswebpp.ini file name.

KAPM04125-E

Log initialization has failed.

KAPM04126-E

Cannot insert new line character.

KAPM04127-E

An attempt to exchange hcndswebpp.ini with tmphcndswebpp.ini has failed.

KAPM04128-E

hcmdsweb registration has failed.

KAPM04129-E

hcmdsweb deletion has failed.

KAPM04130-E

Cannot read hcmdswebpp.ini file.

KAPM04131-E

OpenSCManager command error.

KAPM04132-E

Access is denied.

KAPM04133-E

The parameter is incorrect.

KAPM04134-E

The database specified does not exist.

KAPM04135-E

An unexpected error occurred. Error code = aa...aa

aa...aa: Error code

KAPM04136-E

RegOpenKeyEx command error.ErrorCode(aa...aa)

aa...aa: Error code

KAPM04137-E

A duplicate name exists on the network.

KAPM04138-E

The filename, directory name, or volume label syntax is incorrect.

KAPM04139-E

The account name is invalid or does not exist.

KAPM04140-E

Circular service dependency was specified.

KAPM04141-E

Service already exists. service=aa...aa

aa...aa: service name

KAPM04142-E

The handle is invalid.

KAPM04143-E

The specified service has been marked for deletion.

KAPM04144-E

CreateService command error. code=aa...aa

aa...aa: error code

KAPM04145-E

DeleteService command error. code=aa...aa

aa...aa: error code

KAPM04146-E

OpenService command error. code=aa...aa

aa...aa: error code

KAPM04147-E

The specified service does not exist as an installed service.

KAPM04148-E

RegQueryValueEx command error. code=aa...aa

aa...aa: error code

KAPM04149-E

The error has occurred in aa...aa command. code=bb...bb

aa...aa: command

bb...bb: error code

KAPM04150-E

The directory cannot be removed. directory=aa...aa

aa...aa: directory name

KAPM04151-E

The directory is not empty. directory=aa...aa

aa...aa: directory name

KAPM04152-E

The directory name is invalid. directory=aa...aa

aa...aa: directory name

KAPM04153-E

QueryServiceStatus command error. code=aa...aa

aa...aa: error code

KAPM04154-E

Failed to get installation directory.

KAPM04155-E

Failed to get Service name. service=aa...aa

aa...aa: service name

KAPM04156-E

Service is running. service=aa...aa

aa...aa: service name

KAPM04157-E

Failed to get service status. service=aa...aa

aa...aa: service name

KAPM04158-E

File is not found. file=aa...aa

aa...aa: file name

KAPM04159-E

Failed to delete specified file. file=aa...aa

aa...aa: file name

KAPM04160-E

Failed to rename aa...aa to bb...bb.

aa...aa: File name before the change

bb...bb: File name after the change

KAPM04161-E

Privilege is invalid to access aa...aa file.

aa...aa: file name

KAPM04162-E

Failed to copy from aa...aa to bb...bb.

aa...aa: File name before the copy

bb...bb: File name after the copy

KAPM04163-E

Failed to delete service. service=aa...aa

aa...aa: service name

KAPM04164-W

Failed to delete the war file. file=aa...aa

aa...aa: war file name

KAPM04165-W

Failed to delete the folder. folder=aa...aa

aa...aa: folder name

KAPM04166-E

Failed to delete service. service=aa...aa

aa...aa: service name

KAPM04167-E

Failed to get service folder. service-folder=aa...aa

aa...aa: service folder name

KAPM04168-W

Failed to delete service folder. service-folder=aa...aa

aa...aa: service folder name

KAPM04169-E

File is not found. file=aa...aa

aa...aa: file name

KAPM04172-E

Failed to write usrconf.properties to installation information.

KAPM04173-E

Failed to read usrconf.properties file.

KAPM04174-E

Failed to exchange usrconf.properties to tmpusrconf.properties.

KAPM04175-E

Failed to create directory. directory=aa...aa

aa...aa: directory name

KAPM04176-E

Failed to get the war file name. file=aa...aa

aa...aa: file name

KAPM04177-E

Failed to read javavm.properties file.

KAPM04178-E

An attempt to exchange javavm.properties with tmpjavavm.properties has failed.

KAPM04197-I

Service registration has succeeded. service=aa...aa

aa...aa: service name

KAPM04198-I

Service registration has succeeded. service=aa...aa

aa...aa: service name

KAPM04202-I

Service deletion has succeeded. service=aa...aa

aa...aa: service name

KAPM04205-E

Memory alloc error. code=aa...aa

aa...aa: error code

KAPM04206-E

The system cannot find the file specified.

KAPM04207-E

The system cannot find the path specified.

KAPM04208-E

The system cannot open the file.

KAPM04209-E

The process cannot access the file because it is being used by another process.

KAPM04211-E

Failed to get tmpusrconf.properties file name.

KAPM04212-E

Failed to get usrconf.properties file name.

KAPM04213-E

ExtractionWarFolderPath function error.

KAPM04214-E

Failed to get web-users.xml file name.

KAPM04215-E

Failed to get template usrconf.properties file name.

KAPM04216-E

Failed to get template web-users.xml file name.

KAPM04217-E

Failed to get template javavm.properties file name.

KAPM04218-E

Failed to get Display name.

KAPM04219-E

Failed to load hnr2t.dll. code=aa...aa

aa...aa: error code

KAPM04220-E

The file option is invalid.

KAPM04221-E

The type option is invalid.

KAPM04222-E

The server option is invalid.

KAPM04223-E

The classpath option is invalid.

KAPM04224-E

The librarypath option is invalid.

KAPM04225-E

The javaoption option is invalid.

KAPM04226-E

The Xms option is invalid.

KAPM04227-E

The Xmx option is invalid.

KAPM04228-E

RegCreateKeyEx command error. code=aa...aa

aa...aa: error code

KAPM04229-E

RegSetValueEx command error. code=aa...aa

aa...aa: error code

KAPM04230-I

Service deletion has succeeded. service=aa...aa

aa...aa: service name

KAPM04231-E

Failed to read usrconf.properties file.

KAPM04232-E

An attempt to register the program type in the registry failed.

program type = aa...aa

aa...aa: program type

KAPM04233-E

An attempt to delete the program type in the registry failed.

program type = aa...aa

aa...aa: program type

KAPM04234-E

Failed to remake service.

KAPM04235-E

The minimum heap size has exceeded the maximum heap size.

KAPM04236-E

The minimum heap size has exceeded the already set up maximum heap size.

KAPM04237-E

The service name exceeds 256 characters.

KAPM04238-E

The service registration is not possible because the service name exceeds 256 characters.

KAPM04239-E

An attempt to get the service control manager execution file path failed.

KAPM04240-E

An error occurred when the environment settings folder was created.

KAPM04241-E

An error occurred when the environment settings file was set.

KAPM04242-E

An error occurred when the web application archive file was expanded.

KAPM04243-E

An error occurred when a directory expanded with the web application archive file was deleted.

KAPM04244-E

An error occurred when registering and updating the web server.

KAPM04245-E

An error occurred when registering and updating Tomcat.

KAPM04246-E

An error occurred when the usrconf.properties file was merged.

KAPM04247-E

An attempt to acquire the number of file lines has failed.

KAPM04248-E

An attempt to create Map information has failed.

KAPM04249-E

An attempt to read data from a file has failed.

KAPM04250-E

An attempt to set the javaVM debug option has failed.

KAPM04251-E

The jvmoption option is invalid.

KAPM04252-E

An error occurred in an internal function. (call function = aa...aa, use function = bb...bb, note = cc...cc, error code = dd...dd)

aa...aa: call function

bb...bb: use function

cc...cc: note

dd...dd: error code

KAPM04253-E

A memory allocation error occurred. (call function = aa...aa, use function = bb...bb, note = cc...cc, error code = dd...dd)

aa...aa: call function

bb...bb: use function

cc...cc: note

dd...dd: error code

KAPM04254-E

An attempt to acquire the daemon shell name has failed.

KAPM04255-E

An attempt to write service registration information to the version file has failed.

KAPM04256-E

An attempt to delete service registration information from the version file has failed.

KAPM04257-E

An attempt to start the hcnds64srv command has failed.

KAPM04258-E

An error occurred during execution of the hcnds64srv command.

KAPM04259-E

An attempt to create the boot shell has failed.

KAPM04260-E

The startup mode of the service is invalid. (start mode = aa...aa)

aa...aa: start mode

KAPM04261-E

The starttype option is invalid.

KAPM04262-E

An attempt to create the usrconf.cfg file has failed.

KAPM04263-E

An attempt to deploy the compiled JSP file has failed.

KAPM04264-E

A path was not found for the Web application folder. (folder path = aa...aa)

aa...aa: folder path

KAPM04265-E

A path was not found for the compiled JSP storage folder. (folder path = aa...aa)

aa...aa: folder path

KAPM04266-E

The contents of the directory are invalid. (Directory path = aa...aa)

aa...aa: Directory path

KAPM04267-W

An attempt to delete the hwc directory has failed. (Directory path = aa...aa)

aa...aa: Directory path

KAPM04271-E

An attempt to update the web application version has failed.

KAPM04272-E

Failed to delete specified directory. Directory=aa...aa

aa...aa: Directory

KAPM04273-W

An attempt to execute the aa...aa function has failed. (error code = bb...bb, description = cc...cc)

aa...aa: function name

bb...bb: error code

cc...cc: description

KAPM04274-E

An attempt to load the DLL has failed.

KAPM04275-E

An attempt to acquire the function address in the DLL has failed.

KAPM04276-E

The file does not exist. (file name = aa...aa)

aa...aa: file name

KAPM04279-E

An attempt to add a service description has failed.

KAPM04280-E

A memory allocation error occurred.

KAPM04281-E

The specified service is not registered.

KAPM04282-E

An attempt to acquire the installation directory has failed.

KAPM04283-E

The name of the specified service is invalid.

KAPM04284-E

An attempt to access the service explanation definition file has failed.

KAPM04285-E

The service explanation definition file is invalid.

KAPM04286-E

An attempt to change a service configuration parameter has failed.

KAPM04287-E

An attempt to connect the service control manager has failed.

KAPM04288-E

An attempt to open the service handle has failed.

KAPM04289-E

An attempt to access the service explanation definition file has failed.

KAPM04290-E

The service name was not specified.

KAPM04291-I

Registration of the aa...aa Web application will now start.

aa...aa: Product name

KAPM04292-I

Deletion of the aa...aa Web application will now start.

aa...aa: Product name

KAPM04293-E

An attempt to delete the JSP servlet class file has failed.

KAPM04294-I

The JSP servlet class file was deleted successfully.

KAPM04295-I

Deletion of the JSP servlet class file will now start.

KAPM04296-I

Deletion of the JSP servlet class file will now end.

KAPM04300-I

Uninstallation of aa...aa has started.

aa...aa: Product name

KAPM04301-I

[All processing has finished.]

KAPM04302-I

Uninstallation was successful.

KAPM04303-I

All of the services for aa...aa have been deleted.

aa...aa: Product name

KAPM04304-I

Restart the machine, and then execute the program again.

KAPM04305-E

Uninstallation has failed.

KAPM04306-I

Uninstallation was successful. Restart the machine.

KAPM04307-E

"aa...aa" has not stopped. Stop the service, and then try again.

aa...aa: service name

KAPM04311-E

An attempt to acquire an installation path for aa...aa has failed. Manually delete the installation directory.

aa...aa: Product name

KAPM04312-E

An attempt to acquire registry information has failed.

KAPM04313-E

An attempt to acquire the registry information has failed. Manually delete the registry information.

KAPM04314-E

Some files remained. Manually delete them.

KAPM04315-W

All the files for aa...aa will now be deleted. Is this OK?

aa...aa: Product name

KAPM04316-W

Are you sure you want to delete all of the files?

KAPM04317-I

Uninstallation was interrupted.

KAPM04318-I

The OS setting information was successfully deleted.

KAPM04319-E

An attempt to delete the OS setting information has failed.

KAPM04320-W

The resident process "aa...aa" has not stopped.

aa...aa: process name

KAPM04321-I

The OS settings information will now be deleted to stop the resident process.

KAPM04378-E

DOMException: aa...aa

aa...aa: The message of Exception

KAPM04379-E

RuntimeException occurred. aa...aa

aa...aa: The message of Exception

KAPM04380-E

MalformedURLException occurred. aa...aa

aa...aa: The message of Exception

KAPM04381-E

IllegalDataException occurred.

KAPM04382-E

IllegalOptionException occurred.

KAPM04383-E

IOException occurred. aa...aa

aa...aa: The message of Exception

KAPM04384-E

SAXException occurred. aa...aa

aa...aa: The message of Exception

KAPM04385-E

HttpProtocolException occurred. aa...aa

aa...aa: The message of Exception

KAPM04386-E

ServerNotStartException occurred.

KAPM04389-E

Exception occurred. aa...aa

aa...aa: The message of Exception

KAPM04401-I

Initializing servlet.

KAPM04405-E

Can't read DTD file.

KAPM04411-I

HTTP:POST from aa...aa

aa...aa: IP Address

KAPM04421-E

The error has occurred in Repository process.

KAPM04422-E

The illegal data has detected in Server process.

KAPM04423-E

The error has occurred in Server process.

KAPM04426-E

The version is incorrect. Version aa...aa is required.

aa...aa: Version that the server can support

KAPM04429-E

An error occurred during server processing.

KAPM04440-E

Token has timed out.

KAPM04446-I

Starting information registration...

KAPM04455-W

aa...aa has already registered in Repository.

aa...aa: the value specified in the type option and the displayname option

KAPM04463-W

aa...aa is not found in Repository.

aa...aa: the value specified in the type option and the displayname option

KAPM04464-E

aa...aa is associated with more than one ServiceAccessPoint Instances.

aa...aa: the value specified in the type option and the displayname option

KAPM04465-I

Starting information deletion...

KAPM04468-W

aa...aa is not found in Repository.

aa...aa: the value specified in the type option and the displayname option

KAPM04472-I

Starting information display...

KAPM04475-W

No results were found in Repository.

KAPM04480-E

Type name is too Long.

KAPM04481-E

Type or URL is not set.

KAPM04489-E

This version does not support the add option.

KAPM04499-E

Detail of exception: aa...aa

aa...aa: Detail of exception

KAPM04510-E

Option is invalid. option= aa...aa

aa...aa: option

KAPM04511-E

Option is invalid. option= aa...aa

aa...aa: option

KAPM04512-E

Option is invalid. option= aa...aa

aa...aa: option

KAPM04513-E

Option value is invalid. option-value=aa...aa

aa...aa: option value

KAPM04514-E

Following Option is not supported: aa...aa

aa...aa: option

KAPM04515-E

Option is invalid. option= aa...aa

aa...aa: option

KAPM04516-E

Option is invalid. option= aa...aa

aa...aa: option

KAPM04517-E

Option is invalid.

KAPM04518-E

Option is invalid.

KAPM04519-E

Option is invalid.

KAPM04520-E

Option is invalid.

KAPM04521-E

Option is invalid.

KAPM04522-E

Invalid Group or Role.

KAPM04523-E

Username or password is invalid.

KAPM04524-E

Failed to connect to HiCommand Suite Single Sign On Service.

KAPM04525-E

Failed to connect to HiCommand Device Manager.

KAPM04526-E

HSSOException occurred.

KAPM04527-E

FileNotFoundException occurred.

KAPM04528-E

IOException occurred.

KAPM04529-E

Option needs value. option=aa...aa

aa...aa: option

KAPM04553-E

IOException occurred. aa...aa

aa...aa: The message of Exception

KAPM04554-E

Not support tag type detected.

KAPM04555-E

Value is too long.

KAPM04556-E

Failed to connect to HiCommand Suite Common Web Service.

KAPM04557-E

A single sign-on server exception has occurred.

KAPM04558-E

An invalid role was detected.

KAPM04560-I

hcndsrep add has succeeded. aa...aa

aa...aa: program type

KAPM04561-I

hcmsrep delete has succeeded. aa...aa

aa...aa: program type

KAPM04562-E

hcmsrep add has failed. aa...aa

aa...aa: program type

KAPM04563-E

hcmsrep delete has failed. aa...aa

aa...aa: program type

KAPM04601-E

Command format is invalid.

KAPM04602-E

Command format is invalid. invalid-param=aa...aa

aa...aa: invalid parameter

KAPM04603-E

File is not found. file-name=aa...aa

aa...aa: file name

KAPM04604-E

Directory is not found. directory-name=aa...aa

aa...aa: directory name

KAPM04605-E

Bundle PP Name is invalid. name=aa...aa

aa...aa: invalid parameter

KAPM04606-E

Web Container server is invalid. name=aa...aa

aa...aa: invalid parameter

KAPM04608-I

Setup completed successfully.

KAPM04609-E

Failed to create file. file-name=aa...aa

aa...aa: file name

KAPM04613-I

Delete completed successfully.

KAPM04614-E

Failed to setup server.

KAPM04615-E

Failed to delete server.

KAPM04616-E

Server is running. pid=aa...aa

aa...aa: Process ID

KAPM04623-E

An option is invalid.

KAPM04624-E

The value specified for an option is invalid. (option = aa...aa)

aa...aa: option name

KAPM04625-E

Creation of the directory failed. (path = aa...aa)

aa...aa: path

KAPM04626-E

Execution of the command failed. (path = aa...aa)

aa...aa: path

KAPM04627-E

aa...aa

aa...aa: standard error output

KAPM04628-I

aa...aa

aa...aa: standard output

KAPM04629-I

The service was successfully registered. (service name = aa...aa)

aa...aa: service name

KAPM04630-E

An attempt to upgrade the version of the definition file failed.

KAPM04631-I

The service was successfully deleted. (service name = aa...aa)

aa...aa: service name

KAPM04632-I

The hcndsweb command successfully registered an application.

KAPM04633-I

The hcndsweb command successfully deleted an application.

KAPM04634-E

The configuration information is incorrect. (cause = aa...aa)

aa...aa: cause

KAPM04635-I

The command will now be executed. (command line to be executed = aa...aa)

aa...aa: command line to be executed

KAPM04636-I

The command successfully executed.

KAPM04637-E

Execution of the command failed. (return code = aa...aa)

aa...aa: return code

KAPM04638-E

An error occurred during execution of the command.

KAPM04639-I

The server is already set up. (server name = aa...aa)

aa...aa: server name

KAPM04640-I

The server was successfully set up. (server name = aa...aa)

aa...aa: server name

KAPM04641-E

Setup of the server failed. (server name = aa...aa)

aa...aa: server name

KAPM04642-I

The server was successfully deleted. (server name = aa...aa)

aa...aa: server name

KAPM04643-E

Deletion of the server failed. (server name = aa...aa)

aa...aa: server name

KAPM04644-E

An attempt to acquire the RMI naming port failed. (server name = aa...aa)

aa...aa: server name

KAPM04645-E

Resolution of the local host name failed.

KAPM04646-I

Information about the local host is as follows: IP address = aa...aa, host name = bb...bb

aa...aa: IP address

bb...bb: host name

KAPM04647-W

Deletion of the web application failed. (server name = aa...aa, application name = bb...bb)

aa...aa: server name

bb...bb: application name

KAPM04648-W

An attempt to stop the server failed. (server name = aa...aa)

aa...aa: server name

KAPM04649-W

Deployment of the application failed. (server name = aa...aa, application name = bb...bb)

aa...aa: server name

bb...bb: application name

KAPM04650-W

Deletion of the server failed. (server name = aa...aa)

aa...aa: server name

KAPM04651-I

aa...aa

aa...aa: standard error output

KAPM04653-I

The application was successfully deployed. (server name = aa...aa, application name = bb...bb)

aa...aa: server name

bb...bb: application name

KAPM04654-E

Deployment of the application failed. (server name = aa...aa, application name = bb...bb)

aa...aa: server name

bb...bb: application name

KAPM04655-E

Deletion of the web application directory failed. (path = aa...aa)

aa...aa: path

KAPM04656-E

The value of the parameter to be set on the server exceeds the maximum. (parameter name = aa...aa)

aa...aa: parameter name

KAPM04657-I

The application was successfully deleted. (server name = aa...aa, application name = bb...bb)

aa...aa: server name

bb...bb: application name

KAPM04658-E

Deletion of the web application failed. (server name = aa...aa, application name = bb...bb)

aa...aa: server name

bb...bb: application name

KAPM04659-E

Deletion of the file failed. (path = aa...aa)

aa...aa: path

KAPM04660-I

The service was successfully registered in Service Control Manager. (service name = aa...aa)

aa...aa: service name

KAPM04661-E

Registration of the service in Service Control Manager failed. (service name = aa...aa)

aa...aa: service name

KAPM04662-I

The service was successfully deleted from Service Control Manager. (service name = aa...aa)

aa...aa: service name

KAPM04663-E

Deletion of the service from Service Control Manager failed. (service name = aa...aa)

aa...aa: service name

KAPM04664-I

The service was successfully updated in Service Control Manager. (service name = aa...aa)

aa...aa: service name

KAPM04665-E

The update of the service in Service Control Manager failed. (service name = aa...aa)

aa...aa: service name

KAPM04666-E

An attempt to copy a file failed. (copy source = aa...aa, copy destination = bb...bb)

aa...aa: Name of the source file

bb...bb: Name of the destination file

KAPM04667-W

An attempt to forcibly stop the server failed. (server name = aa...aa)

aa...aa: Server name

KAPM04668-E

The check of the existence of the service failed. (service name = aa...aa)

aa...aa: service name

KAPM04669-E

The check of the service activation status failed. (service name = aa...aa)

aa...aa: service name

KAPM04670-E

An operation on the management book file failed. (operation = aa...aa)

aa...aa: operation

KAPM04671-E

Renaming of the file failed. (path = aa...aa)

aa...aa: path

KAPM04672-E

A directory exists at the destination for which a symbolic link is to be created. (path = aa...aa)

aa...aa: path

KAPM04673-E

Creation of the service control file failed. (path = aa...aa)

aa...aa: path

KAPM04674-E

Creation of the symbolic link failed.

KAPM04675-W

A file remains because an attempt to delete it failed. (path = aa...aa)

aa...aa: path

KAPM04676-E

Execution of the insserv command failed. (error code = aa...aa)

aa...aa: error code

KAPM04677-E

Creation of the flag file failed. (path = aa...aa)

aa...aa: path

KAPM04678-E

Deletion of the flag file failed. (path = aa...aa)

aa...aa: path

KAPM04679-E

An operation on the file failed. (path = aa...aa)

aa...aa: path

KAPM04680-E

An error occurred during input of a file.

KAPM04681-E

Execution of the chkconfig command failed. (error code = aa...aa)

aa...aa: error code

KAPM04682-E

An error occurred in the SAX parser.

KAPM04683-E

A file exists at the destination for which a symbolic link is to be created. (path = aa...aa)

aa...aa: path

KAPM04684-E

An attempt to change the file access permissions failed. (path = aa...aa)

aa...aa: path

KAPM04685-E

The service definition file is invalid.

KAPM04686-W

An attempt to delete the server failed. (server name = aa...aa)

aa...aa: Server name

KAPM04687-E

A class could not be found. (class name = aa...aa)

aa...aa: class name

KAPM04688-E

An operation on the service failed. (operation = aa...aa, service name = bb...bb)

aa...aa: operation

bb...bb: service name

KAPM04689-W

An attempt to perform unsetup of the server failed. (server name = aa...aa)

aa...aa: Server name

KAPM04690-E

No worker information is registered.

KAPM04691-I

A command will now be executed. (command line = aa...aa)

aa...aa: command line

KAPM04692-I

The hcmdsweb command finished successfully.

KAPM04693-E

The hcmdsweb command failed.

KAPM04694-E

A service is starting up. (service name = aa...aa)

aa...aa: service name

KAPM04695-E

The application data has already been deleted. (product name = aa...aa)

aa...aa: product name

KAPM04696-W

A file exists in the location where a symbolic link is to be created. (path = aa...aa)

aa...aa: Path

KAPM04697-E

Parameters required to register the service are not set. (server name = aa...aa, service name = bb...bb, mode = cc...cc, display name = dd...dd)

aa...aa: server name

bb...bb: service name

aa...aa: mode

dd...dd: display name

KAPM04698-W

A directory exists in the location where a symbolic link is to be created. (path = aa...aa)

aa...aa: Path

KAPM04699-E

An unexpected exception occurred.

KAPM04702-E

The option(s) specified is insufficient.

KAPM04703-E

The option value specified is invalid.

KAPM04705-E

The option "aa...aa" is not supported.

aa...aa: option name

KAPM04706-E

The option "aa...aa" appears 2 times or more.

aa...aa: option name

KAPM04707-E

The combination of options is invalid.

KAPM04710-E

An exception occurred.

KAPM04711-E

The file "aa...aa" could not be read.

aa...aa: file name

KAPM04713-E

The input XML contains a grammar mistake.

KAPM04714-E

Failed to connect to HBase Storage Mgmt Common Service.

KAPM04715-E

Failed to connect to HBase Storage Mgmt Web Service.

KAPM04716-E

Failed to connect to the host specified in hssso.conf.

KAPM04717-E

An invalid URL was detected. (aa...aa)

aa...aa: URL

KAPM04718-E

The server returned an empty response.

KAPM04719-E

An unsupported element type was detected in the XML.

KAPM04722-W

aa...aa error(s) were detected in the response.

aa...aa: Number of errors

KAPM04723-E

Invalid error information was detected.

KAPM04724-E

Invalid server information was detected.

KAPM04800-E

Authentication information is insufficient.

KAPM04801-E

Authentication has failed.

KAPM04802-E

A single sign-on server communication exception has occurred.

KAPM04803-E

A single sign-on server exception has occurred.

KAPM04805-E

An XML parser exception occurred.

KAPM04806-E

The received XML element aa...aa contains an unexpected value cc...cc for attribute bb...bb. The expected value is dd...dd. TARGET=ee...ee

aa...aa: XML element tag name that contains an unexpected value

bb...bb: Attribute name unexpected value has been set

cc...cc: unexpected value

dd...dd: Attribute value that the server expects

ee...ee: information of the target

KAPM04807-E

The XML element aa...aa is not allowed as a child of element bb...bb. TARGET=cc...cc

aa...aa: Tag name of an unexpected element

bb...bb: Tag name of the element that contains an unexpected element

cc...cc: information of the target

KAPM04808-W

The received XML attribute aa...aa is not allowed as an attribute of bb...bb. TARGET=cc...cc

aa...aa: Attribute name of unexpected attribute

bb...bb: Tag name of the element with an unexpected attribute

cc...cc: information of the target

KAPM04809-E

Message catalog information is insufficient for the log message. TARGET=aa...aa

aa...aa: information of the target

KAPM04810-E

A CIM Repository exception occurred. TARGET=aa...aa

aa...aa: information of the target

KAPM04812-E

Failed to connect to HiCommand Device Manager.

KAPM04813-E

An exception occurred. TARGET=aa...aa

aa...aa: information of the target

KAPM04814-W

The CIM datatype aa...aa is invalid for bb...bb; it will be handled as a string type.

aa...aa: specified CIM datatype name

bb...bb: Attribute name that is specified data type is specified

KAPM04815-E

This operation aa...aa is unknown. TARGET= bb...bb

aa...aa: The unexpected operation name

bb...bb: information of the target

KAPM04816-E

INSTANCENAME cannot be used for the set operation. TARGET=aa...aa

aa...aa: information of the target

KAPM04817-E

The CIM operation aa...aa is missing required argument bb...bb. TARGET=cc...cc

aa...aa: CIM operation name

bb...bb: required argument

cc...cc: information of the target

KAPM04818-I

Starting CIM access... Method = aa...aa

aa...aa: Java method name of the repository access API

KAPM04819-I

Ending CIM access...

KAPM04820-I

Receiving a request..

KAPM04821-I

Replying to the request....

KAPM04826-I

The instance has been updated. TARGET=aa...aa

aa...aa: information of the target

KAPM04827-I

A new instance has been created. TARGET=aa...aa

aa...aa: information of the target

KAPM04828-I

The class is empty. TARGET=aa...aa

aa...aa: information of the target

KAPM04829-I

The instance could not be found. TARGET=aa...aa

aa...aa: information of the target

KAPM04830-I

The instance was deleted. TARGET=aa...aa

aa...aa: information of the target

KAPM04832-E

The input data aa...aa is not valid for data type bb...bb. TARGET=cc...cc

aa...aa: input data value

bb...bb: input data type

cc...cc: information of the target

KAPM04833-E

The received XML element bb...bb is missing a required attribute aa...aa. TARGET=cc...cc

aa...aa: required attribute

bb...bb: XML element tag name that should include the attributes

cc...cc: information of the target

KAPM04834-E

The received XML element bb...bb is missing a required child element aa...aa. TARGET=cc...cc

aa...aa: required attribute

bb...bb: Parent element tag name

cc...cc: information of the target

KAPM04835-W

The received XML element bb...bb has no child element aa...aa. TARGET=cc...cc

aa...aa: required attribute

bb...bb: Parent element tag name

cc...cc: information of the target

KAPM04836-E

The received XML element aa...aa with attribute bb...bb=cc...cc is duplicated. TARGET=dd...dd

aa...aa: XML element tag names that are duplicated
bb...bb: Attribute name that identifies the elements
cc...cc: Attribute value that identifies the elements
dd...dd: information of the target

KAPM04837-E

The XML element aa...aa as child of element bb...bb is duplicated. TARGET=cc...cc

bb...bb: Attribute name that identifies the elements
bb...bb: Parent element tag name
cc...cc: information of the target

KAPM04838-I

The class has been created. TARGET=aa...aa

aa...aa: information of the target

KAPM04839-I

The class already exist. TARGET=aa...aa

aa...aa: information of the target

KAPM04840-I

The class could not be found. TARGET=aa...aa

aa...aa: information of the target

KAPM04841-I

The class was deleted. TARGET=aa...aa

aa...aa: information of the target

KAPM04842-E

The class aa...aa of the instance is invalid. TARGET=aa...aa

aa...aa: information of the target

KAPM04843-E

An attempt to decrypt authentication data failed.

KAPM04844-E

Login from anything other than a local host is not possible.

KAPM04845-E

The decrypted authentication data is invalid.

KAPM04846-E

Requests containing QueryString are not accepted.

KAPM04901-E

The parameter is invalid.

KAPM04902-E

A fatal error occurred.

KAPM04905-E

An attempt to open the file failed. Path = aa...aa

aa...aa: The absolute path of the file

KAPM04906-I

The alias for aa...aa was set.

aa...aa: PP name

KAPM04907-I

The alias for aa...aa was overwritten.

aa...aa: PP name

KAPM04908-I

The alias for aa...aa was deleted.

aa...aa: PP name

KAPM04909-E

The alias for aa...aa does not exist.

aa...aa: PP name

KAPM04910-W

The alias for aa...aa does not exist.

aa...aa: PP name

KAPM04933-E

An option is invalid.

KAPM04950-I

PrintWriter was created. path = "aa...aa", file = "bb...bb"

aa...aa: The path name of the file "bb ... bb"

bb...bb: file name

KAPM04951-I

BufferedReader was created. path = "aa...aa", file = "bb...bb"

aa...aa: The path name of the file "bb ... bb"

bb...bb: file name

KAPM04952-E

The file was not found. path = "aa...aa", file = "bb...bb"

aa...aa: The path name of the file "bb ... bb"

bb...bb: file name

KAPM04953-I

PrintWriter has closed.

KAPM04954-W

PrintWriter cannot be closed. PrintWriter is null.

KAPM04955-I

BufferedReader has closed.

KAPM04956-W

BufferedReader cannot be closed. BufferedReader is null.

KAPM04957-E

The specified application command is not registered. application name = "aa...aa"

aa...aa: Application name specified in the option

KAPM04958-E

The specified application command is already registered. application name = "aa...aa"

aa...aa: application name

KAPM04959-I

aa...aa has been added to the file.

aa...aa: application name

KAPM04960-I

aa...aa has been removed from the file.

aa...aa: application name

KAPM04970-I

Processing ended normally.

KAPM04971-E

The specified command is already registered.

KAPM04972-E

The specified command is not registered.

KAPM04973-E

An option is invalid.

KAPM04974-E

An unexpected error occurred.

KAPM04975-E

The type of OS is unknown.

KAPM04976-E

IllegalOptionException occurred. Description = "aa...aa"

aa...aa: Description

KAPM04977-E

InconsistencyException occurred. Description = "aa...aa"

aa...aa: Description

KAPM05001-I

hcnds64srv was entered.

KAPM05002-E

Command format is invalid.

KAPM05003-E

Option is invalid. option=aa...aa

aa...aa: invalid parameter

KAPM05004-E

Server name is invalid. server-name=aa...aa

aa...aa: server name

KAPM05005-E

The Win32API has failed. API name=aa...aa, error code=bb...bb

aa...aa: WIN32API name

bb...bb: error code

KAPM05006-E

Failed to start service. service-name=aa...aa

aa...aa: service name

KAPM05007-I

Already started service. service-name=aa...aa

aa...aa: service name

KAPM05008-E

Failed to stop service. service-name=aa...aa

aa...aa: service name

KAPM05009-I

Already stopped service. service-name=aa...aa

aa...aa: service name

KAPM05010-E

Failed to query service. service-name=aa...aa

aa...aa: service name

KAPM05011-E

Failed to control service.

KAPM05012-E

Failed to access registry. maintenance-code=aa...aa

aa...aa: maintenance code

KAPM05013-W

Failed to read init.conf. maintenance-code=aa...aa

aa...aa: maintenance code

KAPM05014-W

Failed to initialize trace. api-name=aa...aa,reason=bb...bb

aa...aa: Log trace API name

bb...bb: maintenance code

KAPM05015-E

An internal function has failed. Function name=aa...aa, error code=bb...bb

aa...aa: Function name

bb...bb: error code

KAPM05016-I

Succeeded in starting of service. service-name=aa...aa

aa...aa: service name

KAPM05017-I

Succeeded in stopping of service. service-name=aa...aa

aa...aa: service name

KAPM05018-E

A system call has failed. API name=aa...aa, error code=bb...bb

aa...aa: system call name

bb...bb: maintenance code

KAPM05019-W

Definition is invalid. name=aa...aa

aa...aa: Defined values name

KAPM05020-E

Failed to open file. maintenance-code=aa...aa

aa...aa: maintenance code

KAPM05021-E

Service does not exist.

KAPM05022-W

Service does not exist.

KAPM05023-E

Could not find executable file. file-name=aa...aa

aa...aa: file name

KAPM05024-W

Failed to initialize trace. Reason=aa...aa

aa...aa: Reason

KAPM05025-I

The start type has been successfully changed. service-name = aa...aa

aa...aa: service name

KAPM05026-E

An attempt to change the start type has failed. service-name = aa...aa

aa...aa: service name

KAPM05027-E

An attempt to start the DBMS service has failed.

KAPM05028-E

An attempt to stop the DBMS service has failed.

KAPM05029-E

An attempt to acquire the status of the DBMS service has failed.

KAPM05030-E

An attempt to query the status of a service has failed. (service name = aa...aa)

aa...aa: service name

KAPM05035-E

An attempt to execute the command aa...aa has failed.

aa...aa: File name that have been executed

KAPM05036-I

The command aa...aa was executed successfully. (return code = bb...bb)

aa...aa: File name that have been executed

bb...bb: return code

KAPM05037-E

An attempt to query a service has failed.

KAPM05038-W

The error has occurred in aa...aa command. code=bb...bb

aa...aa: command

bb...bb: error code

KAPM05044-E

This command cannot be executed now because of internal processing. Wait a while, and then try again.

KAPM05045-E

The execution of the command will be stopped because internal processing failed.

KAPM05046-E

An error occurred in an API. (API name = aa...aa, error code = bb...bb)

aa...aa: API name

bb...bb: error code

KAPM05050-E

Failed to execute the command that stops services. (command name = aa...aa, return code = bb...bb, server name = cc...cc)

aa...aa: command name

bb...bb: return code

cc...cc: server name

KAPM05052-I

The command that stops services was executed successfully. (command name = aa...aa, server name = bb...bb)

aa...aa: command name

bb...bb: server name

KAPM05053-I

hcnds64srv [aa...aa]{, [bb...bb],.....[.....]}

aa...aa: command line argument

bb...bb: command line argument

KAPM05055-W

The path is not a symbolic link. (path = aa...aa)

aa...aa: Path

KAPM05056-E

The directory could not be found. (path = aa...aa)

aa...aa: Path

KAPM05057-E

A memory-allocation error occurred.

KAPM05058-W

Execution of the hcmdsstartapp command failed. (return code = aa...aa)

aa...aa: Return code

KAPM05059-I

A request to start an application was received. (server name = aa...aa)

aa...aa: Server name

KAPM05201-E

The memory is insufficient.(aa...aa)

aa...aa: Variable name

KAPM05202-E

The number of options is insufficient.

KAPM05203-E

There is no value following the option.

KAPM05204-E

Option is invalid.

KAPM05205-E

There is only a value though there is no option.

KAPM05206-E

The error occurred in dispatcher.

KAPM05207-E

The error occurred in the registration of the service controller.

KAPM05208-E

The error occurred in the HandlerRoutine.

KAPM05209-I

The service_stop_thread is started.

KAPM05210-E

The error occurred in the service_stop_thread.

KAPM05211-E

The error occurred in the Report Status.

KAPM05212-E

The error occurred in create JavaVM.

KAPM05213-E

Failed to set processing of JavaVM.

KAPM05214-I

aa...aa started.

aa...aa: service name

KAPM05215-I

aa...aa stopped.

aa...aa: service name

KAPM05216-E

The error occurred in the start of service.

KAPM05217-E

Failed to get to the option definition file value.

KAPM05218-E

Failed to change the current directory.

KAPM05219-E

Failed to create JavaVM.

KAPM05220-E

Failed to connect to JavaVM.

KAPM05221-E

The class is not found.

KAPM05222-E

The method is not found.

KAPM05223-E

The error occurred in the Getinstpath.(aa...aa)

aa...aa: Registry key value

KAPM05224-E

The error occurred in the LoadLibrary.

KAPM05225-E

The error occurred in the GetProcAddress.

KAPM05226-E

The error occurred in the AllocConsole.

KAPM05227-E

The error occurred in the DeleteFile.

KAPM05228-E

The error occurred in the GenerateConsoleCtrlEvent.

KAPM05229-E

An attempt to execute the command to start the Web container server has failed.

KAPM05230-E

An attempt to execute the command to stop the Web container server has failed.

KAPM05231-E

An attempt to execute the thread-dump acquisition command has failed.

KAPM05232-E

The service stopped abnormally. (service name = aa...aa)

aa...aa: service name

KAPM05234-E

Execution of the command to start the J2EE server failed.

KAPM05235-E

Execution of the command to stop the J2EE server failed.

KAPM05236-E

An attempt to delete a file failed. (file path = aa...aa, error code = bb...bb)

aa...aa: File path

bb...bb: Error code

KAPM05237-E

An error occurred in an API function. (API function name = aa...aa, error code = bb...bb)

aa...aa: API function name

bb...bb: Error code

KAPM05250-I

Registration of the information-search user has finished.

KAPM05251-I

Deletion of the information-search user has finished.

KAPM05252-E

An option is invalid.

KAPM05253-E

The specified option contains an invalid character.

KAPM05255-E

An internal error occurred.

KAPM05256-E

A fatal error occurred.

KAPM05257-E

Log initialization has failed.

KAPM05258-I

The command has started.

KAPM05259-I

The command has ended.

KAPM05263-W

No registered information exists.

KAPM05264-E

The file format is invalid.

KAPM05265-E

An error occurred during file I/O processing.

KAPM05266-W

A server has not been registered.

KAPM05280-I

Registration of a secret has succeeded.

KAPM05281-I

Deletion of a secret has succeeded.

KAPM05282-E

An option is invalid.

KAPM05285-E

An internal error occurred.

KAPM05286-E

A fatal error occurred.

KAPM05288-I

The command has started.

KAPM05289-I

The command has finished.

KAPM05293-W

No registered information exists.

KAPM05294-E

The file format is invalid.

KAPM05295-E

An error occurred during file I/O processing.

KAPM05296-W

A server has not been registered.

KAPM05301-E

The license has expired.

KAPM05302-E

The system environment is incorrect.

KAPM05303-E

The entered license key is invalid.

KAPM05304-I

Processing ended normally.

KAPM05308-I

The acquiring of aa...aa logs started.

aa...aa: application name

KAPM05309-I

Backup of aa...aa started.

aa...aa: application name

KAPM05310-E

The acquiring of aa...aa logs abnormally ended.

aa...aa: application name

KAPM05311-I

The acquiring of aa...aa logs successfully ended.

aa...aa: application name

KAPM05312-E

Backup of aa...aa abnormally ended.

aa...aa: application name

KAPM05313-I

Backup of aa...aa successfully ended.

aa...aa: application name

KAPM05314-E

The specified directory is not empty.

KAPM05315-E

An option is invalid.

KAPM05316-E

The specified directory name aa...aa is invalid.

aa...aa: invalid directory name

KAPM05317-E

aa...aa is not registered. bb...bb is available.

aa...aa: PP name specified in the option

bb...bb: Registered PP name

KAPM05318-I

The acquiring of logs successfully ended. aa...aa

aa...aa: PP name

KAPM05319-E

The acquiring of logs abnormally ended. aa...aa

aa...aa: PP name

KAPM05320-I

Backup successfully ended. (aa...aa)

aa...aa: PP name

KAPM05321-E

Backup abnormally ended. (aa...aa)

aa...aa: PP name

KAPM05322-E

aa...aa does not exist.

aa...aa: File name

KAPM05323-I

Information for restore:

To restore the HiCommand shared repository, specify the "/enforce" option .

Before restoring, you have to stop the services "InterServer" and "InterBase Server".

Note that the HiCommand shared repository is overwritten with old backup data after the restore.

KAPM05324-E

The privilege is invalid.

KAPM05325-E

An attempt to execute hcmdsras failed.

KAPM05326-E

An attempt to execute jar has failed.

KAPM05327-E

An attempt to acquire the installed product list has failed.

KAPM05328-I

The hcndsbasebackup processing has succeeded.

KAPM05329-E

The hcndsbasebackup processing has failed.

KAPM05330-E

An option is invalid.

KAPM05331-E

The license has expired.

KAPM05332-E

The system environment is incorrect.

KAPM05333-E

The entered license key is invalid.

KAPM05334-I

Processing ended normally.

KAPM05335-E

The license key file that was entered could not be found.

KAPM05336-E

The license key file that was entered is invalid.

KAPM05337-I

The license key that should be entered does not exist in the license key file.

KAPM05350-E

An attempt to create an archive file of troubleshooting information failed.

KAPM05351-E

Acquire all directories under the directory specified for the dir option, and then contact customer support. (dir option = "aa...aa")

aa...aa: path of the directory specified for the dir option

KAPM05390-I

The hcmsras processing has succeeded.

KAPM05392-W

An attempt to get the System Log failed.

KAPM05393-W

An attempt to get the Application Log failed.

KAPM05394-W

An attempt to get the Syslog Daemon configuration file failed.

KAPM05402-E

The option(s) specified is insufficient.

KAPM05403-E

The option value specified is invalid.

KAPM05405-E

The option "aa...aa" is not supported.

aa...aa: option name

KAPM05406-E

The option "aa...aa" appears 2 times or more.

aa...aa: option name

KAPM05407-E

The combination of options is invalid.

KAPM05410-E

An exception occurred.

KAPM05411-E

The file "aa...aa" could not be read.

aa...aa: file name

KAPM05413-E

The input XML contains a grammar mistake.

KAPM05414-E

A fatal structure error was detected in the input XML.

KAPM05415-E

An error occurred during communication processing. (Detail: aa...aa)

aa...aa: Detail

KAPM05417-E

An invalid URL was detected. (aa...aa)

aa...aa: URL

KAPM05418-E

The server returned an empty response.

KAPM05419-E

An unsupported element type was detected in the XML.

KAPM05422-W

aa...aa error(s) were detected in the response.

aa...aa: Number of errors

KAPM05423-E

Invalid error information was detected.

KAPM05424-E

Invalid server information was detected.

KAPM05425-E

The input file contains a grammar mistake.

KAPM05426-E

An error occurred when inputting the file.

KAPM05427-E

The specified value is invalid. value = aa...aa

aa...aa: value

KAPM05432-E

Link registration processing has failed. Processing is interrupted.

KAPM05433-E

The acquisition as a result of registration processing has failed.

KAPM05434-E

I/O of XML has failed.

KAPM05435-E

An error occurred in the SAX parser.

KAPM05436-E

An attempt to analyze the execution result has failed.

KAPM05437-E

The execution result of the XREP processing was null.

KAPM05438-W

The "aa...aa" xrep processing result is bb...bb.

aa...aa: The output of the hcmdsxrep command

bb...bb: The output of the command

KAPM05439-E

An attempt to register a link has failed.

KAPM05440-E

An attempt to delete a link has failed.

KAPM05441-W

An attempt to check the result has failed.

KAPM05442-E

The registered information was not found.

KAPM05443-E

The table that registers a link does not exist.

KAPM05444-E

An error occurred within the server.

KAPM05445-E

An unexpected error occurred within the server.

KAPM05446-I

Processing ended normally.

KAPM05501-I

Backing up the database to file aa...aa...

aa...aa: file name

KAPM05502-I

INTERBASE_PID=aa...aa.

aa...aa: Process ID of INTERBASE

KAPM05503-W

The file aa...aa will be overwritten. Is this OK?

aa...aa: file name

KAPM05504-W

The HiCommand Server database will be overwritten by this procedure. Is this OK?

KAPM05505-E

The aa...aa file does not exist or is not readable. The HiCommand Server database was not altered.

aa...aa: file name

KAPM05506-E

The aa...aa file does not exist or is not readable. The HiCommand Server database was not altered.

aa...aa: file name

KAPM05507-I

Restoring the database from the aa...aa file...

aa...aa: file name

KAPM05508-E

The path of the specified database file is invalid.

KAPM05509-E

The specified database file was not found.

KAPM05510-E

An attempt to read to a file has failed. file name=aa...aa.

aa...aa: file name

KAPM05511-E

An unexpected error occurred.

KAPM05512-I

Backup has succeeded.

KAPM05513-E

An attempt to back up has failed.

KAPM05514-I

Restoration has succeeded.

KAPM05515-E

An attempt to restore has failed.

KAPM05516-E

The setup of the specified database is invalid.

KAPM05530-I

Backup of the database has started.

KAPM05531-I

Backup of the database has ended.

KAPM05532-I

Restoration of the database has started.

KAPM05533-I

Restoration of the database has ended.

KAPM05534-I

The database will now be backed up to file aa...aa.

aa...aa: Backup file name

KAPM05535-I

The system area has been damaged. Do you want to recover the system? [y or n]

KAPM05536-I

Please press the Enter key.

KAPM05537-I

Stop the HiRDB service before restoring the database.

KAPM05538-I

Re-creation of the system area has started.

KAPM05539-I

Re-creation of the system area has ended.

KAPM05540-I

Re-creation of the RD area has started.

KAPM05541-I

Re-creation of the RD area has ended.

KAPM05544-E

An attempt to back up the database has failed.

KAPM05545-E

An attempt to restore the database has failed.

KAPM05546-W

The backed-up version is different from the version in the current environment.

KAPM05547-I

Do you want to continue and restore the database?

KAPM05548-I

Restoration of the database will continue.

KAPM05550-E

The option(s) specified is invalid.

KAPM05551-E

An attempt to execute the aa...aa command has failed.

aa...aa: command name

KAPM05552-E

HiRDB has not been installed.

KAPM05553-E

The RD area of the specified program type could not be found.

KAPM05554-E

The file aa...aa could not be deleted.

aa...aa: file name

KAPM05555-E

An attempt to set the environment variable has failed.

KAPM05556-E

An attempt to create the backup file has failed.

KAPM05557-E

An I/O error occurred.

KAPM05558-E

An attempt to open the archive file has failed.

KAPM05559-E

The backup file format is invalid.

KAPM05560-E

The database location of the specified program type has not been created.

KAPM05561-I

The database was backed up successfully.

KAPM05562-E

An attempt to back up the database has failed.

KAPM05563-I

The database was completely restored.

KAPM05564-E

An attempt to completely restore the database has failed.

KAPM05565-I

The database was partially restored.

KAPM05566-E

An attempt to partially restore the database has failed.

KAPM05567-E

An exception occurred.

KAPM05568-E

aa...aa:bb...bb

aa...aa: command name

bb...bb: message

KAPM05569-E

aa...aa

aa...aa: command name

KAPM05570-I

Processing ended normally.

KAPM05573-E

The option(s) specified is invalid.

KAPM05574-E

An attempt to execute the aa...aa command has failed.

aa...aa: command name

KAPM05575-E

HiRDB has not been installed.

KAPM05576-E

The RD area of the specified program type could not be found.

KAPM05577-E

An attempt to clear an HiRDB environment variable has failed.

KAPM05578-E

The database location of the specified program type has not been created.

KAPM05579-E

An exception occurred.

KAPM05580-I

Re-creation of the database has started.

KAPM05581-I

Re-creation of the database has ended.

KAPM05582-I

Unsetup of aa...aa has started.

aa...aa: Product name

KAPM05583-I

Unsetup of aa...aa has ended.

aa...aa: Product name

KAPM05584-I

Setup of aa...aa has started.

aa...aa: Product name

KAPM05585-I

Setup of aa...aa has ended.

aa...aa: Product name

KAPM05586-I

Execution of the aa...aa command has started.

aa...aa: command name

KAPM05587-I

Execution of the aa...aa command ended normally.

aa...aa: command name

KAPM05588-I

Backup of the parameter definition file has ended.

KAPM05589-I

The backup file of the parameter definition file has been deleted.

KAPM05590-E

The option(s) specified is invalid.

KAPM05591-E

An attempt to execute the aa...aa command has failed.

aa...aa: command name

KAPM05592-E

HiRDB has not been set up.

KAPM05593-E

The aa...aa file was not found.

aa...aa: file name

KAPM05594-E

The aa...aa file could not be read.

aa...aa: file name

KAPM05595-E

The aa...aa folder could not be deleted.

aa...aa: folder name

KAPM05596-E

An SQL exception occurred.

KAPM05597-E

An attempt to clear the HiRDB system environment variables has failed.

KAPM05598-E

An exception occurred.

KAPM05599-E

aa...aa:bb...bb

aa...aa: command name

bb...bb: message

KAPM05601-I

The acquisition of HiRDB detail logs has started.

KAPM05602-I

The acquisition of HiRDB detail logs was successful.

KAPM05603-I

The acquisition of the HiRDB RDAREA has started.

KAPM05604-I

The acquisition of the HiRDB RDAREA was successful.

KAPM05605-I

The acquisition of the table data has started.

KAPM05606-I

The acquisition of the table data was successful.

KAPM05607-E

The command aa...aa is executing in another process.

aa...aa: command name

KAPM05608-E

The wait for the end of the command aa...aa has failed.

aa...aa: command name

KAPM05609-E

The command aa...aa timed out and ended.

aa...aa: command name

KAPM05610-I

The specified product is a version for which registration data can be moved. (This was determined by comparing the versions of the specified product and the product to be installed.)

KAPM05611-E

The specified product is a version for which registration data cannot be moved. (This was determined by comparing the versions of the specified product and the product to be installed.)

KAPM05612-E

The version of the specified product could not be acquired. (product name = aa...aa)

aa...aa: product name

KAPM05613-E

The format of the version number file for the specified product is invalid.

KAPM05614-E

The specified product is not installed. (product name = aa...aa)

aa...aa: product name

KAPM05615-E

An internal error occurred: aa...aa

aa...aa: Details message

KAPM05616-E

The number of specified options is invalid.

KAPM05617-E

The contents of the version file are invalid.

KAPM05618-I

The hcmdspcheck command has started.

KAPM05619-I

The hcmdspcheck command has ended.

KAPM05620-I

The hcmdspvrs command was successful.

KAPM05621-E

The hcmdspvrs command failed.

KAPM05622-E

Initialization of the log failed.

KAPM05623-E

An attempt to assign memory to store the log file path has failed.

KAPM05624-E

An attempt to acquire the installation path has failed.

KAPM05625-E

The product names do not match.

KAPM05626-E

The product name is not specified.

KAPM05627-E

There is no version number file.

KAPM05628-I

A file already exists at the specified output destination.

KAPM05629-E

A folder already exists at the specified output destination.

KAPM05630-E

There is no registry key for HBase.

KAPM05640-I

The user ID and password were changed successfully.

KAPM05642-W

Neither the user ID nor the password was changed.

KAPM05643-E

The format of the password file is invalid.

KAPM05644-E

An attempt to change the user ID and password has failed.

KAPM05645-E

An option is invalid.

KAPM05646-E

The specified argument contains an invalid character.

KAPM05647-E

An attempt to acquire the HiCommand Suite Common Component installation path has failed.

KAPM05648-E

An attempt to initialize the log has failed.

KAPM05649-E

An internal error occurred.

KAPM05650-E

A fatal error occurred.

KAPM05654-E

An attempt to output the password file has failed.

KAPM05655-E

The character string specified by the option is too long.

KAPM05656-E

The character string specified by the option is too short.

KAPM05657-I

The hcnds64changeaccount command has started.

KAPM05658-I

The hcnds64changeaccount command has ended.

KAPM05659-E

The program product specified by the type option is invalid.

KAPM05660-E

The user ID specified by the newid option is invalid.

KAPM05661-E

The password specified by the newpass option is invalid.

KAPM05662-E

An attempt to read the password file has failed.

KAPM05663-E

The specified user already exists.

KAPM05664-W

To enhance the security of internal accounts, use the hcmds64accountsecret command.

KAPM05672-I

The memory size was changed successfully.

KAPM05673-E

An attempt to change the memory size has failed.

KAPM05674-E

A fatal error occurred during processing.

KAPM05675-E

The service is running.

KAPM05676-E

In a Windows x32 environment, the memory size cannot be changed to Large.

KAPM05677-E

The parameter is invalid.

KAPM05678-I

The current memory size is aa...aa.

aa...aa: memory size

KAPM05679-E

The current memory size is unknown.

KAPM05680-E

An option is invalid.

KAPM05681-E

An entered argument is invalid.

KAPM05682-E

The specified options are insufficient.

KAPM05683-E

The value specified for an option is invalid. (option = aa...aa)

aa...aa: option

KAPM05684-E

The specified value is invalid. (value = aa...aa)

aa...aa: value

KAPM05685-E

The hcnds.home value cannot be acquired.

KAPM05686-E

An attempt to load the file has failed. (file = aa...aa)

aa...aa: file name

KAPM05687-I

Processing ended normally.

KAPM05688-E

Execution of the hcndsweb command has failed.

KAPM05689-E

Execution of the hcndsweb2 command has failed.

KAPM05690-E

In Windows x86 version, you cannot specify Large.

KAPM05691-E

Command execution failed because services were running.

KAPM05692-E

The command cannot be executed because multiple containers are not registered.

KAPM05699-E

An exception occurred.

KAPM05802-E

The option is invalid.

KAPM05803-E

The specified arguments are insufficient.

KAPM05804-E

The specified value of option is invalid. (Option = aa...aa)

aa...aa: Option name

KAPM05805-E

The specified directory cannot be created. (directory = aa...aa)

aa...aa: directory name

KAPM05806-E

The specified directory name already existed as a file. (file = aa...aa)

aa...aa: file name

KAPM05807-E

The specified value is invalid. (value = aa...aa)

aa...aa: value

KAPM05808-E

The file aa...aa does not exist.

aa...aa: file name

KAPM05809-E

The directory aa...aa does not exist.

aa...aa: directory name

KAPM05810-E

The file aa...aa already exists.

aa...aa: file name

KAPM05811-E

Command aa...aa returns value bb...bb. The error message is cc...cc.

aa...aa: command name

bb...bb: Returned value

cc...cc: error message

KAPM05812-I

Processing ended normally.

KAPM05813-E

An IOException occurred. (details = aa...aa)

aa...aa: details

KAPM05814-E

An exception occurred. (details = aa...aa)

aa...aa: details

KAPM05815-E

A NullPointerException occurred. (details = aa...aa)

aa...aa: details

KAPM05816-E

An error occurred while executing the hcmdsauthmode command.

KAPM05817-E

There is no RD area in the system.

KAPM05818-I

The hcmds64authmove command has started.

KAPM05819-I

Processing to import data has started.

KAPM05820-I

Processing to import data has ended.

KAPM05821-I

Processing to export data has started.

KAPM05822-I

Processing to export data has ended.

KAPM05823-E

HiRDB has not started.

KAPM05824-E

The directory aa...aa already exists.

aa...aa: directory name

KAPM05825-E

An HSSOException occurred. (details = aa...aa)

aa...aa: details

KAPM05826-E

A CIMException occurred. (details = aa...aa)

aa...aa: details

KAPM05827-E

The specified directory is not empty. (directory name = aa...aa)

aa...aa: directory name

KAPM05828-E

An attempt to execute the hcnds64authmove command has failed.

KAPM05829-E

A fatal error occurred.

KAPM05830-E

An attempt to establish a connection has failed.

KAPM05831-E

An attempt to execute SQL has failed.

KAPM05832-I

The authentication data was backed up successfully.

KAPM05833-E

An attempt to back up the authentication data has failed.

KAPM05834-I

The authentication data was restored successfully.

KAPM05835-E

An attempt to restore the authentication data has failed.

KAPM05836-E

An attempt to acquire the physical table name has failed. (table name = aa...aa)

aa...aa: table name

KAPM05837-W

The column data exceeds 80 characters. (column data = aa...aa)

aa...aa: column data

KAPM05838-E

An attempt to execute the SQL has failed. (SQL = aa...aa, error code = bb...bb)

aa...aa: SQL statement that was run

bb...bb: error code

KAPM05840-E

The option is invalid.

KAPM05841-E

The option is invalid. Code=[aa...aa], Data=[bb...bb]

aa...aa: Code indicating the occurrence location

bb...bb: occurred options and values

KAPM05842-I

hcnds64banner [aa...aa]{,[bb...bb],.....[.....]}

aa...aa: Command line arguments

bb...bb: Command line arguments

KAPM05843-E

The message file does not exist.

KAPM05844-E

The path specified for the message file is not a file.

KAPM05845-E

The message exceeded 1000 characters.

KAPM05846-E

The path specified in the aa...aa option is not an absolute path.

aa...aa: option

KAPM05850-E

An attempt to set the banner message display has failed.

KAPM05851-E

An attempt to set the banner message display has failed. File = [aa...aa], Code = [bb...bb]

aa...aa: file or directory

bb...bb: Code indicating the occurrence location

KAPM05852-I

Setting of the banner message display has been completed.

KAPM05860-W

The banner message display has already been cancelled.

KAPM05861-E

An attempt to cancel the banner message display has failed.

KAPM05862-E

An attempt to cancel the banner message display has failed. File = [aa...aa], Code=[bb...bb]

aa...aa: file or directory

bb...bb: Code indicating the occurrence location

KAPM05863-I

Cancellation of the banner message display has been completed.

KAPM05864-I

aa...aa

aa...aa: standard error output

KAPM05876-E

A fatal error occurred during processing.

KAPM05879-E

aa...aa

aa...aa: Information for debugging

KAPM05880-E

The value of EXCurrentVersion is invalid.

KAPM05881-E

EXCurrentVersion does not exist.

KAPM05882-E

The registry key that must be acquired does not exist.

KAPM05883-E

A fatal error occurred.

KAPM05884-E

The version management file is invalid

KAPM05885-E

The version management file that must be acquired does not exist.

KAPM05886-E

An attempt to acquire the version has failed.

KAPM05887-I

The hcmdsvrsutil utility was successful.

KAPM05890-I

The hcmdsbasevrs command was successful.

KAPM05891-E

The sub-key that shows the version does not exist.

KAPM05892-I

The hcmdsbasevrs command has started.

KAPM05893-I

The hcmdsbasevrs command has ended.

KAPM05894-E

A fatal error occurred.

KAPM05895-E

The registry key that must be acquired does not exist.

KAPM05896-E

Initialization of the log failed.

KAPM05897-E

An attempt to acquire the installation path has failed.

KAPM05898-E

An attempt to create the log file path has failed.

KAPM05899-E

There is no registry key for HBase.

KAPM05900-I

The hcnds64dbtrans command has started.

KAPM05901-I

The hcnds64dbtrans command ended normally.

KAPM05902-E

An option is invalid.

KAPM05903-E

An option is invalid. Code=[aa...aa], Data=[bb...bb]

aa...aa: Code indicating the occurrence location

bb...bb: occurred options and values

KAPM05904-I

hcnds64dbtrans [aa...aa]{,[bb...bb],.....[.....]}

aa...aa: Command line arguments

bb...bb: Command line arguments

KAPM05905-E

The path specified in the aa...aa option is not an absolute path.

aa...aa: option

KAPM05906-E

Authentication data cannot be registered in a secondary server.

KAPM05907-I

aa...aa

aa...aa: standard error output

KAPM05909-E

An unexpected exception occurred.

KAPM05910-E

An attempt to acquire the version of aa...aa has failed.

aa...aa: Product name

KAPM05911-E

aa...aa is a version that cannot be registered.

aa...aa: Product name

KAPM05912-I

aa...aa cannot be registered because it is not installed.

aa...aa: Product name

KAPM05913-E

Processing to register aa...aa will stop because it is not installed.

aa...aa: Product name

KAPM05914-E

Processing to register aa...aa will stop because it is not in the registration data.

aa...aa: Product name

KAPM05915-E

An attempt was made to register primary server data into the secondary server.

KAPM05916-E

An attempt was made to register secondary server data into the primary server.

KAPM05917-E

An attempt to import the database has failed.

KAPM05918-E

An attempt to export the database has failed.

KAPM05919-E

The hcnds64dbtrans command cannot be executed because the database is currently in use.

KAPM05920-E

The archive file specification is incorrect.

KAPM05921-E

An attempt to extract the archive file has failed.

KAPM05922-E

An attempt to create an archive file has failed.

KAPM05923-E

An archive file cannot be created because the data exceeds 2 GB.

KAPM05924-E

The work directory specification is incorrect.

KAPM05925-E

The work directory is not empty.

KAPM05926-E

The format of the registration data in the work directory is incorrect.

KAPM05927-E

DBMS is not running.

KAPM05928-E

DBMS is not set up.

KAPM05929-W

An attempt to delete the work directory has failed.

KAPM05930-I

aa...aa will now be exported.

aa...aa: "The Application data" or "The Authentication data"

KAPM05931-I

aa...aa has been exported.

aa...aa: "The Application data" or "The Authentication data"

KAPM05932-I

aa...aa has been deleted from the authentication data.

aa...aa: Product name

KAPM05933-I

The archive file will now be created.

KAPM05934-I

The archive file has been created.

KAPM05935-I

The archive file will now be extracted.

KAPM05936-I

The archive file has been extracted.

KAPM05937-I

aa...aa will now be imported.

aa...aa: "The Application data" or "The Authentication data"

KAPM05938-I

aa...aa has been imported.

aa...aa: "The Application data" or "The Authentication data"

KAPM05939-E

aa...aa

aa...aa: detailed data at the time of an error

KAPM05950-E

The specified product is not supported.

KAPM05951-E

The sub-key that shows the version does not exist.

KAPM05952-E

The specified product is not installed.

KAPM05953-I

The processing of the hcndsvrsutil library succeeded.

KAPM05954-E

The product name is not specified.

KAPM05955-E

The product names do not match.

KAPM05956-E

The processing of the hcndsvrsutil library failed.

KAPM05957-E

There is no registry key for the specified product.

KAPM05958-E

An attempt to acquire the sub-key that shows the version of the specified product has failed.

KAPM05959-E

The file that stores the installation path is invalid.

KAPM05970-I

The hcmdspvrs command was successful.

KAPM05971-E

The specified product is not installed. (product name = aa...aa)

aa...aa: product name

KAPM05972-E

An attempt to acquire version information for the specified product has failed.

KAPM05973-I

The hcmdspvrs command has started.

KAPM05974-I

The hcmdspvrs command has ended.

KAPM05975-E

A fatal error occurred.

KAPM05976-E

Log initialization failed.

KAPM05977-E

Initialization of the installation path has failed.

KAPM05978-E

An attempt to assign memory to store the log file path has failed.

KAPM05979-E

The number of specified options is invalid.

KAPM05980-E

A file already exists at the specified output destination.

KAPM05981-E

A folder already exists at the specified output destination.

KAPM05982-E

The file-creation function failed.

KAPM05983-E

The file-writing function failed.

KAPM05984-I

The version was successfully acquired. (product name = aa...aa, version = bb...bb)

aa...aa: product name

bb...bb: version

KAPM05985-E

An attempt to acquire the version has failed. (product name = aa...aa)

aa...aa: product name

KAPM05986-E

A fatal error occurred: aa...aa

aa...aa: Details message

KAPM05987-I

The processing of the hcmdsvrsutil library succeeded.

KAPM05988-E

The processing of the hcmdsvrsutil library failed. (RTN = aa...aa, message = bb...bb)

aa...aa: Return value in the version acquisition function

bb...bb: Error message in the version acquisition function

KAPM05990-E

The version file does not exist. (command line = aa...aa)

aa...aa: command line

KAPM05991-E

The argument is invalid.

KAPM05999-E

Fatal error.

KAPM06001-I

Updating of the database has started.

KAPM06002-I

The database was updated from 01-00 to 01-01.

KAPM06003-I

The database need not be updated to 01-01.

KAPM06004-I

The database updating from 01-01 to 03-00 has started.

KAPM06005-I

The database was updated from 01-01 to 03-00.

KAPM06006-I

The database need not be updated to 03-00.

KAPM06007-I

The database is already updated.

KAPM06008-E

Updating of the database abnormally ended.

KAPM06009-I

Updating of the database has ended.

KAPM06010-E

An attempt to backup of the database has failed.

KAPM06011-E

An attempt to restore of the database has failed.

KAPM06012-I

The database does not need to be updated to aa...aa.

aa...aa: version

KAPM06013-I

The database has been updated from aa...aa to bb...bb.

aa...aa: Previous versions

bb...bb: Newer version

KAPM06015-E

An attempt to change the database meta definition has failed.

KAPM06016-E

The version of the database to be upgraded is unknown.

KAPM06017-E

The current database version could not be obtained.

KAPM06018-E

An attempt to acquire the connection has failed.

KAPM06019-E

An attempt to set up the auto-commit function has failed.

KAPM06020-E

An attempt to create the lock table has failed.

KAPM06021-E

An attempt to lock the table has failed.

KAPM06022-E

An attempt to execute SQL has failed.

KAPM06023-E

An attempt to update the version of the database version table has failed.

KAPM06024-E

An error occurred during an attempt to read a file.

KAPM06025-E

An attempt to acquire the database version has failed.

KAPM06026-E

An attempt to upgrade the database has failed.

KAPM06027-I

The database was successfully updated.

KAPM06028-E

An attempt to set up the environment has failed. (system property name = aa...aa)

aa...aa: system property name

KAPM06029-E

Database is not running.

KAPM06030-E

Disk capacity is insufficient.

KAPM06031-E

An attempt to upgrade the database has failed.

KAPM06032-E

An attempt to acquire the database version has failed.

KAPM06033-E

The current database version is incorrect.

KAPM06034-E

Exclusion control of a TNB_DBVersion table has failed.

KAPM06035-E

The access class of a database could not be found.

KAPM06036-E

Access of a database has failed.

KAPM06037-I

The database has been update from version aa...aa to bb...bb.

aa...aa:version

bb...bb:version

KAPM06038-E

An attempt to acquire the user names of users who access the database has failed.

KAPM06039-E

The version of the target database is unknown.

KAPM06040-E

An unexpected error occurred.

KAPM06041-E

An attempt to clear an HiRDB environment variable has failed.

KAPM06042-W

The SQL will be disregarded. (SQL = aa...aa, error code = bb...bb)

aa...aa: SQL statement that was run

bb...bb: error code

KAPM06043-E

An attempt to perform a rollback has failed.

KAPM06044-E

The version upgrade definition file is invalid.

KAPM06045-I

The SQL will now be executed. (SQL = aa...aa)

aa...aa: SQL statement

KAPM06046-I

Processing to upgrade the database version started. (version = aa...aa)

aa...aa: database version

KAPM06047-I

Processing to upgrade the database version ended. (version = aa...aa)

aa...aa: database version

KAPM06048-E

An attempt to execute the SQL has failed. (SQL = aa...aa, error code = bb...bb)

aa...aa: SQL statement that was run

bb...bb: error code

KAPM06049-E

The RD area of HBase is blocked.

KAPM06050-E

An attempt to add a built-in user group failed.

KAPM06052-E

An attempt to change a resource group attribute has failed. (attribute = aa...aa)

aa...aa: attribute

KAPM06100-I

The hcnds64chgurl command started.

KAPM06101-I

The hcnds64chgurl command successfully ended.

KAPM06102-E

The hcnds64chgurl command abnormally ended.

KAPM06103-I

An attempt to back up the database has succeeded.

KAPM06104-E

An attempt to back up the database has failed.

KAPM06105-I

An attempt to restore the database has succeeded.

KAPM06106-E

An attempt to restore the database has failed.

KAPM06111-I

The URL was changed from "aa...aa" to "bb...bb".

aa...aa: Previous URL

bb...bb: Newer URL

KAPM06112-E

The specified URL before the change is invalid. URL = "aa...aa"

aa...aa: URL

KAPM06113-E

The specified URL after the change is invalid. URL = "aa...aa"

aa...aa: URL

KAPM06114-E

An attempt to connect to the database has failed.

KAPM06115-E

An option is invalid.

KAPM06116-E

CIMException occurred. Description = "aa...aa"

aa...aa: Description

KAPM06117-E

An unexpected error occurred. Description = "aa...aa"

aa...aa: Description

KAPM06118-E

The BaseURL column does not exist in the class. class name = "aa...aa"

aa...aa: class name

KAPM06119-W

The specified URL does not exist in the class. URL = "aa...aa"

aa...aa: URL

KAPM06120-I

The URL is not registered.

KAPM06121-E

IllegalDataException occurred. Description = "aa...aa"

aa...aa: Description

KAPM06122-W

The specified URL before the change and after the change are same.

KAPM06123-W

The program product specified by the type option is invalid.

KAPM06124-W

An attempt to register authentication data failed.

KAPM06130-I

The hcndsinitsetup command has started.

KAPM06131-I

The hcndsinitsetup command was successful.

KAPM06132-E

The hcndsinitsetup command has failed.

KAPM06138-E

A required database path is missing.

KAPM06139-E

An error occurred during a parameter check.

KAPM06140-E

Memory is insufficient.

KAPM06141-E

The HiRDB environment already exists.

KAPM06142-E

Free disk space is insufficient.

KAPM06143-E

An error occurred in the system definition entry file.

KAPM06144-E

The port is already being used.

KAPM06145-E

Other errors.

KAPM06146-E

An attempt to create the file has failed.

KAPM06147-E

An attempt to write to the file has failed.

KAPM06149-E

An attempt to delete the file has failed.

KAPM06153-E

An attempt to execute the command has failed.

KAPM06154-E

An unexpected exception occurred.

KAPM06159-E

An attempt to acquire a cluster configuration file has failed.

KAPM06160-E

The value of hcnds.home cannot be acquired.

KAPM06161-E

The cluster configuration file was not found.

KAPM06162-E

An attempt to acquire the key name has failed.

KAPM06163-E

An attempt to acquire a value has failed.

KAPM06164-E

A CIMClassNotFoundException occurred.

KAPM06165-E

An attempt to delete the file has failed. (file = "aa...aa")

aa...aa: file name

KAPM06166-E

An attempt to register the authentication data has failed.

KAPM06169-E

An attempt to log in as an internal user has failed.

KAPM06170-I

The hcnds64dbstatus command has started.

KAPM06171-I

The hcnds64dbstatus command has ended.

KAPM06172-I

The hcnds64dbstatus command was successful.

KAPM06173-E

The hcnds64dbstatus command has failed.

KAPM06176-I

The DBMS is running.

KAPM06177-I

The DBMS is now starting or shutting down.

KAPM06178-I

The DBMS service has stopped.

KAPM06179-E

The DBMS restart was interrupted.

KAPM06180-E

The DBMS service has stopped or does not exist.

KAPM06181-E

The database has not been set up.

KAPM06182-E

An internal error occurred.

KAPM06183-I

Command execution results: "aa...aa"

aa...aa: Command execution results

KAPM06184-E

An attempt to execute the command has failed.

KAPM06185-E

An exception occurred.

KAPM06186-E

The value of hcnds.home could not be acquired.

KAPM06187-E

An attempt to judge the DBMS status has failed.

KAPM06190-E

An attempt to acquire a parameter failed. (file name = aa...aa, key = bb...bb, value = cc...cc)

aa...aa: file name

bb...bb: key

cc...cc: value

KAPM06191-E

An attempt to set a parameter failed. (file name = aa...aa, key = bb...bb, value = cc...cc)

aa...aa: file name

bb...bb: key

cc...cc: value

KAPM06192-I

The command was executed. (command name = aa...aa, return code = bb...bb)

aa...aa: command name

bb...bb: return code

KAPM06193-I

aa...aa

aa...aa: Debugging information

KAPM06194-W

An attempt to obtain the absolute path of the hcndsChangeSysPass file failed.

KAPM06195-W

An attempt to delete the hcndsChangeSysPass file failed.

KAPM06203-E

The list of table name is empty.

KAPM06206-E

An unexpected error occurred during InterBase processing.

KAPM06207-E

The list of table names is empty.

KAPM06209-I

A table aa...aa has been created.

aa...aa: table name

KAPM06214-E

InterBaseServer is not running.

KAPM06215-E

InterServer is not running.

KAPM06216-E

An argument contains a null value.

KAPM06217-E

The option is invalid.

KAPM06218-E

The specified directory cannot be created. (directory = aa...aa).

aa...aa: directory name

KAPM06219-E

The specified directory name already exists as a file. (file = aa...aa)

aa...aa: File name

aa...aa: file name

KAPM06220-E

The specified file name already exists as a directory. (directory = aa...aa)

aa...aa: directory name

KAPM06221-E

The specified database file (aa...aa) does not exist.

aa...aa: database file name

KAPM06222-E

The specified XML file (aa...aa) does not exist.

aa...aa: XML file name

KAPM06223-E

The specified value is invalid. (value = aa...aa)

aa...aa: value

KAPM06224-E

The specified arguments are insufficient.

KAPM06226-E

The specified file (aa...aa) does not exist in the argument of the pdload command.

aa...aa: The name that is not exist

KAPM06227-I

The processing on table aa...aa finished successfully.

aa...aa: table name

KAPM06228-E

The CSV file (aa...aa) contains an invalid line.

aa...aa: file name

KAPM06229-E

An attempt to read the data from table aa...aa has failed.

aa...aa: table name

KAPM06230-E

An unexpected return value (aa...aa) was returned from the pdload command.

aa...aa: unexpected return value

KAPM06231-E

An attempt to upgrade InterBase has failed.

KAPM06232-E

An SQL exception occurred.

KAPM06234-E

A table name in XML is null or 0 bytes.

KAPM06235-E

An unexpected XML tag (aa...aa) has been detected.

aa...aa: unexpected XML tag

KAPM06239-E

An error occurred during SAX processing.

KAPM06241-E

A fatal error occurred during SAX processing.

KAPM06242-E

An unexpected data length (aa...aa) was detected.

aa...aa: Unexpected value

KAPM06243-E

A SAXException occurred. (details = aa...aa)

aa...aa: Detailed information of SAXException

KAPM06244-E

The length of the data to be moved to HiRDB exceeds the HiRDB limit. (data type of excessively long data, length) = (aa...aa, bb...bb)

aa...aa: Data type of excessively long data

bb...bb: Data length of excessively long data

KAPM06245-E

HiRDB has not started.

KAPM06246-I

The table aa...aa was successfully created.

aa...aa: Table name

KAPM06247-E

The table aa...aa was not created.

aa...aa: Table name

KAPM06248-I

Processing ended normally.

KAPM06249-E

An unexpected exception occurred.

KAPM06250-I

The data was registered successfully in table aa...aa.

aa...aa: Table name

KAPM06251-E

The data was not registered in table aa...aa.

aa...aa: Table name

KAPM06252-E

Authentication has failed at aa...aa.

aa...aa: Database name

KAPM06253-E

Application aa...aa is not supported.

aa...aa: Application name

KAPM06255-I

Processing to initialize database conversion is being performed.

KAPM06256-E

The specified file could not be created. (file = aa...aa)

aa...aa: File name

KAPM06257-I

Data is now being read from the old database. (progress = aa...aa/bb...bb)

aa...aa: The number of the result tables

bb...bb: The number of the target tables

KAPM06258-I

The database is now being converted. (progress = aa...aa/bb...bb)

aa...aa: The number of the result tables

bb...bb: The number of the target tables

KAPM06259-E

The file aa...aa does not exist.

aa...aa: File name

KAPM06262-I

The hcmdssslsetup command has started.

KAPM06263-I

The hcmdssslsetup command has ended.

KAPM06264-I

The hcmdssslsetup command ended successfully.

KAPM06266-E

An option is invalid.

KAPM06267-E

The sslc.cnf file was not found.

KAPM06268-E

The sslc.cnf file is invalid.

KAPM06269-E

Execution of the sslc command failed.

KAPM06270-I

Processing to create a private key has started.

KAPM06271-I

Processing to create a private key has ended.

KAPM06272-E

Processing to create a private key failed.

KAPM06273-I

Processing to create a self-signed certificate has started.

KAPM06274-I

Processing to create a self-signed certificate has ended.

KAPM06275-E

Processing to create a self-signed certificate failed.

KAPM06276-I

Processing to create a self-signed certificate in DER format has started.

KAPM06277-I

Processing to create a self-signed certificate in DER format has ended.

KAPM06278-E

Processing to create a self-signed certificate in DER format failed.

KAPM06280-E

An internal error occurred.

KAPM06281-I

Processing to create a certificate content file started.

KAPM06282-I

Processing to create a certificate content file ended.

KAPM06283-E

Processing to create a certificate content file has failed.

KAPM06284-E

The sslc command was not found.

KAPM06285-E

File deletion has failed.

KAPM06286-E

The private key was not found.

KAPM06287-E

The self-signed certificate was not found.

KAPM06288-E

The DER format self-signed certificate was not found.

KAPM06289-E

The certificate contents file was not found.

KAPM06290-E

An exception occurred.

KAPM06291-W

The host name cannot be acquired.

KAPM06292-E

An attempt to output a file failed.

KAPM06303-E

The option(s) specified is insufficient.

KAPM06304-E

The option value specified is invalid.

KAPM06305-E

The option "aa...aa" is not supported.

aa...aa: Option name

KAPM06306-E

The option "aa...aa" appears 2 times or more.

aa...aa: Option name

KAPM06307-E

The combination of options is invalid.

KAPM06308-E

An argument contains a null value.

KAPM06309-E

An exception occurred.

KAPM06310-E

The file "aa...aa" could not be read.

aa...aa: File name

KAPM06311-E

The input file contains a grammar mistake.

KAPM06312-E

An error occurred when inputting the file.

KAPM06313-E

The specified value is invalid. value = aa...aa

aa...aa: Value

KAPM06317-E

I/O of XML has failed.

KAPM06318-E

An error occurred in the SAX parser.

KAPM06319-I

Processing ended normally.

KAPM06321-E

The "bb...bb" file to be used by "aa...aa" does not exist.

aa...aa: Command name or class name

bb...bb: File name

KAPM06322-E

An SQL exception occurred.

KAPM06323-I

Execution of the "aa...aa" command ended normally.

aa...aa: Command name

KAPM06324-E

An attempt to execute the "aa...aa" command has failed.

aa...aa: Command name

KAPM06325-I

HiRDB was started.

KAPM06326-E

HiRDB was not started.

KAPM06327-I

HiRDB was stopped.

KAPM06328-E

HiRDB was not stopped.

KAPM06330-I

aa...aa processing started.

aa...aa: Method name

KAPM06331-I

aa...aa processing finished.

aa...aa: Method name

KAPM06332-E

The database of the specified product has not been set up.

KAPM06333-E

HiRDB cannot be stopped because a Suite product is connected to HiRDB.

KAPM06334-E

InterBase is not running.

KAPM06335-E

The DBMS has not started.

KAPM06336-E

Authentication has failed at InterBase.

KAPM06337-E

Authentication has failed in the DBMS.

KAPM06338-E

An unexpected exception occurred.

KAPM06339-E

An unexpected exception occurred.

KAPM06340-E

Memory is insufficient.

KAPM06341-E

The DBMS environment already exists.

KAPM06342-E

Free disk space is insufficient.

KAPM06343-E

An error occurred in the system definition entry file.

KAPM06344-E

The port is already being used.

KAPM06345-E

An unexpected exception occurred.

KAPM06346-E

The file "aa...aa" already exists.

aa...aa: File name

KAPM06347-W

The specified file system area "aa...aa" already existed, so it was deleted.

aa...aa: File system area

KAPM06348-I

The database was created successfully.

KAPM06349-E

An attempt to create the database has failed.

KAPM06350-I

The database was deleted successfully.

KAPM06351-E

An attempt to delete the database has failed.

KAPM06352-E

Directory creation has failed. (directory = aa...aa)

aa...aa: Directory name

KAPM06353-I

Set up the database again.

KAPM06354-E

There are no parameter definition files in the specified directory. Specify a directory that contains a parameter definition file.

KAPM06355-W

Database unsetup processing failed. (product name = aa...aa)

aa...aa: Product name

KAPM06356-W

A database has not been set up for the specified product. (product name = aa...aa)

aa...aa: Product name

KAPM06357-I

The database was successfully unsetup. (product name = "aa...aa")

aa...aa: Product name

KAPM06358-I

The initial unsetup processing succeeded.

KAPM06359-W

The initial unsetup processing failed.

KAPM06360-W

Deletion of the RD area failed. (RD area file = aa...aa)

aa...aa: RD area file name

KAPM06361-I

The method was executed. (method name = aa...aa, return code = bb...bb)

aa...aa: Method name

bb...bb: Return code

KAPM06362-E

Acquisition of the name of a set up product failed.

KAPM06363-I

The service is stopped.

KAPM06364-I

The service is running.

KAPM06365-I

The service is starting.

KAPM06366-I

The service is stopping.

KAPM06367-I

The service is now being resumed.

KAPM06368-I

The service is now being paused.

KAPM06369-I

The service is paused.

KAPM06370-I

The service does not exist.

KAPM06371-W

The service is disabled.

KAPM06372-W

Acquisition of the service status failed.

KAPM06373-W

The service status is currently unknown.

KAPM06374-I

Execution of the "aa...aa" command ended successfully. (return code = bb...bb)

aa...aa: Command name

bb...bb: Return code

KAPM06375-E

Execution of the "aa...aa" command failed. (return code = bb...bb)

aa...aa: Command name

bb...bb: Return code

KAPM06376-E

Failed to specify the permission settings. (path = aa...aa)

aa...aa: Path

KAPM06377-E

Failed to specify the permission settings.

KAPM06378-E

The specified directory name already exists as a file name. (file name = aa...aa)

aa...aa: File name

KAPM06379-E

The directory name exceeds 136 characters.

KAPM06381-E

An attempt to set up the unload function has failed.

KAPM06382-E

The unload function is enabled in another product.

KAPM06383-E

The format of the unload function file is invalid.

KAPM06384-E

The directory specified in the option is invalid. (directory = aa...aa)

aa...aa: Directory name

KAPM06385-E

Creation of the directory failed. (directory = aa...aa)

aa...aa: Directory name

KAPM06386-E

Command aa...aa returned the value bb...bb. The error message is cc...cc..

aa...aa: Command name
bb...bb: Return code
cc...cc: Error message

KAPM06396-E

"aa...aa":"bb...bb"

aa...aa: Command name
bb...bb: message

KAPM06398-E

"aa...aa"

aa...aa: Message for the exception

KAPM06399-E

An unexpected exception occurred.

KAPM06403-E

An exception occurred.

KAPM06404-E

The file "aa...aa" could not be read.

aa...aa: File name

KAPM06405-I

Processing ended normally.

KAPM06407-E

The "bb...bb" file to be used by "aa...aa" does not exist.

aa...aa: Command name or class name

bb...bb: File name

KAPM06408-I

Execution of the "aa...aa" command ended normally.

aa...aa: Command name

KAPM06409-E

An attempt to execute the "aa...aa" command has failed.

aa...aa: Command name

KAPM06410-I

The setup status is "not set up".

KAPM06411-I

The setup status is "stand-alone".

KAPM06412-I

The setup status is "active system".

KAPM06413-I

The setup status is "standby system".

KAPM06414-E

The option specification is incorrect.

KAPM06429-E

An unexpected exception occurred.

KAPM06433-E

An exception occurred.

KAPM06434-I

Processing ended normally.

KAPM06436-E

An attempt to execute the "aa...aa" command has failed.

aa...aa: Command name

KAPM06437-E

The option(s) specified is insufficient.

KAPM06438-I

The HiRDB service has started.

KAPM06439-I

The HiRDB service has stopped.

KAPM06440-I

The HiRDB service has already started.

KAPM06441-I

The HiRDB service has already stopped.

KAPM06442-E

The HiRDB service has not been set up.

KAPM06443-E

An attempt to start the HiRDB service has failed.

KAPM06444-E

An attempt to stop the HiRDB service has failed.

KAPM06445-E

HiRDB cannot be stopped because a Suite product is connected to HiRDB.

KAPM06459-E

An unexpected exception occurred.

KAPM06470-I

The hcmsdbconnectcheck command will now start.

KAPM06471-I

Now checking the HiRDB connection... (number of executions = aa...aa, specified number of executions = bb...bb)

aa...aa: Number of executions

bb...bb: Specified number of executions

KAPM06472-I

HiRDB can be connected to.

KAPM06473-I

The hcmsdbconnectcheck command will now end.

KAPM06474-E

A connection with HiRDB could not be confirmed.

KAPM06475-E

The hcmsdbconnectcheck command could not be executed successfully.

KAPM06476-E

An option is invalid.

KAPM06477-E

The value of hcms.home could not be acquired.

KAPM06501-I

The method has started.

KAPM06502-I

The method has finished.

KAPM06503-E

The option is invalid.

KAPM06504-E

A specified option is insufficient.

KAPM06505-E

The value specified in the option is invalid. (option = aa...aa)

aa...aa: Option name

KAPM06506-E

The specified directory cannot be created. (directory = aa...aa)

aa...aa: Directory name

KAPM06507-E

The specified directory already exists as a file. (file = aa...aa)

aa...aa: File name

KAPM06508-E

The specified value is invalid. (value = aa...aa)

aa...aa: Specified value

KAPM06509-E

The file aa...aa does not exist.

aa...aa: File name

KAPM06510-E

The directory aa...aa does not exist.

aa...aa: Directory name

KAPM06511-E

The file aa...aa already exists.

aa...aa: File name

KAPM06512-E

The directory aa...aa already exists.

aa...aa: Directory name

KAPM06513-E

Command aa...aa returned the value bb...bb. The error message is cc...cc.

aa...aa: Command name

bb...bb: Return value

cc...cc: Error message

KAPM06514-I

Processing ended normally.

KAPM06515-E

An IOException occurred. (details = aa...aa)

aa...aa: Details of the exception

KAPM06516-E

An exception occurred. (details = aa...aa)

aa...aa: Details of the exception

KAPM06517-E

A NullPointerException occurred. (details = aa...aa)

aa...aa: Details of the exception

KAPM06518-E

HiRDB has not been installed.

KAPM06519-E

An error occurred while executing the hcmdsdbmode command.

KAPM06520-E

HiRDB has not started.

KAPM06521-E

The RD area for aa...aa has not been set up.

aa...aa: Product name

KAPM06522-E

There is no RD area in the system.

KAPM06523-I

The hcndsdbmove command has started.

KAPM06524-I

Initialization for moving the database is being performed.

KAPM06525-I

The data for aa...aa will now be moved.

aa...aa: Product name

KAPM06526-I

Processing to import data has started.

KAPM06527-I

The table definitions of the database are being imported.

KAPM06528-I

The data is being imported.

KAPM06529-I

The database procedures are being imported.

KAPM06530-I

Processing to import data has ended.

KAPM06531-I

Processing to export data has started.

KAPM06532-I

The table definitions of the database are being exported.

KAPM06533-I

The data is being exported.

KAPM06534-I

The database procedures are being exported.

KAPM06535-I

Processing to export data has ended.

KAPM06536-I

The data is being imported. (progress = aa...aa/bb...bb)

aa...aa: The number of the result data
bb...bb: The number of the target data

KAPM06537-I

The data is being exported. (progress = aa...aa/bb...bb)

aa...aa: The number of the result data
bb...bb: The number of the target data

KAPM06540-I

The view is being imported.

KAPM06541-I

The view is being exported.

KAPM06542-E

The data to be imported to aa...aa is not in the directory in the datapath option.

aa...aa: The name of the product where data imported is not found

KAPM06543-I

The database was exported successfully.

KAPM06544-E

An attempt to export the database has failed.

KAPM06545-I

The database was imported successfully.

KAPM06546-E

An attempt to import the database has failed.

KAPM06548-E

An attempt to delete a table definition from the database failed.

KAPM06549-E

An attempt to defragment the database failed.

KAPM06570-E

An option is invalid.

KAPM06571-E

The specified options are insufficient.

KAPM06572-E

The specified option value is invalid.

KAPM06573-E

The specified directory name already exists as a file name. (file name = aa...aa)

aa...aa: File name

KAPM06574-E

The directory name exceeds aa...aa characters.

aa...aa: The number of characters of the directory name

KAPM06575-E

The same value cannot be specified for the databasepath and exportpath parameters.

KAPM06576-E

An attempt to acquire the key name has failed.

KAPM06577-E

An attempt to acquire a value has failed.

KAPM06578-E

The cluster settings file was not found.

KAPM06579-E

The value of hcnds.home cannot be acquired.

KAPM06580-E

An attempt to clear a DBMS environment variable has failed.

KAPM06581-E

The DBMS has not stopped.

KAPM06582-E

An attempt to load the file has failed. (file = aa...aa)

aa...aa: File name

KAPM06583-E

An attempt to write to the file has failed. (file = aa...aa)

aa...aa: File name

KAPM06584-I

Processing to export data was successful.

KAPM06585-I

Re-creation of the database was successful.

KAPM06586-I

Processing to import data was successful.

KAPM06587-E

An attempt to export data has failed.

KAPM06588-E

An attempt to re-create the database has failed.

KAPM06589-E

An attempt to import data has failed.

KAPM06590-I

Processing ended normally.

KAPM06591-E

The data to be imported was not found in the specified directory.

KAPM06592-E

The data to be imported to aa...aa is not in the directory specified in the exportpath option.

aa...aa: The name of the product where data imported is not found

KAPM06593-I

aa...aa

aa...aa: Standard error output

KAPM06600-I

Entered parameter: aa...aa

aa...aa: Entered parameter

KAPM06601-I

User ID = aa...aa, application = bb...bb, permissions = cc...cc

aa...aa: Target user ID

bb...bb: Target application

cc...cc: Permissions set for a target user

KAPM06602-E

A specified parameter is invalid.

KAPM06603-E

An attempt to read the file has failed. (file = aa...aa)

aa...aa: The absolute path of the file

KAPM06604-E

The database has not started.

KAPM06605-E

An attempt to communicate with the server or database has failed.

KAPM06606-E

An error has occurred.

KAPM06609-I

The command ended normally.

KAPM06610-E

An option specification is invalid.

KAPM06611-E

An attempt to load the hssso.conf file has failed.

KAPM06612-E

Authentication has failed.

KAPM06613-W

Authentication data was not found in the repository.

KAPM06614-E

An attempt to communicate with SSO Server has failed.

KAPM06640-E

A fatal error occurred during processing.

KAPM06641-E

An internal error occurred.

KAPM06642-E

An error occurred during file input.

KAPM06643-E

An attempt to acquire file information has failed.

KAPM06644-E

An option is invalid. Code=[aa...aa], Data=[bb...bb]

aa...aa: Code indicating the occurrence location

bb...bb: Occured options and values

KAPM06645-I

hcmsdbpath [aa...aa]{,[bb...bb],.....[.....]}

aa...aa: Command line argument

bb...bb: Command line argument

KAPM06654-E

The specified backup directory is invalid. Path=[aa...aa], Code=[bb...bb]

aa...aa: Backup directory path

bb...bb: Code indicating the occurrence location

KAPM06659-E

aa...aa

aa...aa: Cause that has occurred and the exception object name, or back trace of the exception object

KAPM06665-I

The DBMS has started.

KAPM06666-I

The DBMS has stopped.

KAPM06667-I

aa...aa processing has started.

aa...aa: Processing name

KAPM06668-I

aa...aa processing has finished.

aa...aa: Processing name

KAPM06669-E

An argument contains a null value.

KAPM06670-E

An exception occurred.

KAPM06671-E

The specified value is invalid. (value = aa...aa)

aa...aa: Value

KAPM06672-E

Execution of the command aa...aa has failed.

aa...aa: Command name

KAPM06673-E

The DBMS did not start.

KAPM06674-E

The DBMS did not stop.

KAPM06675-I

The DBMS has not been set up

KAPM06676-I

The database of the specified product has not been set up.

KAPM06679-E

The value of hcnds.home cannot be acquired.

KAPM06683-E

"aa...aa": "bb...bb"

aa...aa: Command name

bb...bb: Message

KAPM06689-E

Processing has terminated abnormally. (processing name = aa...aa)

aa...aa: Processing name

KAPM06690-E

The file hcndsdbsetRDArea.ini does not exist.

KAPM06691-E

An error occurred during file I/O processing.

KAPM06700-I

The hcmdsscmquery command started.

KAPM06701-I

The hcmdsscmquery command ended successfully.

KAPM06702-E

The hcmdsscmquery command failed.

KAPM06705-E

Acquisition of the installation path failed.

KAPM06706-E

One or more options are invalid.

KAPM06707-E

Allocation of memory to store the log file path failed.

KAPM06708-E

Log initialization failed.

KAPM06709-E

An internal error occurred.

KAPM06719-E

The service status is currently unknown.

KAPM06720-E

A fatal error occurred.

KAPM06721-I

The hcmdsscmquery command ended.

KAPM06722-E

An error occurred in the Win32 API.. (API name = aa...aa, error code = bb...bb)

aa...aa: API name

bb...bb: Error code

KAPM06753-E

A property value in the installation information file is invalid. (aa...aa)

aa...aa: Property name

KAPM06762-I

The hcnds64ssltool command has started.

KAPM06763-I

The hcnds64ssltool command has ended.

KAPM06764-I

The hcnds64ssltool command ended successfully.

KAPM06765-E

An option is invalid.

KAPM06766-E

Creation of a private key failed.

KAPM06767-E

Creation of a self-signed certificate failed.

KAPM06768-E

Creation of a CSR failed.

KAPM06769-E

Creation of a certificate content file failed.

KAPM06770-E

An internal error occurred.

KAPM06771-W

Failed to delete a key store.

KAPM06772-E

No value has been specified for an option.

KAPM06773-E

A fatal error occurred.

KAPM06774-E

The hcnds.home value cannot be acquired.

KAPM06775-E

Analysis of binary data failed.(position = aa...aa,part = bb...bb)

aa...aa: Position

bb...bb: Part

KAPM06776-E

The keytool command failed.

KAPM06777-I

The keytool command has ended.(Return code = aa...aa)

aa...aa: Return code

KAPM06778-E

A specified path already exists as a file or directory. (path = aa...aa)

aa...aa: path

KAPM06780-I

Enter Server Name [default=aa...aa]:

aa...aa: Host name

KAPM06781-I

Enter Organizational Unit:

KAPM06782-I

Enter Organization Name [default=aa...aa]:

aa...aa: Host name

KAPM06783-I

Enter your City or Locality:

KAPM06784-I

Enter your State or Province:

KAPM06785-I

Enter your two-character country-code:

KAPM06786-I

Is aa...aa correct? (y/n) [default=n]:

aa...aa: Distinguished name

KAPM06787-E

Creation of a distinguished name failed.

KAPM06788-W

The host name cannot be acquired.

KAPM06790-E

An IllegalArgumentException occurred.

KAPM06791-E

An IOException occurred.

KAPM06792-E

A HBaseDeleteFileException occurred.

KAPM06793-E

An exception occurred.

KAPM06794-E

A KeyStoreException occurred.

KAPM06795-E

A CertificateException occurred.

KAPM06796-E

An UnrecoverableKeyException occurred.

KAPM06797-E

A NoSuchAlgorithmException occurred.

KAPM06799-I

aa...aa

aa...aa: Information for debugging

KAPM06800-I

The trigger is being imported.

KAPM06801-I

The trigger is being exported.

KAPM06810-I

aa...aa

aa...aa: Standard error output

KAPM06811-I

hcnds64authmove [aa...aa]{, [bb...bb],.....[.....]}

aa...aa: Command line argument

bb...bb: Command line argument

KAPM06820-E

Execution of the cjdeleteapp command failed.

KAPM06821-E

Execution of the cjimportapp command failed.

KAPM06822-E

Execution of the cjstartapp command failed.

KAPM06823-I

The netstat command will now be executed.

KAPM06824-I

The ps command will now be executed.

KAPM06825-I

The tasklist command will now be executed.

KAPM06826-I

These are the execution results of the cjstartsv command.

KAPM06827-E

Execution of the cjstartsv command failed.

KAPM06901-I

The service was started successfully.

KAPM06902-I

Processing to stop the service has started.

KAPM06903-I

The service was stopped successfully.

KAPM06904-I

Processing to start the DBMS has started.

KAPM06905-I

The DBMS was started successfully.

KAPM06906-I

Processing to stop the DBMS has started.

KAPM06907-I

The DBMS was stopped successfully.

KAPM06908-E

An attempt to start the service has failed.

KAPM06909-E

An attempt to stop the service has failed.

KAPM06910-E

An attempt to start the DBMS has failed.

KAPM06911-E

An attempt to stop the DBMS has failed.

KAPM06912-E

An attempt to start the service or the DBMS has failed.

KAPM06913-E

An attempt to stop the service or the DBMS has failed.

KAPM06914-E

The database has not been initialized.

KAPM06915-E

An attempt to release the connection of the connection pool has failed.

KAPM06916-I

hcmds64dbclustersetup [aa...aa]{,[bb...bb],.....[.....]}

aa...aa: Command line argument

bb...bb: Command line argument

KAPM06917-E

Copying of the unload function file failed.

KAPM06920-W

Log initialization failed.

KAPM06921-E

A memory allocation error occurred.

KAPM06922-E

The aa...aa command will stop because setting an environment variable failed. (details = bb...bb)

aa...aa: Command name

bb...bb: Details

KAPM06923-E

The aa...aa command will stop because internal processing failed. (details = bb...bb)

aa...aa: Command name

bb...bb: Details

KAPM06924-E

An error occurred in an internal function. (function = aa...aa, error code = bb...bb)

aa...aa: Function name

bb...bb: Error code

KAPM06925-E

A system environment variable is invalid.

KAPM06926-E

The aa...aa command will stop because setting an environment variable failed. (details = bb...bb)

aa...aa: Command name

bb...bb: Details

KAPM06927-E

The aa...aa command will stop because internal processing failed. (details = bb...bb)

aa...aa: Command name

bb...bb: Details

KAPM06932-W

Failed to initialize a log.

KAPM06933-E

An error occurred in an internal function. (function called = aa...aa, function executed = bb...bb, notes = cc...cc, error code = dd...dd)

aa...aa: Name of the function called

bb...bb: Name of the function executed

cc...cc: Notes

dd...dd: Error code

KAPM06934-E

Failed to create a mutex object.

KAPM06935-E

Failed to release a mutex object.

KAPM06936-E

Failed to lock a file.

KAPM06937-E

Failed to release a file lock.

KAPM06938-E

Failed to open a file. (file path = aa...aa)

aa...aa: File path

KAPM06939-E

Failed to close a file. (file path = aa...aa)

aa...aa: File path

KAPM06940-E

Failed to set permissions for a file. (file path = aa...aa)

aa...aa: File path

KAPM06941-E

Failed to acquire a file descriptor. (file path = aa...aa)

aa...aa: File path

KAPM06942-E

Failed to acquire a mutex object.

KAPM07000-W

Update the current JavaScript to the latest version.

KAPM07001-E

The specified user cannot log in because the user does not have permission to access the manager screen.

KAPM07002-E

The application is not registered on the HSSO Server.

KAPM07003-E

The user ID and/or password are not correct.

KAPM07004-E

The executing user does not have permission to execute the method.

KAPM07005-E

The specified user does not exist.

KAPM07006-E

The specified user already exists.

KAPM07007-E

This user has already been deleted.

KAPM07008-E

A problem occurred during processing.

KAPM07009-E

A communication error occurred during processing.

KAPM07010-E

Null is specified for the argument.

KAPM07011-E

A fatal error occurred during processing.

KAPM07012-E

The specified group does not exist.

KAPM07013-E

An attempt to register user information has failed, because a problem occurred during registration processing.

KAPM07014-E

An attempt to update user information has failed, because a problem occurred during update processing.

KAPM07015-E

An attempt to delete user information has failed, because a problem occurred during deletion processing.

KAPM07016-E

An attempt to change the password has failed, because a problem occurred while processing the change.

KAPM07017-E

A problem occurred during an attempt to acquire user information.

KAPM07018-E

A problem occurred during an attempt to acquire group information.

KAPM07019-I

The user information was successfully deleted.

KAPM07020-I

User ID aa...aa will be deleted.

If deleted, this user will not be able to log on. Is this OK?

aa...aa: User ID

KAPM07021-E

A problem occurred during an attempt to acquire HiCommand application information.

KAPM07022-E

An attempt to update HiCommand application information has failed, because a problem occurred during update processing.

KAPM07023-I

HiCommand application information will now be updated.

KAPM07024-E

A problem occurred during an attempt to acquire user application information.

KAPM07025-E

An attempt to update user application information has failed, because a problem occurred during update processing.

KAPM07026-I

User application information will now be updated.

KAPM07027-W

The specified user application name already exists. application name = aa...aa

aa...aa: Application name

KAPM07028-E

Input Item:aa...aa

This entry is required. Enter a value.

aa...aa: Input Item

KAPM07029-E

Input Item:aa...aa

A character that cannot be used for this entry has been entered.

aa...aa: Input Item

KAPM07030-E

Input Item:aa...aa

The number of characters in this entry exceeds the maximum.

aa...aa: Input Item

KAPM07031-E

The password entries do not match.

KAPM07032-E

Input Item:aa...aa

Enter from 4 to 255 characters for this entry.

aa...aa: Input Item

KAPM07033-W

The specified URL does not exist in the class. URL = aa...aa

aa...aa: URL

KAPM07034-E

IllegalDataException occurred. (details = aa...aa)

aa...aa: Details

KAPM07035-E

The format of the specified URL is invalid. URL = aa...aa

aa...aa: URL

KAPM07036-I

The password will change. Is this OK?

KAPM07037-I

The password will change. Is this OK?

After the password changes, you must log in again.

KAPM07038-E

Input Item:aa...aa

The same value cannot be specified into these input items.

aa...aa: Input Item

KAPM07230-I

The user was registered successfully. (operator = aa...aa, user ID = bb...bb, function = cc...cc)

KAPM07231-I

The user was deleted successfully. (operator = aa...aa, user ID = bb...bb, function = cc...cc)

KAPM07232-I

The password was changed successfully. (operator = aa...aa, user ID = bb...bb, function = cc...cc)

KAPM07233-I

The user information was modified successfully. (operator = aa...aa, user ID = bb...bb, function = cc...cc)

KAPM07235-I

The user was locked successfully. (operator = aa...aa, user ID = bb...bb, function = cc...cc)

aa...aa: Operator name

bb...bb: User ID

cc...cc: Function name

KAPM07236-I

The user was unlocked successfully. (operator = aa...aa, user ID = bb...bb, function = cc...cc)

aa...aa: Operator name

bb...bb: User ID

cc...cc: Function name

KAPM07237-E

The specified password does not satisfy the entry conditions. (operator = aa...aa, user ID = bb...bb, function = cc...cc)

aa...aa: Operator name

bb...bb: User ID

cc...cc: Function name

KAPM07238-E

The specified email is too long. (operator = aa...aa, user ID = bb...bb, function = cc...cc)

aa...aa: Operator name

bb...bb: User ID

cc...cc: Function name

KAPM07239-E

The old password is incorrect. (operator = aa...aa, user ID = bb...bb, function = cc...cc)

aa...aa: Operator name

bb...bb: User ID

cc...cc: Function name

KAPM07240-E

An attempt to execute the aa...aa operation has failed. (operator = bb...bb, user ID = cc...cc, function = dd...dd)

aa...aa: Operation name

bb...bb: Operator name

cc...cc: User ID

dd...dd: Function name

KAPM07241-I

A user was registered successfully. (user ID = aa...aa)

aa...aa: User ID

KAPM07242-E

Registration of a user has failed. (user ID = aa...aa)

aa...aa: User ID

KAPM07243-I

The user information was updated successfully. (user ID = aa...aa)

aa...aa: User ID

KAPM07244-E

An attempt to update the user information has failed. (user ID = aa...aa)

aa...aa: User ID

KAPM07245-I

A user was deleted successfully. (user ID = aa...aa)

aa...aa: User ID

KAPM07246-E

Deletion of a user has failed. (user ID = aa...aa)

aa...aa: User ID

KAPM07247-I

The authorization group was added successfully. (operator = aa...aa, distinguished name = bb...bb, function = cc...cc)

aa...aa: Operator name

bb...bb: Distinguished name

cc...cc: Function name

KAPM07248-E

An attempt to execute the aa...aa operation has failed. (operator = bb...bb, distinguished name = cc...cc, function = dd...dd)

aa...aa: Operation name

bb...bb: Operator name

cc...cc: Distinguished name

dd...dd: Function name

KAPM07249-I

The authorization group was deleted successfully. (operator = aa...aa, distinguished name = bb...bb, function = cc...cc)

aa...aa: Operator name
bb...bb: Distinguished name
cc...cc: Function name

KAPM07250-I

The permissions were changed successfully. (operator = aa...aa, distinguished name = bb...bb, permissions = cc...cc)

aa...aa: Operator name
bb...bb: Distinguished name
cc...cc: permissions after the change

KAPM07251-I

The authorization group was registered successfully. (distinguished name = aa...aa)

aa...aa: Distinguished name

KAPM07252-E

An attempt to register the authorization group has failed. (distinguished name = aa...aa)

aa...aa: Distinguished name

KAPM07253-I

The authorization group was deleted successfully. (distinguished name = aa...aa)

aa...aa: Distinguished name

KAPM07254-E

An attempt to delete the authorization group has failed. (distinguished name = aa...aa)

aa...aa: Distinguished name

KAPM07255-I

The authorization group's permissions were changed successfully. (distinguished name = aa...aa)

aa...aa: Distinguished name

KAPM07256-E

An attempt to change the authorization group's permissions has failed. (distinguished name = aa...aa)

aa...aa: Distinguished name

KAPM07257-I

The resource group was successfully registered. (resource group name = aa...aa, device type = bb...bb, device number = cc...cc)

aa...aa: Resource group name

bb...bb: Device type

cc...cc: Device number

KAPM07258-E

Registration of the resource group failed. (resource group name = aa...aa, device type = bb...bb, device number = cc...cc)

aa...aa: Resource group name

bb...bb: Device type

cc...cc: Device number

KAPM07259-I

The resource group was successfully deleted. (resource group name = aa...aa, device type = bb...bb, device number = cc...cc)

aa...aa: Resource group name

bb...bb: Device type

cc...cc: Device number

KAPM07260-E

Deletion of the resource group failed. (resource group name = aa...aa, device type = bb...bb, device number = cc...cc)

aa...aa: Resource group name

bb...bb: Device type

cc...cc: Device number

KAPM07261-I

The resource group was successfully updated. (resource group name = aa...aa, device type = bb...bb, device number = cc...cc)

aa...aa: Resource group name

bb...bb: Device type

cc...cc: Device number

KAPM07262-E

Updating of the resource group failed. (resource group name = aa...aa, device type = bb...bb, device number = cc...cc)

aa...aa: Resource group name

bb...bb: Device type

cc...cc: Device number

KAPM07263-I

The user group was successfully registered. (resource group name = aa...aa, device type = bb...bb, device number = cc...cc)

aa...aa: User group name

bb...bb: Device type

cc...cc: Device number

KAPM07264-E

Registration of the user group failed. (user group name = aa...aa, device type = bb...bb, device number = cc...cc)

aa...aa: User group name

bb...bb: Device type

cc...cc: Device number

KAPM07265-I

The user group was successfully deleted. (user group name = aa...aa, device type = bb...bb, device number = cc...cc)

aa...aa: User group name

bb...bb: Device type

cc...cc: Device number

KAPM07266-E

Deletion of the user group failed. (user group name = aa...aa, device type = bb...bb, device number = cc...cc)

aa...aa: User group name

bb...bb: Device type

cc...cc: Device number

KAPM07267-I

The user group was successfully updated. (user group name = aa...aa, device type = bb...bb, device number = cc...cc)

aa...aa: User group name

bb...bb: Device type

cc...cc: Device number

KAPM07268-E

Updating of the user group failed. (user group name = aa...aa, device type = bb...bb, device number = cc...cc)

aa...aa: User group name

bb...bb: Device type

cc...cc: Device number

KAPM07269-I

The role was successfully registered. (role name = aa...aa, device type = bb...bb, device number = cc...cc)

aa...aa: Role name

bb...bb: Device type

cc...cc: Device number

KAPM07270-E

Registration of the role failed. (role name = aa...aa, device type = bb...bb, device number = cc...cc)

aa...aa: Role name

bb...bb: Device type

cc...cc: Device number

KAPM07271-I

The role was successfully deleted. (role name = aa...aa, device type = bb...bb, device number = cc...cc)

aa...aa: Role name

bb...bb: Device type

cc...cc: Device number

KAPM07272-E

Deletion of the role failed. (role name = aa...aa, device type = bb...bb, device number = cc...cc)

aa...aa: Role name

bb...bb: Device type

cc...cc: Device number

KAPM07273-I

The role was successfully updated. (role name = aa...aa, device type = bb...bb, device number = cc...cc)

aa...aa: Role name

bb...bb: Device type

cc...cc: Device number

KAPM07274-E

Updating of the role failed. (role name = aa...aa, device type = bb...bb, device number = cc...cc)

aa...aa: Role name

bb...bb: Device type
cc...cc: Device number

KAPM07275-I

The user account was successfully assigned to the user group. (user group name = aa...aa, user ID = bb...bb)

aa...aa: User group name
bb...bb: User ID

KAPM07276-E

The user account failed to be assigned to the user group. (user group name = aa...aa, user ID = bb...bb)

aa...aa: User group name
bb...bb: User ID

KAPM07277-I

The permission was successfully assigned to the role. (role name = aa...aa, permission name = bb...bb)

aa...aa: Role name
bb...bb: Permission name

KAPM07278-E

The permission failed to be assigned to the role. (role name = aa...aa, permission name = bb...bb)

aa...aa: Role name
bb...bb: Permission name

KAPM07279-I

Assignment processing was successful for a user group and an external authentication group, a resource group, and a role. (user group name and external authentication group name = aa...aa, resource group name = bb...bb, role name = cc...cc)

aa...aa: User group name and external authentication group name
bb...bb: Resource group name

cc...cc: Role name

KAPM07280-E

Assignment processing failed for a user group and an external authentication group, a resource group, and a role. (user group name and external authentication group name = aa...aa, resource group name = bb...bb, role name = cc...cc)

aa...aa: User group name and external authentication group name

bb...bb: Resource group name

cc...cc: Role name

KAPM07300-I

The hcmdshpsimcert command has started.

KAPM07301-I

The hcmdshpsimcert command has terminated.

KAPM07302-I

The hcmdshpsimcert command was successful.

KAPM07303-E

The hcmdshpsimcert command has failed.

KAPM07306-E

The value of hcnds.home cannot be acquired.

KAPM07307-E

An option is invalid.

KAPM07308-E

An exception occurred.

KAPM07309-E

An internal error occurred.

KAPM07310-I

Importing of the certificate has started.

KAPM07311-I

Importing of the certificate has ended.

KAPM07312-E

The host name or the port number is invalid.

KAPM07313-E

An attempt to communicate with the HPSIM server has failed.

KAPM07314-E

The format of the certificate acquired from the HPSIM server is invalid.

KAPM07315-E

An attempt to load the keystore file has failed.

KAPM07316-W

The certificate of the specified host is already registered.

KAPM07317-I

The following certificate was imported into the keystore.

KAPM07318-E

An attempt to output the keystore file has failed.

KAPM07319-E

An attempt to input the keystore file has failed.

KAPM07320-I

Host name: "aa...aa"

aa...aa: Host name

KAPM07321-I

Processing to display the certificate list has started.

KAPM07322-I

Processing to display the certificate list has ended.

KAPM07323-I

The certificate is not stored.

KAPM07324-E

A problem occurred while displaying the certificate list.

KAPM07325-I

Deletion of the certificate has started.

KAPM07326-I

The certificate has been deleted.

KAPM07327-I

The certificate for the aa...aa host was deleted.

aa...aa: Host name

KAPM07328-W

The certificate for the aa...aa host is not registered.

aa...aa: Host name

KAPM07329-E

An attempt to delete the certificate has failed.

KAPM07330-E

An attempt to renew the keystore has failed.

KAPM07342-E

An exception occurred.

KAPM07343-E

An internal error occurred.

KAPM07344-I

GET processing for "/Proxy/Getkey" has started.

KAPM07345-I

GET processing for "/Proxy/Getkey" has ended.

KAPM07346-I

The request from "aa...aa" was accepted.

aa...aa: Host name

KAPM07347-I

The one-time key was issued. (key = aa...aa)

aa...aa: One-time key

KAPM07348-E

An attempt to issue the one-time key has failed.

KAPM07349-E

An attempt to create the one-time key failed because the number of keys had exceeded the maximum.

KAPM07350-W

The one-time key does not exist. (key = aa...aa)

aa...aa: One-time key

KAPM07351-W

The expiration date of the one-time key has passed. (key = aa...aa)

aa...aa: One-time key

KAPM07352-I

The one-time key was deleted normally. (key = aa...aa)

aa...aa: One-time key

KAPM07355-I

The one-time key that passed the expiration date was deleted. (key = aa...aa)

aa...aa: One-time key

KAPM07356-I

GET processing for "/Proxy/SSO" has started.

KAPM07357-I

GET processing for "/Proxy/SSO" has ended.

KAPM07358-E

An error occurred during a parameter check.

KAPM07359-I

Parameter output: "aa...aa" = "bb...bb"

aa...aa: Parameter name

bb...bb: Value

KAPM07360-E

An attempt to load the keystore has failed.

KAPM07363-I

The host name is valid.

KAPM07364-E

The host name is invalid.

KAPM07367-I

The one-time key is valid.

KAPM07368-W

The one-time key is invalid.

KAPM07371-I

Verification of the request parameter was successful.

KAPM07372-E

An attempt to verify the request parameter has failed.

KAPM07375-I

The URL is a normal value.

KAPM07376-E

The URL is an invalid value.

KAPM07377-E

An attempt to convert the aa...aa permission has failed.

aa...aa: Permission name

KAPM07378-I

A redirection to "aa...aa" will be performed.

aa...aa: Redirection URL

KAPM07379-E

An attempt to load the keystore file has failed.

KAPM07380-I

The certificate of aa...aa has been imported.

aa...aa: Alias name

KAPM07381-E

The certificate of aa...aa has not been imported.

aa...aa: Alias name

KAPM07382-E

A server problem occurred.

KAPM07383-I

Data verification has started.

KAPM07384-I

Data verification has ended.

KAPM07385-E

An invalid character string was specified for the token.

KAPM07386-E

"SHA1with RSA" is not supported.

KAPM07387-E

The certificate format is invalid.

KAPM07388-E

The signature object has not been initialized.

KAPM07389-E

"US-ASCII" is not supported.

KAPM07390-I

Generation of the HSSO token has started.

KAPM07391-I

Generation of the HSSO token has ended.

KAPM07392-E

The permission conversion definition file was not found.

KAPM07393-E

An attempt to load the permission conversion definition file has failed.

KAPM07400-E

The definition file was not found.

KAPM07401-I

Generation of the X509 certificate object has started.

KAPM07402-I

Generation of the X509 certificate object has ended.

KAPM07403-E

The specified port number is invalid.

KAPM07404-E

The host name is invalid.

KAPM07405-E

An attempt to communicate with the HPSIM server has failed.

KAPM07406-E

The format of the certificate acquired from HPSIM is invalid.

KAPM07407-E

An attempt to output the keystore file has failed.

KAPM07410-I

Authentication succeeded.

KAPM07411-W

Authentication failed.

KAPM07420-E

Null is specified for the argument. (aa...aa)

aa...aa: Argument

KAPM07421-E

A specified value is invalid. (aa...aa, bb...bb)

aa...aa: Parameter name

bb...bb: Value

KAPM07422-E

An exception occurred.

KAPM07423-E

The domain name is invalid.

KAPM07424-E

The user name is invalid.

KAPM07430-E

Authentication failed.

KAPM08001-E

A fatal error occurred during processing.

KAPM08002-E

Illegal parameters have been specified to create HSSO Context.

KAPM08003-E

A CIMException was generated during Console screen display processing.

KAPM08004-E

A CIMRepositoryException was generated during menu bar display processing.

KAPM08005-E

A CIMProviderException was generated during menu bar display processing.

KAPM08006-E

A NoSuchElementException was generated during menu bar display processing.

KAPM08007-E

A CIMException was generated during menu bar display processing.

KAPM08008-E

An error occurred on the HSSO Server.

KAPM08009-I

The logout processing finished. (session ID = aa...aa)

aa...aa: Session ID

KAPM08010-E

An internal error occurred.

KAPM08011-E

Your session is invalid.

KAPM08013-E

A frame-enabled browser is required.

KAPM08014-I

Now loading...

KAPM08015-E

The registered data in the common repository is invalid.(aa...aa)

aa...aa: Class name

KAPM08016-E

The registered data in the common repository is invalid.

KAPM08017-E

The registered data in the common repository is invalid.

KAPM08018-E

The token is invalid.

KAPM08019-E

An error occurred on the SSO Server.

KAPM08020-E

An attempt to communicate with the SSO server has failed.

KAPM08021-E

The DBMS is stopped.

KAPM08022-E

The Common Component database is blocked.

KAPM08100-E

Null is specified for the argument.

KAPM08101-E

The specified node was not found. key=(aa...aa)

aa...aa: Key to node

KAPM08102-E

The object tree has not been created.

KAPM08103-E

An attempt to create the object tree has failed.

KAPM08104-E

An attempt to add a child node to the object tree has failed. (aa...aa)

aa...aa: Key to node

KAPM08105-E

The specified node has already been registered. key=(aa...aa)

aa...aa: Key to node

KAPM08106-E

The tree information cannot be acquired. (aa...aa)

aa...aa: Key to node

KAPM08107-E

The node information is invalid. (aa...aa, bb...bb)

aa...aa: Parameter name

bb...bb: Acquired value

KAPM08108-E

An invalid argument was specified during node creation. (aa...aa, bb...bb)

aa...aa: Parameter name

bb...bb: Acquired value

KAPM08109-E

The tree information is invalid. (aa...aa, bb...bb)

aa...aa: Key to root node (in the database)

bb...bb: Key to root node (in the memory)

KAPM08110-E

The node array cannot be acquired. (aa...aa, bb...bb)

aa...aa: Parameter name

bb...bb: Acquired value

KAPM08111-E

The hierarchy number of the node array cannot be acquired. (aa...aa, bb...bb)

aa...aa: Parameter name

bb...bb: Acquired value

KAPM08112-E

The node array is invalid. (aa...aa, bb...bb)

aa...aa: Parameter name

bb...bb: Acquired value

KAPM08113-E

The hierarchy number of the node array is invalid. (aa...aa)

aa...aa: The hierarchy number of the node array

KAPM08114-W

An invalid argument was specified during node creation. (aa...aa, bb...bb)

aa...aa: Parameter name

bb...bb: Acquired value

KAPM08115-E

An internal error occurred.

KAPM08116-E

A value that exceeds the maximum value has been specified. (aa...aa, bb...bb)

aa...aa: Parameter name

bb...bb: Value

KAPM08150-E

The request is invalid. (aa...aa, bb...bb)

aa...aa: Key

bb...bb: Value

KAPM08152-E

The request is invalid. (aa...aa)

aa...aa: Key

KAPM08154-E

An attempt to display the object tree has failed.

KAPM08160-E

The data registered in the common repository is invalid. (aa...aa, bb...bb)

aa...aa: Key

bb...bb: Value

KAPM08200-E

The request parameter required for the display of the Application Bar area is invalid.

KAPM08201-E

An internal error occurred.

If you click the "Refresh Tree" button, the initial object tree will be displayed. If you cannot display the tree, log out, and then log in again.

KAPM08202-E

The number of elements in the array does not match the other arrays.

KAPM08203-E

The request parameter required for the display of the Summary area is invalid.

KAPM08302-E

An error occurred while acquiring the resource bundle.

KAPM08303-E

An error occurred while reading the resource file.

KAPM08304-E

An attempt to access the resource file has failed.

KAPM08308-E

An internal error occurred.

KAPM08309-E

The URL object cannot be created.

KAPM08311-E

An attempt to access the file has failed.

KAPM08330-E

The system environment is invalid.

KAPM08402-E

An unusable HTML tag is included.

KAPM08403-E

The warning banner message exceeded 1000 characters.

KAPM08404-E

An attempt to register the warning banner message has failed.

KAPM08405-E

An attempt to delete the warning banner message has failed.

KAPM08406-E

The specified file name already exists as a directory name. (directory name = aa...aa)

aa...aa: Directory name

KAPM08407-E

The specified directory name already exists as a file name. (file name = aa...aa)

aa...aa: File name

KAPM08408-E

The directory does not exist. (directory name = aa...aa)

aa...aa: Directory name

KAPM08409-E

An attempt to delete the warning banner message has failed.

KAPM08410-E

The specified node is invalid. (node name = aa...aa)

aa...aa: Node name

KAPM08411-E

hcnds.home is not set in the Java system properties.

KAPM08412-E

The bannertaglist.conf file does not exist.

KAPM08431-E

An attempt to register the security settings information has failed.

KAPM08910-E

An exception occurred.

KAPM08911-E

A fatal error occurred during processing.

KAPM08912-E

Null is specified for the argument.(aa...aa)

aa...aa: Argument

KAPM08913-E

A value is invalid.(aa...aa, bb...bb)

aa...aa: Key

bb...bb: Value

KAPM08914-E

The request is invalid.

KAPM08915-E

There is an invalid statement in the configuration file of HBase Storage Mgmt Web Service.

KAPM08916-I

Succeeded in starting of service.

KAPM08917-I

Succeeded in stopping of service.

KAPM08918-E

Failed to start service.

KAPM08919-E

Failed to stop service.

KAPM08920-E

The value of hcnds.home cannot be acquired.

KAPM08921-E

An attempt to acquire a value has failed.

KAPM08922-E

Communication with the HBase Storage Mgmt Web Service failed.

KAPM08923-E

Requests containing QueryString are not accepted.

KAPM08980-E

An attempt to acquire RequestDispatcher has failed.

KAPM08999-E

aa...aa

aa...aa: Cause that has occurred and the exception object name or back trace of the exception object

KAPM09062-E

An internal error occurred.

KAPM09064-E

No registered information exists.

KAPM09065-E

The file format is invalid.

KAPM09066-E

An error occurred during file I/O processing.

KAPM09067-E

A server has not been registered.

KAPM09068-E

An attempt to read a file has failed.

KAPM09069-E

An attempt to output a file has failed.

KAPM09070-E

An argument contains a null value.

KAPM09090-E

hcnds.home is not specified in the Java system properties.

KAPM09091-E

An error occurred during reading of a library. library path = aa...aa

aa...aa: Library path

KAPM09092-E

A timeout was generated during lock acquisition.

KAPM09093-E

The acquisition of the lock has failed. error code = aa...aa

aa...aa: Error code

KAPM09094-E

The release of the lock has failed. error code = aa...aa

aa...aa: Error code

KAPM09100-I

Enter a value for the option. (option name = aa...aa)

aa...aa: Option name

KAPM09101-I

For confirmation, re-enter the value of the aa...aa option.

aa...aa: Option name

KAPM09102-E

hcnds.home is not set in the Java system properties.

KAPM09103-E

An error occurred during the reading of the library. (library path = aa...aa)

aa...aa: Library path

KAPM09104-E

The value entered the first time does not match the value entered the second time.

KAPM09110-E

A specified argument is invalid.

KAPM09111-E

An error occurred in the API. (API name = aa...aa, error code = bb...bb)

aa...aa: API name

bb...bb: Error code

KAPM09200-E

The system environment is incorrect.

KAPM09210-E

hcnds.home is not specified in the Java system properties.

KAPM09211-E

An error occurred during reading of a library. library path = aa...aa

aa...aa: library path

KAPM09212-E

An attempt to execute JNI has failed. function = aa...aa, error code = bb...bb

aa...aa: Function

bb...bb: Error code

KAPM09213-E

A specified argument is invalid.

KAPM10009-E

The specified authorization group already exists. (distinguished name = aa...aa)

aa...aa: Distinguished name

KAPM10011-E

Communication with the external authentication server has failed. (domain name = aa...aa)

aa...aa: Domain name

KAPM10012-E

The information search user is not registered. (domain name = aa...aa)

aa...aa: Domain name

KAPM10013-E

An attempt to search for the specified distinguished name has failed. (distinguished name = aa...aa)

aa...aa: Distinguished name

KAPM10014-E

DNS communication with the external authentication server has failed. (domain name = aa...aa)

aa...aa: Domain name

KAPM10015-E

The SRV record in the LDAP server is not registered. (distinguished name = aa...aa, domain name = bb...bb)

aa...aa: Distinguished name

bb...bb: Domain name

KAPM10016-E

A DNS error has occurred. (distinguished name = aa...aa, domain name = bb...bb)

aa...aa: Distinguished name

bb...bb: Domain name

KAPM10017-W

The length of the specified distinguished name is invalid. (line number = aa...aa, distinguished name = bb...bb)

aa...aa: Line number

bb...bb: Distinguished name

KAPM10022-E

The SRV record of the Kerberos server is not registered in DNS. (distinguished name = aa...aa, domain name = bb...bb)

aa...aa: Distinguished name

bb...bb: Domain name

KAPM10029-E

The specified Distinguished Name cannot be found. (Distinguished Name = aa...aa)

aa...aa: Distinguished name

KAPM10030-W

The specified Distinguished Name already exists. (Distinguished Name = aa...aa)

aa...aa: Distinguished name

KAPM10031-E

The specified Distinguished Name already exists in another domain. (Distinguished Name = aa...aa)

aa...aa: Distinguished name

KAPM10032-E

The operation cannot proceed because the external authentication group linkage function is disabled.

KAPM10033-E

No groups that the user belongs to are registered. (user name = aa...aa)

aa...aa: User name

KAPM10034-E

No groups that the user belongs to exist. (user name = aa...aa)

aa...aa: User name

KAPM10035-E

The format of the specified Distinguished Name is invalid.(Distinguished Name = aa...aa)

aa...aa: Distinguished name

KAPM10036-E

No information regarding the specified group was found.

KAPM10037-I

Nest group information for the group. (group name = aa...aa)

aa...aa: Nest group name

KAPM10038-I

Nest group: aa...aa

aa...aa: Nest group name

KAPM10039-W

The group was not found. (group name = aa...aa)

aa...aa: Group name

KAPM10040-E

The thread was interrupted.

KAPM10041-E

The installed version of JP1/Base is not supported.

KAPM10042-E

JP1/Base initialization failed.

KAPM10043-E

An attempt to connect to JP1/Base failed.

KAPM10044-E

Authentication of the JP1 token failed. (JP1 token = aa...aa)

aa...aa: JP1 token

KAPM10045-E

An error occurred while linking to JP1/Base. (internal code = aa...aa)

aa...aa: Internal code

KAPM10046-E

An error occurred because the value is invalid. (value = aa...aa)

aa...aa: Value

KAPM10047-E

An error occurred because the virtual host does not exist. (virtual host = aa...aa)

aa...aa: Virtual host

KAPM10048-E

An error occurred because the virtual host definition is invalid. (virtual host = aa...aa)

aa...aa: Virtual host

KAPM10049-W

The value is invalid. (value = aa...aa)

aa...aa: Value

KAPM10050-E

Acquisition of the JP1/Base version failed.

KAPM10051-W

Valid suite product permissions were not allocated to the JP1 resource group. (JP1 resource group = aa...aa)

aa...aa: JP1 resource group

KAPM10052-E

Acquisition of the table failed. (table = aa...aa)

aa...aa: Table

KAPM10053-E

No authentication server is set up.

KAPM10054-E

Permissions are not assigned to the user. (user name = aa...aa)

aa...aa: User name

KAPM10055-E

Suite product permissions are not assigned to the user. (user name = aa...aa)

aa...aa: User name

KAPM10056-E

A buffer error occurred.

KAPM10057-W

The format of the value is invalid. (value = aa...aa)

aa...aa: Value

KAPM10058-W

The permissions do not correspond to the suite product permissions. (permissions = aa...aa)

aa...aa: Permissions

KAPM10059-W

The permissions could not be converted to suite product permissions. (permissions = aa...aa)

aa...aa: Permissions

KAPM10060-E

Loading of the library failed. (library = aa...aa)

aa...aa: Library

KAPM10061-E

hcnds.home is not set in the Java system properties.

KAPM10062-E

Acquisition of user permission information from JP1/Base failed.

KAPM10063-E

Preprocessing failed.

KAPM10064-E

JP1/Base initialization failed.

KAPM10065-E

Authentication of the JP1 token failed. (JP1 token = aa...aa)

aa...aa: JP1 token

KAPM10066-I

The external authentication server successfully authenticated the information. (user name = aa...aa, protocol = bb...bb)

aa...aa: User name

bb...bb: Protocol

KAPM10067-I

User permission information was successfully acquired from JP1/Base. (user name = aa...aa)

aa...aa: User name

KAPM10100-E

Authentication was canceled because a search user has not been registered. (domain name = aa...aa, host = bb...bb, port = cc...cc, protocol = dd...dd)

aa...aa: Domain name

bb...bb: Host name

cc...cc: Port number

dd...dd: Protocol

KAPM10101-E

Authentication was canceled because a setting in the configuration file for the external authentication server (exauth.properties) is invalid.

KAPM10102-I

The group information was acquired from the LDAP server. (domain name = aa...aa, host = bb...bb, port = cc...cc, protocol = dd...dd, basedn = ee...ee)

aa...aa: Domain name

bb...bb: Host name

cc...cc: Port number

dd...dd: Protocol

ee...ee: Base distinguished name

KAPM10103-E

Acquisition of group information failed. (userId = aa...aa, domain name = bb...bb, host = cc...cc, port = dd...dd, protocol = ee...ee, basedn = ff...ff)

aa...aa: User name

bb...bb: Domain name

cc...cc: Host name

dd...dd: Port number

ee...ee: Protocol

ff...ff: Base distinguished name

KAPM10104-E

Confirmation of the existence of a group failed because a setting in the configuration file for the external authentication server (exauth.properties) is invalid or a search user setting is invalid.

KAPM10105-E

A search user has not been registered. (domain name = aa...aa)

aa...aa: Domain name

KAPM10106-I

The existence of a group was successfully confirmed. (groupDN = aa...aa, domain name = bb...bb, host = cc...cc, port = dd...dd, protocol = ee...ee)

aa...aa: Group distinguished name

bb...bb: Domain name

cc...cc: Host name

dd...dd: Port number

ee...ee: Protocol

KAPM10112-I

Authentication by a search user was successful. (host=aa...aa, port=bb...bb,protocol=cc...cc)

aa...aa: Host name

bb...bb: Port number

cc...cc: Protocol

KAPM10114-E

Authentication stopped because a setting in the configuration file for the external authentication server (exauth.properties) or a search user setting is invalid.

KAPM10115-E

The Kerberos realm, KDC, or a search user definition is invalid. (realm name = aa...aa)

aa...aa: Realm name

KAPM10116-I

Communication with the directory server was successfully established. (host = aa...aa, port = bb...bb, protocol = cc...cc)

aa...aa: Host name

bb...bb: Port number

cc...cc: Protocol

KAPM10117-E

Communication with the directory server failed to be established. (host = aa...aa, port = bb...bb, protocol = cc...cc)

aa...aa: Host name

bb...bb: Port number

cc...cc: Protocol

KAPM10118-I

Communication with the RADIUS server was successfully established. (host = aa...aa, port = bb...bb, protocol = cc...cc)

aa...aa: Host name

bb...bb: Port number

cc...cc: Protocol

KAPM10119-E

Communication with the RADIUS server failed to be established. (host = aa...aa, port = bb...bb, protocol = cc...cc)

aa...aa: Host name

bb...bb: Port number

cc...cc: Protocol

KAPM10120-I

Communication with the Kerberos server was successfully established. (KDC = aa...aa)

aa...aa: KDC

KAPM10121-E

Communication with the Kerberos server failed to be established. (KDC = aa...aa)

aa...aa: KDC

KAPM10122-I

Communication with the DNS server was successfully established.

KAPM10123-E

Communication with the DNS server failed to be established.

KAPM10124-I

A TLS session with a directory server was successfully negotiated. (host = aa...aa, port = bb...bb, protocol = cc...cc)

aa...aa: Host name

bb...bb: Port number

cc...cc: Protocol

KAPM10125-E

A TLS session with a directory server failed to be negotiated. (host = aa...aa, port = bb...bb, protocol = cc...cc)

aa...aa: Host name

bb...bb: Port number

cc...cc: Protocol

KAPM10126-I

An information-search user was successfully authenticated by the directory server. (distinguished name = aa...aa, host = bb...bb, port = cc...cc, protocol = dd...dd)

aa...aa: Distinguished name

bb...bb: Host name

cc...cc: Port number

dd...dd: Protocol

KAPM10127-W

An information-search user failed to be authenticated by the directory server. (distinguished name = aa...aa, host = bb...bb, port = cc...cc, protocol = dd...dd)

aa...aa: Distinguished name

bb...bb: Host name

cc...cc: Port number

dd...dd: Protocol

KAPM10128-I

A user was successfully authenticated by the directory server. (user ID = aa...aa, host = bb...bb, port = cc...cc, protocol = dd...dd)

aa...aa: User ID

bb...bb: Host name

cc...cc: Port number

dd...dd: Protocol

KAPM10129-W

No users are registered on the directory server. (user ID = aa...aa, host = bb...bb, port = cc...cc, protocol = dd...dd)

aa...aa: User ID

bb...bb: Host name

cc...cc: Port number

dd...dd: Protocol

KAPM10130-W

A user failed to be authenticated by the directory server. (user ID = aa...aa, host = bb...bb, port = cc...cc, protocol = dd...dd)

aa...aa: User ID
bb...bb: Host name
cc...cc: Port number
dd...dd: Protocol

KAPM10131-I

A user was successfully authenticated by the RADIUS server. (user ID = aa...aa, host = bb...bb, port = cc...cc, protocol = dd...dd)

aa...aa: User ID
bb...bb: Host name
cc...cc: Port number
dd...dd: Protocol

KAPM10132-W

A user failed to be authenticated by the RADIUS server. (user ID = aa...aa, host = bb...bb, port = cc...cc, protocol = dd...dd)

aa...aa: User ID
bb...bb: Host name
cc...cc: Port number
dd...dd: Protocol

KAPM10133-I

A user was successfully authenticated by the Kerberos server. (Kerberos principal = aa...aa, KDC = bb...bb)

aa...aa: Kerberos principal name
bb...bb: List of KDC

KAPM10134-W

A user failed to be authenticated by the Kerberos server. (Kerberos principal = aa...aa, KDC = bb...bb)

aa...aa: Kerberos principal name

bb...bb: List of KDC

KAPM10135-I

User information was successfully acquired from the directory server. (user ID = aa...aa, domain name = bb...bb, host = cc...cc, port = dd...dd, protocol = ee...ee, base DN = ff...ff)

aa...aa: User ID

bb...bb: Domain name

cc...cc: Host name

dd...dd: Port number

ee...ee: Protocol

ff...ff: Base DN

KAPM10136-E

Acquisition of user information from the directory server failed. (user ID = aa...aa, domain name = bb...bb, host = cc...cc, port = dd...dd, protocol = ee...ee, base DN = ff...ff)

aa...aa: User ID

bb...bb: Domain name

cc...cc: Host name

dd...dd: Port number

ee...ee: Protocol

ff...ff: Base DN

KAPM10137-I

An SRV record was successfully acquired from the DNS server. (record key = aa...aa)

aa...aa: SRV record key

KAPM10138-E

An SRV record failed to be acquired from the DNS server. (record key = aa...aa)

aa...aa: SRV record key

KAPM10139-I

JP1/Base was successfully connected to.

KAPM10140-E

An attempt to connect to JP1/Base failed.

KAPM10141-I

User authentication in JP1/Base was successful. (aa...aa = bb...bb)

aa...aa: Key

bb...bb: Value

KAPM10142-W

JP1/Base user authentication failed. (aa...aa = bb...bb)

aa...aa: Key

bb...bb: Value

KAPM10143-I

JP1/Base was successfully logged out from. (JP1 token = aa...aa)

aa...aa: JP1 token

KAPM10144-I

User permission information was successfully acquired from JP1/Base. (user name = aa...aa)

aa...aa: User name

KAPM10145-E

Acquisition of user permission information from JP1/Base failed. (user name = aa...aa)

aa...aa: User name

KAPM10146-I

JP1/Base was successfully initialized.

KAPM10147-E

JP1/Base initialization failed.

KAPM10148-I

The JP1/Base version was successfully acquired.

KAPM10149-E

Acquisition of the JP1/Base version failed.

KAPM11003-E

The function is not supported. (function = aa...aa)

aa...aa: Function name

KAPM11051-E

The request was invalid.

KAPM11052-E

Login processing failed.

KAPM11101-E

The specified user does not exist. (instance ID = aa...aa)

aa...aa: Instance ID

KAPM11102-E

The built-in user account cannot be deleted.

KAPM11103-E

A required parameter is not specified. (operation = aa...aa, parameter name = bb...bb)

aa...aa: Operation

bb...bb: Parameter name

KAPM11105-E

The instance ID specified for a parameter differs from the instance ID specified for the URL. (operation = aa...aa, instance ID specified for the parameter = bb...bb, instance ID specified for the URL = cc...cc)

aa...aa: Operation

bb...bb: Instance ID specified for the parameter

cc...cc: Instance ID specified for the URL

KAPM11106-E

An inappropriate parameter is specified. (operation = aa...aa, parameter name = bb...bb)

aa...aa: Operation

bb...bb: Parameter name

KAPM11107-E

The request data is invalid.

KAPM11108-E

The specified user already exists. (login ID = aa...aa)

aa...aa: Login ID

KAPM11109-E

The password for a user authenticated by an external authentication server cannot be changed. (instance ID = aa...aa)

aa...aa: Instance ID

KAPM11110-E

The password is not set up.

KAPM11112-E

The password cannot be changed for a user mapped to an external authentication group. (login ID = aa...aa)

aa...aa: Login ID

KAPM11113-E

The password for a user authenticated by an external authentication server cannot be changed. (login ID = aa...aa)

aa...aa: Login ID

KAPM11114-E

There is a logout request for a user who is not logged in.

KAPM11115-E

The session information contains no token information. (token = aa...aa)

aa...aa: Token

KAPM11116-E

Authentication for this session is not basic authentication.

KAPM11117-E

The password conflicts with the input rules.

KAPM11120-E

The specified parameter is too long. (operation = aa...aa, parameter name = bb...bb)

aa...aa: Operation

bb...bb: Parameter name

KAPM11121-E

The specified parameter value is invalid. (operation = aa...aa, parameter name = bb...bb)

aa...aa: Operation

bb...bb: Parameter name

KAPM11122-E

The user information to be registered already exists. (login ID = aa...aa)

aa...aa: Login ID

KAPM11201-E

The built-in user group cannot be deleted. (instance ID = aa...aa)

aa...aa: Instance ID

KAPM11202-E

The specified user group does not exist. (instance ID = aa...aa)

aa...aa: Instance ID

KAPM11203-E

An external authorization group cannot be deleted. (instance ID = aa...aa)

aa...aa: Instance ID

KAPM11204-E

The specified value differs from the registered setting value. (operation = aa...aa, parameter name = bb...bb, specified value = cc...cc, registered setting value = dd...dd)

aa...aa: Operation

bb...bb: Parameter name

cc...cc: Specified value

dd...dd: Registered setting value

KAPM11205-E

The specified user group name already exists. (user group name = aa...aa)

aa...aa: User group name

KAPM11206-E

The operation cannot be performed for an external authorization group. (operation = aa...aa, instance ID = bb...bb)

aa...aa: Operation

bb...bb: Instance ID

KAPM11207-E

The name of the built-in user group cannot be changed. (instance ID = aa...aa)

aa...aa: Instance ID

KAPM11208-E

The external authorization group cannot be updated. (instance ID = aa...aa)

aa...aa: Instance ID

KAPM11209-E

The specified external authorization group already exists. (Distinguished Name = aa...aa)

aa...aa: Distinguished Name

KAPM11210-E

The user group information to be registered already exists. (user group name = aa...aa)

aa...aa: User group name

KAPM11211-E

The external authorization group to be registered already exists. (Distinguished Name = aa...aa)

aa...aa: Distinguished Name

KAPM11212-W

The format of the specified Distinguished Name is invalid. (Distinguished Name = aa...aa)

aa...aa: Distinguished Name

KAPM11301-E

The specified role does not exist. (instance ID = aa...aa)

aa...aa: Instance ID

KAPM11351-E

The specified resource group does not exist. (instance ID = aa...aa)

aa...aa: Instance ID

KAPM11999-E

An unexpected exception occurred.

KAPM14000-E

An exception occurred.

KAPM14003-I

Command execution started.

KAPM14004-I

The command was executed successfully.

KAPM14005-E

Command execution failed.

KAPM14006-E

An option is invalid.

KAPM14007-E

The command cannot be executed because the database is down.

KAPM14008-E

Command execution failed. (command name = aa...aa)

aa...aa: Command name

KAPM14009-E

An attempt to read a file failed. (file name = aa...aa)

aa...aa: File name

KAPM14010-E

Table information could not be acquired. (table name = aa...aa)

aa...aa: Table name

KAPM14011-W

A key is invalid. (key name = aa...aa)

aa...aa: Key name

KAPM14012-I

Association information will be deleted because the chain was broken. (hcndsID = aa...aa, association = bb...bb)

aa...aa: Product ID

bb...bb: Association

KAPM14013-I

Incorrect product information will be removed. (product name = aa...aa)

aa...aa: Product name

KAPM14014-E

The value of hcnds.home could not be acquired.

KAPM14015-E

An attempt to delete the product information has failed. (product name = aa...aa)

aa...aa: Product name

KAPM14016-E

An attempt to delete the association information has failed. (association = aa...aa)

aa...aa: Association

KAPM14017-E

The DBMS is blocked.

KAPM14018-E

An attempt to get association information failed.

KAPM14019-E

An attempt to get the class name failed.

KAPM14020-W

Processing is being re-executed.

KAPM14021-E

An authentication error occurred.

KAPM14022-E

An error occurred during DBMS access processing.

KAPM14030-I

The hcndsServiceCtrl command started.

KAPM14031-I

The hcndsServiceCtrl command finished successfully.

KAPM14032-E

The hcndsServiceCtrl command failed.

KAPM14033-E

A memory allocation error occurred.

KAPM14034-E

Acquisition of the HBase64 installation path failed.

KAPM14035-W

Log initialization failed.

KAPM14036-E

An option is invalid.

KAPM14039-E

An error occurred in an internal function. (calling function = aa...aa, executed function = bb...bb, note = cc...cc, error code = dd...dd)

aa...aa: Calling function name
bb...bb: Executed function name
cc...cc: Note
dd...dd: Error code

KAPM14040-E

The service is running. (service name = aa...aa)

aa...aa: Service name

KAPM14041-I

The service operation was executed. (operation name = aa...aa)

aa...aa: Operation name

KAPM14152-I

A command will now be executed. (command line = aa...aa)

aa...aa: Command line

KAPM14153-E

An option is invalid.

KAPM14154-I

The path is a symbolic link. (path = aa...aa)

aa...aa: Path

KAPM14155-W

The path is not a symbolic link. (path = aa...aa)

aa...aa: Path

KAPM14156-E

The path to be checked could not be obtained.

KAPM14157-E

The directory could not be found. (path = aa...aa)

aa...aa: Path

KAPM14158-E

An exception occurred.

KAPM15002-I

The hcnds64checkauth command will now start.

KAPM15003-I

The configuration check of aa...aa will now start.

aa...aa: Phase number

KAPM15004-I

The result of the configuration check of aa...aa was normal.

aa...aa: Phase number

KAPM15005-E

The result of the configuration check of aa...aa was abnormal.

aa...aa: Phase number

KAPM15006-I

The configuration of the server aa...aa will now be checked.

aa...aa: Server name

KAPM15007-I

The result of the configuration check of the server aa...aa was normal.

aa...aa: Server name

KAPM15008-E

The result of the configuration check of the server aa...aa was abnormal.

aa...aa: Server name

KAPM15009-I

The configuration check of aa...aa has finished normally.

aa...aa: Phase number

KAPM15010-I

The connection to the server aa...aa will now be checked. (host = bb...bb, port = cc...cc, protocol = dd...dd)

aa...aa: Server name

bb...bb: Host name

cc...cc: Port number

dd...dd: Protocol

KAPM15011-I

The server aa...aa can be connected to normally.

aa...aa: Server name

KAPM15012-E

The result of checking the connection to the server aa...aa indicated an error.

aa...aa: Server name

KAPM15013-E

A connection error occurred.

KAPM15014-E

An authentication error occurred.

KAPM15015-I

The command hcmds64checkauth will now finish.

KAPM15016-E

A file was not found. (file name = aa...aa)

aa...aa: File name

KAPM15017-E

A file could not be read. (file name = aa...aa)

aa...aa: File name

KAPM15018-E

The settings of the external authentication server are invalid.

KAPM15019-E

The configuration file contains a syntax error. (line number = aa...aa, value = bb...bb)

aa...aa: Line number

bb...bb: Value

KAPM15020-E

The same property key already exists. (line number = aa...aa, key = bb...bb)

aa...aa: Line number

bb...bb: Key

KAPM15021-E

A required parameter has not been specified. (key = aa...aa)

aa...aa: Key

KAPM15022-W

An optional parameter has been omitted. (value = aa...aa)

aa...aa: Value

KAPM15023-W

A property key cannot be identified. (line number = aa...aa)

aa...aa: Line number

KAPM15024-E

A secret does not exist.

KAPM15025-E

No connection could be made from the secondary server.

KAPM15026-E

A fatal error occurred during processing.

KAPM15027-E

An option is invalid.

KAPM15028-E

No value has been specified for an option.

KAPM15029-E

The value of hcnds.home could not be acquired.

KAPM15030-I

Processing has finished normally.

KAPM15031-E

An exception occurred.

KAPM15032-E

The configuration file was not found. (file name = aa...aa)

aa...aa: File name

KAPM15033-E

An error occurred on the aa...aa server.

aa...aa: Server name

KAPM15034-E

Authentication information cannot be acquired. (server name = aa...aa)

aa...aa: Server name

KAPM15035-I

Authentication information has been acquired.

KAPM15036-E

Authentication information cannot be acquired.

KAPM15037-E

Specify a value for at least one key. (key = aa...aa)

aa...aa: Key

KAPM15039-I

A connection was successfully established. (server name = aa...aa)

aa...aa: Server name

KAPM15040-E

A connection attempt has failed. (server name = aa...aa)

aa...aa: Server name

KAPM15041-E

Authentication has failed. (server name = aa...aa)

aa...aa: Server name

KAPM15042-E

A syntax error occurred. (server name = aa...aa)

aa...aa: Server name

KAPM15043-E

A check cannot be performed because the external authentication server type is unknown.

KAPM15044-E

A check cannot be performed because the server identification name is unknown.

KAPM15045-E

A parameter has not been specified. (key = aa...aa)

aa...aa: Key

KAPM15046-E

An invalid value has been specified for a parameter. (key = aa...aa)

aa...aa: Key

KAPM15047-I

The authentication method will now be internal authentication.

KAPM15049-E

The configuration file could not be accessed. (File name = aa...aa)

aa...aa: File name

KAPM15050-E

Authentication of the user account used for information searching has failed.

KAPM15051-E

The DN of the user account used for information searching was not found.

KAPM15052-E

Authentication of the specified user has failed.

KAPM15053-E

The specified user was not found.

KAPM15054-E

The specified user was not found. (error code = aa...aa)

aa...aa: Error code

KAPM15056-E

The specified user was not found.

KAPM15057-E

A dn value is invalid.

KAPM15058-I

The message outputs LDAP connection information. (aa...aa = bb...bb, aa...aa = bb...bb,)

aa...aa: Key

bb...bb: Value

KAPM15059-E

aa...aa

aa...aa: Detailed data at the time of an error

KAPM15060-I

The file targeted for generation management was successfully saved.

KAPM15061-E

No file targeted for generation management exists.

KAPM15062-E

There is not enough free space to save the file.

KAPM15063-E

The specified management target is a directory.

KAPM15064-E

The permissions for the file to be managed are invalid.

KAPM15065-E

An attempt to store the managed file has failed.

KAPM15066-W

The specified number of generations exceeds the maximum (99).

KAPM15067-E

Creation of the directory has failed.

KAPM15068-E

An option is invalid.

KAPM15069-E

A fatal error occurred.

KAPM15070-I

The hcmsfilerotate command has started.

KAPM15071-I

The hcmsfilerotate command has ended.

KAPM15072-I

A file whose file number is 99 has been overwritten.

KAPM15073-W

The command log cannot be output.

KAPM15074-E

The value specified for an option is invalid.

KAPM15080-E

Authentication of the user account used for information searching has failed. (server name = aa...aa)

aa...aa: Server name

KAPM15081-E

The DN of the user account used for information searching was not found. (server name = aa...aa)

aa...aa: Server name

KAPM15082-E

Authentication of the specified user has failed. (server name = aa...aa)

aa...aa: Server name

KAPM15083-E

The specified user was not found. (server name = aa...aa)

aa...aa: Server name

KAPM15084-E

LDAP directory server error is detected. (information = aa...aa)

aa...aa: Information

KAPM15085-E

An SSL setting is invalid.

KAPM15086-E

The specified user was not found. (server name = aa...aa)

aa...aa: Server name

KAPM15087-E

A dn value is invalid. (server name = aa...aa)

aa...aa: Server name

KAPM15088-I

The common-items check will now start.

KAPM15089-I

The results of the common-items check were normal.

KAPM15090-E

The results of the common-items check include abnormal values.

KAPM15091-I

The individual-realm check will now start.

KAPM15092-I

The results of the realm identified name aa...aa check were normal.

aa...aa: Realm identified name

KAPM15093-E

The results of the realm identified name aa...aa check include abnormal values.

aa...aa: Realm identified name

KAPM15094-I

The results of the individual-realm check were normal.

KAPM15095-E

The results of the individual-realm check include abnormal values.

KAPM15096-E

The same value already exists. (line number = aa...aa, value = bb...bb)

aa...aa: Line number

bb...bb: Value

KAPM15097-E

There is no auth.kerberos.<realm identification name>.realm that corresponds to auth.kerberos.default_realm.

KAPM15098-I

The server connection will now be checked. (user id = aa...aa, realm name = bb...bb)

aa...aa: User ID

bb...bb: Realm name

KAPM15102-I

The hcnds64unlockaccount command has started.

KAPM15103-I

The hcnds64unlockaccount command has finished.

KAPM15104-E

The hcnds64unlockaccount command cannot be executed on the secondary server. Execute this command on the primary server.

KAPM15105-E

The user account to be unlocked does not have the User Management permission.

KAPM15108-I

The user account was unlocked successfully.

KAPM15109-I

The user account "aa...aa" will now be unlocked.

aa...aa: User name

KAPM15110-E

The value of hcnds.home could not be acquired.

KAPM15111-E

A command option is invalid.

KAPM15112-E

No value has been specified for an option.

KAPM15113-E

A fatal error occurred.

KAPM15114-E

Communication with the authentication server has failed.

KAPM15115-E

The user ID or password is incorrect.

KAPM15116-E

An HSSOException occurred.

KAPM15117-E

An IOException occurred.

KAPM15118-E

An HcmdsIllegalArgumentException occurred.

KAPM15119-E

An HcmdsUserManagementException occurred.

KAPM15120-E

An exception occurred.

KAPM15130-E

An option is invalid.

KAPM15131-I

The hcmdsmergelog command ended successfully.

KAPM15132-W

The format of the specified date format configuration file is invalid. (line number: "aa...aa")

aa...aa: Line number

KAPM15133-W

The format of the specified merge-target configuration file is invalid. (line number: "aa...aa")

aa...aa: Line number

KAPM15134-W

The specified merge-target file "aa...aa" was not found.

aa...aa: The specified merge-target configuration file

KAPM15135-W

The specified merge-target file "aa...aa" cannot be opened.

aa...aa: The specified merge-target configuration file

KAPM15136-E

The specified file "aa...aa" cannot be written to.

aa...aa: The specified file

KAPM15137-W

The specified file cannot be opened. (file name = "aa...aa")

aa...aa: File name

KAPM15138-E

Execution of the hcndsmergelog command failed.

KAPM15139-E

An unexpected error occurred.

KAPM15140-W

The format of the specified variable configuration file is invalid. (line number: "aa...aa")

aa...aa: Line number

KAPM15141-E

The name of the merge-target configuration file "aa...aa" does not end in "mergelog.conf".

aa...aa: Name of the merge-target configuration file

KAPM15142-E

The hcndsmergelog command failed to acquire memory.

KAPM15143-E

The date format configuration file "aa...aa" was not found.

aa...aa: Date format configuration file

KAPM15144-W

An attempt to write to the log file hcndsmergelog.log has failed.

KAPM15145-E

Deletion of a temporary work file has failed.

KAPM15146-E

The specified time range is invalid.

KAPM15147-W

The size of the specified file "aa...aa" cannot be acquired.

aa...aa: File name

KAPM15148-E

The file cannot be written to.

KAPM15149-E

The sort command could not be executed.

KAPM15150-E

Creation of an execution process failed.

KAPM15151-E

The process is not in the signal status.

KAPM15152-E

The process status could not be acquired.

KAPM15153-W

No log records to be merged were found.

KAPM15154-E

The specified date format configuration file "aa...aa" was not found.

aa...aa: The specified date format configuration file

KAPM15155-E

The size of the specified date format configuration file "aa...aa" cannot be acquired.

aa...aa: The specified date format configuration file

KAPM15156-E

The specified date format configuration file "aa...aa" cannot be read.

aa...aa: The specified date format configuration file

KAPM15157-E

The specified variable configuration file "aa...aa" was not found.

aa...aa: The specified variable configuration file

KAPM15158-E

The size of the specified variable configuration file "aa...aa" cannot be acquired.

aa...aa: The specified variable configuration file

KAPM15159-E

The specified variable configuration file "aa...aa" cannot be read.

aa...aa: The specified variable configuration file

KAPM15160-E

The specified merge-target configuration file "aa...aa" was not found.

aa...aa: The specified merge-target configuration file

KAPM15161-E

The specified merge-target configuration file "aa...aa" cannot be acquired.

aa...aa: The specified merge-target configuration file

KAPM15162-E

The specified merge-target configuration file "aa...aa" cannot be read.

aa...aa: The specified merge-target configuration file

KAPM15163-E

The specified output file cannot be created.

KAPM15164-E

The specified output file cannot be written to.

KAPM15165-W

The log file "hcmdsmergelog.log" cannot be created in the specified log folder.

KAPM15166-E

The format of the specified time range is invalid.

KAPM15167-E

The date and time format is not set.

KAPM15170-E

Acquisition of the installation path has failed.

KAPM15171-E

The command aa...aa will stop because internal processing failed. (details = bb...bb)

aa...aa: Command name

bb...bb: Details

KAPM15172-W

Log initialization failed.

KAPM15173-E

A memory allocation error occurred.

KAPM15174-E

The command aa...aa will stop because setting of an environment variable failed. (details = bb...bb)

aa...aa: Command name

bb...bb: Details

KAPM15175-E

An error occurred in an internal function. (function = aa...aa, error code = bb...bb)

aa...aa: Function

bb...bb: Error code

KAPM15200-I

A connection was successfully established. (KDC = aa...aa)

aa...aa: KDC

KAPM15201-E

An attempt to connect failed. (KDC = aa...aa)

aa...aa: KDC

KAPM15202-E

An attempt to connect to the DNS server failed.

KAPM15203-E

On the DNS server,the SRV record corresponding to the realm name is not defined. (realm name = aa...aa)

aa...aa: Realm name

KAPM15204-E

An unexpected error occurred on the DNS server.

KAPM15205-E

The KDC resolution failed. (KDC = aa...aa)

aa...aa: KDC

KAPM15206-E

An attempt to authenticate failed. (KDC = aa...aa)

aa...aa: KDC

KAPM15207-E

The specified user was not found. (KDC = aa...aa)

aa...aa: KDC

KAPM15208-E

The specified password is invalid. (KDC = aa...aa)

aa...aa: KDC

KAPM15209-E

The time difference between servers exceeds the specified value in exauth.properties. (KDC = aa...aa)

aa...aa: KDC

KAPM15210-E

The authentication user password has expired. (KDC = aa...aa)

aa...aa: KDC

KAPM15211-E

The authentication user account is invalid. (KDC = aa...aa)

aa...aa: KDC

KAPM15212-I

Check the DNS server to confirm the connection status.

KAPM15213-I

Use the default realm to confirm the connection status.

KAPM15214-E

The command cannot be executed on the secondary server.

KAPM15215-E

Creation of the file failed. (file name = aa...aa)

aa...aa: File name

KAPM15216-E

A syntax error occurred.

KAPM15217-W

The DBMS is not running.

KAPM15218-W

The DBMS is blocked.

KAPM15219-W

An error occurred while the DBMS was being accessed.

KAPM15220-W

The user to be authenticated was not found in the DBMS. (user id = aa...aa)

aa...aa: User ID

KAPM15221-W

An unexpected error occurred on the DBMS.

KAPM15222-E

Acquisition of the KDC from aa...aa failed.

aa...aa: Realm name

KAPM15223-E

An unexpected error occurred. (KDC = aa...aa)

aa...aa: KDC

KAPM15224-W

The specified user is not registered in the DBMS as a user of the Kerberos authentication method. (user id = aa...aa)

KAPM15225-W

The configuration file contains a syntax error. (line number = aa...aa, value = bb...bb)

aa...aa: Line number

bb...bb: Value

KAPM15226-E

An information search user is not registered. (aa...aa = bb...bb)

aa...aa: Attribute name

bb...bb: Attribute value

KAPM15227-I

Group linkage is enabled.

KAPM15228-W

The external authentication group was not linked to because an authentication user was found on the DBMS.

KAPM15229-I

Group acquisition for the server will now be checked. (aa...aa = bb...bb, host = cc...cc, port = dd...dd, protocol = ee...ee)

aa...aa: Attribute name
bb...bb: Attribute value
cc...cc: Host
dd...dd: Port
ee...ee: Protocol

KAPM15230-I

Group acquisition was successful.

KAPM15231-E

Group acquisition failed.

KAPM15232-E

The group was not registered.

KAPM15233-E

On the DNS server,the SRV record corresponding to the domain name is not defined. (domain name = aa...aa)

aa...aa: Domain name

KAPM15234-I

The DNS server has been referenced. (aa...aa = bb...bb, domain name = cc...cc)

aa...aa: Attribute name
bb...bb: Attribute value
cc...cc: Domain name

KAPM15235-E

A server error occurred. (aa...aa = bb...bb)

aa...aa: Attribute name

bb...bb: Attribute value

KAPM15236-E

A check cannot be performed because the group definition is invalid.

KAPM15237-I

Group acquisition was successful. (aa...aa = bb...bb)

aa...aa: Attribute name

bb...bb: Attribute value

KAPM15238-E

Group acquisition failed. (aa...aa = bb...bb)

aa...aa: Attribute name

bb...bb: Attribute value

KAPM15239-E

The group was not registered. (aa...aa = bb...bb)

aa...aa: Attribute name

bb...bb: Attribute value

KAPM15240-E

On the DNS server,the SRV record corresponding to the domain name is not defined. (aa...aa = bb...bb)

aa...aa: Attribute name

bb...bb: Attribute value

KAPM15241-E

An attempt to connect to the DNS server failed. (aa...aa = bb...bb)

aa...aa: Attribute name

bb...bb: Attribute value

KAPM15242-E

An unexpected error occurred on the DNS server. (aa...aa = bb...bb)

aa...aa: Attribute name

bb...bb: Attribute value

KAPM15243-E

The common items cannot be checked because they are not set correctly.

KAPM15244-I

The connection for realm aa...aa was checked.

aa...aa: Realm name

KAPM15245-I

A connection was successfully established. (aa...aa = bb...bb)

aa...aa: Attribute name

bb...bb: Attribute value

KAPM15246-E

A connection attempt has failed. (aa...aa = bb...bb)

aa...aa: Attribute name

bb...bb: Attribute value

KAPM15247-E

Authentication of the user account used for information searching has failed. (aa...aa = bb...bb)

aa...aa: Attribute name

bb...bb: Attribute value

KAPM15248-E

The DN of the user account used for information searching was not found. (aa...aa = bb...bb)

aa...aa: Attribute name

bb...bb: Attribute value

KAPM15249-E

Authentication of the specified user has failed. (aa...aa = bb...bb)

aa...aa: Attribute name

bb...bb: Attribute value

KAPM15250-E

The specified user was not found. (aa...aa = bb...bb)

aa...aa: Attribute name

bb...bb: Attribute value

KAPM15251-E

The specified user was not found. (aa...aa = bb...bb)

aa...aa: Attribute name

bb...bb: Attribute value

KAPM15252-E

A dn value is invalid. (aa...aa = bb...bb)

aa...aa: Attribute name

bb...bb: Attribute value

KAPM15253-E

The JP1/Base connection could not be verified because the authentication user was not found in the DBMS.

KAPM15254-E

HiCommand Base does not support this version of JP1/Base.

KAPM15255-E

Acquisition of the JP1/Base version failed.

KAPM15256-E

An attempt to connect to JP1/Base failed.

KAPM15257-E

JP1/Base initialization failed.

KAPM15258-I

The JP1/Base connection will now be checked.

KAPM15259-I

The JP1/Base connection was successfully checked.

KAPM15260-E

JP1/Base user authentication failed.

KAPM15261-E

JP1/Base authentication failed because the user ID or password is incorrect.

KAPM15262-I

HiCommand Base will now check whether user permission information can be acquired from JP1/Base.

KAPM15263-I

User permission information was successfully acquired from JP1/Base.

KAPM15264-E

Permissions have not been assigned to the user in JP1/Base.

KAPM15265-E

JP1/Base is not installed.

KAPM15266-E

Acquisition of user permission information from JP1/Base failed.

KAPM15267-E

This JP1/Base version is not supported.

KAPM15268-I

The user permission information will now be acquired from JP1/Base and checked.

KAPM15269-E

The value of the property could not be acquired. (property name = aa...aa)

aa...aa: Property name

KAPM15270-E

An attempt to acquire an SSL setting failed. (aa...aa = bb...bb)

aa...aa: Property name

bb...bb: Property value

KAPM15271-E

There is no supported cipher suite. (aa...aa = bb...bb)

aa...aa: Property name

bb...bb: Property value

KAPM15272-E

There is no supported protocol. (aa...aa = bb...bb)

aa...aa: Property name

bb...bb: Property value

KAPM15273-I

Multi-domain LDAP authentication is enabled.

KAPM15274-E

The following attributes cannot be enabled at the same time: "auth.ldap.multi_domain" and "auth.ldap.<server-identification-name>.dns_lookup".

KAPM15275-I

The server connection will now be checked. (user ID = aa...aa)

aa...aa: User ID

KAPM15276-I

The server connection will now be checked. (user ID = aa...aa, domain name = bb...bb)

aa...aa: User ID

bb...bb: Domain name

KAPM15277-E

There is no configuration corresponding to the specified domain name. (domain name = aa...aa)

aa...aa: Domain name

KAPM15278-W

Failed to access the database.

KAPM15279-I

The global catalog is enabled.

KAPM15280-E

The domain name corresponding to auth.ldap.default_domain is not specified for auth.ldap.<server-identification-name>.domain.

KAPM15281-E

The number of host names does not match the number of port numbers. (server name = aa...aa)

aa...aa: Server name

KAPM15282-E

The following attributes cannot be enabled at the same time: "auth.ldap.default_domain" and "auth.ldap.<server-identification-name>.dns_lookup".

KAPM15283-W

The specified user is not registered in the DBMS as a user of the LDAP authentication method. (user ID = aa...aa)

aa...aa: User ID

KAPM15300-I

The hcmdslicense3 command started.

KAPM15301-I

The hcmdslicense3 command successfully executed.

KAPM15302-E

The hcmdslicense3 command failed.

KAPM15305-E

Acquisition of the installation path failed.

KAPM15306-E

One or more options are invalid.

KAPM15307-E

Allocation of memory to store the log file path failed.

KAPM15308-E

Log initialization failed.

KAPM15309-I

The license was successfully displayed.

KAPM15310-E

An attempt to display the license failed.

KAPM15311-E

Encoding failed.

KAPM15312-E

Decoding failed.

KAPM15313-I

License registration processing started.

KAPM15314-I

License deletion processing started.

KAPM15315-I

License display processing started.

KAPM15316-I

License reset processing started.

KAPM15317-E

The entered total capacity license is not supported.

KAPM15318-E

The entered server capacity license is not supported.

KAPM15319-I

The license key was processed. (identifier = aa...aa, number = bb...bb)

aa...aa: Identifier

bb...bb: Number

KAPM15320-I

aa...aa

aa...aa

aa...aa: Command line argument

KAPM15321-E

A memory allocation error occurred.

KAPM15322-E

Exclusion processing failed. (function = aa...aa, detailed error code = bb...bb)

aa...aa: Function name

bb...bb: Detailed error code

KAPM15323-E

Exclusive control has failed.

KAPM15324-E

Information related to the exclusion control failure will be output. (function name = aa...aa, detailed error code = bb...bb, processing time = cc...cc)

aa...aa: Function name

bb...bb: Detailed error code

cc...cc: Processing time

KAPM15325-E

An attempt to release the lock failed.

KAPM15330-I

Processing ended normally. (aa...aa : bb...bb) cc...cc

aa...aa: Return code

bb...bb: Error code

cc...cc: License information

KAPM15331-E

The system environment is invalid.

KAPM15332-E

The license has expired.

KAPM15333-E

The entered license key is invalid. (aa...aa : bb...bb) cc...cc

aa...aa: Return code

bb...bb: Error code

cc...cc: License information

KAPM15334-E

The license key file that was entered could not be found.

KAPM15335-E

The license key file that was entered is invalid.

KAPM15336-E

The license key to be processed does not exist in the license key file.

KAPM15337-E

The license to be deleted does not exist.

KAPM15338-E

The entered subscription license key has expired.

KAPM15400-I

A Daemon will now start.

KAPM15401-I

A Daemon has stopped.

KAPM15402-E

A Daemon has terminated abnormally. Code=[aa...aa]

aa...aa: Termination code of a Daemon

KAPM15411-I

hcmdssvlog [aa...aa]{,[bb...bb],.....[.....]}

aa...aa: Command line arguments

bb...bb: Command line arguments

KAPM15417-E

An option is invalid. Code=[aa...aa], Data=[bb...bb]

aa...aa: Code indicating the occurrence location

bb...bb: Occured options and values

KAPM15418-E

An unexpected exception occurred.

KAPM15422-E

The option is invalid.

KAPM15423-E

The specified value of option is invalid. (option = aa...aa)

aa...aa: Option name

KAPM15424-E

The directory aa...aa does not exist.

aa...aa: Directory name

KAPM15425-E

A file with the same name as the specified directory already exists. (file = aa...aa)

aa...aa: File name

KAPM15426-E

The license information file does not exist in the specified directory. (license information file = aa...aa)

aa...aa: License information file name

KAPM15427-E

The license information file cannot be accessed. (license information file = aa...aa)

aa...aa: License information file name

KAPM15428-E

The license information file might be corrupted. (license information file = aa...aa)

aa...aa: License information file name

KAPM15429-E

The license information file at the transfer destination cannot be accessed. (license information file = aa...aa)

aa...aa: License information file name

KAPM15430-E

An attempt to write to the license information file failed. (license information file = aa...aa)

aa...aa: License information file name

KAPM15431-E

Comparison of the license definition files at the transfer source and transfer destination failed.

KAPM15433-E

An attempt to give the license information file the hidden attribute failed.

KAPM15434-E

An attempt to transfer license information in the DKC_info format failed.

KAPM15435-E

The numbers of license information items on the transfer source and the transfer destination do not match. (transfer source = aa...aa, transfer destination = bb...bb)

aa...aa: The number of license information items on the transfer source

bb...bb: The number of license information items on the transfer destination

KAPM15436-E

The status lines of the license information files at the transfer source and transfer destination do not match. (line number = aa...aa)

aa...aa: The line number of the license information files at the transfer source

KAPM15437-E

The PPID values of the transfer source and transfer destination do not match. (transfer source = aa...aa, transfer destination = bb...bb)

aa...aa: The PPID value of the transfer source

bb...bb: The PPID value of the transfer destination

KAPM15438-E

The device numbers of the transfer source and transfer destination do not match. (transfer source = aa...aa, transfer destination = bb...bb)

aa...aa: The device number of the transfer source

bb...bb: The device number of the transfer destination

KAPM15439-E

The license key types of the transfer source and the transfer destination do not match. (transfer source = aa...aa, transfer destination = bb...bb)

aa...aa: The license key type of the transfer source

bb...bb: The license key type of the transfer destination

KAPM15440-E

The device types of the transfer source and the transfer destination do not match. (transfer source = aa...aa, transfer destination = bb...bb)

aa...aa: The device type of the transfer source

bb...bb: The device type of the transfer destination

KAPM15442-E

The license capacities of the transfer source and the transfer destination do not match. (transfer source = aa...aa, transfer destination = bb...bb)

aa...aa: The license capacity of the transfer source
bb...bb: The license capacity of the transfer destination

KAPM15443-E

The expiration dates of the transfer source and the transfer destination do not match. (transfer source = aa...aa, transfer destination = bb...bb)

aa...aa: The expiration date of the transfer source
bb...bb: The expiration date of the transfer destination

KAPM15444-E

The serial numbers of the transfer source and the transfer destination do not match. (transfer source = aa...aa, transfer destination = bb...bb)

aa...aa: The serial number of the transfer source
bb...bb: The serial number of the transfer destination

KAPM15445-E

The license information file at the transfer destination cannot be accessed. (type = aa...aa)

aa...aa: Product name

KAPM15446-E

The license information file at the transfer destination might be corrupted. (type = aa...aa)

aa...aa: Product name

KAPM15447-E

Execution of the hcmdssethiddenfile command failed.

KAPM15448-I

The hcmdslicenseconvert command ended normally.

KAPM15449-E

An unexpected exception occurred.

KAPM15450-I

hcmdslicenseconvert [aa...aa]{,[bb...bb],.....[.....]}

aa...aa: Command line arguments

bb...bb: Command line arguments

KAPM15451-E

An attempt to transfer a license failed because the fixed character string inserted into the license information file on the transfer destination was invalid.

KAPM15452-I

License information before migration: aa...aa

aa...aa: License information

KAPM15460-I

The hcmds64chgjdk command started.

KAPM15461-I

The hcmds64chgjdk command successfully ended.

KAPM15462-E

The hcnds64chgjdk command failed.

KAPM15465-E

Acquisition of the installation path failed.

KAPM15466-E

One or more options are invalid.

KAPM15467-E

Allocation of memory to store the log file path failed.

KAPM15468-E

Log initialization failed.

KAPM15469-E

An internal error occurred.

KAPM15470-E

A fatal error occurred.

KAPM15471-I

The hcnds64chgjdk command ended.

KAPM15472-I

The JDK being used was changed.

KAPM15473-I

The JDK being used was not changed.

KAPM15474-E

The platform is not supported.

KAPM15475-E

Creation of a symbolic link failed.

KAPM15476-W

A JDK could not be detected from the installation information of this OS.

KAPM15477-E

Detection of a JDK failed.

KAPM15478-I

JDK version = aa...aa

aa...aa: JDK version

KAPM15479-I

JDK currently being used: name = aa...aa

aa...aa: Character string of JDK type

KAPM15480-I

Selected JDK: name = aa...aa, installation path = bb...bb

aa...aa: Character string of JDK type

bb...bb: Installation path of JDK

KAPM15481-E

The file "aa...aa" does not exist.

aa...aa: File name

KAPM15482-E

Execution of the aa...aa command failed.

aa...aa: Command name

KAPM15483-I

Enter the number of the JDK to use.

KAPM15484-I

JDK currently being used: aa...aa

aa...aa: Character string of JDK type

KAPM15485-I

Enter the JDK installation path.

KAPM15486-I

To maintain the current settings, do not enter anything, and then press [Enter].

KAPM15487-I

Bundled JDK

KAPM15488-I

Enter the JDK installation path.

KAPM15489-E

The specified value is invalid.

KAPM15490-E

The specified JDK could not be used.

KAPM15491-I

Detected JDK: name = aa...aa, installation path = bb...bb

aa...aa: Character string of JDK type

bb...bb: Installation path of JDK

KAPM15492-E

The file system at the installation destination is not NTFS.

KAPM15493-E

An error occurred during execution of the aa...aa command.

aa...aa: Command name

KAPM15494-E

An attempt to copy from the file "aa...aa" to the file "bb...bb" failed.

aa...aa: File name before the copy

bb...bb: File name after the copy

KAPM15495-E

An attempt to edit the file "aa...aa" failed.

aa...aa: File name

KAPM15496-I

The command was executed. (command name = aa...aa, return code = bb...bb)

aa...aa: Command name

bb...bb: Return code

KAPM15497-E

A memory allocation error occurred.

KAPM15500-I

Execution of the "aa...aa" command has started.

aa...aa: Command name

KAPM15501-I

The command was executed. (command name = aa...aa, return code = bb...bb)

aa...aa: Command name

bb...bb: Return code

KAPM15502-E

The error has occurred in aa...aa command. code=bb...bb

aa...aa: Command

bb...bb: Error code

KAPM15503-I

aa...aa

aa...aa: Command line arguments

KAPM15504-E

An error occurred in an internal function. (function = aa...aa, error code = bb...bb)

aa...aa: Function

bb...bb: Error code

KAPM15505-E

Log initialization failed.

KAPM15506-E

Acquisition of the installation path failed.

KAPM15507-E

Allocation of memory to store the log file path failed.

KAPM15510-I

The hcmsdbpdl command ended successfully.

KAPM15511-E

Execution of the hcmsdbpdl command failed.

KAPM15512-E

An option is invalid.

KAPM15513-E

The directory does not exist. (directory path = aa...aa)

aa...aa: Directory path

KAPM15514-E

Hitachi Command Suite Common Component has not been installed.

KAPM15515-E

Execution of the pdls command failed.

KAPM15516-I

The pdls command execution results: aa...aa

aa...aa: The screen output of the command executed

KAPM15517-I

The hcmdsdbpdl command has started.

KAPM15518-I

A connection with HiRDB has been established.

KAPM15519-I

A connection with HiRDB has not been established.

KAPM15520-E

An attempt to output a file has failed. (file path = aa...aa)

aa...aa: File path

KAPM15521-E

The path is not an absolute path. (file path = aa...aa)

aa...aa: File path

KAPM15522-E

Acquisition of the HiCommand Base installation path failed.

KAPM15523-E

An attempt to set the environment variable has failed.

KAPM15524-W

An attempt to delete the file failed. (file path = aa...aa)

aa...aa: File path

KAPM15525-E

An attempt to delete the file to which the HiRDB connection status is output failed. (file path = aa...aa)

aa...aa: File path

KAPM15526-E

Analysis of the pdls results failed.

KAPM15527-E

Memory allocation failed.

KAPM15528-E

An error occurred in an internal function. (function = aa...aa, error code = bb...bb)

aa...aa: Function name

bb...bb: Error code

KAPM15529-E

One or more arguments specified for the hcndsPutenv function are invalid.

KAPM15530-W

An attempt to output the execution results of the pdls command to the log file failed.

KAPM15550-E

Acquisition of the version of aa...aa failed.

aa...aa: Product name

KAPM15551-E

The system environment is invalid.

KAPM15552-E

Reading of the file failed. (file name = aa...aa)

aa...aa: File name

KAPM15553-E

The product version of the backup is different from the product version of the current environment.

KAPM15554-W

Deletion of a file failed. (file name = aa...aa)

aa...aa: File name

KAPM15555-W

Deletion of a directory failed. (directory name = aa...aa)

aa...aa: directory name

KAPM15556-W

Creation of a directory failed. (directory name = aa...aa)

aa...aa: directory name

KAPM15557-E

The configuration of the product when it was backed up is different from the configuration of the product in the current environment.

KAPM15558-I

aa...aa

aa...aa: Standard error output

KAPM15560-I

The host name was changed successfully. (before = aa...aa, after = bb...bb)

aa...aa: Host name before the change

bb...bb: Host name after the change

KAPM15561-I

The set host name will now be displayed. (host name = aa...aa)

aa...aa: Host name

KAPM15562-E

One or more arguments are invalid.

KAPM15563-E

The specified host name is invalid.

KAPM15564-E

The configuration file could not be accessed.

KAPM15565-E

The configuration file format is invalid.

KAPM15566-E

An unexpected error occurred.

KAPM15567-E

An attempt to acquire the installation path has failed.

KAPM15568-E

A memory allocation error occurred.

KAPM15569-E

An attempt to output a file has failed.

KAPM15570-E

Log initialization failed.

KAPM15580-E

One or more arguments are invalid.

KAPM15581-E

An unexpected error occurred.

KAPM15582-E

An attempt to acquire the installation path has failed.

KAPM15583-E

A memory allocation error occurred.

KAPM15584-E

Log initialization failed.

KAPM15585-E

The service will not be stopped because the status of the service could not be confirmed. (service name = aa...aa)

aa...aa: Service name

KAPM15586-E

The service will not be started because the status of the service could not be confirmed. (service name = aa...aa)

aa...aa: Service name

KAPM15587-E

Acquisition of the displayed service name failed. (service name = aa...aa)

aa...aa: Service name

KAPM15588-E

The Win32API has failed. API name=aa...aa, error code=bb...bb

aa...aa: WIN32API name

bb...bb: Error code returned by the GetLastError()

KAPM15608-I

JDK currently being used: aa...aa [bb...bb]

aa...aa: Character string of JDK type

bb...bb: Installation path of JDK

KAPM15609-W

An attempt to get the symbolic link information failed.

KAPM15610-E

Execution of the readlink function failed. (error code = aa...aa)

aa...aa: Error code

KAPM15611-E

Addition of a parameter to the sysconf.cfg file failed.

KAPM15612-E

The JDK version check failed. (version = aa...aa)

aa...aa: Version

KAPM15613-E

Information about supported JDK versions could not be acquired.

KAPM15614-E

Execution of the aa...aa function failed. (error code = bb...bb)

aa...aa: Function name

bb...bb: Error code

KAPM15615-W

An attempt to check whether the JDK is the 64-bit version failed.

KAPM15616-E

A Win32 API function failed. (API function name = aa...aa, error code = bb...bb)

aa...aa: WIN32API name

bb...bb: Error code returned by the GetLastError()

KAPM15617-E

A file exists at the destination for which a symbolic link is to be created.

KAPM15618-E

A directory exists at the destination for which a symbolic link is to be created.

KAPM15619-E

An error occurred in an API function. (API function name = aa...aa, error code = bb...bb)

aa...aa: API function name

bb...bb: Error code

KAPM15622-I

The hcnds64dbrepair command has started.

KAPM15623-I

The hcnds64dbrepair command has finished.

KAPM15624-E

The hcnds64dbrepair command cannot be executed in a standby system. Execute this command in an online system.

KAPM15625-E

The value of hcnds.home could not be acquired.

KAPM15626-E

An option is invalid.

KAPM15627-E

No value has been specified for an option.

KAPM15628-E

The backup data is invalid.

KAPM15629-E

A fatal error occurred.

KAPM15630-I

The parameter definition file has been backed up.

KAPM15631-I

The backup file of the parameter definition file has been deleted.

KAPM15632-E

An attempt to execute the aa...aa command has failed.

aa...aa: Command name

KAPM15633-E

An attempt to acquire the key name has failed.

KAPM15634-E

An attempt to acquire a value has failed.

KAPM15635-E

HiRDB has not been set up.

KAPM15636-E

The backup data format contains an error. (target data = aa...aa)

aa...aa: Target data

KAPM15637-E

An attempt to extract the archive file has failed.

KAPM15638-E

Processing cannot be continued because the backed-up product data is insufficient.

KAPM15639-W

The installed product and backed-up product versions do not match.

KAPM15640-W

If you continue, the database might become corrupted. Do you want to continue? (y/n) [default=n]

KAPM15641-W

Are you sure you want to continue? (y/n) [default=n]

KAPM15642-E

An exception occurred.

KAPM15643-I

The unsetup operation has started.

KAPM15644-I

The unsetup operation has ended.

KAPM15645-I

Setup has started.

KAPM15646-I

Setup has ended.

KAPM15647-E

The aa...aa file was not found.

aa...aa: File name

KAPM15648-E

The aa...aa file could not be read.

aa...aa: File name

KAPM15649-E

The aa...aa directory could not be deleted.

aa...aa: Directory name

KAPM15650-E

You cannot continue because the parameter definition file is insufficient.

KAPM15651-W

Processing of the hcmds64dbrepair command was interrupted.

KAPM15652-I

Version information is output. (product name = aa...aa, installed product version = bb...bb, backup data version = cc...cc)

aa...aa: Product name

bb...bb: Installed product version

cc...cc: Product version of backup data

KAPM15653-E

The unsetup operation on the database has failed.

KAPM15655-E

Starting of the HiRDB service has failed.

KAPM15656-I

Data import was successful.

KAPM15657-E

An attempt to re-create the database has failed.

KAPM15658-E

An attempt to import data has failed.

KAPM15659-E

The data to be imported was not found in the specified directory. (product name = aa...aa)

aa...aa: Product name

KAPM15660-I

Processing ended normally.

KAPM15661-E

An attempt to clear a DBMS environment variable has failed.

KAPM15662-E

An attempt to stop the service or the DBMS has failed.

KAPM15663-E

An internal error occurred.

KAPM15664-E

The "bb...bb" file to be used by "aa...aa" does not exist.

aa...aa: Function name

bb...bb: File name

KAPM15665-E

An attempt to write to the file has failed. (file name = aa...aa)

aa...aa: File name

KAPM15666-E

Copying of the unload function file failed.

KAPM15667-I

The value of parameter aa...aa is bb...bb.

aa...aa: Variable name

bb...bb: Value

KAPM15720-E

An exception occurred.

KAPM15723-I

The hcnds64dbuser command will now start.

KAPM15724-I

The command hcnds64dbuser will now finish.

KAPM15726-E

An option is invalid.

KAPM15727-E

The command cannot be executed because the database is down.

KAPM15728-E

hcnds.home is not specified in the Java system properties.

KAPM15729-E

An error occurred during reading of a library. library path = aa...aa

aa...aa: Library path

KAPM15730-E

The system environment is invalid.

KAPM15731-E

An error occurred in an internal function. (function = aa...aa, error code = bb...bb)

aa...aa: Function

bb...bb: Error code

KAPM15732-E

A file was not found. (file name = aa...aa)

aa...aa: File name

KAPM15733-E

An attempt to access the file has failed. (file name = aa...aa)

aa...aa: File name

KAPM15748-E

The file format is invalid. (file name = aa...aa)

aa...aa: File name

KAPM15749-E

An attempt to output a file failed. (file path = aa...aa)

aa...aa: File path

KAPM15750-I

The command was executed successfully.

KAPM15751-E

Command execution failed.

KAPM15752-I

The database user authentication information will now be changed. (type = aa...aa)

aa...aa: Program type

KAPM15753-I

The database user authentication information will now be restored to default. (type = aa...aa)

aa...aa: Program type

KAPM15754-I

The database user authentication information will now be reset. (type = aa...aa)

aa...aa: Program type

KAPM15755-E

An attempt to execute JNI failed.

KAPM15756-E

An error occurred during file I/O processing.

KAPM15757-I

Registration processing was successful. (target = aa...aa, return code = bb...bb)

aa...aa: Information of the target

bb...bb: Return code

KAPM15758-I

Deletion processing was successful. (target = aa...aa, return code = bb...bb)

aa...aa: Information of the target

bb...bb: Return code

KAPM15759-E

An error occurred during access to the DBMS.

KAPM15760-E

An error occurred during access to the DBMS. (error code = aa...aa)

aa...aa: Error code

KAPM15765-E

The ID or password is invalid.

KAPM15766-E

The ID or password is invalid. (error code = aa...aa)

aa...aa: Error code

KAPM15767-I

Common Component is set to the default settings.

KAPM15768-I

Common Component is not set to the default settings.

KAPM15769-E

The specified ID cannot be used, because it is reserved.

KAPM15770-I

Confirm that the Common Component settings are the default settings.

KAPM15781-E

A fatal error occurred.

KAPM15782-E

The specified argument is invalid.

KAPM15783-I

The specified string contains one or more invalid characters.

KAPM15784-I

The command ended normally.

KAPM15785-E

The specified string contains an invalid character.

KAPM15792-E

An option is invalid.

KAPM15793-E

An internal error occurred.

KAPM15794-E

The file format is invalid.

KAPM15800-I

The size of the work area was successfully changed.

KAPM15801-I

The size of the system file area was successfully changed.

KAPM15802-I

Are you sure you want to execute the hcmsdbchgwork command? (Y/N)

KAPM15804-I

The size of the work area is aa...aa.

aa...aa: Specified size

KAPM15805-I

The size of the system file area is aa...aa.

aa...aa: Specified size

KAPM15808-I

The command will now be executed. (specified command = aa...aa)

aa...aa: Specified command line

KAPM15810-I

The size of the work area will now be changed.

KAPM15811-I

The size of the system file area will now be changed.

KAPM15812-I

Change processing completed.

KAPM15813-I

The service and database were stopped.

KAPM15814-I

The HiRDB service was successfully stopped.

KAPM15815-I

bb...bb was set for the aa...aa key in the hcmsdbchgwork_setting file.

aa...aa: Key name

bb...bb: Setting value

KAPM15816-I

The hcmsdbchgwork_setting file was created.

KAPM15820-E

HiRDB is not set up.

KAPM15821-E

The HiRDB setup status is "Standby".

KAPM15822-E

Stopping of the service or database failed.

KAPM15823-E

An internal error occurred.

KAPM15824-E

An unexpected exception occurred.

KAPM15825-E

Starting of the HiRDB service failed.

KAPM15826-E

Stopping of the HiRDB service failed.

KAPM15827-E

Reading of the configuration file failed.

KAPM15828-E

One or more command options are invalid.

KAPM15829-E

A user operation interrupted the command execution.

KAPM15830-E

hcmsdbchgwork command execution failed.

KAPM15831-E

Command execution failed. (return code = aa...aa)

aa...aa: Return code

KAPM15832-E

An invalid value is set in the aa...aa file.

aa...aa: File name

KAPM15833-E

An exception occurred during command execution.

KAPM15834-E

No command arguments are specified.

KAPM15840-I

The hcmdlicenseconvert3 command started.

KAPM15841-I

The hcmdlicenseconvert3 command finished successfully.

KAPM15842-E

The hcmdlicenseconvert3 command failed.

KAPM15845-E

Acquisition of the HBase installation path failed.

KAPM15846-E

Acquisition of the HBase64 installation path failed.

KAPM15847-E

HBase is not installed.

KAPM15848-E

There is no license information file. (type = aa...aa)

aa...aa: Product type

KAPM15849-E

An option is invalid.

KAPM15850-E

An attempt to transfer the license information failed. (type = aa...aa)

aa...aa: Product type

KAPM15852-E

A memory allocation error occurred.

KAPM15853-E

A fatal error occurred.

KAPM15854-W

Log initialization failed.

KAPM15855-W

The license information file at the transfer destination was overwritten. (type = aa...aa)

aa...aa: Product type

KAPM15856-E

Modification of the file attribute failed. (file = aa...aa)

aa...aa: File path

KAPM15857-E

An error occurred in an internal function. (calling function = aa...aa, function used = bb...bb, notes = cc...cc, error

code = dd...dd)

aa...aa: Calling function

bb...bb: Function used

cc...cc: Notes

dd...dd: Error code

KAPM15858-W

There is no license history. (type = aa...aa)

aa...aa: Product type

KAPM15859-W

An attempt to transfer the license history failed. (type = aa...aa)

aa...aa: Product type

KAPM15860-W

An attempt to transfer the license log file failed. (type = aa...aa)

aa...aa: Product type

KAPM15861-W

Creation of the directory for backing up the license history failed. (type = aa...aa)

aa...aa: Product type

KAPM15862-I

The license information file will now be migrated. (type = aa...aa)

aa...aa: Product type

KAPM15872-E

An option is incorrect.

KAPM15873-E

An option is incorrect. (code = [aa...aa], data = [bb...bb])

aa...aa: Code indicating the incorrect location

bb...bb: Incorrect options and values

KAPM15874-I

hcmds64dbconvert [aa...aa]{,[bb...bb],...[...]}

aa...aa: Command line arguments

bb...bb: Command line arguments

KAPM15875-I

The hcmd64dbconvert command started.

KAPM15876-I

The hcmd64dbconvert command finished normally.

KAPM15877-I

Product data will not be registered, because the data will not be migrated. (product name = aa...aa)

aa...aa: Product name

KAPM15900-I

Re-create the database in the following directory.

KAPM15901-I

Set the system area in the following directory.

KAPM15902-I

If you continue, the database will be re-created. Are you sure you want to continue? (y/n) [default=n]

KAPM15903-I

If you continue, the system area will be set. Are you sure you want to continue? (y/n) [default=n]

KAPM15904-E

An option is invalid.

KAPM15905-E

The registered product is not supported by the hcmds64dbinit command. (product name = aa...aa)

aa...aa: Product name

KAPM15906-E

HiRDB has not been set up.

KAPM15907-E

Failed to stop the HiRDB service.

KAPM15908-E

An attempt to perform an unsetup of the database failed. Retry the operation. If the problem persists, contact customer support, who might ask you to collect troubleshooting information.

KAPM15909-E

Failed to start the HiRDB service.

KAPM15910-E

Failed to re-create the database. Remove the cause of the failure to create the database, and then try again. If the problem persists, contact customer support, who might ask you to collect troubleshooting information.

KAPM15911-E

A command of the registered product failed. (product name = aa...aa)

aa...aa: Product name

KAPM15912-E

A fatal error occurred.

KAPM15913-W

An attempt to delete a temporary directory failed. Manually delete the directory. (path = aa...aa)

aa...aa: Path

KAPM15914-I

Processing ended normally.

KAPM15915-E

The parameter definition file of a higher-level product required to re-create the database is corrupted. Restore the parameter definition file, and then try again. (product name = aa...aa)

aa...aa: Product name

KAPM15916-E

The process for re-creating the database will stop because the setup destination of the database cannot be acquired.

KAPM15917-E

The specified directory path is invalid. (path = aa...aa) Specify another directory.

aa...aa: Path

KAPM15918-E

The database setup file remains because an attempt to delete it failed. (path = aa...aa) Manually delete the file.

aa...aa: Path

KAPM15919-I

Re-create the database as the online system of the cluster system in the directory below.

KAPM15922-I

The hcnds64dbinit command started.

KAPM15923-I

The hcnds64dbinit command finished.

KAPM15924-I

Read processing of a recovery file was performed.

KAPM15925-E

A file with the same name as the specified directory name already exists. (path = aa...aa)

aa...aa: Path

KAPM15926-E

An exception occurred.

KAPM15927-E

The absolute path of the location to which the system area was installed cannot be acquired.

KAPM15928-E

The contents of the hcmsdbinit.ini file are invalid.

KAPM15929-E

The hcmsdbset.ini file does not exist.

KAPM15930-E

The hcmsdbsetCheck.ini file does not exist.

KAPM15931-E

The hcmsdbsetOrder.ini file does not exist.

KAPM15932-I

HiRDB is in a stand-alone setup.

KAPM15933-I

HiRDB is in an online setup.

KAPM15934-I

HiRDB is in a standby setup.

KAPM15935-E

The file was not found. (file name = aa...aa)

aa...aa: File name

KAPM15936-E

The database mode is invalid. (mode = aa...aa)

aa...aa: Mode

KAPM15937-E

The path of the location in which the database is stored cannot be acquired. (product name = aa...aa)

aa...aa: Product name

KAPM15938-E

The database has not been set up. (product name = aa...aa)

aa...aa: Product name

KAPM15939-E

Failed to delete the specified file. (path = aa...aa)

aa...aa: Path

KAPM15940-E

The command of the product for re-creating the database does not exist. (product name = aa...aa)

aa...aa: Product name

KAPM15941-E

An attempt to clear a DBMS environment variable failed.

KAPM15942-I

Backup of the configuration file is complete.

KAPM15943-I

Execution of an internal command was successful. (command path = aa...aa, return code = bb...bb)

aa...aa: Command path

bb...bb: Return code

KAPM15944-E

Execution of an internal command failed. (command path = aa...aa, return code = bb...bb)

aa...aa: Command path

bb...bb: Return code

KAPM15945-I

Execution of the hcnds64srv command did not stop the service.

KAPM15946-E

The hcnds64srv command failed to stop the service.

KAPM15947-E

hcnds.home is not set for the environment variable.

KAPM15948-I

File aa...aa will be copied.

aa...aa: File name

KAPM15949-E

The directory name exceeds aa...aa characters.

aa...aa: The number of characters

KAPM15952-I

A command will now be executed. (command line = aa...aa)

aa...aa: Command line

KAPM15953-E

The hcnds64chgtsid command failed.

KAPM15954-E

An option is invalid.

KAPM15955-I

The trusted server ID will be displayed. (trusted server ID = aa...aa)

aa...aa: Trusted server ID

KAPM15956-I

The trusted server ID was changed successfully. (trusted server ID = aa...aa)

aa...aa: Trusted server ID

KAPM15957-E

The trusted server ID file was not found.

KAPM15958-E

Failed to open the trusted server ID file.

KAPM15959-E

A value set in the trusted server ID file is invalid.

KAPM15960-E

The value of hcnds.home could not be acquired.

KAPM15961-E

The trusted server ID was invalid. (trusted server ID = aa...aa)

aa...aa: Trusted server ID

KAPM15962-I

A new settings file was created.

KAPM15963-E

Failed to write to the trusted server ID settings file.

KAPM15964-I

Execution of the hcnds64chgtsid command was successful.

KAPM15966-E

Creation of the settings file failed.

KAPM15967-E

No trusted server ID is specified for the argument.

KAPM15968-E

The length of the trusted server ID exceeds 255 characters.

KAPM15969-E

The trusted server ID is not registered.

KAPM15970-E

The trusted server ID is being used in the trusted server information registered by the hcnds64trust command.
(trusted server ID = aa...aa)

aa...aa: Trusted server ID

KAPM15999-E

An unexpected exception occurred.

KAPM16000-E

Execution of the command for stopping the service failed.

KAPM16001-E

Execution of the command to perform an unsetup of a database failed.

KAPM16002-E

The recovery point is invalid. (recovery point = aa...aa)

aa...aa: Recovery point

KAPM16003-E

The status of the service is invalid. (service status = aa...aa)

aa...aa: Service status

KAPM16004-E

An error occurred during database setup.

KAPM16005-E

The hcmsdbsetRDArea.ini file does not exist.

KAPM16006-E

A user operation interrupted execution of the command.

KAPM16007-E

Execution of the hcmdsgetname command failed.

KAPM16008-I

Processing to stop the HiRDB service is complete.

KAPM16009-I

Deletion of the database is complete.

KAPM16010-I

The processing following deletion of a database is complete.

KAPM16011-I

Processing to start the HiRDB service is complete.

KAPM16012-I

Processing to set up the database is complete.

KAPM16013-I

Execution of the command for re-creating the database of each product is complete.

KAPM16014-I

The recovery point was set up. (recovery point = aa...aa)

aa...aa: Recovery point

KAPM16015-I

Processing to check whether the higher-level product supports database re-creation is complete.

KAPM16016-I

Setup state processing of a database is complete.

KAPM16017-I

Processing to check the parameter definition file is complete.

KAPM16018-I

Processing to delete the HiRDB client environment variable is complete.

KAPM16019-I

The setup mode of the database was set up. (mode = aa...aa)

aa...aa: Mode

KAPM16020-I

The check of the setup state of a database is complete.

KAPM16021-I

The check of the value specified for the databasepath option is complete.

KAPM16022-I

Deployment of the database setup file is complete.

KAPM16023-I

Deployment of a cluster file is complete.

KAPM16024-I

Creation of the directory specified for the databasepath option is complete.

KAPM16025-I

The confirmation message for a non-cluster environment was displayed.

KAPM16026-I

The confirmation message for the online system in a cluster environment was displayed.

KAPM16027-I

The confirmation message for the standby system in a cluster environment was displayed.

KAPM16028-I

The database was set up in the location specified for the databasepath option.

KAPM16029-I

The database was set up in the existing location.

KAPM16031-E

The hcnds64dbinit command could not re-create the database because the hcnds64dbclustersetup command did not finish normally.

KAPM16032-E

The hcnds64dbinit command could not re-create the database because the hcnds64dbrepair command did not finish normally.

KAPM16033-I

The check of whether the database operation completed has finished. (operation = aa..aa)

aa..aa: Command name

KAPM16034-E

The cluster.conf file does not exist.

KAPM16035-E

The contents of the cluster.conf file are invalid.

KAPM16036-I

The entered character was not y or n. Please enter y or n.

KAPM16037-E

Copying of the unload function file failed.

KAPM16038-I

aa...aa

aa...aa: Standard error output

KAPM16052-I

A command will execute. (command line = aa...aa)

aa...aa: Command line

KAPM16053-I

The hcnds64trust command finished successfully.

KAPM16054-E

The hcnds64trust command failed.

KAPM16055-E

An option is invalid.

KAPM16056-E

There is an error in the specified secret.

KAPM16057-W

The trusted server information is not registered.

KAPM16058-I

The registered trusted server information will be output to the screen.

KAPM16059-I

The access point information was registered successfully. (host name = aa...aa, bb...bb = cc...cc, trusted server ID = dd...dd)

aa...aa: Host name

bb...bb: Port type

cc...cc: Port number

dd...dd: Trusted server ID

KAPM16060-I

The trusted server information was deleted successfully. (trusted server ID = aa...aa)

aa...aa: Server ID

KAPM16061-I

All trusted server information was deleted successfully.

KAPM16062-E

The value of hcnds.home could not be acquired.

KAPM16063-E

The trusted server information file was not found.

KAPM16064-E

Failed to delete the trusted server ID because there is no matching trusted server ID.

KAPM16065-E

Failed to delete the trusted server information file.

KAPM16066-E

The trusted server information file was altered.

KAPM16067-E

The hcndsfilehash command failed. (code = aa...aa)

aa...aa: Return code

KAPM16068-E

The setting value for the trusted server information file is invalid.

KAPM16069-E

Failed to read the trusted server information file.

KAPM16070-E

A trusted server ID is invalid. (trusted server ID = aa...aa)

aa...aa: Server ID

KAPM16071-E

No trusted server ID is specified in the argument.

KAPM16072-E

The length of the trusted server ID exceeds 255 characters.

KAPM16073-E

The access point information is invalid. (host name = aa...aa, bb...bb = cc...cc)

aa...aa: Host name

bb...bb: Port type

cc...cc: Port number

KAPM16074-E

Failed to authenticate. (host name = aa...aa, bb...bb = cc...cc)

aa...aa: Host name

bb...bb: Port type

cc...cc: Port number

KAPM16075-E

Failed to connect to the specified server. (host name = aa...aa, bb...bb = cc...cc)

aa...aa: Host name

bb...bb: Port type

cc...cc: Port number

KAPM16076-E

The version of the product for the access point is old.

KAPM16077-E

Failed to create a token.

KAPM16078-E

Failed to connect to the external authentication server.

KAPM16079-E

The DBMS is not running.

KAPM16080-E

Failed to confirm the connection. (host name = aa...aa, bb...bb = cc...cc)

aa...aa: Host name

bb...bb: Port type

cc...cc: Port number

KAPM16081-E

Failed to acquire the trusted server ID from the token.

KAPM16082-E

Failed to write to the trusted server information file.

KAPM16083-E

Failed to acquire the input value.

KAPM16084-W

The specified trusted server information is already registered. (host name = aa...aa, bb...bb = cc...cc)

aa...aa: Host name

bb...bb: Port type
cc...cc: Port number

KAPM16085-E

The specified trusted server information is already registered. (host name = aa...aa, bb...bb = cc...cc)

aa...aa: Host name
bb...bb: Port type
cc...cc: Port number

KAPM16087-E

Resolution of the specified host name failed. (host name = aa...aa)

aa...aa: Host name

KAPM16088-E

Registration failed because the server ID of the specified connection destination is the same as the trusted server ID.
(host name = aa...aa, bb...bb = cc...cc)

aa...aa: Host name
bb...bb: Port type
cc...cc: Port number

KAPM16089-I

A command will execute. (command line = aa...aa)

aa...aa: Command line

KAPM16090-E

The command cannot be executed on the secondary server.

KAPM16091-E

The configuration definition file for SSL communication does not exist.

KAPM16092-E

The specified cipher type is invalid, or the specified cipher suites are invalid. (invalid ciphers = aa...aa)

aa...aa: Invalid ciphers

KAPM16093-E

The specified SSL protocols are invalid. (invalid SSL protocols = aa...aa)

aa...aa: Invalid SSL protocols

KAPM16094-E

An attempt to configure SSL communication failed.

KAPM16095-W

The SSL protocols defined by the cipher type will be used. (cipher type = aa...aa, SSL protocols = bb...bb)

aa...aa: cipher type

bb...bb: SSL protocols

KAPM16096-E

The DBMS of the access point is not running.

KAPM16097-E

The DBMS of the local system is not running.

KAPM16098-E

The DBMS is blocked.

KAPM16099-E

An unexpected exception occurred.

KAPM16100-I

The filesCopy method started.

KAPM16101-I

The file aa...aa already exists.

aa...aa: File path

KAPM16102-I

A file was not copied. (file = aa...aa)

aa...aa: File path

KAPM16103-W

Failed to create a directory. (directory = aa...aa)

aa...aa: Directory path

KAPM16104-I

Copying was successful. (from aa...aa, to bb...bb)

aa...aa: File path

bb...bb: File path

KAPM16105-W

Copying failed. (from aa...aa, to bb...bb)

aa...aa: File path

bb...bb: File path

KAPM16106-E

The specified directory name already exists as a file. (file = aa...aa)

aa...aa: File path

KAPM16107-E

The specified directory was not found. (directory = aa...aa)

aa...aa: Directory path

KAPM16108-E

An IO Exception occurred.

KAPM16109-I

The filesCopy method finished.

KAPM16200-E

The file "aa...aa" is invalid.

aa...aa: File name

KAPM16201-W

The JDK used will be changed to the JDK bundled with the product.

KAPM16202-E

An attempt to acquire the JDK version failed.

KAPM16220-W

The following server certificate will soon expire (days remaining = aa...aa) or has already expired.

aa...aa: Number of days

KAPM16221-W

A server certificate will soon expire (days remaining = aa...aa) or has already expired. (bb...bb)

aa...aa: Number of days

bb...bb: Certificate information

KAPM16222-W

The following server certificate was not found.

KAPM16223-W

A server certificate that is subject to be checked does not exist.

KAPM16224-I

No server certificate will expire within the following number of days: aa...aa.

aa...aa: Number of days

KAPM16225-I

All server certificates are indicated below.

KAPM16226-E

The server certificate information file is invalid. (path = aa...aa)

aa...aa: Path

KAPM16227-E

The hcnds64checkcerts command ended abnormally.

KAPM16228-E

An option is invalid.

KAPM16231-W

Failed to load a server certificate file. (path = aa...aa)

aa...aa: Path

KAPM16232-W

A server certificate will soon expire (days remaining = aa...aa) or has already expired. (bb...bb)

aa...aa: Number of days

bb...bb: Certificate information

KAPM16233-W

A server certificate does not exist. (aa...aa)

aa...aa: Certificate information

KAPM16234-I

A server certificate is indicated. (aa...aa)

aa...aa: Certificate information

KAPM16235-I

The hcnds64checkcerts command started.

KAPM16236-I

The command hcnds64checkcerts will now finish.

KAPM16237-I

hcnds64checkcerts [aa...aa]{, [bb...bb],.....[.....]}

aa...aa: Command line argument

bb...bb: Command line argument

KAPM16238-I

SSL communication for Common Component has not been set.

KAPM16239-E

A syntax error occurred in the user_httpsd.conf file. (path = aa...aa)

aa...aa: Path

KAPM16240-W

The following SSL certificates will expire within aa...aa days or have already expired.

aa...aa: Number of days

KAPM16241-W

The SSL certificate will expire within aa...aa days or has already expired. (bb...bb)

aa...aa: Number of days

bb...bb: Certificate information

KAPM16242-W

The SSL certificate will expire within aa...aa days or has already expired. (bb...bb)

aa...aa: Number of days

bb...bb: Certificate information

KAPM16243-W

The following SSL certificates could not be found.

KAPM16244-W

There are no SSL certificates to be checked.

KAPM16245-I

There are no SSL certificates that will expire within aa...aa days.

aa...aa: Number of days

KAPM16246-I

All SSL certificates are displayed below.

KAPM16247-E

The SSL certificate information file is invalid. (path = aa...aa)

aa...aa: Path

KAPM16248-W

Failed to load the SSL certificate. (path = aa...aa)

aa...aa: Path

KAPM16249-W

The SSL certificate does not exist. (aa...aa)

aa...aa: Certificate information

KAPM16300-I

Information about the SSL certificate is displayed. (aa...aa)

aa...aa: Certificate information

KAPM16400-E

An option is invalid.

KAPM16401-I

A command was executed. (command path = aa...aa, option = bb...bb)

aa...aa: command path

bb...bb: option

KAPM16422-I

hcnds64accountsecret [aa...aa]{,[bb...bb],.....[.....]}

aa...aa: Command line argument

bb...bb: Command line argument

KAPM16423-E

An option is invalid.

KAPM16424-E

An attempt to obtain the secret failed.

KAPM16425-E

There is an error in the specified secret.

KAPM16426-I

The hcnds64accountsecret command started.

KAPM16427-I

The hcnds64accountsecret command finished.

KAPM16429-E

An attempt to delete the secret file failed.

KAPM16430-I

An operation on the secret file failed.

KAPM16431-E

An attempt to change the attributes of the secret file failed.

KAPM16432-E

Execution of the hcndssethiddenfile command failed.

KAPM16433-I

The secret was successfully registered.

KAPM16434-I

The secret function of the account was successfully reset.

KAPM16435-E

An error occurred during encryption processing.

KAPM16436-E

An error occurred during decryption processing.

KAPM16437-E

An error occurred during processing to obtain random numbers.

KAPM16438-E

One or more arguments are invalid.

KAPM16439-E

The hcnds64accountsecret command failed.

KAPM16449-E

A fatal error occurred.

KAPM16450-I

Execution of the method has started.

KAPM16451-I

Execution of the method has finished.

KAPM16452-I

hcnds64restviewuser [aa...aa]{,[bb...bb],.....[.....]}

aa...aa: Command line argument

bb...bb: Command line argument

KAPM16453-E

An option is invalid.

KAPM16454-I

Execution of the hcnds64restviewuser command has started.

KAPM16455-I

Execution of the hcnds64restviewuser command has finished.

KAPM16456-I

Reference permissions were successfully set.

KAPM16457-I

Reference permissions were successfully reset.

KAPM16458-E

The command cannot be executed on the secondary server.

KAPM16459-E

The DBMS is not running.

KAPM16460-E

The specified user does not exist. (user id = aa...aa)

aa...aa: User ID

KAPM16461-E

Authentication failed.

KAPM16462-W

An attempt to reset reference permissions failed because the user does not exist. (user id = aa...aa)

aa...aa: User ID

KAPM16463-I

Reference permissions for all accounts were successfully reset.

KAPM16464-I

There are no accounts that have reference permissions.

KAPM16465-I

Reference permissions for the user were set. (user id = aa...aa)

aa...aa: User ID

KAPM16466-I

Reference permissions for the user were reset. (user id = aa...aa)

aa...aa: User ID

KAPM16467-E

An error occurred when the common repository was accessed.

KAPM16468-E

This operation cannot be performed on built-in user accounts.

KAPM16469-E

Communication with the authentication server failed.

KAPM16479-E

A fatal error occurred.

KAPM16480-I

The method started.

KAPM16481-I

The method finished.

KAPM16482-I

hcmsstartapp [aa...aa]{,[bb...bb],.....[.....]}

aa...aa: Command line argument

bb...bb: Command line argument

KAPM16483-E

An option is invalid.

KAPM16484-I

The command will now be executed. (command line to be executed = aa...aa)

aa...aa: Command line to be executed

KAPM16485-I

aa...aa

aa...aa: Standard error output

KAPM16486-I

aa...aa

aa...aa: Standard output

KAPM16487-I

The command successfully executed.

KAPM16488-W

Execution of the command failed. (return code = aa...aa)

aa...aa: Return code

KAPM16489-E

An error occurred during execution of the command.

KAPM16490-E

An attempt to acquire the HCS operations manager failed.

KAPM16492-E

The specified server is not registered. (server name = aa...aa)

aa...aa: Server name

KAPM16493-E

Analysis of the management file failed.

KAPM16494-E

An attempt to read the management file failed.

KAPM16495-I

A request to start an application was received. (server name = aa...aa, application name = bb...bb)

aa...aa: Server name
bb...bb: Application name

KAPM16496-E

The specified server is not a J2EE server. (server name = aa...aa)

aa...aa: Server name

KAPM16497-E

The J2EE server does not exist.

KAPM16498-E

Execution of the hcndsstartapp command failed.

KAPM16499-E

A fatal error occurred.

KAPM49001-E

aa...aa

aa...aa: Cause that has occurred and the exception object name or back trace of the exception object

2. Messages displayed in the Event tab

The **Event** tab of JPI/OA displays messages that convey system and metric statuses.

This chapter describes the information that is displayed in the **Level** and **Message** columns.

2.1 Information displayed in the Level column

The **Level** column shows the severity level of each message. Messages are classified into the following types:

- Information
- Warning
- Error

2.2 Information displayed in the Message column

2.2.1 Message specification format

In this manual, the information displayed in the **Message** column is specified in the format described below.

Message text

English message

Parameters

Information represented by variables in the message text. The parameters correspond to the variables {0}, {1}, ..., {n} in the order that they appear, starting from the first.

2.2.2 Messages indicating changes in the system status

(1) Information-level messages

Table 2-1 Information-level messages indicating changes in the system status

	Message text	Parameters
1.	{0} was added to the monitored target.	Target resource display name
2.	{0} was excluded from the monitored target.	Target resource display name
3.	A FC port was added. Device=name:{0} Added FC port=name:{1},WWN:{2}	Device display name FC port name Port WWN
4.	A FC connection for storage was added. Device=name:{0} Connected storage=WWN:{1} Connected FC port=WWN:{2}	Device display name Target resource WWN Target port WWN
5.	A FC connection was added. Device=name:{0} Connected FC port=name:{1},WWN:{2}	Device display name Connection-destination FC port name Connection-destination FC port WWN
6.	A management port was added. Device=name:{0} Added management port=IP address:{1}	Device display name IP address
7.	A FC switch port was added. Device=name:{0} Added port=name:{1},WWN:{2},port number:{3}	Device display name, FC port name Port WWN Port number
8.	A drive(mount point) was added. Device=name:{0} Added drive(mount point)=name:{1}	Device display name Mount point

	Message text	Parameters
9.	An accessible FC port was added. Device=name:{0} Permitted FC port=WWN:{1}	Device display name Access-permitted FC port WWN
10.	An accessible LUN was added. Device=name:{0} Added LUN=host LUN:{1},size:{2} bytes	Device display name H-LU number Capacity
11.	A IP switch port was added. Device=name:{0} Added port=MAC address:{1},port number:{2}	Device display name MAC address Port number
12.	A LAN connection was added. Device=name:{0} Connected ethernet port=MAC address:{1}	Device display name Connection-destination MAC address
13.	An iSCSI connection was added. Device=name:{0} Connected iSCSI target=iSCSI name:{1},IP address:{2}	Device display name Connection-destination iSCSI name Connection-destination IP address
14.	A SCSI disk drive was added. Device=name:{0} Added SCSI disk drive=name:{1},model:{2}	Device display name SCSI disk drive name Model
15.	A software was installed. Device=name:{0} Installed software=name:{1}	Device display name Software name
16.	A disk drive was added. Device=name:{0} Added disk drive=name:{1},model:{2}	Device display name Disk drive name Model
17.	A CPU was added. Device=name:{0} Added cpu=name:{1}	Device display name Software name
18.	A disk controller was added. Device=name:{0} Added disk controller=name:{1}	Device display name Disk controller name
19.	A network drive was added. Device=name:{0} Added network drive=host name:{1},share name:{2}	Device display name Server name Share name
20.	An iSCSI software initiator was installed. Device=name:{0} Installed iSCSI software initiator=iSCSI name:{1}	Device display name iSCSI name

	Message text	Parameters
21.	An operating system was installed. Device=name:{0} Installed operating system:{1}	Device display name OS name
22.	A logical volume was added. Device=name:{0} Added volume=name:{1},location:{2}	Device display name Volume name Location (local, network, or unknown)
23.	A file system was added. Device=name:{0} Added file system=name:{1},type:{2}	Device display name File system name File system type
24.	A network adapter was added. Device=name:{0} Added network adapter=name:{1},interface name:{2},manufacturer:{3},MAC address:{4},IP address:{5}	Device display name Adapter display name Interface name Manufacturer MAC address IP address
25.	A file share was added. Device=name:{0} Added file share=name:{1},shared path:{2}	Device display name Share name Shared path
26.	An iSCSI port was added. Device=name:{0} Added iSCSI port=IP address:{1},MAC address:{2}	Device display name IP address MAC address
27.	A host group was added. Device=name:{0} Added host group=name:{1} FC port=name:{2}	Device display name Host group name FC port name
28.	An iSCSI target was added. Device=name:{0} Added iSCSI target=target name:{1},iSCSI name:{2}	Device display name Target name iSCSI name
29.	An accessible iSCSI initiator was added. Device=name:{0} Permitted iSCSI initiator=iSCSI name:{1}	Device display name Access-permitted iSCSI initiator name
30.	A logical unit was added. Device=name:{0} Added logical unit=logical unit number:{1},size:{2} bytes	Device display name Logical unit number Capacity
31.	A parity group was added. Device=name:{0} Added parity group=parity group name:{1},size:{2} bytes	Device display name Parity group name Capacity

	Message text	Parameters
32.	A storage controller was added. Device=name:{0} Added storage controller=name:{1}	Device display name Controller name
33.	A storage disk drive was added. Device=name:{0} Added disk drive=disk number:{1}	Device display name Disk number
34.	A power supply was added. Device=name:{0} Added power supply=name:{1},device ID:{2}	Device display name Component display name Device ID
35.	A fan was added. Device=name:{0} Added fan=name:{1},device ID:{2}	Device display name Component display name Device ID
36.	A battery was added. Device=name:{0} Added battery=name:{1},device ID:{2}	Device display name Component display name Device ID
37.	A cache was added. Device=name:{0} Added cache=name:{1},device ID:{2}	Device display name Component display name Device ID
38.	A virtual machine was added. Device=name:{0} Added virtual machine=name:{1},OS:{2},UUID:{3},VMware tools version:{4}	Device display name Virtual machine name OS name UUID VMware Tools version
39.	A virtual machine can no longer be recognized. Device=name:{0} Unrecognizable virtual machine=name:{1},OS:{2},UUID:{3},VMware tools version:{4}	Device display name Virtual machine name OS name UUID VMware Tools version
40.	A VM Kernel NIC was added. Device=name:{0} Added VM Kernel NIC=IP address:{1},subnet mask:{2},MAC address:{3}	Device display name IP address Subnet mask MAC address
41.	A service console NIC was added. Device=name:{0} Added service console NIC=IP address:{1},subnet mask:{2}	Device display name IP address Subnet mask
42.	A virtual switch was added. Device=name:{0} Added virtual switch=name:{1}	Device display name Device name

	Message text	Parameters
43.	A port group was added. Device=name:{0} Added port group=name:{1},VLAN ID:{2}	Device display name Port group name VLAN ID
44.	A FC network port was added. Device=name:{0} Added FC network port=portWwn:{1}, portName:{2},	Device display name Port WWN Port name
45.	An IP network port was added. Device=name:{0} Added IP network port=MAC address:{1}, IP address:{2}, subnet mask:{3}	Device display name MAC address IP address Subnet mask
46.	A capacity was added. Device=name:{0} Added capacity=name:{1}, capacity:{2} bytes, free space:{3} bytes	Device display name Capacity name Maximum capacity Available capacity
47.	A software was installed. Device=name:{0} Installed software=name:{1}, version:{2}	Device display name Software name Software version
48.	An iSCSI Initiator was added. Device=name:{0} Added iSCSI Initiator=iSCSI name:{1}	Device display name iSCSI name
49.	A permitted iSCSI initiator was added. Device=name:{0} Permitted iSCSI initiator=iSCSI name:{1}	Device display name iSCSI name
50.	A permitted WWN initiator was added. Device=name:{0} Permitted WWN=WWN name:{1}	Device display name WWN name
51.	A file share was added. Device=name:{0} Added file share=name:{1}, path:{2}	Device display name File share name Shared file path
52.	A file system was added. Device=name:{0} Added file system=name:{1}, size:{2} bytes, free space:{3} bytes	Device display name File system name Maximum capacity Available capacity
53.	{0} failed in connection.	Resource name
54.	MonitoringStatus attribute of {0} has changed to an Error status.	Resource name
55.	Unreachable attribute of {0} is changed from Error status to Normal status.	Resource name
56.	MonitoringStatus attribute of {0} has changed to a Normal status.	Resource name

	Message text	Parameters
57.	The service is monitored. Device=name:{0} Service=name:{1}	Device display name Service display name
58.	The service is not monitored. Device=name:{0} Service=name:{1}	Device display name Service display name
59.	Service was not found to match pattern(name:{0}). Device=name:{1}	Pattern display name Device display name
60.	{1} on {0} changed to an Error status. Details: {2}	Resource name Component name Status
61.	{1} on {0} changed to a Warning status. Details: {2}	Resource name Component name Status
62.	{1} on {0} changed to an Unknown status. Details: {2}	Resource name Component name Status
63.	The status of {0} could not be obtained. Please refer to the log.	Resource name
64.	The name of the FC network port was changed from {0} to {1}. Device=name:{2} FC network port=name:{3}, WWN={4}	Old port name New port name Device display name Port name Port WWN
65.	The FC network port WWN was changed from {0} to {1}. Device=name:{2} FC network port=name:{3}, WWN={4}	Old WWN New WWN Device display name Port name Port WWN
66.	The maximum capacity size was changed from {0} bytes to {1} bytes. Device=name:{2} Capacity=name:{3}, size:{4} bytes, free space:{5} bytes	Old maximum capacity New maximum capacity Device display name Capacity name Maximum capacity Available capacity

	Message text	Parameters
67.	The capacity name was changed from {0} to {1}. Device=name:{2} Capacity=name:{3}, size:{4} bytes, freeSpace:{5} bytes	Old name New name Device display name Capacity name Maximum capacity Available capacity
68.	The version of the installed software was changed from {0} to {1}. Device=name:{2} Installed software=name:{3}, version:{4}	Old version New version Device display name Software name Software version
69.	The IP address of the IP network port was changed from {0} to {1}. Device=name:{2} IP network port=IP address:{3}, MAC address:{4}, subnet mask:{5}	Old IP address New IP address Device display name IP address MAC address Subnet mask
70.	The MAC address of the IP network port was changed from {0} to {1}. Device=name:{2} IP network port=IP address:{3}, MAC address:{4}, subnet mask:{5}	Old MAC address New MAC address Device display name IP address MAC address Subnet mask
71.	The subnet mask of the IP network port was changed from {0} to {1}. Device=name:{2} IP network port=IP address:{3}, MAC addresss:{4}, subnet mask:{5}	Old subnet New subnet Device display name IP address MAC address Subnet mask
72.	The iSCSI name of the iSCSI Initiator was changed from {0} to {1}. Device=name:{2} iSCSI Initiator=iSCSI name:{3}	Old iSCSI name New iSCSI name Device display name iSCSI name
73.	The iSCSI name of the permitted iSCSI Initiator was changed from {0} to {1}. Device=name:{2} Permitted iSCSI Initiator=iSCSI name:{3}	Old iSCSI name New iSCSI name Device display name iSCSI name

	Message text	Parameters
74.	The WWN name of the permitted WWN was changed from {0} to {1}. Device=name:{2} Permitted WWN=WWN name:{3}	Old WWN New WWN Device display name WWN name
75.	The path of the file share was changed from {0} to {1}. Device=name:{2} File share=name:{3}	Old path New path Device display name File share display name
76.	The MAC address of the file share port was changed from {0} to {1}. Device=name:{2} File share port=name:{3}, IP address:{4}, subnet mask:{5}	Old address New address Device display name Port display name IP address Subnet mask
77.	The subnet mask of the file share port was changed from {0} to {1}. Device=name:{2} File share port=name:{3}, IP address:{4}, MAC address:{5}	Old subnet New subnet Device display name Port display name IP address MAC address
78.	The size of the file system was changed from {0} bytes to {1} bytes. Device=name:{2} File system=name:{3}, free space:{4} bytes	Old maximum capacity New maximum capacity Device display name File system name Available capacity
79.	The share name of the file system was changed from {0} to {1}. Device=name:{2} File system=size:{3} bytes, free space:{4} bytes	Old share name New share name Device display name Maximum capacity Available capacity
80.	The name of the virtual CPU of the Management OS was changed from {0} to {1}. Device=name:{2} CPU=name:{3}	Old CPU name New CPU name Device display name CPU name
81.	The supported SNMP version was changed from {0} to {1}. Device=name:{2}	Old SNMP version New SNMP version Device display name

	Message text	Parameters
82.	The host name of the virtual machine was changed from {0} to {1}. Device=name:{2}	Old host name New host name Device display name
83.	The manufacturer of the disk controller was changed from {0} to {1}. Device=name:{2} Disk controller=name:{3}, device ID:{4}, manufacturer:{5}	Old manufacturer New manufacturer Device display name Disk controller name Device ID Manufacturer
84.	The manufacturer of the disk drive was changed from {0} to {1}. Device=name:{2} Disk drive=drive name:{3}, device name:{4}, model:{5}, manufacturer:{6}	Old manufacturer New manufacturer Device display name Disk drive name Device name Model Manufacturer
85.	The type of the FC network port was changed from {0} to {1}. Device=name:{2} FC network port=name:{3}, WWN:{4}, port type:{5}	Old port type New port type Device display name Port name WWN Port type
86.	The name of the FC-HBA port was changed from {0} to {1}. Device=name:{2} FC-HBA Port=name:{3}, WWN:{4}, port speed:{5}	Old port name New port name Device display name Port name WWN Port speed
87.	The FC port of the FC switch was changed from {0} to {1}. Device=name:{2} FC Port=name:{3}, WWN:{4}, port speed:{5}	Old port name New port name Device display name Port name WWN Port speed

	Message text	Parameters
88.	The FC port of the storage subsystem was changed from {0} to {1}. Device=name:{2} FC Port=name:{3}, WWN:{4}	Old port name New port name Device display name Port name WWN
89.	The fabric name of the FC switch was changed from {0} to {1}. Device=name:{2}, fabric name:{3}	Old fabric name New fabric name Device display name Fabric name
90.	The type of the capacity was changed from {0} to {1}. Device=name:{2} Capacity=name:{3}, size:{4}, type:{5}	Old type New type Device display name Name Capacity Type
91.	The name of the installed software was changed from {0} to {1}. Device=name:{2} Installed Software=name:{3}, version:{4}, installed date:{5}	Old name New name Device display name Name Version Installation date/time
92.	The installed date of the installed software was changed from {0} to {1}. Device=name:{2} Installed Software=name:{3}, version:{4}, installed date:{5}	Old name New name Device display name Name Version Installation date/time
93.	The vendor of the HBA was changed from {0} to {1}. Device=name:{2} HBA=name:{3}, model:{4}, firmware version:{5}, vendor:{6}	Old vendor New vendor Device display name Name Model Firmware Vendor

	Message text	Parameters
94.	The model of the HBA was changed from {0} to {1}. Device=name:{2} HBA=name:{3}, model:{4}, firmware version:{5}, vendor:{6}	Old model name New model name Device display name Name Model Firmware Vendor
95.	The firmware version of the network adapter was changed from {0} to {1}. Device=name:{2} Network Adapter=name:{3}, device ID:{4}, manufacturer:{5}, IP address:{6}, MAC address:{7}, firmware version:{8}, driver version:{9}	Old firmware New firmware Device display name Name Device ID Manufacturer IP address MAC address Firmware Driver
96.	The firmware version of the network adapter was changed from {0} to {1}. Device=name:{2} Network Adapter=name:{3}, device ID:{4}, manufacturer:{5}, IP address:{6}, MAC address:{7}, firmware version:{8}, driver version:{9}	Old driver New driver Device display name Name Device ID Manufacturer IP address MAC address Firmware Driver
97.	{0} was added.	Element name (ElementName) of the component
98.	A CPU was added. Device=name:{0} Added CPU=name:{1}	Device display name, CPU display name
99.	A virtual machine was added. Device=name:{0} Added virtual machine=name:{1},OS:{2},UUID:{3}	Device display name Virtual machine name OS name UUID

	Message text	Parameters
100.	A virtual machine can no longer be recognized. Device=name:{0} Unrecognizable virtual machine=name:{1},OS:{2},UUID:{3}	Device display name Virtual machine name OS name UUID
101.	The monitoring mode of {0} was changed to the suspension.	Target device display name
102.	{0} was deleted.(component type:{1})	Component name Component type
103.	A fan was added. Device=name:{0} Added fan=name:{1},device ID:{2}	Device display name Device display name Device ID
104.	A logical drive was added. Device=name:{0} Added logical drive=name:{1},device ID:{2}	Device display name Device display name Device ID
105.	A physical drive was added. Device=name:{0} Added physical drive=name:{1},device ID:{2}	Device display name Device display name Device ID
106.	A power supply was added. Device=name:{0} Added power supply=name:{1},device ID:{2}	Device display name Device display name Device ID
107.	A storage management battery was added. Device=name:{0} Added storage management battery=name:{1},device ID:{2}	Device display name Device display name Device ID
108.	A storage management was added. Device=name:{0} Added storage management=name:{1},device ID:{2}	Device display name Device display name Device ID
109.	A temperature sensor was added. Device=name:{0} Added temperature sensor=name:{1},device ID:{2}	Device display name Device display name Device ID
110.	A voltage sensor was added. Device=name:{0} Added voltage sensor=name:{1},device ID:{2}	Device display name Device display name Device ID
111.	The storage volume can now be managed.	
112.	A memory was added. Device=name:{0}, total size:{1} bytes	Device display name Memory capacity

	Message text	Parameters
113.	A raw mapped virtual disk was added. Device=name:{0} Added raw mapped virtual disk=name:{1}, device name:{2}, size:{3} bytes, mode:{4}	Device display name Disk name Device name Size Mode
114.	A virtual disk was added. Device=name:{0} Added virtual disk=name:{1}, size:{2} bytes	Device display name Disk name Size
115.	A virtual NIC was added. Device=name:{0} Added virtual NIC=IP address:{1}, MAC address:{2}	Device display name, IP address MAC address
116.	The number of ports of the Storage Controller was changed from {0} to {1}. Device=name:{2} Storage Controller=name:{3}, number of ports:{4}	Number of old ports Number of new ports Device display name Controller name Number of ports
117.	The file share port of the storage subsystem was added. Device=name:{0} Port=IP address:{1}, subnet mask:{2}, MAC address:{3}	Device display name IP address Subnet mask MAC address
118.	The size of the LUN was changed from {0} bytes to {1} bytes. Device=name:{2} LUN=name:{3}, LU num:{4}, size:{5} bytes	Old value New value Device display name LU name LU number Size
119.	A connected Ethernet Port was added. Device=name:{0} Connected Port=MAC address:{1}, PortID:{2}, VLAN ID:{3}	Device display name MAC address Port number VLAN ID
120.	A connected FC Port was added. Device=name:{0} Connected Port=WWN:{1}	Device display name WWN

	Message text	Parameters
121.	The Port ID of the Connected Ethernet Port was changed from {0} to {1}. Device=name:{2} Connected Port=MAC Address:{3}, PortID:{4}, VLAN ID:{5}	Old value New value Device display name MAC address Port ID VLAN ID
122.	The installed date of the installed software was changed from {0} to {1}. Device=name:{2} Installed Software=name:{3}, version:{4}, installed date:{5}	Old value New value Device display name Software name Version Installation date/time
123.	The device ID of the disk controller was changed from {0} to {1}. Device=name:{2} Disk controller=name:{3}, device ID:{4}, manufacturer:{5}	Old value New value Device display name Controller name Device ID Manufacturer
124.	The MAC address of the management port was changed from {0} to {1}. Device=name:{2} Management Port=IP address:{3}, MAC address:{4}, subnet mask:{5}	Old value New value Device display name IP address MAC address Subnet mask
125.	The subnet mask of the management port was changed from {0} to {1}. Device=name:{2} Management Port=IP address:{3}, MAC address:{4}, subnet mask:{5}	Old value New value Device display name IP address MAC address Subnet mask
126.	The name of the virtual disk was changed from {0} to {1}. Device=name:{2} Virtual disk=name:{3}, size:{4} bytes	Old value New value Device display name Disk name Size

	Message text	Parameters
127.	The type of the storage file system was changed from {0} to {1}. Device=name:{2} File system=name:{3}, size:{4} bytes, free space:{5} bytes	Old value New value Device display name Disk name Size Available capacity
128.	The FC ID of the FC port to which a connection was established was changed from {0} to {1}. Device=name:{2} Connected Fc Port=name:{3}, target resource WWN:{4}, target port WWN:{5}	Old value New value Host name Target name Target resource WWN Target port WWN
129.	The resource WWN of the FC port to which a connection was established was changed from {0} to {1}. Device=name:{2} Connected Fc Port=name:{3}, target resource WWN:{4}, target port WWN:{5}	Old value New value Host name Target name Target resource WWN Target port WWN
130.	The iSCSI Name of the Connected iSCSI Target was changed from {0} to {1}. Device=name:{2} Connected iSCSI Target=name:{3}, target iSCSI name:{4}, target IP address:{5}	Old value New value Host name Device name Target resource iSCSI name Target IP address
131.	A FC connection was added. Device=name:{0} FC port=name:{1}, WWN:{2} Connected FC port=linked WWN:{3}	Device display name Connection-source FC port name Connection-source FC port WWN Connection-destination FC port WWN
132.	A memory size was changed from {0} bytes to {1} bytes. Device=name:{2} Total memory:{3} bytes	Old memory capacity New memory capacity Device display name Memory capacity

	Message text	Parameters
133.	{2} was added to {1}. Source device=name:{0} UUID:{3}	Source device display name Destination device display name Virtual machine name UUID
134.	{2} was removed from {0}. Destination device=name:{1} UUID:{3}	Source device display name Destination device display name Virtual machine name UUID
135.	A file system was added to {1}. Device=name:{0} File system=name:{2}, size:{3} bytes, free space:{4} bytes	Device display name Virtual machine name File system name Size Available capacity
136.	A file system can no longer be recognized from {1}. Device=name:{0} File system=name:{2}, size:{3} bytes, free space:{4} bytes	Device display name Virtual machine name File system name Size Available capacity
137.	A virtual NIC was added to {1}. Device=name:{0} Added virtual NIC=IP address:{2}, MAC address:{3}	Device display name Virtual machine name IP address MAC address
138.	A virtual NIC can no longer be recognized from {1}. Device=name:{0} Unrecognizable virtual NIC=IP address:{2}, MAC address:{3}	Device display name Virtual machine name IP address MAC address
139.	A virtual disk was added to {1}. Device=name:{0} Added virtual disk=name:{2}, size:{3} bytes	Device display name Virtual machine name Device name Size
140.	A virtual disk can no longer be recognized from {1}. Device=name:{0} Unrecognizable virtual disk=name:{2}, size:{3} bytes	Device display name Virtual machine name Device name Size

	Message text	Parameters
141.	A memory size of the virtual machine was changed from {0} bytes to {1} bytes. Device=name:{2} Virtual machine=host name:{4}, total memory:{3} bytes	Old memory capacity New memory capacity Device display name Memory capacity Host name
142.	The number of CPU cores of the virtual machine was changed from {0} to {1}. Device=name:{2} Virtual machine=host name:{4}, number of CPU cores:{3}	Number of old CPU cores Number of new CPU cores Device display name Number of CPU cores Host name
143.	A DP pool was added. Device=name:{0} Added DP pool=DP pool name:{1}, size:{2} bytes	Device display name DP pool name Capacity
144.	A DP pool can no longer be recognized. Device=name:{0} Unrecognizable DP pool=DP pool name:{1}, size:{2} bytes	Device display name DP pool name Capacity
145.	A storage MPB was added. Device=name:{0} Added storage MPB=ID:{1}	Device display name MPB ID
146.	A storage MPB can no longer be recognized. Device=name:{0} Unrecognizable storage MPB=ID:{1}	Device display name MPB ID
147.	A DP pool Tier was added. Device=name:{0} Added DP pool Tier=DP Pool name:{1}; ID:{2}	Device display name DP pool name Tier ID
148.	A DP Pool Tier can no longer be recognized. Device=name:{0} Unrecognizable DP pool Tier=DP Pool name:{1}; ID:{2}	Device display name DP pool name Tier ID
149.	The storage cache size was changed from {0} bytes to {1} bytes. Device=name:{2}, cache size:{3} bytes	Old cache capacity New cache capacity Device display name Cache capacity
150.	The DP pool size was changed from {0} bytes to {1} bytes. Device=name:{2} DP pool=DP pool name:{3}, size:{4} bytes	Old capacity New capacity Device display name DP pool name Capacity

	Message text	Parameters
151.	A storage was added. Device=name:{0} Added storage=name:{1}	Name of managed device Storage name
152.	A storage can no longer be recognized. Device=name:{0} Unrecognizable Storage=name:{1}	Name of managed device Storage name
153.	The performance status of "IP Pkts Sent" in {1} on {0} changed from Unknown to Ignored.	Resource name Component name
154.	The processing to update resource information was successfully recovered by updating the resource credential information. (resource:{0})	Resource name
155.	The collector or discovery processing was successfully recovered by updating the resource credential information. (credential:{0})	Credential name
156.	The performance status of "Disk Read" in {1} on {0} changed from Ignored to Monitor Off.	Resource name Component name
157.	The performance status of "Disk Write" in {1} on {0} changed from Ignored to Monitor Off.	Resource name Component name
158.	Management IP address was changed from {0} to {1}.	Old management IP address New management IP address
159.	The firmware version was changed from {0} to {1}. Device=name:{2} Firmware=version:{3}	Old firmware version New firmware version Device display name Firmware version
160.	The FC port target was changed from {0} to {1}. Device=name:{2} Target resource=resource WWN:{3},target FC port WWN:{4},target FC ID:{5}	Old connection-destination port WWN New connection-destination port WWN Resource display name Connection-destination resource WWN Connection-destination port WWN Connection-destination FC ID

	Message text	Parameters
161.	The IP address of the iSCSI target was changed from {0} to {1}. Device=name:{2} iSCSI target=target iSCSI name:{3},target IP address:{4}	Old connection-destination IP address New connection-destination IP address Device display name Connection-destination iSCSI name Connection-destination IP address
162.	The CPU was changed from {0} to {1}. Device=name:{2} CPU=name:{3}	Old CPU display name New CPU display name Device display name CPU display name
163.	The disk controller was changed from {0} to {1}. Device=name:{2} Disk controller=name:{3},device ID:{4}	Old disk controller name New disk controller name Device display name Disk controller name Device ID
164.	The disk drive was changed from {0} to {1}. Device=name:{2} Disk drive=drive name:{3},device name:{4},model:{5},interface:{6},size:{7} bytes	Old model or interface New model or interface Device display name Drive name Device name Model Interface Capacity
165.	The server IP address was changed from {0} to {1}. Device=name:{2} Network adapter=name:{3},IP address:{4},subnet mask:{5},MAC address:{6}	Old IP address New IP address Device display name Adapter display name IP address Subnet mask MAC address

	Message text	Parameters
166.	The storage IP address was changed from {0} to {1}. Device=name:{2} Storage controller=name:{3} iSCSI port=IP address:{4},subnet mask:{5},MAC address:{6}	Old IP address New IP address Device display name Controller name IP address Subnet mask MAC address
167.	The server subnet mask was changed from {0} to {1}. Device=name:{2} Network adapter=name:{3},IP address:{4},subnet mask:{5},MAC address:{6}	Old subnet mask New subnet mask Device display name Adapter display name IP address Subnet mask MAC address
168.	The storage subnet mask was changed from {0} to {1}. Device=name:{2} Storage controller=name:{3} iSCSI port=IP address:{4},subnet mask:{5},MAC address:{6}	Old subnet mask New subnet mask Device display name Controller name IP address Subnet mask MAC address
169.	The server LAN port was changed from {0} to {1}. Device=name:{2} Network adapter=name:{3},IP address:{4},subnet mask:{5},MAC address:{6}	Old MAC address New MAC address Device display name Adapter display name IP address Subnet mask MAC address
170.	The storage iSCSI port was changed from {0} to {1}. Device=name:{2} Storage controller=name:{3} iSCSI port=IP address:{4},subnet mask:{5},MAC address:{6}	Old MAC address New MAC address Device display name Controller name IP address Subnet mask MAC address

	Message text	Parameters
171.	The file share protocol was changed from {0} to {1}. Device=name:{2} File share=name:{3},protocol:{4},pathname:{5}	Old protocol New protocol Device display name Share name Shared protocol Path name
172.	The file share path was changed from {0} to {1}. Device=name:{2} File share=name:{3},protocol:{4},pathname:{5}	Old path name New path name Device display name Share name Shared protocol Path name
173.	The FC ID was changed from {0} to {1}. Device=name:{2} FC port=WWN:{3},FCID:{4}	Old FC ID New FC ID Device display name Port WWN FC ID
174.	The FC port speed was changed from {0} to {1}. Device=name:{2} FC port=WWN:{3},FCID:{4},speed:{5}	Old port speed New port speed Device display name Port WWN FC ID Port speed
175.	The FC switch mode was changed from {0} to {1}. Device=name:{2} FC switch=mode:{3}	Old operating mode New operating mode Device display name Operating mode
176.	The FC switch domain ID was changed from {0} to {1}. Device=name:{2} FC switch=domain ID:{3}	Old domain number New domain number Device display name Domain number
177.	The resource WWN was changed from {0} to {1}. Device=name:{2} FC switch=resource WWN:{3}	Old resource WWN New resource WWN Device display name Resource WWN

	Message text	Parameters
178.	The FC switch name was changed from {0} to {1}. Device=name:{2} FC switch=device name:{3}	Old device name New device name Device display name Device name
179.	The FC switch port speed was changed from {0} to {1}. Device=name:{2} FC switch port= port number:{3},speed:{4}	Old port speed New port speed Device display name Port number Port speed
180.	The FC switch port number was changed from {0} to {1}. Device=name:{2} FC switch port=port number:{3},WWN:{4}	Old port number New port number Device display name Port number Port WWN
181.	The FC switch port mode was changed from {0} to {1}. Device=name:{2} FC switch port= port number:{3},mode:{4}	Old operating mode New operating mode Device display name Port number Operating mode
182.	The FC switch port type was changed from {0} to {1}. Device=name:{2} FC switch port= port number:{3},port type:{4}	Old port type New port type Device display name Port number Port type
183.	The file system type was changed from {0} to {1}. Device=name:{2} File system=name:{3},type:{4}	Old file system type New file system type Device display name File system name File system type
184.	The file system size was changed from {0} bytes to {1} bytes. Device=name:{2} File system=name:{3},size:{4} bytes	Old size, New size Device display name File system name Size

	Message text	Parameters
185.	The HBA firmware version was changed from {0} to {1}. Device=name:{2} HBA=device ID:{3},model:{4},serial number:{5},firmware version:{6},driver version:{7}	Old firmware version New firmware version Device display name Device ID Model Serial number Firmware version Driver version
186.	The HBA was changed from {0} to {1}. Device=name:{2} HBA=device ID:{3},model:{4},serial number:{5},firmware version:{6},driver version:{7}	Old serial number New serial number Device display name Device ID Model Serial number Firmware version Driver version
187.	The HBA driver version was changed from {0} to {1}. Device=name:{2} HBA=device ID:{3},model:{4},serial number:{5},firmware version:{6},driver version:{7}	Old driver version New driver version Device display name Device ID Model Serial number Firmware version Driver version
188.	The software version was changed from {0} to {1}. Device=name:{2} Installed software=name:{3},version:{4}	Old version New version Device display name Software name Version
189.	The IP switch device name was changed from {0} to {1}. Device=name:{2} IP switch=device name:{3}	Old device name New device name Device display name Device name

	Message text	Parameters
190.	The IP switch port speed was changed from {0} bps to {1} bps. Device=name:{2} IP switch port=port number:{3},MAC address:{4},speed:{5} bps	Old line speed New line speed Device display name Port number MAC address Line speed
191.	The IP switch port number was changed from {0} to {1}. Device=name:{2} IP switch port= port number:{3},MAC address:{4},speed:{5} bps	Old port number New port number Device display name Port number MAC address Line speed
192.	The IP switch port was changed from {0} to {1}. Device=name:{2} IP switch port= port number:{3},MAC address:{4},speed:{5} bps	Old MAC address New MAC address Device display name Port number MAC address Line speed
193.	The driver version of the iSCSI software initiator was changed from {0} to {1}. Device=name:{2} iSCSI software initiator=iSCSI name:{3},driver ID:{4},driver version:{5}	Old driver version New driver version Device display name iSCSI name Driver ID Driver version
194.	The memory size was changed from {0} bytes to {1} bytes. Device=name:{2} Total memory:{3} bytes	Old memory capacity New memory capacity Device display name Memory capacity
195.	The device ID of the network adapter was changed from {0} to {1}. Device=name:{2} Network adapter=name:{3},device ID:{4},interface name:{5},manufacturer:{6},MAC address:{7},IP address:{8}	Old device ID New device ID Device display name Adapter display name Device ID Interface name Manufacturer MAC address IP address

	Message text	Parameters
196.	The network adapter was changed from {0} to {1}. Device=name:{2} Network adapter=name:{3},device ID:{4},interface name:{5},manufacturer:{6},MAC address:{7},IP address:{8}	Old manufacturer New manufacturer Device display name Adapter display name Device ID Interface name Manufacturer MAC address IP address
197.	The interface name of the network adapter was changed from {0} to {1}. Device=name:{2} Network adapter=name:{3},device ID:{4},interface name:{5},manufacturer:{6},MAC address:{7},IP address:{8}	Old interface name New interface name Device display name Adapter display name Device ID Interface name Manufacturer MAC address IP address
198.	The share name of the network drive was changed from {0} to {1}. Device=name:{2} Network drive=host name:{3},share name:{4}	Old share name New share name Device display name Server name Share name
199.	The host name of the network drive was changed from {0} to {1}. Device=name:{2} Network drive=host name:{3},share name:{4}	Old server name New server name Device display name Server name Share name
200.	The operating system was changed from {0} to {1}. Device=name:{2} Operating system=name:{3},version:{4}	Old OS name New OS name Device display name OS name OS version
201.	The operating system version was changed from {0} to {1}. Device=name:{2} Operating system=name:{3},version:{4}	Old OS version New OS version Device display name OS name OS version

	Message text	Parameters
202.	The target of the SCSI disk drive was changed from {0} to {1}. Device=name:{2} SCSI disk drive=name:{3},model:{4},port number:{5},bus ID:{6},target ID:{7},LUN ID:{8}	Old target ID New target ID Device display name Drive name Model Adapter number Bus ID Target ID LUN ID
203.	The port number of the SCSI disk drive was changed from {0} to {1}. Device=name:{2} SCSI disk drive=name:{3},model:{4},port number:{5},bus ID:{6},target ID:{7},LUN ID:{8}	Old adapter number New adapter number Device display name Drive name Model Adapter number Bus ID Target ID LUN ID
204.	The LUN of the SCSI disk drive was changed from {0} to {1}. Device=name:{2} SCSI disk drive=name:{3},model:{4},port number:{5},bus ID:{6},target ID:{7},LUN ID:{8}	Old LUN ID New LUN ID Device display name Drive name Model Adapter number Bus ID Target ID LUN ID
205.	The bus ID of the SCSI disk drive was changed from {0} to {1}. Device=name:{2} SCSI disk drive=name:{3},model:{4},port number:{5},bus ID:{6},target ID:{7},LUN ID:{8}	Old bus ID New bus ID Device display name Drive name Model Adapter number Bus ID Target ID LUN ID

	Message text	Parameters
206.	The host name was changed from {0} to {1}. Device=name:{2},host name:{3},type:{4}	Old host name New host name Device display name Host name Virtualization type
207.	The server type was changed from {0} to {1}. Device=name:{2},host name:{3},type:{4}	Old virtualization type New virtualization type Device display name Host name Virtualization type
208.	The iSCSI target name was changed from {0} to {1}. Device=name:{2} iSCSI target=target name:{3},iSCSI name:{4}	Old target name New target name Device display name Target name iSCSI name
209.	The parity group size was changed from {0} bytes to {1} bytes. Device=name:{2} Parity group=parity group name:{3},size:{4} bytes	Old capacity New capacity Device display name Parity group name Capacity
210.	The storage name was changed from {0} to {1}. Device=name:{2},device name:{3}	Old device name New device name Device display name Device name
211.	The logical unit size was changed from {0} bytes to {1} bytes. Device=name:{2} Logical unit=logical unit number:{3},size:{4} bytes	Old capacity New capacity Device display name LUN Capacity
212.	The share name of the logical volume was changed from {0} to {1}. Device=name:{2} Volume=name:{3},location:{4},provider name:{5},size:{6} bytes	Old netClient server name New netClient server name Device display name Volume name Drive location netClient server name Capacity

	Message text	Parameters
213.	The logical volume location was changed from {0} to {1}. Device=name:{2} Volume=name:{3},location:{4},provider name:{5},size:{6} bytes	Old drive location New drive location Device display name Volume name Drive location netClient server name Capacity
214.	The logical volume size was changed from {0} bytes to {1} bytes. Device=name:{2} Volume=name:{3},location:{4},provider name:{5},size:{6} bytes	Old capacity New capacity Device display name Volume name Drive location netClient server name Capacity
215.	The VMware Tools version was changed from {0} to {1}. Device=name:{2} Virtual machine=name:{4},VMware Tools version:{3}	Old VMware Tools version New VMware Tools version Device display name VMware Tools version Host name
216.	The OS of the virtual machine was changed from {0} to {1}. Device=name:{2} Virtual Machine=host name:{4},OS:{3}	Old OS name New OS name Device display name OS name Host name
217.	The virtual disk size was changed from {0} bytes to {1} bytes. Device=name:{2} Virtual disk=name:{3},size:{4} bytes	Old disk capacity New disk capacity Device display name Virtual disk name Disk capacity
218.	The compatibility mode was changed from {0} to {1}. Device=name:{2} Raw mapped virtual disk=name:{3},compatibility mode:{4}	Old compatibility mode New compatibility mode Device display name Device name Compatibility mode

	Message text	Parameters
219.	The subnet mask of the VM Kernel NIC was changed from {0} to {1}. Device=name:{2} VM Kernel NIC=MAC address:{3},IP address:{4},subnet mask:{5}	Old subnet mask New subnet mask Device display name MAC address IP address Subnet mask
220.	The subnet mask of the service console NIC was changed from {0} to {1}. Device=name:{2} Service console NIC= MAC address:{3},IP address:{4},subnet mask:{5}	Old subnet mask New subnet mask Device display name MAC address IP address Subnet mask
221.	The drive name of the disk drive was changed from {0} to {1}. Device=name:{2} Disk drive=drive name:{3},device name:{4},model:{5},interface:{6},size:{7} bytes	Old drive name New drive name Device display name Drive name Device name Model Interface Capacity
222.	The disk drive size was changed from {0} bytes to {1} bytes. Device=name:{2} Disk drive=drive name:{3},device name:{4},model:{5},interface:{6},size:{7} bytes	Old capacity New capacity Device display name Drive name Device name Model Interface Capacity
223.	The FC switch type was changed from {0} to {1}. Device=name:{2},type:{3}	Old type New type Device name Switch type
224.	The resource information from {0} was successfully collected.	Resource name
225.	A hypervisor was added. Device=name:{0} Added hypervisor=name:{1}	Name of managed device Hypervisor name

	Message text	Parameters
226.	A hypervisor can no longer be recognized. Device=name:{0} Unrecognizable hypervisor=name:{1}	Name of managed device Hypervisor name
227.	A cluster was added. Device=name:{0} Added cluster=name:{1}, type:{2}	Name of managed device Cluster name Type
228.	A cluster can no longer be recognized. Device=name:{0} Unrecognizable cluster=name:{1}, type:{2}	Name of managed device Cluster name Type
229.	A datastore was added. Device=name:{0} Added dataStore=name:{1}, type:{2}	Name of managed device Datastore name Type
230.	A datastore can no longer be recognized. Device=name:{0} Unrecognizable dataStore=name:{1}, type:{2}	Name of managed device Datastore name Type
231.	A management software was added. Device=name:{0} Added management software=name:{1}, productFullName:{2}	Name of managed device Name Software name
232.	A management software can no longer be recognized. Device=name:{0} Unrecognizable management software=name:{1}, product full name:{2}	Name of managed device Name Software name
233.	A vCenter event was received from a resource of {0}. "{1}"	Resource name Message
234.	{0} was removed.	Target resource display name
235.	Information was successfully collected from {0}.	Target resource display name
236.	{1} on {0} is changed from Error status to Warning status. Details: {2}	Resource name Component name Status
237.	{1} on {0} is changed from Error status to Unknown status. Details: {2}	Resource name Component name Status
238.	{1} on {0} is changed from Error status to Normal status. Details: {2}	Resource name Component name Status
239.	{1} on {0} is changed from Warning status to Error status. Details: {2}	Resource name Component name Status

	Message text	Parameters
240.	{1} on {0} is changed from Warning status to Unknown status. Details: {2}	Resource name Component name Status
241.	{1} on {0} is changed from Warning status to Normal status. Details: {2}	Resource name Component name Status
242.	{1} on {0} is changed from Unknown status to Error status. Details: {2}	Resource name Component name Status
243.	{1} on {0} is changed from Unknown status to Warning status. Details: {2}	Resource name Component name Status
244.	{1} on {0} is changed from Normal status to Error status. Details: {2}	Resource name Component name Status
245.	{1} on {0} is changed from Normal status to Warning status. Details: {2}	Resource name Component name Status
246.	{1} on {0} is changed from Normal status to Unknown status. Details: {2}	Resource name Component name Status
247.	An administrator changed {1} on {0} from a Warning status to a Normal status. Details: {2}	Resource name Component name Status
248.	An administrator changed {1} on {0} from an Error status to a Normal status. Details: {2}	Resource name Component name Status
249.	An administrator changed {1} on {0} from an Unknown status to a Normal status. Details: {2}	Resource name Component name Status
250.	An administrator changed {1} on {0} from a Normal status to a Warning status. Details: {2}	Resource name Component name Status
251.	An administrator changed {1} on {0} from a Normal status to an Error status. Details: {2}	Resource name Component name Status

	Message text	Parameters
252.	An administrator changed {1} on {0} from a Normal status to an Unknown status. Details: {2}	Resource name Component name Status
253.	An administrator changed {1} on {0} from an Error status to an Ignore status. Details: {2}	Resource name Component name Status
254.	An administrator changed {1} on {0} from a Warning status to an Ignore status. Details: {2}	Resource name Component name Status
255.	An administrator changed {1} on {0} from a Normal status to an Ignore status. Details: {2}	Resource name Component name Status
256.	An administrator changed {1} on {0} from an Unknown status to an Ignore status. Details: {2}	Resource name Component name Status
257.	An administrator changed {1} on {0} from an Ignore status to an Error status. Details: {2}	Resource name Component name Status
258.	An administrator changed {1} on {0} from an Ignore status to a Warning status. Details: {2}	Resource name Component name Status
259.	An administrator changed {1} on {0} from an Ignore status to a Normal status. Details: {2}	Resource name Component name Status
260.	An administrator changed {1} on {0} from an Ignore status to an Unknown status. Details: {2}	Resource name Component name Status
261.	Execution of the command ended. (action name:{0}, command's return code:{1})	Action name Command's return code
262.	The service started. (host:{0})	Host name
263.	The service will now stop. (host:{0})	Host name
264.	{1} on {0} is changed to Unknown status.	Resource name Component name
265.	{1} on {0} is changed to Normal status.	Resource name Component name
266.	{2} changed {1} on {0} from a Warning status to a Normal status.	Resource name Component name Status

	Message text	Parameters
267.	{2} changed {1} on {0} from an Error status to a Normal status.	Resource name Component name Status
268.	{2} changed {1} on {0} from a link down status to a Normal status.	Resource name Component name Status
269.	{2} changed {1} on {0} from an Unknown status to a Normal status.	Resource name Component name Status
270.	{2} changed {1} on {0} from an Ignore status to a Normal status.	Resource name Component name Status

(2) Warning-level messages

Table 2-2 Warning-level messages indicating changes in the system status

	Message text	Parameters
1.	The system cannot obtain the information of device {0} by using the configured user certification.	Device display name
2.	The system was able to confirm the type ({1}) of the resource ({0}). However, the resource information could not be obtained by using the registered credential information.	Resource name Resource type
3.	A connection between the device (type = {1}) to the resource ({0}) was established. However, information could not be obtained, because you do not have the necessary permissions.	Resource name Resource type
4.	The requested information could not be acquired ({0}).	Other error
5.	There was change in the configuration of the device ({0}).	Device display name
6.	A FC port can no longer be recognized. Device=name:{0} Unrecognizable FC port=name:{1},WWN:{2}	Device display name FC port name Port WWN
7.	A FC connection for storage can no longer be recognized. Device=name:{0} Disconnected storage=WWN:{1} Disconnected FC port=WWN:{2}	Device display name Target resource WWN Target port WWN
8.	A FC connection can no longer be recognized. Device=name:{0} Disconnected FC port=name:{1},WWN:{2}	Device display name Connection-destination FC port name Connection-destination FC port WWN

	Message text	Parameters
9.	A management port can no longer be recognized. Device=name:{0} Unrecognizable management port=IP address:{1}	Device display name IP address
10.	A FC switch port can no longer be recognized. Device=name:{0} Unrecognizable port=name:{1},WWN:{2},port number:{3}	Device display name FC port name Port WWN Port number
11.	A drive(mount point) can no longer be recognized. Device=name:{0} Unrecognizable drive(mount point)=name:{1}	Device display name Mount point
12.	An accessible FC port can no longer be recognized. Device=name:{0} Forbidden FC port=WWN:{1}	Device display name Inaccessible FC port WWN
13.	An accessible LUN can no longer be recognized. Device=name:{0} Unrecognizable LUN=host LUN:{1},size:{2} bytes	Device display name Host LU number Capacity
14.	A IP switch port can no longer be recognized. Device=name:{0} Unrecognizable port=MAC address:{1},port number:{2}	Device display name MAC address Port number
15.	A LAN connection can no longer be recognized. Device=name:{0} Disconnected ethernet port=MAC address:{1}	Device display name Connection-destination MAC address
16.	An iSCSI connection can no longer be recognized. Device=name:{0} Disconnected iSCSI target=iSCSI name:{1},IP address:{2}	Device display name Connection-destination iSCSI name Connection-destination IP address
17.	A SCSI disk drive can no longer be recognized. Device=name:{0} Unrecognizable SCSI disk drive=name:{1},model:{2}	Device display name SCSI disk drive name Model
18.	A software was uninstalled. Device=name:{0} Uninstalled software=name:{1}	Device display name Software name
19.	A disk drive can no longer be recognized. Device=name:{0} Unrecognizable disk drive=name:{1},model:{2}	Device display name Disk drive name Model

	Message text	Parameters
20.	A CPU can no longer be recognized. Device=name:{0} Unrecognizable CPU=name:{1}	Device display name CPU name
21.	A disk controller can no longer be recognized. Device=name:{0} Unrecognizable disk controller=name:{1}	Device display name Disk controller name
22.	A network drive can no longer be recognized. Device=name:{0} Unrecognizable network drive=host name:{1},share name:{2}	Device display name Server name Share name
23.	An iSCSI software initiator was uninstalled. Device=name:{0} Uninstalled iSCSI software initiator=iSCSI name:{1}	Device display name iSCSI name
24.	An operating system was uninstalled. Device=name:{0} Uninstalled operating system:{1}	Device display name OS name
25.	A logical volume can no longer be recognized. Device=name:{0} Unrecognizable volume=name:{1},location:{2}	Device display name Volume name Location (local, network, or unknown)
26.	A file system can no longer be recognized. Device=name:{0} Unrecognizable file system=name:{1},type:{2}	Device display name File system name File system type
27.	A network adapter can no longer be recognized. Device=name:{0} Unrecognizable network adapter=name:{1},interface name:{2},manufacturer:{3},MAC address:{4},IP address:{5}	Device display name Adapter display name Interface name Manufacturer MAC address IP address
28.	A file share can no longer be recognized. Device=name:{0} Unrecognizable file share=name:{1},shared path:{2}	Device display name Share name Shared path
29.	An iSCSI port can no longer be recognized. Device=name:{0} Unrecognizable iSCSI port=IP address:{1},MAC address:{2}	Device display name IP address MAC address

	Message text	Parameters
30.	A host group can no longer be recognized. Device=name:{0} Unrecognizable host group=name:{1} FC port=name:{2}	Device display name Host group name FC port name
31.	An iSCSI target can no longer be recognized. Device=name:{0} Unrecognizable iSCSI target=target name:{1},iSCSI name:{2}	Device display name Target name iSCSI name
32.	An accessible iSCSI initiator can no longer be recognized. Device=name:{0} Forbidden iSCSI initiator=iSCSI name:{1}	Device display name Inaccessible iSCSI initiator name
33.	A logical unit can no longer be recognized. Device=name:{0} Unrecognizable logical unit=logical unit number:{1},size:{2} bytes	Device display name LU number Capacity
34.	A parity group can no longer be recognized. Device=name:{0} Unrecognizable parity group=parity group name:{1},size:{2} bytes	Device display name Parity group name Capacity
35.	A storage controller can no longer be recognized. Device=name:{0} Unrecognizable storage controller=name:{1}	Device display name Controller name
36.	A storage disk drive can no longer be recognized. Device=name:{0} Unrecognizable disk drive=disk number:{1}	Device display name Disk number
37.	A power supply can no longer be recognized. Device=name:{0} Unrecognizable power supply=name:{1},device ID:{2}	Device display name Component display name Device ID
38.	A fan can no longer be recognized. Device=name:{0} Unrecognizable fan=name:{1},device ID:{2}	Device display name Component display name Device ID
39.	A battery can no longer be recognized. Device=name:{0} Unrecognizable fan=name:{1},device ID:{2}	Device display name Component display name Device ID
40.	A cache can no longer be recognized. Device=name:{0} Unrecognizable cache=name:{1},device ID:{2}	Device display name Component display name Device ID

	Message text	Parameters
41.	A VM Kernel NIC can no longer be recognized. Device=name:{0} Unrecognizable VM Kernel NIC=IP address:{1},subnet mask:{2},MAC address:{3}	Device display name IP address Subnet mask MAC address
42.	A service Console NIC can no longer be recognized. Device=name:{0} Unrecognizable service console NIC=IP address:{1},subnet mask:{2}	Device display name IP address Subnet mask
43.	A virtual switch can no longer be recognized. Device=name:{0} Unrecognizable virtual switch=name:{1}	Device display name Device name
44.	A port group can no longer be recognized. Device=name:{0} Unrecognizable port group=name:{1},VLAN ID:{2}	Device display name Port group name VLAN ID
45.	A FC network port can no longer be recognized. Device=name:{0} Unrecognizable FC network port=portWwn:{1}, portName:{2},	Device display name Port WWN Port name
46.	An IP network port can no longer be recognized. Device=name:{0} Unrecognizable IP network port=MAC address:{1}, IP address:{2}, subnet mask:{3}	Device display name MAC address IP address Subnet mask
47.	A capacity can no longer be recognized. Device=name:{0} Unrecognizable capacity=name:{1}, capacity:{2} bytes, free space:{3} bytes	Device display name Capacity name Maximum capacity Available capacity
48.	A software was uninstalled. Device=name:{0} Unrecognizable installed software=name:{1}, version:{2}	Device display name Software name Software version
49.	An iSCSI Initiator can no longer be recognized. Device=name:{0} Unrecognizable iSCSI Initiator=iSCSI name:{1}	Device display name iSCSI name
50.	A permitted iSCSI initiator can no longer be recognized. Device=name:{0} Unrecognizable permitted iSCSI initiator=iSCSI name:{1}	Device display name iSCSI name
51.	A permitted WWN initiator can no longer be recognized. Device=name:{0} Unrecognizable permitted iSCSI initiator=iSCSI name:{1}	Device display name WWN name

	Message text	Parameters
52.	A file share can no longer be recognized. Device=name:{0} Unrecognizable file share=name:{1}, path:{2}	Device display name File share name Shared file path
53.	A file system can no longer be recognized. Device=name:{0} Unrecognizable file system=name:{1}, size:{2} bytes, free space:{3} bytes	Device display name File system name Maximum capacity Available capacity
54.	{0} can no longer be recognized.	Element name (ElementName) of the component
55.	A CPU can no longer be recognized. Device=name:{0} Added CPU=name:{1}	Device display name CPU display name
56.	A fan can no longer be recognized. Device=name:{0} Unrecognizable fan=name:{1},device ID:{2}	Device display name Device display name Device ID
57.	A logical drive can no longer be recognized. Device=name:{0} Unrecognizable logical drive=name:{1},device ID:{2}	Device display name Device display name Device ID
58.	A physical drive can no longer be recognized. Device=name:{0} Unrecognizable physical drive=name:{1},device ID:{2}	Device display name Device display name Device ID
59.	A power supply can no longer be recognized. Device=name:{0} Unrecognizable power supply=name:{1},device ID:{2}	Device display name Device display name Device ID
60.	A storage management battery can no longer be recognized. Device=name:{0} Unrecognizable storage management battery=name:{1},device ID:{2}	Device display name Device display name Device ID
61.	A storage management can no longer be recognized. Device=name:{0} Unrecognizable storage management=name:{1},device ID:{2}	Device display name Device display name Device ID
62.	A temperature sensor can no longer be recognized. Device=name:{0} Unrecognizable temperature sensor=name:{1},device ID:{2}	Device display name Device display name Device ID
63.	A voltage sensor can no longer be recognized. Device=name:{0} Unrecognizable voltage sensor=name:{1},device ID:{2}	Device display name Device display name Device ID

	Message text	Parameters
64.	Storage volumes that exceed the {0} limit are not supported. Please adjust the number of volumes to {0} or less.	Maximum allowable number of storage volumes
65.	A raw mapped virtual disk can no longer be recognized. Device=name:{0} Unrecognizable raw mapped virtual disk=name:{1}, device name:{2}, size:{3} bytes, mode:{4}	Device display name Disk name Device name Size Mode
66.	A virtual disk can no longer be recognized. Device=name:{0} Unrecognizable virtual disk=name:{1}, size:{2} bytes	Device display name Disk name Size
67.	A virtual NIC can no longer be recognized. Device=name:{0} Unrecognizable virtual NIC=IP address:{1}, MAC address:{2}	Device display name IP address MAC address
68.	The file share port of the storage subsystem can no longer be recognized. Device=name:{0} Port=IP address:{1}, subnet mask:{2}, MAC address:{3}	Device display name IP address Subnet mask MAC address
69.	A connected Ethernet Port can no longer be recognized. Device=name:{0} Connected Port=MAC Address:{1}, PortID:{2}, VLAN ID:{3}	Device display name MAC address Port number VLAN ID
70.	A connected FC Port can no longer be recognized. Device=name:{0} Connected Port=WWN:{1}	Device display name WWN
71.	A FC connection can no longer be recognized. Device=name:{0} FC port=name:{1}, WWN:{2} Disconnected FC port=linked WWN:{3}	Device display name Connection-source FC port name Connection-source FC port WWN Connection-destination FC port WWN
72.	{0} could not be sent by the specified mail server.	External events
73.	OFF is the performance data collection mode of {0}.	Resource name
74.	Notification of the completion of the collector or discovery processing could not be sent by the specified mail server.	
75.	An administrator set {0} to an inactive state.	Resource name

	Message text	Parameters
76.	The processing to update resource information failed repeatedly, because resource credential information is currently being updated. (resource:{0}, credential:{1}, cooperation product:{2}, update time:{3})	Resource name Credential Product for which credential information is being updated Date and time of last update
77.	Execution of the collector or discovery processing failed repeatedly, because device credential information is currently being updated. (credential:{0}, cooperation product:{1}, update time:{2})	Credential name Product for which credential information is being updated Date and time of last update
78.	Because the usage rate of the database exceeded the threshold, it resulted in a condition that is similar to a full database.	
79.	The free disk space that is required to automatically increment the database is becoming limited.	
80.	MonitoringStatus attribute of {0} is changed to Warning status.	Resource name
81.	OID ({0}) was reported from {1}.	OID string IP address string
82.	Status information about one or more components can no longer be obtained. (number of components:{0}, resource:{1})	Number of components Resource display name
83.	Performance information about one or more components can no longer be obtained. (number of performance components = {0}, resource = {1})	Number of performance components for which performance information can no longer be collected Resource display name
84.	Performance information about one or more performance components could not be obtained. (number of components = {0}, resource = {1})	Number of performance components for which performance information cannot be collected Resource display name
85.	Processing of the specified file has been delayed. The delay is caused by either too many events or it is taking a lot of time to process the file. If this issue occurs frequently, please check the file. (specified file path:{0})	Specified file path
86.	An error occurred in the processing to collect the resource information from {0}, and the monitoring status changed to a warning status.	Resource name
87.	The value of the performance status item "Disk Free Space" of the component ({1}) on the node ({0}) became unknown, because a value greater than the capacity was set for the threshold value. (Capacity Value = {2} MB, Threshold Value = {3} MB)	Resource name Component name Capacity Threshold value

	Message text	Parameters
88.	The value of the performance status item "Disk Free Space" of the component ({1}) on the node ({0}) became unknown, because a value greater than the capacity was set for the threshold value. (Capacity Value = {2} MB, Threshold Value = {3} MB)	Resource name Component name Capacity Threshold value
89.	The value of the performance status item "StoragePool Free Space" of the component ({1}) on the node ({0}) became unknown, because a value greater than the capacity was set for the threshold value. (Capacity Value = {2} GB, Threshold Value = {3} GB)	Resource name Component name Capacity Threshold value
90.	The value of the performance status item "StoragePool Free Space" of the component ({1}) on the node ({0}) became unknown, because a value greater than the capacity was set for the threshold value. (Capacity Value = {2} GB, Threshold Value = {3} GB)	Resource name Component name Capacity Threshold value
91.	The value of the performance status item "Disk Free Space" of the component ({1}) on the node ({0}) became unknown, because a value greater than the capacity was set for the threshold value. (Capacity Value = {2} MB, Threshold Value = {3} MB)	Resource name Component name Capacity Threshold value
92.	The value of the performance status item "StorageFileSystem Free Space" of the component ({1}) on the node ({0}) became unknown, because a value greater than the capacity was set for the threshold value. (Capacity Value = {2} MB, Threshold Value = {3} MB)	Resource name Component name Capacity Threshold value
93.	The value of the performance status item "Disk Free Space" of the component ({1}) on the node ({0}) became unknown, because a value greater than the capacity was set for the threshold value. (Capacity Value = {2} MB, Threshold Value = {3} MB)	Resource name Component name Capacity Threshold value
94.	The value of the performance status item "Disk Free Space" of the component ({1}) on the node ({0}) became unknown, because a value greater than the capacity was set for the threshold value. (Capacity Value = {2} MB, Threshold Value = {3} MB)	Resource name Component name Capacity Threshold value
95.	{1} on {0} is changed to Warning status.	Resource name Component name

(3) Error-level messages

Table 2-3 Error-level messages indicating changes in the system status

	Message text	Parameters
1.	The scheduled update was unsuccessful (schedule type:{0}). Please reboot the program.	Schedule type
2.	The system cannot obtain the information of the monitored device ({0}).	Device display name

	Message text	Parameters
3.	Because of the restrictions with the user account's access permissions, the configuration update failed.	
4.	Because the logon attempt was unsuccessful, the configuration update failed.	
5.	Because there was no connection to the device, the configuration update failed.	
6.	As a result of unknown causes, the configuration could not be completed. Please refer to the service message log.	
7.	An end-to-end connection could not be established.	
8.	The {1} on {0} does not exist.	Resource name Component name
9.	An error occurred while collecting the performance data of {1} on {0}.	Resource name Component name
10.	The {1} on {0} does not exist.	Resource name Component name
11.	An error occurred while collecting the capacity data of {1} on {0}.	Resource name Component name
12.	The database is already full. Perform database maintenance.	
13.	There is insufficient free disk space to expand the database.	
14.	The database cannot be incremented automatically. There is not enough free disk space.	
15.	An automatic increment of the database cannot be completed. Please expand the current database scale so that there is sufficient free disk space.	
16.	The performance status of "Temperature Sensor" in {1} on {0} changed from Ignored to Error. (Performance Value = {2} degrees Celsius)	Resource name Component name Performance value
17.	An attempt to run the specified file has failed. (File:"{0}")	File path
18.	An unexpected error occurred. (Errormessage = {0})	Exception message (in English)
19.	A timeout occurred with the ({0}) process.	Process
20.	Monitoring of the resource ({0}) was disabled, because the processing to acquire information from the resource took too long. Check whether there are any problems with the resource or its management server. After troubleshooting, enable monitoring of the resource.	Resource name
21.	Processing of the specified file has been delayed. The delay is caused by either too many events or it is taking a lot of time to process the file. Please check the specified file, and then modify the file to shorten executing. time. (specified file path:{0})	Specified file path

	Message text	Parameters
22.	The command to be executed when an event occurs was skipped, possibly because command execution was taking too long. Check and revise the specified file to reduce the processing time. (program file path = {0})	Specified file path
23.	Execution of the command might have been skipped for events that occurred in the following time frame: {0} to {1}.	Time at which command execution was first skipped Time at which command execution was last skipped
24.	Because of a command is running, an attempt to replication has failed. Replication can not until running command is finished.	
25.	An error occurred in the processing to collect the resource information from {0}, and the monitoring status changed to an error status.	Resource name
26.	Event collection failed, because this user account does not have the necessary permissions.	
27.	Event collection failed, because login was unsuccessful.	
28.	Event collection failed, because a connection to the device could not be established.	
29.	Event collection failed because of unknown causes. For more information, see the service message log.	
30.	Failed to connect to {0}.	Target resource display name
31.	The system cannot obtain the information from {0} by using the configured credentials.	Target resource display name
32.	An error occurred in the processing to collect information from {0}.	Target resource display name
33.	The command timed out and was forcibly stopped. (action name:{0})	Action name
34.	{1} on {0} is changed to a link down status.	Resource name Component name
35.	{1} on {0} is changed to Error status.	Resource name Component name

2.2.3 Messages indicating changes in a metric status

(1) Information-level messages

Table 2-4 Information-level messages indicating changes in a metric status

	Message text	Parameters
1.	The performance status of "{2}" in {1} on {0} changed from Warning to Normal. (Performance Value = {3} {4})	Resource name Component name Performance value Metric display name Metric unit

	Message text	Parameters
2.	The performance status of "{2}" in {1} on {0} changed from Error to Normal. (Performance Value = {3} {4})	Resource name Component name Performance value Metric display name Metric unit
3.	The performance status of "{2}" in {1} on {0} changed from Unknown to Ignored.	Resource name Component name Metric display name
4.	The performance status of "{2}" in {1} on {0} changed from Normal to Ignored.	Resource name Component name Metric display name
5.	The performance status of "{2}" in {1} on {0} changed from Warning to Ignored.	Resource name Component name Metric display name
6.	The performance status of "{2}" in {1} on {0} changed from Error to Ignored.	Resource name Component name Metric display name
7.	The performance status of "{2}" in {1} on {0} changed from Ignored to Normal. (Performance Value = {3} {4})	Resource name Component name Performance value Metric display name Metric unit
8.	The performance status of "{2}" in {1} on {0} changed from Ignored to Monitor Off.	Resource name Component name Metric display name
9.	The performance status of "{2} " in {1} on {0} changed from Monitor Off to Ignored.	Resource name Component name Metric display name

(2) Warning-level messages

Table 2-5 Warning-level messages indicating changes in a metric status

	Message text	Parameters
1.	The performance status of "{2}" in {1} on {0} changed from Unknown to Warning. (Performance Value = {3} {4})	Resource name Component name Performance value Metric display name Metric unit

	Message text	Parameters
2.	The performance status of "{2}" in {1} on {0} changed from Normal to Warning. (Performance Value = {3} {4})	Resource name Component name Performance value Metric display name Metric unit
3.	The performance status of "{2}" in {1} on {0} changed from Error to Warning. (Performance Value = {3} {4})	Resource name Component name Performance value Metric display name Metric unit
4.	The performance status of "{2}" in {1} on {0} changed from Ignored to Warning. (Performance Value = {3} {4})	Resource name Component name Performance value Metric display name Metric unit

(3) Error-level messages

Table 2-6 Error-level messages indicating changes in a metric status

	Message text	Parameters
1.	The performance status of "{2}" in {1} on {0} changed from Unknown to Error. (Performance Value = {3} {4})	Resource name Component name Performance value Metric display name Metric unit
2.	The performance status of "{2}" in {1} on {0} changed from Normal to Error. (Performance Value = {3} {4})	Resource name Component name Performance value Metric display name Metric unit
3.	The performance status of "{2}" in {1} on {0} changed from Warning to Error. (Performance Value = {3} {4})	Resource name Component name Performance value Metric display name Metric unit

	Message text	Parameters
4.	The performance status of "{2}" in {1} on {0} changed from Ignored to Error. (Performance Value = {3} {4})	Resource name Component name Performance value Metric display name Metric unit

Appendix A. Version Changes

This appendix describes the changes between versions.

(1) Changes in version 11-50

- The following messages were added:
KNAQ03623-I - KNAQ03625-I, KNAQ70001-E - KNAQ70009-E, KNAQ70011-E - KNAQ70013-E, KNAQ73001-I - KNAQ73005-E, KNAV21000-E - KNAV21003-W, KNAV30164-E - KNAV30184-E, KNAV50418-E - KNAV50429-E, KNAV50803-E - KNAV50842-E, KNAV50980-E - KNAV50988-E, KAPM00146-E, KAPM01193-E, KAPM02497-E, KAPM03972-E, KAPM03973-E, KAPM04667-W, KAPM04686-W, KAPM04689-W, KAPM04696-W, KAPM04698-W, KAPM04846-E, KAPM05058-W, KAPM05059-I, KAPM05350-E, KAPM05351-E, KAPM05664-W, KAPM06820-E - KAPM06827-E, KAPM08330-E, KAPM08923-E, KAPM15279-I - KAPM15283-W, KAPM16056-E, KAPM16450-I - KAPM16469-E, KAPM16479-E - KAPM16490-E, KAPM16492-E - KAPM16499-E
- The following messages were deleted:
KAPM01170-I, KAPM01171-I, KAPM01174-I, KAPM01175-I, KAPM01178-E, KAPM01179-E, KAPM01189-W, KAPM02455-E, KAPM02514-I, KAPM02516-I, KAPM02518-I, KAPM02522-W, KAPM02526-I - KAPM02529-I, KAPM02709-I, KAPM04065-I, KAPM04066-I, KAPM04082-I, KAPM04083-I, KAPM05051-W, KAPM05054-I, KAPM05641-I, KAPM06692-W, KAPM06703-I, KAPM06704-I, KAPM06710-I - KAPM06718-I, KAPM06723-I, KAPM06760-I, KAPM06761-I, KAPM06812-W, KAPM14150-I, KAPM14151-I, KAPM15303-I, KAPM15304-I, KAPM15463-I, KAPM15464-I, KAPM15620-I, KAPM15621-I, KAPM15920-I, KAPM15921-I, KAPM15950-I, KAPM15951-I, KAPM16050-I, KAPM16051-I, KAPM16420-I, KAPM16421-I

(2) Changes in version 11-10

- The following messages were added:
KNAQ00931-E, KNAQ01901-W, KNAQ03565-E - KNAQ03596-E, KNAQ03598-E - KNAQ03602-E, KNAQ03610-E, KNAQ03611-E, KNAQ03616-E - KNAQ03622-Q, KNAQ10195-E, KNAQ10199-E, KNAQ13000-E, KAPM01187-W - KAPM01192-E, KAPM02495-W, KAPM02496-E, KAPM02553-E, KAPM02555-E, KAPM02557-E, KAPM02709-I, KAPM04070-I - KAPM04085-W, KAPM04666-E, KAPM04672-E, KAPM04683-E, KAPM04843-E - KAPM04845-E, KAPM05050-E - KAPM05057-E, KAPM05236-E, KAPM05237-E, KAPM06124-W, KAPM06194-W, KAPM06195-W, KAPM06291-W, KAPM06292-E, KAPM06386-E, KAPM06778-E, KAPM06788-W, KAPM06811-I, KAPM06812-W, KAPM09210-E - KAPM09213-E, KAPM14150-I - KAPM14158-E, KAPM15269-E - KAPM15278-W, KAPM15617-E - KAPM15619-E, KAPM16091-E - KAPM16098-E, KAPM16200-E - KAPM16202-E, KAPM16220-W - KAPM16228-E, KAPM16231-W - KAPM16249-W, KAPM16300-I, KAPM16400-E, KAPM16401-I, KAPM16420-I - KAPM16427-I, KAPM16429-E - KAPM16439-E, KAPM16449-E
- The following messages were changed:
KAPM01167-E
- A message indicating changes to the system status was added.

(3) Changes in version 11-00

- The following messages were added:
KNAV40110-I, KNAV40111-I, KNAV40112-I, KNAV40113-I, KNAV40114-I, KNAV40109-E, KNAQ03544-E, KNAQ10084-E, KNAQ10086-I, KNAQ10089-I
- The following messages were changed:
KNAV20129-E, KNAV50712-E, KNAQ00022-W, KNAQ00911-E, KNAQ00912-E, KNAQ00913-E, KNAQ00914-E, KNAQ00915-E, KNAQ00916-E, KNAQ00917-E, KNAQ00918-E, KNAQ00919-E, KNAQ00920-E, KNAQ00921-E, KNAQ00922-E, KNAQ00923-E, KNAQ00924-E, KNAQ00925-E, KNAQ00926-E, KNAQ00927-E, KNAQ00928-E, KNAQ00986-E, KNAQ00987-I, KNAQ00988-E, KNAQ00989-E, KNAQ00990-E, KNAQ00991-E, KNAQ00992-E, KNAQ00993-E, KNAQ00994-E, KNAQ00995-W, KNAQ00996-E, KNAQ00997-E, KNAQ03003-E, KNAQ03005-E, KNAQ03006-W, KNAQ03008-E, KNAQ03009-E, KNAQ03010-E, KNAQ03011-E, KNAQ03012-E, KNAQ03013-E, KNAQ03014-E, KNAQ03015-E, KNAQ03016-E, KNAQ03017-E, KNAQ03018-E, KNAQ03019-E, KNAQ03032-E, KNAQ03034-E, KNAQ03036-W, KNAQ03044-E, KNAQ03045-E, KNAQ03050-I, KNAQ03051-I, KNAQ03052-E, KNAQ03053-W, KNAQ03054-W, KNAQ03143-E, KNAQ03144-E, KNAQ03147-E, KNAQ03148-E, KNAQ03171-E, KNAQ03174-E, KNAQ03176-E, KNAQ03179-E, KNAQ03180-E, KNAQ03182-E, KNAQ03184-E, KNAQ03185-E, KNAQ03201-E, KNAQ03205-E, KNAQ03208-I, KNAQ03209-E, KNAQ03210-W, KNAQ03212-E, KNAQ03213-E, KNAQ03226-E, KNAQ03229-E, KNAQ03525-E, KNAQ03532-E, KNAQ03533-W, KNAQ03534-E, KNAQ03535-E, KNAQ03540-I, KNAQ03541-I, KNAQ03542-W, KNAQ03543-E
- The following messages were deleted:
KNAQ00998-W, KNAQ00999-E

 **Hitachi, Ltd.**

6-6, Marunouchi 1-chome, Chiyoda-ku, Tokyo, 100-8280 Japan
